**Ecosys** 

> PRINT > COPY > SCAN > FAX

ECOSYS M5526cdn ECOSYS M5526cdw







# **Preface**

Thank you for purchasing this machine.

This Operation Guide is intended to help you operate the machine correctly, perform routine maintenance, and take simple troubleshooting measures as needed so that the machine can always be used in the optimum condition.


Please read this Operation Guide before using the machine.

# To maintain quality, we recommend using genuine Kyocera toner containers, which must pass numerous quality inspections.

The use of non-genuine toner containers may cause failure.


We will not be liable for any damages caused by the use of third party supplies in this machine.

A label is affixed to our genuine supplies, as shown below.



### **Checking the Equipment's Serial Number**

The equipment's serial number is printed in the location shown in the figure.



You'll need the equipment's serial number when contacting your Service Representative. Please check the number before contacting your Service Representative.

# Contents

1

2

	Preface	
	Contents	
	Overview	
	Machine Features	
	Color and Image Quality Functions	
	Basic Color Modes	
	Adjusting Image Quality and Color	
	Guides Provided with the Machine	
	About the Operation Guide (this Guide)	
	Structure of the guide	
	Conventions Used in This Guide	
	Мепи Мар	xxi
gal an	d Safety Information	
	Notice	
	Safety Conventions in This Guide	
	Environment	
	Precautions for Use	
	Laser Safety (Europe)	
	SAFETY OF LASER BEAM (USA)	
	Safety Instructions Regarding the Disconnection of Power	
	Compliance and Conformity	
	Other precautions (for users in California, the United States)	
	Warranty (the United States and Canada)	
	Legal Restriction on Copying/Scanning	
	EN ISO 7779	
	EK1-ITB 2000	
	Wireless Connection (Mexico only)	
	Security Precautions when Using Wireless LAN (If equipped)	
	Limited Use of This Product (If equipped)	
	Legal Information	
	Energy Saving Control Function	
	Automatic 2-Sided Print Function	
	Resource Saving - Paper	
	Environmental benefits of "Power Management"	
	Energy Star (ENERGY STAR®) Program	
alling	g and Setting up the Machine	
	Part Names (Connectors/Interior)	
	Part Names (With Optional Equipments Attached)	
	Connecting the Machine and Other Devices	
	Connecting Cables	
	Connecting LAN Cable	
	Connecting USB Cable	
	Connecting the Power Cable	
	Power On/Off	
	Power On	
	Power Off	
	Using the Operation Panel	
	Operation Panel Keys	
	Touch Panel	
	Home Screen	
	Display for Device Information	
	Functions key	
	Display of Keys That Cannot Be Set	
		<b>_</b> _ 10

	Using the [Enter] key	2-19
	Using the [Quick No. Search] key	2-19
	Help Screen	2-20
	Login/Logout	2-21
	Login	2-21
	Logout	
	Default Settings of the Machine	
	Setting Date and Time	
	Network Setup	
	Configuring the Wired Network	
	Configuring the Wireless Network	
	Setting Wi-Fi Direct	
	Energy Saver function	
	Sleep	
	Auto Sleep	
	Sleep Rules (models for Europe)	
	Sleep Level (Energy Saver and Quick Recovery) (models except for Europe)	
	Power Off Rule (models for Europe)	
	Quiet Mode	
	Quick Setup Wizard	
	Installing Software	
	Software on DVD (Windows)	
	Installing Software in Windows	
	Uninstalling the Software	
	Installing Software in Mac Computer	
	Setting TWAIN Driver	
	Setting WIA Driver	
	Checking the Counter	
	Additional Preparations for the Administrator	
	Sending Documents to a PC	
	Strengthening the Security	2-51
	Command Center RX	
	Accessing Command Center RX	2-53
	Changing Security Settings	2-54
	Changing Device Information	2-56
	E-mail Settings	2-58
	Registering Destinations	2-62
	Transferring Data from Our Other Products	2-63
	Migrating the Address Book	
<b>n</b>	wation hafana llaa	• •
Prepa	ration before Use	3-1
	Loading Paper	3-2
	Precaution for Loading Paper	
	Selecting the Paper Feeder Units	
	Loading in the Cassette 1	
	Loading in the Cassette 2	
	Precautions for Outputting Paper	
	Paper Stopper	
	Preparation for Sending a Document to a Shared Folder in a PC	
	Making a note of the computer name and full computer name	
	Making a note of the user name and domain name	
	Creating a Shared Folder, Making a Note of a Shared Folder	
	Configuring Windows Firewall	
	Registering Destinations in the Address Book	
	Adding a Destination (Address Book)	
	Adding a Destination on One Touch Key (One Touch Key)	<i>3-</i> 26

3

4	Printing from PC	. 4-1
	Printer Driver Properties Screen	4-2
	Displaying the Printer Driver Help	
	Changing the Default Printer Driver Settings (Windows 8.1)	4-3
	Printing from PC	4-4
	Printing on Standard Sized Paper	
	Printing on Non-standard Sized Paper	
	Canceling Printing from a Computer	
	Printing from the Handheld Device	
	Printing by AirPrint	
	Printing by Google Cloud Print	
	Printing by Mopria	
	Printing with Wi-Fi Direct	
	Printing Data Saved in the Printer	
	Specifying the Job Box from a Computer and Storing the Job	
	Printing Documents from Private Print Box	
	Deleting the Documents Stored in the Private Print Box	
	Printing Document from Stored Job Box	
	Deleting the Documents Stored in the Stored Job Box	
	Printing Document from Quick Copy Box	
	Deleting the Documents Stored in the Quick Copy Box	
	Printing Document from Proof and Hold Box Deleting the Documents Stored in the Proof and Hold Box	
	Monitoring the Printer Status (Status Monitor)	
	Accessing the Status Monitor	
	Exiting the Status Monitor	
	Quick View State	
	Printing Progress Tab	
	Paper Tray Status Tab	
	Toner Status Tab	
	Alert Tab	
	Status Monitor Context Menu	-
	Status Monitor Notification Settings	
5	Operation on the Machine	. 5-1
	Loading Originals	
	Placing Originals on the Platen	
	Loading Originals in the Document Processor	
	Loading Paper in the Multipurpose Tray	
	Favorites	
	Registering Favorite Using the Wizard Mode	
	Registering Favorite Using the Program Mode	
	Recalling Favorite using the Wizard Mode	
	Recalling Favorite using the Program Mode	
	Editing Favorite	
	Deleting Favorite	5-12
	Registering Shortcuts	5-13
	Adding Shortcuts	5-13
	Editing Shortcuts	5-14
	Deleting Shortcuts	
	Copying	5-15
	Basic Operation	5-15
	Canceling Jobs	
	Frequently-Used Sending Method	
	Sending Document via E-mail	
	Configuring Settings before Sending	
	Sending Scanned Document via E-mail	
	Sending Document to Desired Shared Folder on a Computer (Scan to PC)	
	Configuring Settings before Sending	5-20

Sending Document to Desired Shared Folder on a Computer	
Sending Document to Folder on an FTP Server (Scan to FTP)	5-23
Configuring Settings before Sending	5-23
Sending Document to Folder on an FTP Server	5-23
Scanning using TWAIN or WIA	5-25
Configuring Settings before Sending	
Scanning Document Using Application	
Useful Sending Method	5-26
WSD Scan	5-27
Installing Driver Software	5-27
WSD scan	5-28
Scanning with File Management Utility	5-29
Configuring Settings before Sending	5-29
Recalling a Favorite Configured in FMU	
Sending to Different Types of Destinations (Multi Sending)	5-30
Send to Me (E-mail)	5-31
Configuring Settings before Sending	5-31
Sending a document to the mail address of the logged in user	5-31
Canceling Sending Jobs	5-32
Handling Destination	
Specifying Destination	
Choosing from the Address Book	
Choosing from the External Address Book	
Choosing from the One Touch Key	
Checking and Editing Destinations	
Confirmation Screen of Destinations	5-38
Recall	5-38
How to use the FAX Function	5-39
Using Document Boxes	5-40
What is Job Box?	5-40
What is Removable Memory Box?	
Sub Address Box/Polling Box	
Operating using Removable USB Memory	
Printing Documents Stored in Removable USB Memory	
Saving Documents to USB Memory (Scan to USB)	
Check the USB Memory Information	
Removing USB Memory	5-44
rious Functions	6-1
Functions Available on the Machine	. 6-2
About Functions Available on the Machine	
Сору	
Send	
Removable Memory (Store File, Printing Documents)	
Functions	
Paper Selection	
Zoom	
Density	
,	6-11
Duplex	
Duplex	6-12
Combine	6-12 6-14
Combine Color Selection	6-12 6-14 6-16
Combine Color Selection Collate	6-12 6-14 6-16 6-16
Combine Color Selection Collate Original Size	6-12 6-14 6-16 6-16 6-17
Combine Color Selection Collate Original Size Original Orientation	6-12 6-14 6-16 6-16 6-17 6-18
Combine Color Selection Collate Original Size Original Orientation Mixed Size Originals	6-12 6-14 6-16 6-16 6-17 6-18 6-19
Combine Color Selection Collate Original Size Original Orientation	6-12 6-14 6-16 6-16 6-17 6-18 6-19 6-19
Combine Color Selection Collate Original Size Original Orientation Mixed Size Originals Original Image	6-12 6-14 6-16 6-16 6-17 6-18 6-19 6-19 6-20

6

Sharpness	6-22
Contrast	6-22
Background Density Adj. (Background Density Adjustment)	6-23
Skip Blank Page	6-23
Saturation	6-24
Continuous Scan	6-24
Job Finish Notice	
File Name Entry	
Priority Override	
File Format	
Duplex (2-sided Original)	6-30
Sending Size	
File Separation	
Scan Resolution	
E-mail Subject/Body	
FTP Encrypted TX	
Storing Size	
Encrypted PDF Password	
JPEG/TIFF Print	6-34
XPS Fit to Page	

7	Status/Job Cancel	7-1
	Checking Job Status	7-2
	Details of the Status Screens	
	Checking Detailed Information of Jobs	7-7
	Checking Job History	
	Checking the Detailed Information of Histories	
	Sending the Log History	
	Job Operation	
	Pause and Resumption of Jobs	
	Canceling of Jobs	
	Device/Communication	
	Checking the Remaining Amount of Toner and Paper (Paper/Supplies)	


8	Setup and Registration (System Menu)	8-1
	System Menu	8-2

stem Menu	-2
Operation Method 8-	-2
System Menu Settings 8-	-3
Language 8	-5
Report 8-	-5
User Property 8-	-7
Cassette/MP Tray Settings 8-	-8
Common Settings 8-1	0
Home	9
Сору 8-2	20
Send 8-2	21
Document Box 8-2	22
FAX	22
Address Book/One Touch 8-2	22
User Login/Job Accounting 8-2	23
Printer	24
System/Network 8-2	26
Date/Timer/Energy Saver 8-3	38
Adjustment/Maintenance 8-4	11

9	User Authentication and Accounting (User Login, Job Accounting)	9-1
	Overview of User Login Administration	9-2
	Managing the Job Account from PC	
	Enabling User Login Administration	
	Setting User Login Administration	
	Authentication Security	
	Adding a User (Local User List)	
	Changing User Properties	
	User Login Administration for Printing	
	Managing the Users to Scan Using TWAIN	
	Managing the Users to Scan Using WIA	
	Managing the Users that Send Faxes from a PC	
	Group Authorization Settings	
	Guest Authorization Set.	
	Obtain NW User Property	
	Simple Login Settings	
	ID Card Settings	
	PIN Login Settings	
	Using User Login Administration	
	Login/Logout	
	Overview of Job Accounting	
	To Manage the Number of Sheets Used on Jobs Printed from a PC	
	Enabling Job Accounting	9-29
	Job Accounting Access	9-29
	Setting an Account	9-30
	Adding an Account	9-30
	Restricting the Use of the Machine	9-31
	Editing an Account	
	Deleting an Account	
	Job Accounting for Printing	
	Job Accounting for Scan Using TWAIN	
	Job Accounting for Scan Using WIA	
	Job Accounting for the FAX Transmitted from a Computer	
	Configuring Job Accounting	
	Default Setting	
	•	
	Counting the Number of Pages Printed	
	Print Accounting Report	
	Using Job Accounting	
	Login/Logout	
	Unknown User Settings	
	Unknown ID Job	
	Registering Information for a User whose ID is Unknown	9-43
10	Troublochooting	40.4
10	Troubleshooting	
	Regular Maintenance	
	Cleaning	
	Cleaning Glass Platen	10-2
	Cleaning Slit Grass	10-3
	Cleaning Paper Transfer Unit	
	Toner Container Replacement	
	Loading Paper	
	Troubleshooting	
	Solving Malfunctions	
	Machine Operation Trouble	
	Printed Image Trouble	
	Color printing trouble	
	Responding to Messages	
	Adjustment/Maintenance	
	•	
	Overview of Adjustment/Maintenance	10-29

	Color Registration Procedure	10-29
	Drum Refresh	10-34
	Calibration	10-34
	Laser Scanner Cleaning	10-34
	Clearing Paper Jams	10-35
	Jam Location Indicators	10-35
	Remove any jammed paper in Cassette 1	10-36
	Remove any jammed paper in Cassette 2	
	Remove any jammed paper in the Multipurpose Tray	10-39
	Remove any jammed paper in Rear Cover 1	
	Remove any jammed paper in the Document Processor	10-45
11	Appendix	11-1
	Optional Equipment	
	Overview of Optional Equipment	
	Optional Applications	
	Starting Application Use	
	Checking Details of Application	
	Character Entry Method	
	Entry Screens	
	Entering Characters	
	Paper	
	Basic Paper Specifications	
	Choosing the Appropriate Paper	11-12
	Special Paper	
	Specifications	11-19
	Machine	11-19
	Copy Functions	11-21
	Printer Functions	11-21
	Scanner Functions	11-22
	Document Processor	11-22
	Paper Feeder	11-23
	Glossary	11-24
	Index	Index-1

### **Overview**



### 💽 ΝΟΤΕ


- Before using the machine, be sure to read the following:
- Legal and Safety Information (page 1-1)
- To prepare the device for use, including setting up cable connections and installing software.
- Installing and Setting up the Machine (page 2-1)
- To learn how to load paper, set up shared folders, and add addresses to the address book, refer to the following:
- Preparation before Use (page 3-1)

# **Machine Features**


The machine is equipped with many useful functions.


Using Various Functions (page 6-1)

Here are some examples.



time (Mixed Size Originals) separate batches and produce as one options (Multi Sending) job (Continuous Scan) Folio A (Legal) 1~30 1~10 11~20 21~30 It is useful when preparing many-page It is useful when preparing conference You can send a same document to the handouts. multiple destinations using a different materials. method. You can set the different sized originals at When a large number of originals cannot one time so you don't need to reset the be placed in the document processor at You can specify multiple destinations of originals regardless of size. one time, the originals can be scanned in different send methods such as E-mail, separate batches and then copied or sent SMB, and Fax. Mixed Size Originals (page 6-19) as one job. You can reduce your workflow by sending a job at once. Continuous Scan (page 6-24) Sending to Different Types of Destinations (Multi Sending) (page 5-30)






Various functions are available for

51)

administrators to strengthen security.

Strengthening the Security (page 2-



You can make the machine quiet by

reducing its running noise. ON/OFF

switching by one-touch is possible.

Quiet Mode (page 2-34)

If there is a wireless LAN environment, it

addition, Wi-Fi Direct, etc. are supported.


Configuring the Wireless Network

Setting Wi-Fi Direct (page 2-30)

is possible to install the unit without

(page 2-26)

worrying about the network wiring. In



# **Color and Image Quality Functions**

The machine is equipped with various color and image quality functions. You can adjust the scanned image as desired.

### **Basic Color Modes**

The basic color modes are as follows.

Color mode	Description	Reference image		Reference
		Before	After	page
Full Color	Scans a document in full color.		***	<u>page 6-16</u>
Grayscale	Scans a document in grayscale.	***	×	page 6-16
Black & White	Scans a document in black & white.		<b>※</b>	<u>page 6-16</u>

For details, refer to the following:

Color Selection (page 6-16)

### **Adjusting Image Quality and Color**

To adjust the image quality or color of an image, use the following functions.

Lucrat de	Sample image		Franklar	
I want to	Before	After	- Function	Page
djust the color precisely.				
Adjust the density.			Density	<u>page 6-11</u>
Adjust the color by strengthening blue or red tones. Example: Strengthening red			Color Balance	page 6-21
Change the image by individually adjusting each of the six colors: red, blue, green, cyan, magenta, and yellow. Example: Changing red tones close to yellow to yellow, and cyan tones close to blue to blue			Hue adjustment	page 6-20
Adjust the saturation.			Saturation	page 6-24
djust the image quality precisely				
Emphasize or blur the image outline. Example: Emphasize the image outlines			Sharpness	<u>page 6-22</u>
Adjust the difference between dark and light parts of the image.			Contrast	page 6-22
Darken or lighten the background (the area with no texts or images) of a document. Example: Lightening the background		A ====================================	Background Density	page 6-23
djust the scanned image				
Decrease the file size and produce the characters clearly.	Copy	Copy	File format [High Comp. PDF]	page 6-27

# **Guides Provided with the Machine**

The following guides are provided with the machine. Refer to each guide as needed.

The contents of the guides are subject to change without notice for the purpose of improvement of machine performance.

#### **Printed guides**

Start using the machine quickly



### **Quick Guide**

Explains how to use basic functions of the machine, how to use convenient features, how to perform routine maintenance, and what to do when problems occur.

#### For safe use of the machine



#### Safety Guide

Provides safety and cautionary information for installation environment and use of the machine. Be sure to read this guide before using the machine.

#### Safety Guide (ECOSYS M5526cdn/ECOSYS M5526cdw)

Indicates the space required for machine installation, and describes the cautionary labels and other safety information. Be sure to read this guide before using the machine.

Version 8.0 or later

### Guides (PDF) on the DVD (Product Library)

#### Use the machine Explains how to load paper and perform copy, print and scan operations, and indicates thoughtfully default settings and other information. FAX Operation Guide Use the fax functions Explains how to use the fax function. Card Authentication Kit (B) Operation Guide Use the ID card Explains how to perform authentication using the ID card. **Easily register** Command Center RX User Guide machine information Explains how to access the machine from a Web browser on your computer to check and and configure settings change settings. **Printer Driver User Guide** Print data from a computer Explains how to install the printer driver and use the printer function. **KYOCERA Net Direct Print Operation Guide** Directly print a PDF file Explains how to print PDF files without launching Adobe Acrobat or Reader. Monitor the machine **KYOCERA Net Viewer User Guide** and printers on the Explains how to monitor your network printing system (the machine) with KYOCERA Net network Viewer. File Management Utility User Guide Scan images and save Explains how to use File Management Utility to set various parameters and send and save with information scanned documents. PRESCRIBE Commands Command Reference Describes the native printer language (PRESCRIBE commands). Print without using the printer driver PRESCRIBE Commands Technical Reference Describes the PRESCRIBE command functions and control for each type of emulation. Maintenance Menu User Guide Adjust the print or Maintenance Menu provides the explanation on how to configure the print, scan, and other scan position

Install the following versions of Adobe Reader to view the manuals on the DVD.

**Operation Guide (This Guide)** 

xvii

# **About the Operation Guide (this Guide)**


### Structure of the guide

The Operation Guide contains the following chapters.

	Chapter	Contents		
1	Legal and Safety Information	Provides precautions regarding use of the machine and trademark information.		
2	Installing and Setting up the Machine	Explains part names, cable connections, installation of the software, login, logout, and other matters related to administration of the machine.		
3	Preparation before Use	Explains preparations and settings that are required in order to use the machine, such as how to load paper, and create an address book.		
4	Printing from PC	Explains functions that are available when the machine is used as a printer.		
5	Operation on the Machine	Explains the basic procedures for using the machine, such as placing originals, making copies, sending documents, and using document boxes.		
6	Using Various Functions	Explains convenient functions that are available on the machine.		
7	Status/Job Cancel	Explains how to check the status of a job and the job history, and how to cancel jobs being printed or waiting to print. Also explains how to check paper and toner levels, how to check the device status, and how to cancel fax transmission.		
8	Setup and Registration (System Menu)	Explains System Menu and how it relates to the operation of the machine.		
9	User Authentication and Accounting (User Login, Job Accounting)	Explains user login and job accounting.		
10	Troubleshooting	Explains what to do when toner runs out, an error is displayed, or a paper jam or other problem occurs.		
11	Appendix	Describes convenient options that are available for the machine. Provides information on media types and paper sizes, and gives a glossary of terms. Explains how to enter characters, and lists the specifications of the machine.		

### **Conventions Used in This Guide**

Adobe Reader XI is used as an example in the explanations below.



### 阈 ΝΟΤΕ

The items that appear in Adobe Reader vary depending on how it is used. If the Table of Contents or tools do not appear, refer to Adobe Reader Help.

Certain items are indicated in this guide by the conventions described below.

Convention	Description	
[Bold]	Indicates keys and buttons.	
"Regular" Indicates a message or setting.		

### Conventions used in procedures for operating the machine

In this Operation Guide, continuous operation of the keys on the touch panel is as follows:

Actual procedure	Procedure indicated in this guide
Select the [System Menu] key.	[System Menu] key > [Common Settings] > [Sound]
▼	
Select [\scilon].	
$\checkmark$	
Select [Common Settings].	
$\checkmark$	
Select [Sound].	

#### Size and Orientation of Paper

Paper sizes such as A5 and Statement can be used in both the horizontal and vertical orientations. To distinguish the orientations when these sizes are used, "R" is added to sizes used in the vertical orientation. In addition, the following icons are used to indicate paper placement orientations on the touch panel.


Orientation		Setting Position (X=Length, Y=Width)	Icons on the touch panel	Indicated size in this Guide <sup>*1</sup>
Vertical orientation (-R)	Cassette	Y X		A5-R, Statement-R
	Multi purpose tray	Y Y		A5-R, Statement-R
Horizontal orientation	Cassette	Y		A5
	Multi purpose tray	Y		A5, Statement

\*1 Paper sizes that can be used vary depending on the function and source tray. For details, refer to the following.

Specifications (page 11-19)

### **Menu Map**

This is a list of menus displayed on the touch panel. Depending on the settings, some menus may not be displayed. Some menu names may differ from their reference titles.





One Touch Key (page 5-37)

Address Book (page 5-34)

#### Ext Address Book (Refer to Command Center RX User Guide.)

E-mail (page 5-18)

Folder (<u>page 5-20</u>)(<u>page 5-23</u>)

FAX (Refer to FAX Operation Guide.)

WSD Scan (page 5-28)

#### Functions

Color Selection (page 6-16)
File Format ( <u>page 6-27</u> )
Original Size ( <u>page 6-17</u> )
Original Orientation (page 6-18)
Mixed Size Originals (page 6-19)
Duplex ( <u>page 6-30</u> )
Sending Size (page 6-31)
File Separation (page 6-31)
Scan Resolution (page 6-32)
Density (page 6-11)
Original Image (page 6-19)
Sharpness (page 6-22)
Contrast (page 6-22)
Background Density Adj. (page 6-23)
Skip Blank Page (page 6-23)
FAX TX Resolution (Refer to FAX Operation Guide.)
Zoom ( <u>page 6-10</u> )
Continuous Scan (page 6-24)
File Name Entry (page 6-26)
E-mail Subject/Body (page 6-32)
Job Finish Notice (page 6-25)
FTP Encrypted TX (page 6-33)
FAX Delayed Transmission (Refer to FAX Operation Guide.)
FAX Direct Transmission (Refer to FAX Operation Guide.)
FAX Polling RX (Refer to FAX Operation Guide.)
FAX TX Report (Refer to FAX Operation Guide.)

-

Job Box	
Job Box	Private Print/Stored Job (page 4-12)
	Quick Copy/Proof and Hold (page 4-14)



Removable Memory	Print	Paper Selection (page 6-9)			
		Collate (page 6-16)			
		Duplex (page 6-12)			
		Color Selection (page 6-16)			
		Functions	EcoPrint (page 6-20)		
			Job Finish Notice (page 6-25)		
			Priority Override (page 6-26)		
			Encrypted PDF	Password ( <u>page 6-34</u> )	
			JPEG/TIFF Print	t ( <u>page 6-34</u> )	
			XPS Fit to Page	( <u>page 6-34</u> )	
	Menu	Store File	File Format (pag	<u>je 6-27</u> )	
			Duplex ( <u>page 6-30</u> )		
			Scan Resolution (page 6-32)		
			Density ( <u>page 6-11</u> )		
			File Name Entry ( <u>page 6-26</u> )		
			Color Selection (page 6-16)		
			Functions	Original Size ( <u>page 6-17</u> )	
				Original Orientation (page 6-18)	
				Mixed Size Originals (page 6-19)	
				Storing Size (page 6-33)	
				Original Image ( <u>page 6-19</u> )	
				Sharpness (page 6-22)	
				Contrast ( <u>page 6-22</u> )	
				Background Density Adj. (page 6-23)	
				Skip Blank Page ( <u>page 6-23</u> )	
				Zoom ( <u>page 6-10</u> )	
				Continuous Scan ( <u>page 6-24</u> )	
				Job Finish Notice ( <u>page 6-25</u> )	
				File Separation (page 6-31)	



Sub Address Box (Refer to FAX Operation Guide.)



Polling Box (Refer to FAX Operation Guide.)





Print Job Status (page 7-8)
Send Job Status (page 7-4)
Store Job Status (page 7-5)
Scheduled Job (page 7-6)
Print Job Log (page 7-8)
Send Job Log (page 7-8)
Store Job Log (page 7-8)
FAX Job Log (Refer to FAX Operation Guide.)
Scanner (page 7-11)
Printer (page 7-11)
FAX (refer to FAX Operation Guide.)
Toner Status (page 7-13)
Paper Status (page 7-13)
Removable Memory (page 7-11)
USB Keyboard (page 7-11)
Network Connection Status (page 7-11)
Wi-Fi Direct (page 7-12)
Wi-Fi ( <u>page 7-12</u> )

#### System Menu / Counter





or

Quick Setur Wirerd [AV Setur (2000 2.25)			
Quick Setup Wizard	FAX Setup (page 2-35)		
	Paper Setup (page 2-35)		
	Energy Saver Setup (page 2-35)		
	Network Setup (page 2	-35)	
Language ( <u>page 8-5</u> )			
Report	Report Print	Status Page ( <u>page 8-5</u> )	
		Font List (page 8-5)	
		Network Status (page 8-5)	
		Service Status (page 8-5)	
		Accounting Report (page 8-6)	
		Sub Address Box List (Refer to FAX Operation Guide.)	
		FAX List (Index) (Refer to FAX Operation Guide.)	
		FAX List (No.) (Refer to FAX Operation Guide.)	
		Outgoing FAX Report (Refer to FAX Operation Guide.)	
		Incoming FAX Report (Refer to FAX Operation Guide.)	
	Admin Report	Outgoing FAX Report (Refer to FAX Operation Guide.)	
	Settings	Incoming FAX Report (Refer to FAX Operation Guide.)	
	Result Report Setting	Send Result Report (page 8-6)	
		RX Result Report (Refer to FAX Operation Guide.)	
		Job Finish Notice Setting (page 8-6)	
	Send Log History	Sending Log History (page 8-7)	
		Auto Sending (page 8-7)	
		Destination (page 8-7)	
		Job Log Subject ( <u>page 8-7</u> )	
		Personal Information (page 8-7)	
Counter	Printed Pages ( <u>page 2-50</u> )		
	Scanned Pages (page 2-50)		
User Property (page 9	<u>9-8</u> )		
Cassette/MP Tray	Cassette 1 ( <u>page 8-8</u> )		
Settings	Cassette 2 ( <u>page 8-8</u> )		
	Multipurpose Tray (page 8-9)		
	wumpurpose Tray ( <u>page 8-9</u> )		

Common Settings         Default Screen (page 8-10)		
	Sound	Buzzer (page 8-10)
		FAX Speaker Volume (Refer to FAX Operation Guide.)
		FAX Monitor Volume (Refer to FAX Operation Guide.)
	Original Settings	Custom Original Size (page 8-11)
		Auto Detect Original Size (DP) (page 8-11)
		Default Original Size (page 8-12)
		Default Original Size (Platen) (page 8-12)
	Paper Settings	Custom Paper Size (page 8-13)
		Media Type Settings (page 8-15)
		Default Paper Source (page 8-14)
		Paper Selection (page 8-14)
		Media for Auto (Color) (page 8-14)
		Media for Auto (B & W) (page 8-14)
		Special Paper Action (page 8-14)
		Show Paper Setup Message (page 8-14)
	Function Defaults	File Format (page 8-16)
		Original Orientation (page 8-16)
		Collate ( <u>page 8-16</u> )
		File Separation ( <u>page 8-16</u> )
		Scan Resolution ( <u>page 8-16</u> )
		Color Selection (Copy) (page 8-16)
		Color Select. (Send/Store) (page 8-16)
		Original Image (Copy) ( <u>page 8-16</u> )
		Original Image (Send/Store) (page 8-16)
		Background Density Adj. (Copy) ( <u>page 8-16</u> )
		Background Density Adj. (Send/Store) ( <u>page 8-16</u> )
		EcoPrint ( <u>page 8-16</u> )
		Skip Blank Page (Copy) ( <u>page 8-16</u> )
		Skip Blank Page (Send/Store) ( <u>page 8-16</u> )
		FAX TX Resolution (Refer to FAX Operation Guide.)
		Zoom ( <u>page 8-16</u> )

Common Settings	Function Defaults	Continuous Scan (Con	v) (page 8-16)		
common detungs		Continuous Scan (Copy) (page 8-16) Continuous Scan (FAX) (Refer to <b>FAX Operation Guide</b> .)			
-		Continuous Scan (FAX) (Refer to FAX Operation Guide.) Continuous Scan (Send/Store) (page 8-16)			
		File Name Entry (page			
		E-mail Subject/Body (p			
		FTP Encrypted TX (page 8-17)         JPEG/TIFF Print (page 8-17)         XPS Fit to Page (page 8-17)			
		Detail Settings	Image Quality ( <u>page 8-17</u> )		
			PDF/A ( <u>page 8-17</u> )		
			High Comp. PDF (page 8-17)		
			Blank Detection Level (Copy) (page 8-17)		
			Blank Detection Level (Send/Store) (page 8-17)		
	Preset Limit (page 8-17	)			
	Error Handling	Duplexing Error (page 8	<u></u>		
		Paper Mismatch Error (	page 8-18)		
	Color Toner Empty Action	on ( <u>page 8-18</u> )			
	Measurement (page 8-1	<u>18</u> )			
	Low Toner Alert (page 8	<u>3-18</u> )			
	Keyboard Layout (page	<u>8-19</u> )			
USB Keyboard Type (page 8-19) Format SD Card (page 8-19)					
	Display Status/Log (page 8		<u>e 8-19</u> )		
	Show Power Off Messa	ge ( <u>page 8-19</u> )			
Home	Customize Desktop (pag	<u>ge 2-13)</u>			
	Customize Task Screen	( <u>page 2-13</u> )			
	Wallpaper (page 2-13)				
Сору	Auto Paper Selection (p	page 8-20)			
	Auto % Priority (page 8-	-20)			
	DP Read Action (page 8-20)				
	Platen Scan Action (page	<u>ge 8-20</u> )			
Send	Dest. Check before Sen	nd ( <u>page 8-21</u> )			
	Entry Check for New De				
Send and Forward (page 8-21)					
	Color TIFF Compression	-			
	Default Screen (page 8-				
	New Destination Entry (page 8-21) Recall Destination (page 8-21)				
	Recoil Destination (pay	<u> </u>	Recall Destination (page 8-21)		

Document Box	Sub Address Box (Refer to FAX Operation Guide.)			
	Job Box	Quick Copy Job Retention (page 8-22)		
		Deletion of Job Retention	on ( <u>page 8-22</u> )	
	Polling Box (Refer to FAX Operation Guide.)			
FAX (Refer to FAX Op	eration Guide.)			
Address Book/One	Address Book (page 3-	<u>20</u> )		
Touch	One Touch Key (page 3	<u>3-26</u> )		
	Address Book	Sort ( <u>page 8-23</u> )		
	Defaults	Address Book (page 8-	<u>23</u> )	
	Print List (Refer to FAX Operation Guide.)			
User Login/Job	User Login Settings	User Login (page 9-3)		
Accounting		Local User List ( <u>page 9-5</u> )		
		ID Card Settings	Keyboard Login (page 9-25)	
			Additional Authentication (page 9-25)	
		PIN Login(page 9-26)		
		Simple login settings	Simple Login (page 9-23)	
			Simple Login Setup (page 9-23)	
		User Account Lockout Settings	Lockout (page 9-4)	
			Lockout Policy (page 9-4)	
			Locked out Users List (page 9-4)	
		Group Authorization Set.	Group Authorization (page 9-15)	
			Group List (page 9-16)	
		Guest Authorization Set.	Guest Authorization (page 9-18)	
			Guest Property (page 9-19)	
		Obtain NW User Proper	rty ( <u>page 9-21</u> )	

User Login/Job Accounting	Job Accounting Settings	Job Accounting (page 9-29)		
		Job Accounting Access (page 9-29)		
		Print Accounting Report (page 9-40)		
		Total Job Accounting (page 9-39)		
		Each Job Accounting (page 9-39)		
		Accounting List (page 9-30)		
		Default Setting	Apply Limit (page 9-38)	
			Copy/Printer Count (page 9-38)	
			Default Counter Limit (page 9-38)	
	Unknown User Settings	Unknown ID Job (page 9-42)		
		User Property (page 9-43)		
Printer	Emulation (page 8-24)			
	Color Setting (page 8-24)			
	EcoPrint (page 8-24)			
	Override A4/Letter (page 8-24)			
	Duplex (page 8-24)			
	Copies (page 8-24)			
	Orientation (page 8-24)			
	Wide A4 ( <u>page 8-24</u> )			
	Form Feed TimeOut (page 8-24)			
	LF Action (page 8-24)			
	CR Action (page 8-25)			
	Job Name ( <u>page 8-25</u> )			
	User Name ( <u>page 8-25</u> )			
	MP Tray Priority (page 8-25)			
	Paper Feed Mode (page 8-25)			
	Auto cassette Change (page 8-25)			
	Resolution (page 8-25)			
	Gloss Mode (page 8-25)			

System/Network	Network	Host Name (page 8-26)		
-		Wi-Fi Direct Settings	Wi-Fi Direct ( <u>page 8-26</u> )	
		-	Device Name (page 8-26)	
			IP Address (page 8-26)	
			Auto Disconnect (page 8-26)	
		Wi-Fi Settings	Wi-Fi ( <u>page 8-26</u> )	
		Ũ	Setup ( <u>page 8-27</u> )	
			TCP/IP Settings (page 8-28)	
			Restart Network (page 8-29)	
		Wired Network Settings	TCP/IP Settings (page 8-29)	
			LAN Interface (page 8-29)	
		Bonjour	Protocol Setting (page 8-30)	
			Available Network (Wi-Fi Direct) (page 8-30)	
			Available Network (Wi-Fi) (page 8-30)	
			Available Network (Wired Network) (page 8-30)	
		IPSec ( <u>page 8-30</u> )		
		Protocol Settings (page 8-30)		
		Security Settings	SSL ( <u>page 8-35</u> )	
			IPP Security (page 8-35)	
			HTTP Security (page 8-35)	
			SMTP Security (page 8-35)	
			POP3 Security (User 1) (page 8-35)	
			POP3 Security (User 2) (page 8-35)	
			POP3 Security (User 3) (page 8-35)	
		Ping ( <u>page 8-35</u> )		
		Restart Network ( <u>page 8-36</u> )		
-	Primary Network (Client) (page 8-36)			
	Interface Block Setting	USB Host ( <u>page 8-36</u> )		
		USB Device ( <u>page 8-36</u> )		
		USB Storage (page 8-36)		
-	Security Level (page 8-36)			
-	Restart ( <u>page 8-37</u> )			
-	RAM Disk Setting (page	<u>8-37</u> )		
	Optional Memory (page	<u>8-37</u> )		
	Optional Function (page 8-37)			

Date/Timer/Energy Saver	Date/Time (page 8-38)		
	Date Format (page 8-38)		
	Time Zone (page 8-38)		
	Auto Panel Reset (page 8-38)		
	Panel Reset Timer (page 8-38)		
	Sleep Rules (models for Europe) (page 8-39)		
	Sleep Level (models except for Europe) (page 8-39)		
	Sleep Timer (page 8-39)		
	EnergySaver RecoveryLevel (page 8-39)		
	Power Off Rule (models for Europe) (page 8-40		
	Power Off Timer (models for Europe) (page 8-40)		
	Auto Error Clear (page 8-40)		
	Error Clear Timer (page 8-40)		
	Unusable Time (Refer to FAX Operation Guide.)		
	Ping Timeout (page 8-4	<u>0</u> )	
Adjustment/ Maintenance	Density Adjustment	Copy ( <u>page 8-41</u> )	
Maintenance		Send/Box (page 8-41)	
	Contrast	Copy ( <u>page 8-41</u> )	
		Send/Box (page 8-41)	
	Correcting Black Line (page 8-41)		
	Display Brightness (page 8-41)		
	Color Registration (page 8-41)		
	Drum Refresh (page 8-41)		
	Calibration (page 8-41)		
	Laser Scanner Cleaning (page 8-41)		
	Service Setting (page 8-41)		

# 1 Legal and Safety Information

Please read this information before using your machine. This chapter provides information on the following topics.

Notice	1-2
Safety Conventions in This Guide	1-2
Environment	1-3
Precautions for Use	1-4
Laser Safety (Europe)	1-5
SAFETY OF LASER BEAM (USA)	1-6
Safety Instructions Regarding the Disconnection of Power	1-7
Compliance and Conformity	1-7
Other precautions (for users in California, the United States)	1-7
Warranty (the United States and Canada)	1-8
Legal Restriction on Copying/Scanning	1-9
EN ISO 7779	1-9
EK1-ITB 2000	1-9
Wireless Connection (Mexico only)	1-9
Security Precautions when Using Wireless LAN (If equipped)	1-9
Limited Use of This Product (If equipped)	1-10
Legal Information	1-11
Energy Saving Control Function	1-17
Automatic 2-Sided Print Function	
Resource Saving - Paper	1-17
Environmental benefits of "Power Management"	1-17
Energy Star (ENERGY STAR®) Program	1-17

## **Notice**

### **Safety Conventions in This Guide**

The sections of this guide and parts of the machine marked with symbols are safety warnings meant to protect the user, other individuals and surrounding objects, and ensure correct and safe usage of the machine. The symbols and their meanings are indicated below.




WARNING: Indicates that serious injury or even death may result from insufficient attention to or incorrect compliance with the related points.



CAUTION: Indicates that personal injury or mechanical damage may result from insufficient attention to or incorrect compliance with the related points.

### Symbols

The  $\triangle$  symbol indicates that the related section includes safety warnings. Specific points of attention are indicated inside the symbol.



The 🛇 symbol indicates that the related section includes information on prohibited actions. Specifics of the prohibited action are indicated inside the symbol.



... [Warning of prohibited action]



(N) ... [Disassembly prohibited]

The • symbol indicates that the related section includes information on actions which must be performed. Specifics of the required action are indicated inside the symbol.

... [Alert of required action]



... [Remove the power plug from the outlet]



... [Always connect the machine to an outlet with a ground connection]

Please contact your service representative to order a replacement if the safety warnings in this Operation Guide are illegible or if the guide itself is missing (fee required).

### 💽 NOTE

An original which resembles a bank note closely may not be copied properly in some rare cases because this machine is equipped with a counterfeiting prevention function.

### **Environment**

The service environmental conditions are as follows:

Temperature	50 to 90.5°F (10 to 32.5°C)	
Humidity	10 to 80%	

Avoid the following locations when selecting a site for the machine.

- Avoid locations near a window or with exposure to direct sunlight.
- · Avoid locations with vibrations.
- Avoid locations with drastic temperature fluctuations.
- Avoid locations with direct exposure to hot or cold air.
- Avoid poorly ventilated locations.

If the floor is delicate against casters, when this machine is moved after installation, the floor material may be damaged.

During copying, some ozone is released, but the amount does not cause any ill effect to one's health. If, however, the machine is used over a long period of time in a poorly ventilated room or when making an extremely large number of prints, the smell may become unpleasant. To maintain the appropriate environment for copy work, it is suggested that the room be properly ventilated.

# **Precautions for Use**

### Cautions when handling consumables

# 

Do not attempt to incinerate parts which contain toner. Dangerous sparks may cause burns.

Keep parts which contain toner out of the reach of children.

If toner happens to spill from parts which contain toner, avoid inhalation and ingestion, as well as contact with your eyes and skin.

- If you do happen to inhale toner, move to a place with fresh air and gargle thoroughly with a large amount of water. If coughing develops, contact a physician.
- If you do happen to ingest toner, rinse your mouth with water and drink 1 or 2 cups of water to dilute the contents of your stomach. If necessary, contact a physician.
- If you do happen to get toner in your eyes, flush them thoroughly with water. If there is any remaining tenderness, contact a physician.
- If toner does happen to get on your skin, wash with soap and water.

Do not attempt to force open or destroy parts which contain toner.

### Other precautions

Return the exhausted toner container to your dealer or service representative. The collected toner container will be recycled or disposed in accordance with the relevant regulations.

Store the machine while avoiding exposure to direct sunlight.

Store the machine in a place where the temperature stays below 40°C while avoiding sharp changes of temperature and humidity.


If the machine will not be used for an extended period of time, remove the paper from the cassette and the Multipurpose (MP) Tray, return it to its original package and reseal it.

# Laser Safety (Europe)

Laser radiation could be hazardous to the human body. For this reason, laser radiation emitted inside this machine is hermetically sealed within the protective housing and external cover. In the normal operation of the product by user, no radiation can leak from the machine.

This machine is classified as Class 1 laser product under IEC/EN 60825-1:2014.

Regarding CLASS 1 laser products, information is provided on the rating label.




# **SAFETY OF LASER BEAM (USA)**

### 1. Safety of laser beam

This machine has been certified by the manufacturer to Class 1 level under the radiation performance standards established by the U.S.DHHS (Department of Health and Human Services) in 1968. This indicates that the product is safe to use during normal operation and maintenance. The laser optical system, enclosed in a protective housing and sealed within the external covers, never permits the laser beam to escape.

### 2. The CDRH Act

A laser-product-related act was implemented on Aug. 2, 1976, by the Center for Devices and Radiological Health (CDRH) of the U.S. Food and Drug Administration (FDA). This act prohibits the sale of laser products in the U.S. without certification, and applies to laser products manufactured after Aug. 1, 1976. The label shown below indicates compliance with the CDRH regulations and must be attached to laser products marketed in the United States. The position of the rating label is show below.



### 3. Maintenance

For safety of the service personnel, follow the maintenance instructions in the other section of this manual.

### 4. Safety switch

The power to the laser unit is cut off when the front cover is opened.

# Safety Instructions Regarding the Disconnection of Power

**Caution**: The power plug is the main isolation device! Other switches on the equipment are only functional switches and are not suitable for isolating the equipment from the power source.

**Attention:** Le débranchement de la fiche secteur est le seul moyen de mettre l'appareil hors tension. Les interrupteurs sur l'appareil ne sont que des interrupteurs de fonctionnement: ils ne mettent pas l'appareil hors tension.

# **Compliance and Conformity**

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- · Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- · Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.
- The use of a non-shielded interface cable with the referenced device is prohibited.

CAUTION — The changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of FCC Rules.

Operation is subject to the following two conditions; (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

The antenna(s) used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located or operating in conjunction with any other transmitter.

\* The above statements are valid only in the United States of America and Canada.

NOTE — Use shielded interface cables.

### Other precautions (for users in California, the United States)

Perchlorate Material - special handling may apply. See www.dtsc.ca.gov/hazardouswaste/perchlorate.

# Warranty (the United States and Canada)

### ECOSYS M5526cdw COLOR MULTIFUNCTIONAL PRODUCT LIMITED WARRANTY

KYOCERA Document Solutions America, Inc. and KYOCERA Document Solutions Canada, Ltd. (both referred to as "KYOCERA") warrant the Customer's new color Multifunctional Product (referred to as "MFP"), and the new accessories installed with the initial installation of the MFP, against any defects in material and workmanship for a period of one year, or 100,000 copies/prints from date of installation, whichever first occurs. In the event the MFP or an accessory is found to be defective within the warranty period, KYOCERA's only obligation and the Customer's exclusive remedy shall be replacement of any defective parts. KYOCERA shall have no obligation to furnish labor.

This warranty is valid only for the original retail purchaser (referred to as the "Customer") of a new KYOCERA MFP in the United States of America or Canada, based upon the country of purchase.

In order to obtain performance of this warranty, the Customer must immediately notify the Authorized KYOCERA Dealer from whom the product was purchased. If the KYOCERA Dealer is not able to provide service, write to KYOCERA at the address below for the name and address of the Authorized KYOCERA Dealer in your area, or check KYOCERA's website at <a href="http://www.kyoceradocumentsolutions.com">http://www.kyoceradocumentsolutions.com</a> for KYOCERA Document Solutions America, Inc. or <a href="http://www.kyoceradocumentsolutions.ca">http://www.kyoceradocumentsolutions.ca</a> for KYOCERA Document Solutions Canada, Ltd.

This warranty does not cover MFPs or accessories which: (a) have become damaged due to operator negligence, misuse, accidents, improper storage or unusual physical or electrical stress, (b) have used parts or supplies which are not genuine KYOCERA brand parts or supplies, (c) have been installed or serviced by a technician not employed by KYOCERA or an Authorized KYOCERA Dealer, or (d) have had the serial number modified, altered, or removed.

This warranty does not cover Maintenance Kits or the components of Maintenance Kits, which consist of the drum unit, the developing unit, the transfer belt, and the fixing unit which have a separate warranty.

This warranty gives the Customer specific legal rights. The Customer may also have other rights, which vary from state to state, or province to province. Neither the seller, nor any other person, is authorized to extend the time period or expand this warranty on behalf of KYOCERA.

THIS WARRANTY IS MADE IN LIEU OF ALL OTHER WARRANTIES AND CONDITIONS, EXPRESS OR IMPLIED, AND KYOCERA SPECIFICALLY DISCLAIMS ANY IMPLIED WARRANTY OR CONDITION OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. THIS WARRANTY SHALL NOT EXTEND TO, AND KYOCERA SHALL NOT BE LIABLE FOR, ANY INCIDENTAL OR CONSEQUENTIAL DAMAGES WHICH MAY ARISE OUT OF THE USE OF, OR INABILITY TO USE, THE MFP.

### **KYOCERA** Document Solutions America, Inc.

### **KYOCERA** Document Solutions Canada, Ltd.

225 Sand Road, Fairfield, New Jersey 07004-0008, USA

6120 Kestrel Rd., Mississauga, ON L5T 1S8, Canada

# **Legal Restriction on Copying/Scanning**

It may be prohibited to copy/scan copyrighted material without permission of the copyright owner.

Copying/Scanning the following items is prohibited and may be penalized by low. It may not be limited to these items. Do not knowingly copy/scan the items that are not to be copied/scanned.

- Paper money
- Bank note
- Securities
- Stamp
- Passport
- Certificate

Local laws and regulations may prohibit or restrict copying/scanning of other items not mentioned above.

### **EN ISO 7779**

Maschinenlärminformations-Verordnung 3. GPSGV, 06.01.2004: Der höchste Schalldruckpegel beträgt 70 dB (A) oder weniger gemäß EN ISO 7779.

# **EK1-ITB 2000**

Das Gerät ist nicht für die Benutzung im unmittelbaren Gesichtsfeld am Bildschirmarbeitsplatz vorgesehen. Um störende Reflexionen am Bildschirmarbeitsplatz zu vermeiden, darf dieses Produkt nicht im unmittelbaren Gesichtsfeld platziert werden.

# **Wireless Connection (Mexico only)**

The operation of this equipment is subject to the following two conditions:

(1) it is possible that this equipment or device may not cause harmful interference, and (2) this equipment or device must accept any interference, including interference that may cause undesired operation.

La operación de este equipo está sujeta a las siguientes dos condiciones:

(1) es posible que este equipo o dispositivo no cause interferencia perjudicial y (2) este equipo o dispositivo debe aceptar cualquier interferencia, incluyendo la que pueda causar su operación no deseada.

# **Security Precautions when Using Wireless LAN** (If equipped)

Wireless LAN allows information to be exchanged between wireless access points instead of using a network cable, which offers the advantage that a LAN connection can be established freely within an area in which radio waves can be transmitted.

On the other hand, the following problems may occur if security settings are not configured, because radio waves can pass through obstacles (including walls) and reach everywhere within a certain area.

### **Secretly Viewing Communication Contents**

A third person with malicious objectives may intentionally monitor radio waves and gain unauthorized access to the following communication contents.

- · Personal information including ID, passwords, and credit card numbers
- Contents of email messages

### **Illegal Intrusion**

A third party with malicious intent may gain unauthorized access to personal or company networks and conduct the following illegal actions.

- · Extracting personal and confidential information (information leak)
- Entering into communication while impersonating a specific person and distributing unauthorized information (spoofing)
- · Modifying and retransmitting intercepted communications (falsification)
- Transmitting computer viruses and destroying data and systems (destruction)

Wireless LAN cards and wireless access points contain built-in security mechanisms to address these problems and to reduce the possibility of these problems occurring by configuring the security settings of wireless LAN products when the product is used.

We recommend that customers take responsibility and use their judgment when configuring the security settings and that they ensure that they fully understand the problems that can occur when the product is used without configuring the security settings.

# Limited Use of This Product (If equipped)

- Radio waves transmitted from this product may affect medical equipment. When using this product in a medical institution or in the vicinity of medical instruments, either use this product according to the instructions and precautions provided by the administrator of the institution or those provided on the medical instruments.
- Radio waves transmitted from this product may affect automatic control equipment including automatic doors and fire alarms. When using this product in the vicinity of the automatic control equipment, use this product according to the instructions and precautions provided on the automatic control equipment.
- If this product is used in devices that are directly related to service including airplanes, trains, ships, and automobiles
  or this product is used in applications requiring high reliability and safety to function and in devices requiring accuracy
  including those used in disaster prevention and crime prevention and those used for various safety purposes, please
  use this product after considering the safety design of the entire system including adoption of a failsafe design and
  redundancy design for reliability and safety maintenance of the entire system. This product is not intended for use in
  applications requiring high reliability and safety including aerospace instruments, trunk communication equipment,
  nuclear power control equipment, and medical equipment; hence, the decision as to whether to use this product in
  these applications needs to be fully considered and determined.

# **Legal Information**

Copying or other reproduction of all or part of this guide without the prior written consent of KYOCERA Document Solutions Inc. is prohibited.

### **Regarding Trade Names**

- PRESCRIBE and ECOSYS are registered trademark of Kyocera Corporation.
- KPDL is a trademark of Kyocera Corporation.
- Microsoft, Windows, Windows XP, Windows Server 2003, Windows Vista, Windows Server 2008, Windows 7, Windows Server 2012, Windows 8, Windows 8.1, Windows 10 and Internet Explorer are registered trademarks or trademarks of Microsoft Corporation in the U.S.A. and/or other countries.
- · PCL is a trademark of Hewlett-Packard Company.
- · Adobe Acrobat, Adobe Reader and PostScript are trademarks of Adobe Systems Incorporated.
- Ethernet is a registered trademark of Xerox Corporation.
- IBM and IBM PC/AT are trademarks of International Business Machines Corporation.
- AppleTalk, Bonjour, Macintosh, and Mac OS are trademarks of Apple Inc., registered in the U.S. and other countries.
- All European language fonts installed in this machine are used under licensing agreement with Monotype Imaging Inc.
- · Helvetica, Palatino and Times are registered trademarks of Linotype GmbH.
- ITC Avant Garde Gothic, ITC Bookman, ITC ZapfChancery and ITC ZapfDingbats are registered trademarks of International Typeface Corporation.
- · ThinPrint is a trademark of Cortado AG in Germany and other countries.
- UFST<sup>™</sup> MicroType<sup>®</sup> fonts by Monotype Imaging Inc. are installed in this machine.
- This machine contains the software having modules developed by Independent JPEG Group.
- iPad, iPhone and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries.
- AirPrint and the AirPrint logo are trademarks of Apple Inc.
- iOS is a trademark or registered trademark of Cisco in the U.S. and other countries and is used under license by Apple Inc.
- Google and Google Cloud Print<sup>™</sup> are trademarks and/or registered trademarks of Google Inc.
- Mopria<sup>™</sup> is registered trademarks of Mopria<sup>™</sup> Alliance.
- Wi-Fi and Wi-Fi Direct are trademarks and/or registered trademarks of Wi-Fi Alliance.

All other brands and product names are registered trademarks or trademarks of their respective companies. The designations <sup>™</sup> and <sup>®</sup> will not be used in this Operation Guide.

### **GPL/LGPL**

This product contains GPL (http://www.gnu.org/licenses/gpl.html) and/or LGPL (http://www.gnu.org/licenses/lgpl.html) software as part of its firmware. You can get the source code, and you are permitted to copy, redistribute and modify it under the terms of GPL/LGPL. For further information including availability of the source code, visit http://www.kyoceradocumentsolutions.com/gpl/.

#### **OpenSSL License**

Copyright (c) 1998-2006 The OpenSSL Project. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- 1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- 2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- All advertising materials mentioning features or use of this software must display the following acknowledgment: "This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit. (http://www.openssl.org/)"
- The names "OpenSSL Toolkit" and "OpenSSL Project" must not be used to endorse or promote products derived from this software without prior written permission.
   For written permission, please contact openssl-core@openssl.org.
- 5. Products derived from this software may not be called "OpenSSL" nor may "OpenSSL" appear in their names without prior written permission of the OpenSSL Project.
- 6. Redistributions of any form whatsoever must retain the following acknowledgment: "This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit (http://www.openssl.org/)"

THIS SOFTWARE IS PROVIDED BY THE OpenSSL PROJECT "AS IS" AND ANY EXPRESSED OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE OpenSSL PROJECT OR ITS CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

#### **Original SSLeay License**

Copyright (C) 1995-1998 Eric Young (eay@cryptsoft.com) All rights reserved.

This package is an SSL implementation written by Eric Young (eay@cryptsoft.com). The implementation was written so as to conform with Netscapes SSL.

This library is free for commercial and non-commercial use as long as the following conditions are adhered to. The following conditions apply to all code found in this distribution, be it the RC4, RSA, lhash, DES, etc., code; not just the SSL code. The SSL documentation included with this distribution is covered by the same copyright terms except that the holder is Tim Hudson (tjh@cryptsoft.com).

Copyright remains Eric Young's, and as such any Copyright notices in the code are not to be removed.

If this package is used in a product, Eric Young should be given attribution as the author of the parts of the library used.

This can be in the form of a textual message at program startup or in documentation (online or textual) provided with the package.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- 1. Redistributions of source code must retain the copyright notice, this list of conditions and the following disclaimer.
- 2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- 3. All advertising materials mentioning features or use of this software must display the following acknowledgement: "This product includes cryptographic software written by Eric Young (eay@cryptsoft.com)" The word 'cryptographic' can be left out if the routines from the library being used are not cryptographic related :-).
- 4. If you include any Windows specific code (or a derivative thereof) from the apps directory (application code) you must include an acknowledgement: "This product includes software written by Tim Hudson (tjh@cryptsoft.com)"

THIS SOFTWARE IS PROVIDED BY ERIC YOUNG "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE AUTHOR OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

The licence and distribution terms for any publically available version or derivative of this code cannot be changed. i.e. this code cannot simply be copied and put under another distribution licence [including the GNU Public Licence.]

#### **Monotype Imaging License Agreement**

- 1 *Software* shall mean the digitally encoded, machine readable, scalable outline data as encoded in a special format as well as the UFST Software.
- 2 You agree to accept a non-exclusive license to use the Software to reproduce and display weights, styles and versions of letters, numerals, characters and symbols (*Typefaces*) solely for your own customary business or personal purposes at the address stated on the registration card you return to Monotype Imaging. Under the terms of this License Agreement, you have the right to use the Fonts on up to three printers. If you need to have access to the fonts on more than three printers, you need to acquire a multiuser license agreement which can be obtained from Monotype Imaging. Monotype Imaging retains all rights, title and interest to the Software and Typefaces and no rights are granted to you other than a License to use the Software on the terms expressly set forth in this Agreement.
- 3 To protect proprietary rights of Monotype Imaging, you agree to maintain the Software and other proprietary information concerning the Typefaces in strict confidence and to establish reasonable procedures regulating access to and use of the Software and Typefaces.
- 4 You agree not to duplicate or copy the Software or Typefaces, except that you may make one backup copy. You agree that any such copy shall contain the same proprietary notices as those appearing on the original.
- 5 This License shall continue until the last use of the Software and Typefaces, unless sooner terminated. This License may be terminated by Monotype Imaging if you fail to comply with the terms of this License and such failure is not remedied within thirty (30) days after notice from Monotype Imaging. When this License expires or is terminated, you shall either return to Monotype Imaging or destroy all copies of the Software and Typefaces and documentation as requested.
- 6 You agree that you will not modify, alter, disassemble, decrypt, reverse engineer or decompile the Software.
- 7 Monotype Imaging warrants that for ninety (90) days after delivery, the Software will perform in accordance with Monotype Imaging-published specifications, and the diskette will be free from defects in material and workmanship. Monotype Imaging does not warrant that the Software is free from all bugs, errors and omissions.

The parties agree that all other warranties, expressed or implied, including warranties of fitness for a particular purpose and merchantability, are excluded.

8 Your exclusive remedy and the sole liability of Monotype Imaging in connection with the Software and Typefaces is repair or replacement of defective parts, upon their return to Monotype Imaging.

In no event will Monotype Imaging be liable for lost profits, lost data, or any other incidental or consequential damages, or any damages caused by abuse or misapplication of the Software and Typefaces.

9 Massachusetts U.S.A. law governs this Agreement.

- 10 You shall not sublicense, sell, lease, or otherwise transfer the Software and/or Typefaces without the prior written consent of Monotype Imaging.
- 11 Use, duplication or disclosure by the Government is subject to restrictions as set forth in the Rights in Technical Data and Computer Software clause at FAR 252-227-7013, subdivision (b)(3)(ii) or subparagraph (c)(1)(ii), as appropriate. Further use, duplication or disclosure is subject to restrictions applicable to restricted rights software as set forth in FAR 52.227-19 (c)(2).
- 12 You acknowledge that you have read this Agreement, understand it, and agree to be bound by its terms and conditions. Neither party shall be bound by any statement or representation not contained in this Agreement. No change in this Agreement is effective unless written and signed by properly authorized representatives of each party. By opening this diskette package, you agree to accept the terms and conditions of this Agreement.

#### **Knopflerfish License**

This product includes software developed by the Knopflerfish Project. http://www.knopflerfish.org

Copyright 2003-2010 The Knopflerfish Project. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

- Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
- Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
- Neither the name of the KNOPFLERFISH project nor the names of its contributors may be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE COPYRIGHT HOLDERS AND CONTRIBUTORS "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE COPYRIGHT OWNER OR CONTRIBUTORS BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

#### Apache License (Version 2.0)

Apache License Version 2.0, January 2004 http://www.apache.org/licenses/

TERMS AND CONDITIONS FOR USE, REPRODUCTION, AND DISTRIBUTION

1. Definitions.

"License" shall mean the terms and conditions for use, reproduction, and distribution as defined by Sections 1 through 9 of this document.

"Licensor" shall mean the copyright owner or entity authorized by the copyright owner that is granting the License.

"Legal Entity" shall mean the union of the acting entity and all other entities that control, are controlled by, or are under common control with that entity. For the purposes of this definition, "control" means (i) the power, direct or indirect, to cause the direction or management of such entity, whether by contract or otherwise, or (ii) ownership of fifty percent (50%) or more of the outstanding shares, or (iii) beneficial ownership of such entity.

"You" (or "Your") shall mean an individual or Legal Entity exercising permissions granted by this License.

"Source" form shall mean the preferred form for making modifications, including but not limited to software source code, documentation source, and configuration files.

"Object" form shall mean any form resulting from mechanical transformation or translation of a Source form, including but not limited to compiled object code, generated documentation, and conversions to other media types.

"Work" shall mean the work of authorship, whether in Source or Object form, made available under the License, as indicated by a copyright notice that is included in or attached to the work (an example is provided in the Appendix below).

"Derivative Works" shall mean any work, whether in Source or Object form, that is based on (or derived from) the Work and for which the editorial revisions, annotations, elaborations, or other modifications represent, as a whole, an original work of authorship. For the purposes of this License, Derivative Works shall not include works that remain separable from, or merely link (or bind by name) to the interfaces of, the Work and Derivative Works thereof.

"Contribution" shall mean any work of authorship, including the original version of the Work and any modifications or additions to that Work or Derivative Works thereof, that is intentionally submitted to Licensor for inclusion in the Work by the copyright owner or by an individual or Legal Entity authorized to submit on behalf of the copyright owner. For the purposes of this definition, "submitted" means any form of electronic, verbal, or written communication sent to the Licensor or its representatives, including but not limited to communication on electronic mailing lists, source code control systems, and issue tracking systems that are managed by, or on behalf of, the Licensor for the purpose of discussing and improving the Work, but excluding communication that is conspicuously marked or otherwise designated in writing by the copyright owner as "Not a Contribution."

"Contributor" shall mean Licensor and any individual or Legal Entity on behalf of whom a Contribution has been received by Licensor and subsequently incorporated within the Work.

- 2. Grant of Copyright License. Subject to the terms and conditions of this License, each Contributor hereby grants to You a perpetual, worldwide, non-exclusive, no-charge, royalty-free, irrevocable copyright license to reproduce, prepare Derivative Works of, publicly display, publicly perform, sublicense, and distribute the Work and such Derivative Works in Source or Object form.
- 3. Grant of Patent License. Subject to the terms and conditions of this License, each Contributor hereby grants to You a perpetual, worldwide, non-exclusive, no-charge, royalty-free, irrevocable (except as stated in this section) patent license to make, have made, use, offer to sell, sell, import, and otherwise transfer the Work, where such license applies only to those patent claims licensable by such Contributor that are necessarily infringed by their Contribution(s) alone or by combination of their Contribution(s) with the Work to which such Contribution(s) was submitted. If You institute patent litigation against any entity (including a cross-claim or counterclaim in a lawsuit) alleging that the Work or a Contribution incorporated within the Work constitutes direct or contributory patent infringement, then any patent licenses granted to You under this License for that Work shall terminate as of the date such litigation is filed.
- 4. Redistribution. You may reproduce and distribute copies of the Work or Derivative Works thereof in any medium, with or without modifications, and in Source or Object form, provided that You meet the following conditions:
  - (a)You must give any other recipients of the Work or Derivative Works a copy of this License; and
  - (b)You must cause any modified files to carry prominent notices stating that You changed the files; and
  - (c)You must retain, in the Source form of any Derivative Works that You distribute, all copyright, patent, trademark, and attribution notices from the Source form of the Work, excluding those notices that do not pertain to any part of the Derivative Works; and
  - (d)If the Work includes a "NOTICE" text file as part of its distribution, then any Derivative Works that You distribute must include a readable copy of the attribution notices contained within such NOTICE file, excluding those notices that do not pertain to any part of the Derivative Works, in at least one of the following places: within a NOTICE text file distributed as part of the Derivative Works; within the Source form or documentation, if provided along with the Derivative Works; or, within a display generated by the Derivative Works, if and wherever such third-party notices normally appear. The contents of the NOTICE file are for informational purposes only and do not modify the License. You may add Your own attribution notices within Derivative Works that You distribute, alongside or as an addendum to the NOTICE text from the Work, provided that such additional attribution notices cannot be construed as modifying the License.

You may add Your own copyright statement to Your modifications and may provide additional or different license terms and conditions for use, reproduction, or distribution of Your modifications, or for any such Derivative Works as a whole, provided Your use, reproduction, and distribution of the Work otherwise complies with the conditions stated in this License.

- 5. Submission of Contributions. Unless You explicitly state otherwise, any Contribution intentionally submitted for inclusion in the Work by You to the Licensor shall be under the terms and conditions of this License, without any additional terms or conditions. Notwithstanding the above, nothing herein shall supersede or modify the terms of any separate license agreement you may have executed with Licensor regarding such Contributions.
- Trademarks. This License does not grant permission to use the trade names, trademarks, service marks, or product names of the Licensor, except as required for reasonable and customary use in describing the origin of the Work and reproducing the content of the NOTICE file.
- 7. Disclaimer of Warranty. Unless required by applicable law or agreed to in writing, Licensor provides the Work (and each Contributor provides its Contributions) on an "AS IS" BASIS, WITHOUT WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied, including, without limitation, any warranties or conditions of TITLE, NON-INFRINGEMENT, MERCHANTABILITY, or FITNESS FOR A PARTICULAR PURPOSE. You are solely responsible for determining the appropriateness of using or redistributing the Work and assume any risks associated with Your exercise of permissions under this License.
- 8. Limitation of Liability. In no event and under no legal theory, whether in tort (including negligence), contract, or otherwise, unless required by applicable law (such as deliberate and grossly negligent acts) or agreed to in writing, shall any Contributor be liable to You for damages, including any direct, indirect, special, incidental, or consequential damages of any character arising as a result of this License or out of the use or inability to use the Work (including but not limited to damages for loss of goodwill, work stoppage, computer failure or malfunction, or any and all other commercial damages or losses), even if such Contributor has been advised of the possibility of such damages.
- 9. Accepting Warranty or Additional Liability. While redistributing the Work or Derivative Works thereof, You may choose to offer, and charge a fee for, acceptance of support, warranty, indemnity, or other liability obligations and/or rights consistent with this License. However, in accepting such obligations, You may act only on Your own behalf and on Your sole responsibility, not on behalf of any other Contributor, and only if You agree to indemnify, defend, and hold each Contributor harmless for any liability incurred by, or claims asserted against, such Contributor by reason of your accepting any such warranty or additional liability.

#### END OF TERMS AND CONDITIONS

APPENDIX: How to apply the Apache License to your work.

To apply the Apache License to your work, attach the following boilerplate notice, with the fields enclosed by brackets "[]" replaced with your own identifying information. (Don't include the brackets!) The text should be enclosed in the appropriate comment syntax for the file format. We also recommend that a file or class name and description of purpose be included on the same "printed page" as the copyright notice for easier identification within third-party archives.

#### Copyright [yyyy] [name of copyright owner]

Licensed under the Apache License, Version 2.0 (the "License"); you may not use this file except in compliance with the License. You may obtain a copy of the License at

#### http://www.apache.org/licenses/LICENSE-2.0

Unless required by applicable law or agreed to in writing, software distributed under the License is distributed on an "AS IS" BASIS, WITHOUT WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied. See the License for the specific language governing permissions and limitations under the License.

# **Energy Saving Control Function**

The device comes equipped with a Sleep where printer and fax functions remain in a waiting state but power consumption is reduced to a minimum after a certain amount of time elapses since the device was last used. If the machine is not used while in sleep mode, the power automatically turns off.

Power Off Rule (models for Europe) (page 2-33)

# **Automatic 2-Sided Print Function**

This device includes 2-sided printing as a standard function. For example, by printing two 1-sided originals onto a single sheet of paper as a 2-sided print, it is possible to lower the amount of paper used.

Duplex (page 6-12)

Printing in duplex mode reduces paper consumption and contributes to the conservation of forest resources. Duplex mode also reduces the amount of paper that must be purchased, and thereby reduces cost. It is recommended that machines capable of duplex printing be set to use duplex mode by default.

### **Resource Saving - Paper**

For the preservation and sustainable use of forest resources, it is recommended that recycled as well as virgin paper certified under environmental stewardship initiatives or carrying recognised ecolabels, which meet EN 12281:2002<sup>\*</sup> or an equivalent quality standard, be used.

This machine also supports printing on 64 g/m<sup>2</sup> paper. Using such paper containing less raw materials can lead to further saving of forest resources.

\* : EN12281:2002 "Printing and business paper - Requirements for copy paper for dry toner imaging processes"

Your sales or service representative can provide information about recommended paper types.

### **Environmental benefits of "Power Management"**

To reduce power consumption when idle, this machine is equipped with a power management function that automatically activates energy-saving mode when the machine is idle for a certain period of time. Although it takes the machine a slight amount of time to return to READY mode when in energy-saving mode, a significant reduction in energy consumption is possible. It is recommended that the machine be used with the activation time for energy-saving mode set to the default setting.

# Energy Star (ENERGY STAR<sup>®</sup>) Program



We have determined as a participating company in the International Energy Star Program that this product is compliant with the standards laid out in the International Energy Star Program. ENERGY STAR<sup>®</sup> is a voluntary energy efficiency program with the goal of developing and promoting the use of products with high energy efficiency in order to help prevent global warming. By purchasing ENERGY STAR<sup>®</sup> qualified products, customers can help reduce emissions of greenhouse gases during product use and cut energy-related costs. 2


# Installing and Setting up the Machine

This chapter provides information for the administrator of this machine, such as part names, cable connection, and software installation.


Part Names (Machine Exterior)	2-2
Part Names (Connectors/Interior)	
Part Names (With Optional Equipments	
Attached)	2-6
Connecting the Machine and Other	
Devices	2-7
Connecting Cables	2-8
Connecting LAN Cable	2-8
Connecting USB Cable	2-9
Connecting the Power Cable	2-9
Power On/Off	2-10
Power On	2-10
Power Off	2-10
Using the Operation Panel	. 2-11
Operation Panel Keys	. 2-11
Touch Panel	
Home Screen	2-12
Display for Device Information	2-16
Functions key	2-17
Display of Keys That Cannot	
Be Set	2-18
Using the [Enter] key	
Using the [Quick No. Search] key	2-19
Help Screen	2-20
Login/Logout	2-21
Login	2-21
Logout	2-22
Default Settings of the Machine	
Setting Date and Time	2-23
Network Setup	2-24
Configuring the Wired Network	2-24
Configuring the Wireless Network	2-26
Setting Wi-Fi Direct	2-30
Energy Saver function	2-32
Sleep	2-32
Auto Sleep	2-32
Sleep Rules (models for Europe)	2-33
Sleep Level (Energy Saver and	
Quick Recovery) (models except for	
Europe)	
Power Off Rule (models for Europe)	
Quiet Mode	
Quick Setup Wizard	2-35

Installing Software	2-37
Software on DVD (Windows)	2-37
Installing Software in Windows	
Uninstalling the Software	
Installing Software	- • •
in Mac Computer	2-45
Setting TWAIN Driver	
Setting WIA Driver	
Checking the Counter	
Additional Preparations for	
the Administrator	2-51
Sending Documents to a PC	2-51
Strengthening the Security	2-51
Command Center RX	
Accessing Command	
Center RX	2-53
Changing Security Settings	2-54
Changing Device Information	2-56
E-mail Settings	
Registering Destinations	
Transferring Data from Our Other	
Products	2-63
Migrating the Address Book	2-63

# **Part Names (Machine Exterior)**




- 1 Document Processor
- 2 Inner Tray
- 3 Paper Stopper
- 4 Cassette 1
- 5 Power Switch
- 6 Button (Right Cover Open)
- 7 USB Memory Slot
- 8 Right Cover
- 9 Original Stopper



- 10 Original Eject Table
- 11 Original Table
- 12 Original Width Guides
- 13 Slit Glass
- 14 Handles
- 15 Operation Panel
- 16 Platen
- 17 Original Size Indicator Plates







18 Handles


19 Anti-theft Lock Slot


20 Rear Cover 1

# **Part Names (Connectors/Interior)**










- 1 TEL Connector
- 2 LINE Connector
- 3 USB Interface Connector
- 4 Network Interface Connector
- 5 Feed Cover
- 6 Paper Length Guide

- 7 Paper Width Guides
- 8 Multipurpose Tray
- 9 Tray Extension
- 10 Paper Width Guides
- 11 Fuser Cover





- 12 Toner Container (Yellow)
- 13 Toner Container (Cyan)

14 Toner Container (Magenta)

15 Toner Container (Black)16 Toner Container Lock Lever

# **Part Names (With Optional Equipments Attached)**





- 1 Cassette 2
- 2 Rear Cover 2
- Optional Equipment (page 11-2)


# **Connecting the Machine and Other Devices**

Prepare the cables necessary to suit the environment and purpose of the machine use.

### When Connecting the Machine to the PC via USB



#### When Connecting the Machine to the PC or Tablet by network cable, Wi-Fi, or Wi-Fi direct



### NOTE

If you are using wireless LAN, refer to the following.

Configuring the Wireless Network (page 2-26)

### Cables that Can Be Used

Connection Environment	Function	Necessary Cable
Connect a LAN cable to the machine.	Printer/Scanner/Network FAX	LAN cable (10BASE-T, 100BASE-TX, 1000BASE-T)
Connect a USB cable to the machine.	Printer/Scanner (TWAIN/WIA)	USB 2.0 compatible cable (Hi-Speed USB compliant, max. 5.0 m , shielded)

### **IMPORTANT**

Using a cable other than a USB 2.0 compatible cable may cause failure.

# **Connecting Cables**

# **Connecting LAN Cable**

### **IMPORTANT**


Make sure that the power to the machine is turned off.

Power Off (page 2-10)

1

### Connect the cable to the machine.

1 Connect the LAN cable to the network interface connector.



2 Connect the other end of the cable to the hub or the PC.



Power on the machine and configure the network.

► <u>Network Setup (page 2-24)</u>

# **Connecting USB Cable**

### **IMPORTANT**


Make sure that the power to the machine is turned off.

Power Off (page 2-10)

1

### Connect the cable to the machine.

1 Connect the USB cable to the USB interface connector.



**2** Connect the other end of the cable to the hub.

### **2** Power on the machine.

### **Connecting the Power Cable**

### Connect the cable to the machine.


Connect one end of the supplied power cable to the machine and the other end to a power outlet.

# IMPORTANTOnly use the power cable that comes with the machine.

# **Power On/Off**

## **Power On**


Turn the power switch on.



### **Power Off**

1

Turn the power switch off.



The confirmation message for power supply off is displayed.

Show Power Off Message (page 8-19)

It takes approximately 3 minutes for power off.

# 

If this machine will be left unused for an extended period (e.g. overnight), turn it off at the power switch. If the machine will not be used for an even longer period of time (e.g. vacation), remove the power plug from the outlet as a safety precaution.

### **IMPORTANT**

- Note that turning the machine off at the power switch disables fax transmission and reception.
- Remove paper from the cassettes and seal it in the paper storage bag to protect it from humidity.

# Using the Operation Panel Operation Panel Keys



- 1 [Home] key: Displays the Home screen.
- 2 [Status/Job Cancel] key: Displays the Status/Job Cancel screen.
- 3 [System Menu/Counter] key: Displays the System Menu/Counter screen.
- 4 Touch panel: Displays icons for configuring machine settings.
- 5 [Processing] indicator: Blinks while printing or sending/receiving.
- 6 [Memory] indicator: Blinks while the machine is accessing the machine memory or fax memory.
- 7 [Attention] indicator: Lights or blinks when an error occurs and a job is stopped.
- 8 [Enter] key: Finalizes numeric key entry, and finalizes details during setting of functions. Operates linked with the on-screen [OK].
- 9 [Start] key: Starts copying and scanning operations and processing for setting operations.
- 10 [Stop] key: Cancels or pauses the job in progress.
- 11 [Quiet Mode] key: Lower print and scan speed for quiet processing.
- 12 [Authentication/Logout] key: Authenticates user switching, and exits the operation for the current user (i.e. log out).
- 13 [Energy Saver] key: Puts the machine into Sleep Mode. Recovers from Sleep if in Sleep Mode.
- 14 [Reset] key: Returns settings to their default states.
- 15 [Clear] key: Clears entered numbers and characters.
- 16 [Quick No. Search] key: Specifies registered information such as address numbers and user IDs by number.
- 17 Numeric keys: Enter numbers and symbols.


# **Touch Panel**

### **Home Screen**

This screen is displayed by selecting the [Home] key on the operation panel. Touching an icon will display the corresponding screen.

You can change the icons to display on the Home screen as well as its background.





\* The appearance may differ from your actual screen, depending on your configuration and option settings.

No.	Item	Description
1	Message	Displays the message depending on the status.
2	Desktop	Displays the function icon. Registered function to favorites are also displayed. Icons that are not displayed on the first page will appear by changing the page.
3	Screen-switching keys	Use these buttons to switch between desktop pages. This is displayed when there are multiple pages.
4	[Status]	Displays the Status screen. If an error occurs, the icon will show "!". Once the error clears, the display will return to normal.
5	[Task Screen]	Displays the Task Screen.
6	[Logout]	Logs out the current user. This is displayed when user login administration is enabled.
7	Login User Name	Displays the logged-in user name. This is displayed when user login administration is enabled. Selecting "Login User Name" will display the information of the logged-in user.
8	Task Screen	Displays the task icons.
9	[Desktop]	Displays the Desktop.

### **Editing the Home Screen**

You can change the background of the Home screen as well as which icons are displayed.

### **1** Display the screen.

1 [System Menu/Counter] key > [Home]

### NOTE

If user login administration is enabled, you can only change the settings by logging in with administrator privileges.

The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

### **2** Configure the settings.

The available settings are shown below.

Item	Description
Customize Desktop	Specify the function icons to display on the desktop. <sup>*1</sup>
	Select [ ] to display the screen for selecting the function to display. Select the function to display and <b>[OK</b> ].
	Select an icon and [ <b>Previous</b> ] or [ <b>After</b> ] to change the display position of the selected icon on the Desktop.
	To delete an icon from desktop, select the desired one and select [ 🎆 ].
Customize Task Screen	Specify the task icons to display on the task screen. <sup>*2</sup>
Wallpaper	Configure the wallpaper of the Home screen. Value: Images 1 to 8

\*1 Displays a maximum of 43 function icons.

\*2 5 task icons can be displayed.

Function	lcon	Description	Reference page
Copy <sup>*1</sup>		Displays the Copy screen.	<u>page 5-15</u>
Send <sup>*1</sup>	2	Displays the Send screen.	page 5-17
FAX <sup>*1</sup>		Displays the FAX screen.	Refer to FAX Operation Guide.
Job Box <sup>*2</sup>	ġ,	Displays the Job Box screen.	page 4-11
Removable Memory <sup>*1</sup>	<u></u>	Displays the Removable Memory screen.	page 5-41
Sub Address Box <sup>*1</sup>		Displays the Sub Address Box screen.	Refer to FAX Operation Guide.
Polling Box <sup>*1</sup>		Displays the Polling Box screen.	Refer to FAX Operation Guide.
Send to Me (E-mail) <sup>*3</sup>	and	Displays the Send screen. The E-mail address of the logged-in user is set as the destination.	page 5-31
Favorites		Calls up the registered favorite. The icon will change according to the function of the favorite.	<u>page 5-8</u>

### Available Functions to Display on Desktop

\*1 Selected at the time of shipment from factory.
\*2 This appears when expansion memory or an SD/SDHC memory card is inserted.
\*3 Displayed when user login administration is enabled.

Function	lcon	Description	Reference page
Status/Job Cancel	0	Displays the Status screen. If an error occurs, the icon will show "!". Once the error clears, the display will return to normal.	-
Device Information	0	Displays the Device Information screen. Check the system and network information. You can also check information on the options that are used.	page 2-16
		•	
Language	0	Displays the Language setting screen in System Menu.	<u>page 8-5</u>
Wi-Fi Direct <sup>*1</sup>	0	Wi-Fi Direct is set and a list of information relating to the machine that can use the network appears.	<u>page 8-26</u>
System Menu	0	Displays the System Menu screen.	<u>page 8-3</u>
Favorites	3	Displays the favorite list screen.	<u>page 5-8</u>

### Available Functions to Display on Task Screen

\*1 Displayed only when the wireless network function is available on the machine.

## **Display for Device Information**

Allows you to check system and network information, as well as options that are used.

- 1 [Home] key > [Task Screen] > [Device Information]
- **2** Check the device information.


Device information

Tab	Description
Identification/Wired Network	You can check ID information such as the model name, serial number, host name and location, and the IP address.
Wi-Fi <sup>*1</sup>	You can check ID information such as the model name, serial number, host name and location, and the IP address of the wireless network.
FAX	You can check the local fax number, local fax name, local fax ID and other fax information.
Software Ver./Capability	You can check the software version and performance.
Option	You can check information on the options that are used.

\*1 Displayed only when the wireless network function is available on the machine.

# **Functions key**


This screen appears when the Functions icon is selected.



- 1 Display functions.
- 2 Select [Functions] to display other functions.
- 3 Select [ $\land$ ] or [ $\checkmark$ ] to scroll up and down.

# **Display of Keys That Cannot Be Set**

Keys of features that cannot be used due to feature combination restrictions or non-installation of options are in a non-selectable state.



### 

If a key that you wish to use is grayed out, the settings of the previous user may still be in effect. In this case, select the [**Reset**] key and try again.

# Using the [Enter] key

The [Enter] key has the same function as the key with the Enter mark (↔), such as the [OK ↔] key and the [Close ↔].



# Using the [Quick No. Search] key

The [Quick No. Search] key is used when using the numeric keys to directly enter the number, for example, when specifying the destination for the transmission using a speed-dial number.

For more information on speed dialing, refer to the following:

Specifying Destination (page 5-33)



## **Help Screen**

If you have difficulty operating the machine, you can check how to operate it using the touch panel.

When the [?] (help) is displayed on the touch panel, you can select it to display the Help screen. The Help screen shows explanations of functions and how to use them.

Example: Checking the paper selection Help screen

Ready to copy. (Full ( Paper Selection	Color)	10:10	Ready to copy. (Full Color)	10:
Auto	Ut	1.00	Select the cassette or the multipurpose tray with the desired paper size.	
	Plain	1/2	Auto: Automatically selects the appropriate paper size. Cassette 1: Selects the paper in cassette 1.	1/
A4	Plain	~	Cassette 2: Selects the paper in cassette 2. MP Tray: Selects the paper in the multipurpose tray.	1
0	Cancel	ок	×	1
Ready to copy. (Full O Paper Selection Select the cassette with the desired pa	or the multipurpose tray 4	10:10	<ol> <li>Help titles</li> <li>Displays information about function and machine operation.</li> </ol>	ns
paper size. Cassette 1: Selects	selects the appropriate	1/2	3 Closes the Help screen and return the original screen.	۱S
	the paper in cassette 2. The paper in the multipurpose tray.	N	4 Scrolls up and down when the hel text cannot be displayed in its ention on a single screen.	•

# Login/Logout

If you are setting a function that requires administrator rights, or if user login administration is enabled, you must enter your login user name and login password.

### 

The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

You will be unable to login if you forget your login user name or login password. In this event, login with administrator privileges and change your login user name or login password.

# Login

### Normal login



### Enter the login user name and login password to login.

1 If this screen is displayed during operations, select [Keyboard] to enter the login user name.

10:10
Keyboard
Keyboard
Login

2 [Password] > Enter the login password > [OK]

### 💽 NOTE

If **[Network Authentication**] is selected as the user authentication method, authentication destinations are displayed and either **[Local]** or **[Network]** can be selected as the authentication destination.

### 2 Select [Login].

### Simple Login

01 A	02 B	03 C	
<sup>04</sup> None	05 None	<sup>06</sup> None	1/3
<sup>07</sup> None	08 None	<sup>09</sup> None	


If this screen is displayed during operations, select a user and log in.

### ΜΟΤΕ

If a user password is required, an input screen will be displayed.

✤ Simple Login Settings (page 9-23)

## Logout



To logout from the machine, select the [Authentication/Logout] key to return to the login user name/login password entry screen.

Users are automatically logged out in the following circumstances:

- When the machine enters the sleep state.
- When the auto panel reset function is activated.

## **Default Settings of the Machine**

Before using this machine, configure such settings as date and time, network configuration, and energy saving functions as needed. The Machine Setup Wizard is launched when the equipment is turned on for the first time after being installed. Also, configure the following settings if necessary.

#### 🚫 ΝΟΤΕ

The default settings of the machine can be changed in System Menu. For settings that are configurable from System Menu, refer to the following:

Setup and Registration (System Menu) (page 8-1)

### **Setting Date and Time**

Follow the steps below to set the local date and time at the place of installation.

When you send an E-mail using the transmission function, the date and time as set here will be printed in the header of the E-mail message. Set the date, time and time difference from GMT of the region where the machine is used.

#### 🚫 ΝΟΤΕ

- To make changes after this initial configuration, refer to the following:
- Date/Timer/Energy Saver (page 8-38)
- The correct time can be periodically set by obtaining the time from the network time server.
- Command Center RX User Guide

#### Display the screen.

[System Menu/Counter] key > [Date/Timer/Energy Saver]

#### 2 Configure the settings.

[Time Zone] > [Date/Time] > [Date Format]

Item	Description
Time Zone	Set the time difference from GMT. Choose the nearest listed location from the list. If you select a region that utilizes summer time, configure settings for summer time.
Date/Time	Set the date and time for the location where you use the machine. If you perform Send as E-mail, the date and time set here will be displayed on the header. Value: Year (2000 to 2037), Month (1 to 12), Day (1 to 31), Hour (00 to 23), Minute (00 to 59), Second (00 to 59)
Date Format	Select the display format of year, month, and date. The year is displayed in Western notation. Value: Month/Day/Year, Day/Month/Year, Year/Month/Day

## **Network Setup**

## **Configuring the Wired Network**

The machine is equipped with network interface, which is compatible with network protocols such as TCP/IP (IPv4), TCP/IP (IPv6), NetBEUI, and IPSec. It enables network printing on the Windows, Macintosh, UNIX and other platforms.

Set up TCP/IP (IPv4) to connect to the Windows network.

Be sure to connect the network cable before configuring the settings.

Connecting LAN Cable (page 2-8)

For other network settings, refer to the following:

Network (page 8-26)

#### 🚺 ΝΟΤΕ

If user login administration is enabled, you can only change the settings by logging in with administrator privileges. If user login administration is disabled, the user authentication screen appears. Enter a login user name and password, and select [Login].

The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

#### IPv4 setting

#### 1 Display the screen.

[System Menu/Counter] key > [System/Network] > [Network] > [Wired Network Settings] > [TCP/IP Setting] > [IPv4]

#### **2** Configure the settings.

When using DHCP server

[DHCP]: Set to [On].

When setting the static IP address

[DHCP]: Set to [Off].

[IP Address]: Enter the address.

[Subnet Mask]: Enter the subnet mask in decimal representation (0 to 255).

[Default Gateway]: Enter the address.

[Auto-IP]: Set to [Off].

When using the Auto-IP, enter "0.0.0.0" in [IP Address].

#### **IMPORTANT**

After changing the setting, restart the network from System Menu, or turn the machine OFF and then ON.

Restart Network (page 8-36)

#### ΝΟΤΕ

Ask your network administrator for the IP address in advance, and have it ready when you configure this setting.

In the following cases, set the IP address of DNS server on the Command Center RX.

- When using the host name with "DHCP" setting set to "Off"
- When using the DNS server with IP address that is not assigned by DHCP automatically.

Setting the IP Address of the DNS Server, refer to the following:

Command Center RX User Guide

## **Configuring the Wireless Network**

When the wireless network function is available on the machine and the connection settings are configured, it is possible to print or send in a wireless network (wireless LAN) environment. The configuration methods are as follows:

Configuration Method	Description	Reference Page
Configuring the Connection from the Operation Panel on This Machine	Use Quick Setup Wizard when configuring the network in a wizard-style screen, without setting individually in System menu.	Quick Setup Wizard (page 2-35)
	Use Wi-Fi Settings or Wireless Network to configure the network in details from System menu.	Wi-Fi Settings (page 8-26)
Setting the Connection by Using the Wi-Fi Setup Tool	This is the tool included in the Product Library. You can configure the connection according to the instructions provided by the wizard.	Setting the Connection by Using the Wi-Fi Setup Tool (page 2-26)
Configuring Connections on the Web Page	The connection can be set from the Command Center RX.	Command Center RX User Guide

#### 🚫 NOTE

On a model with a Wi-Fi function, change the settings in "Primary Network (Client)" appropriately if you switch to other than a wired network interface.

➡ Interface Block Setting (page 8-36)

#### Setting the Connection by Using the Wi-Fi Setup Tool

To send the Wi-Fi settings configured in the Wi-Fi Setup Tool to the machine, connect the computer or handheld device with the machine locally. The connection methods are wired connection via LAN cable and wireless LAN connection (Wi-Fi Direct).

#### 💽 ΝΟΤΕ

- Before using the Wi-Fi Setup Tool, connect your computer to this machine locally with wired LAN cable or Wi-Fi Direct.
- To use Wi-Fi Direct, confirm that the Wi-Fi Direct is enabled (Wi-Fi Direct is set to [**ON**]) and Restart Network from the operation panel, before your computer will be connected to this machine with Wi-Fi Direct.
- To use a wired LAN cable directly connected to the machine, the Auto-IP (Link-local) address will be assigned to the machine and the computer. This machine applies Auto-IP as the default settings.
- · Configure the settings on the operation panel if your computer supports WPS.
  - ➡ <u>Wi-Fi Settings (page 8-26)</u>

#### Wired Connection by Using LAN Cable

#### Connect the machine with a computer

- 1 Connect the machine with a computer via LAN cable when the machine is powered on.
- 2 Turn on the computer.

IP address (link local address) of the machine and computer is generated automatically.



#### 💽 ΝΟΤΕ

- Installation on Windows must be done by a user logged on with administrator privileges.
- If the "Welcome to the Found New Hardware Wizard" dialog box displays, select [Cancel].
- If the autorun screen is displayed, click [Run setup.exe].
- If the user account management window appears, click [Yes] ([Allow]).

#### 3 Display the screen.



- 1 Click [View License Agreement] and read the License Agreement.
- 2 Click [Accept].

#### **4** Select [Maintenance].



## 5 [Wi-Fi Setup Tool] > [OK]

#### **6** Configure the settings.

- 1 [Do not use automatic configuration] > [Next] > [Next]
- 2 [Use LAN cable] > [Next] > [Next]

#### 3 [Easy setup] > [Next]

The machine is detected.

#### 💽 ΝΟΤΕ

- Only one machine can be searched using Wi-Fi Setup Tool. It may take times to search the machine.
- If the machine is not detected, select [Advanced setup] > [Next]. Select [Express] or [Custom] as device discovery method and specify the IP address or host name to search the machine.
- 4 Select the machine > [Next]
- **5** Select [**Use the device settings.**] on [**Authentication mode**], and enter the login user name and password. Login user name and Password are both Admin.
- 6 Configure the communication settings > [Next]
- 7 Change the settings of access point as necessary > [Next]

The network is configured.

#### Wireless LAN Connection by Using Wi-Fi Direct

Δ

#### **1** Display the screen.

[System Menu/Counter] key > [System/Network] > [Network] > [Wi-Fi Direct Settings] > [Wi-Fi Direct]

#### 2 Configure the settings.

[On] > [OK]

#### **Restart the network.**

[System Menu/Counter] key > [System/Network] > [Network] > [Restart Network] > [Yes]

#### Connect a computer or a handheld device with the machine.

Setting Wi-Fi Direct (page 2-30)

#### **5** Insert the DVD.



#### 🔇 NOTE

- Installation on Windows must be done by a user logged on with administrator privileges.
- If the "Welcome to the Found New Hardware Wizard" dialog box displays, select [Cancel].
- If the autorun screen is displayed, click [Run setup.exe].
- If the user account management window appears, click [Yes] ([Allow]).

#### 6 Display the screen.



- 1 Click [View License Agreement] and read the License Agreement.
- 2 Click [Accept].

#### **7** Select [Maintenance].

#### 8 [Wi-Fi Setup Tool] > [OK]

* total	
NAME AND ADDRESS OF AD	
	1
*	
	2
	Á
Bell 1	ALC: NO. OF CO.

#### **9** Configure the settings.

- 1 [Do not use automatic configuration] > [Next] > [Next]
- 2 [Wi-Fi Direct] > [Next] > [Next]
- 3 [Advanced setup] > [Next]

Select [**Express**] or [**Custom**] as device discovery method and specify the IP address or host name to search the machine.

- 4 Select the machine > [Next]
- 5 Select [Use the device settings.] on [Authentication mode], and enter the login user name and password. Login user name and Password are both Admin.
- 6 Configure the communication settings > [Next]
- 7 Change the settings of access point as necessary > [Next]

The network is configured.

## **Setting Wi-Fi Direct**

When the wireless network function is available on the machine, setting Wi-Fi Direct enables you to print from the Wi-Fi Direct environment. The configuration methods are as follows:

#### Configuring the Connection from the Operation Panel on This Machine

Connecting to Computers or Handheld Devices that Support Wi-Fi Direct

#### 1 Display the screen.

[System Menu/Counter] key > [System/Network] > [Network] > [Wi-Fi Direct Settings] > [Wi-Fi Direct]

#### 2 Configure the settings.

[On] > [OK]



#### Restart the network.

[System Menu/Counter] key > [System/Network] > [Network] > [Restart Network] > [Yes]

## 4 Specify the machine name from the computer or handheld device.

If a confirmation message appears on the operation panel of the machine, select [**Yes**]. The network between this machine and the handheld device is configured.

#### Connecting to Computers or Handheld Devices Unsupported Wi-Fi Direct

Here, we'll explain the procedures for connecting to iOS handheld devices.

#### **1** Display the screen.

[System Menu/Counter] key > [System/Network] > [Network] > [Wi-Fi Direct Settings] > [Wi-Fi Direct]

#### Configure the settings.

[On] > [OK]

#### **3** Restart the network.

[System Menu/Counter] key > [System/Network] > [Network] > [Restart Network] > [Yes]

#### [Home] key > [Task Screen] > [Wi-Fi Direct]

**5** Note the network name (SSID), IP address, and password.

**6** Configure the handheld device.

- 1 [Settings] > [Wi-Fi]
- 2 Select the network name (SSID) appeared in step 5 from the list.
- Enter the password that was provided in step 5 > [Connect]
   The network between this machine and the handheld device is configured.

#### **Configuring the Connection by Using Push Button**

When your computer or handheld device does not support Wi-Fi Direct but supports WPS, you can configure the network using push button.

#### **1** Display the screen.

[System Menu/Counter] key > [System/Network] > [Network] > [Wi-Fi Direct Settings] > [Wi-Fi Direct]

#### 2 Configure the settings.

[On] > [OK]

#### **3** Restart the network.

[System Menu/Counter] key > [System/Network] > [Network] > [Restart Network] > [Yes]

#### [Home] key > [Task Screen] > [Wi-Fi Direct]

# **5** Press the push button on the computer or handheld device and select [Push Button] on the screen of operation panel simultaneously.

The network between this machine and the computer or handheld device is configured.

#### **IMPORTANT**

You can connect up to three handheld devices at the same time using Wi-Fi Direct setting. When the devices that support Wi-Fi Direct are connected, if you want to connect other device, disconnect the already-connected devices from the network. The disconnection methods are as follows:

- Disconnect the network from the computer or handheld computer
- · Disconnecting all devices from the network on the operation panel

Select [Home] key > [Task Screen] > [Wi-Fi Direct] > [Connected Device List] > [Disconnect All]

- Configuring auto disconnecting time from the System menu
  - ➡ <u>Wi-Fi Direct Settings (page 8-26)</u>
- Configuring auto disconnecting time from the Command Center RX
  - Command Center RX User Guide

## **Energy Saver function**

If a certain period of time elapses after the machine is last used, the machine automatically enters sleep mode, which minimizes power consumption. If the machine is not used while in sleep mode, the power automatically turns off.

#### ΝΟΤΕ

If user login administration is enabled, you can only change the settings by logging in with administrator privileges. If user login administration is disabled, the user authentication screen appears. Enter a login user name and password, and select [Login].


The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

### Sleep

To enter Sleep, select the [**Energy Saver**] key. Touch panel and all indicators on the operation panel will go out to save a maximum amount of power except the Energy Saver indicator. This status is referred to as Sleep.



If print data is received during Sleep, the machine automatically wakes up and starts printing.

Also when fax data arrives while the machine is in Sleep, the machine automatically wakes up and starts printing. To resume, perform the following actions.

• Select the [Energy Saver] key.

The machine will be ready to operate within 13 seconds.

Note that ambient environmental conditions, such as ventilation, may cause the machine to respond more slowly.

## **Auto Sleep**

Auto Sleep automatically switches the machine into Sleep if left idle for a preset time.

The amount of time before entering Sleep is as follows.

• 1 minute (default setting).

To change the preset sleep time, refer to the following:

Quick Setup Wizard (page 2-35)

## **Sleep Rules (models for Europe)**

You can set whether sleep mode operates for each function. When the machine enters sleep mode, the ID card cannot be recognized.

For more information on Sleep Rules settings, refer to the following:

Sleep Rules (models for Europe) (page 8-39)

### Sleep Level (Energy Saver and Quick Recovery) (models except for Europe)

For sleep level, you can toggle between the following two modes: Energy Saver mode and Quick Recovery mode. The default setting is Energy Saver mode.

Energy Saver mode reduces power consumption even more than Quick Recovery mode, and allows Sleep Mode to be set separately for each function. The ID card cannot be recognized.

To resume, select the [**Energy Saver**] key on the operation panel. If print data is received during Sleep, the machine automatically wakes up and starts printing.

For more information on Sleep Level settings, refer to the following:

Quick Setup Wizard (page 2-35)

## **Power Off Rule (models for Europe)**

The Power Off Rule is used to stop the power from automatically turning off.

The default preset time is 3days.


For more information on Power Off Rule settings, refer to the following:

Power Off Rule (models for Europe) (page 8-40)

## **Quiet Mode**

Lower print speed for quiet processing. Select this mode when the running noise is uncomfortable.

When the [Quiet Mode] key is selected, the [Quiet Mode] key blinks and Quiet Mode is enabled.



#### 

The processing speed will be slower than normal when in Quiet Mode.

## **Quick Setup Wizard**

For FAX functions, paper settings, Energy Saver functions and network settings, the following settings can be configured in a wizard-style screen.

FAX Setup	Configures basic fax settings.			
	FAX Operation Guide			
	1. Dialing/RX Mode		Dialing Mode <sup>*1</sup>	
			Reception Mode	
			Auto (DRD) <sup>*2</sup>	
	2. Local FAX Info		Local FAX Name	
			Local FAX Number	
			Local FAX ID	
			тті	
	3. Sound		Speaker Volume	
			Monitor Volume	
			Job Finish Buzzer	
	4. Rings		Normal <sup>*3</sup>	
			Answering Machine <sup>*3</sup>	
			FAX/TEL Switch <sup>*3</sup>	
	5. Redial		Retry Times	
Paper Setup	Configures the paper size and media type of paper to be used in cassettes and multipurpose tray.			
	1. Cassette 1		Paper Size	
			Media Type	
	2. Cassette 2 <sup>*4</sup>		Paper Size	
			Media Type	
	3. MP Tray		Paper Size	
			Media Type	
Energy Saver Setup	Configures sleep mode.			
	1. Sleep Mode		Sleep Timer	
			Sleep Level (models except for Europe)	
Network Setup	Configures network settings.			
	1. Network	Wi-Fi <sup>*5</sup>	Wi-Fi	
			Available Network	
		Wired Network	Obtain IP Address	
			IP Address <sup>*6</sup>	
			Subnet Mask <sup>*6</sup>	
			Default Gateway <sup>*6</sup>	

\*1 Inch version only.

\*2 DRD reception mode is available for some countries.

\*3 This setting does not appear in some regions.

\*4 Displayed only when the optional paper feeder is installed.

\*5 This function is displayed when the wireless network function is available on the machine.

\*6 Not displayed when "Obtain IP Address" is set to [Auto (DHCP)].

#### ΝΟΤΕ

If the user authentication screen appears, enter your login user name and login password and select [Login]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

#### Display the screen.

[System Menu/Counter] key > [Quick Setup Wizard]

#### **?** Select a function.

#### 3 (

#### Configure the settings.

Start the wizard. Follow the instructions on the screen to configure settings.

#### NOTE

If you experience difficulty configuring the settings, refer to the following:

→ Help Screen (page 2-20)

Control	Description
End	Exits the wizard. Settings configured so far are applied.
Previous	Returns to the previous item.
Skip	Advances to the next item without setting the current item.
Next	Advances to the next screen.
Back	Returns to the previous screen.
Complete	Register the settings and exit the wizard.

## **Installing Software**

Install appropriate software on your PC from the included DVD (Product Library) if you want to use the printer function of this machine or perform TWAIN / WIA transmission or Network FAX transmission from your PC.

## **Software on DVD (Windows)**

You can use either [Express Install] or [Custom Install] can be selected for the installation method. [Express Install] is the standard installation method. To install components that cannot be installed by [Express Install], use [Custom Install].

For details on Custom Installation, refer to the following:

Custom Install (page 2-40)

Software	Description	Express Install
KX DRIVER	This driver enables files on a computer to be printed by the machine. Multiple page description languages (PCL XL, KPDL, etc.) are supported by a single driver. This printer driver allows you to take full advantage of the features of the machine. Use this driver to create PDF files.	0
KX XPS DRIVER	This printer driver supports the XPS (XML Paper Specification) format developed by Microsoft Corporation.	-
KPDL mini-driver/PCL mini-driver	This is a Microsoft MiniDriver that supports PCL and KPDL. There are some restrictions on the machine features and option features that can be used with this driver.	-
FAX Driver	This makes it possible to send a document created in a computer software application as a fax via the machine.	-
Kyocera TWAIN Driver	This driver enables scanning on the machine using a TWAIN-compliant software application.	0
Kyocera WIA Driver	WIA (Windows Imaging Acquisition) is a function of Windows that enables reciprocal communication between an imaging device such as a scanner and an image processing software application. An image can be acquired using a WIA-compliant software application, which is convenient when a TWAIN-compliant software application is not installed in the computer.	-
KYOCERA Net Viewer	This is a utility that enables monitoring of the machine on the network.	-
Status Monitor	This is a utility that monitors the printer status and provides an ongoing reporting function.	0
File Management Utility	This makes it possible to send and save a scanned document to a specified network folder.	-
KYOCERA Net Direct Print	This makes it possible to print a PDF file without starting Adobe Acrobat/Reader.	-
FONTS	These are display fonts that enable the machine's built-in fonts to be used in a software application.	0

#### NOTE

- Installation on Windows must be done by a user logged on with administrator privileges.
- WIA Driver and KX XPS DRIVER cannot be installed on Windows XP.

## **Installing Software in Windows**

#### **Express Install**

The following procedure is an example for installing the software in Windows 8.1 using [Express Install].

For details on Custom Installation, refer to the following:

Custom Install (page 2-40)


1



#### 🔊 NOTE

- Installation on Windows must be done by a user logged on with administrator privileges.
- If the "Welcome to the Found New Hardware Wizard" dialog box displays, select [Cancel].
- If the autorun screen is displayed, click [Run setup.exe].
- If the user account management window appears, click [Yes] ([Allow]).

#### **2** Display the screen.



- 1 Click [View License Agreement] and read the License Agreement.
- 2 Click [Accept].

3

Select [Express Install].

#### Install the software.

2 	4ic
2         2	
LHC .	3

You can also select [**Use host name for port name**] and set to use the host name of the standard TCP/IP port. (A USB connection cannot be used.)

#### **IMPORTANT**

If Wi-Fi or Wi-Fi Direct is enabled, be sure to specify the IP address for the port name. Installation may fail if the host name is specified.

#### 🚫 NOTE

- The machine cannot be detected unless it is on. If the computer fails to detect the machine, verify that it is connected to the computer via a network or USB cable and that it is turned on and click C (Reload).
- If the Windows security window appears, click [Install this driver software anyway].
- To install Status Monitor on Windows versions preceding Windows 8, it is necessary to install Microsoft .NET Framework 4.0 beforehand.



#### **5** Finish the installation.

and an markets		
100	(brail)	
Contraction (Section 1)	Tradicity .	-
🛃 ya dan kanala kanala	- autor	
/ Laula Horina 1	2 diates	
- 10676	T-skilled	
d news	. marint	
i 🗖 🕸 Kodulariyaya (		_
t ∓iĝis torenti olisien. t ∓iĝis orojo din cué		

When "Your software is ready to use" appears, you can use the software. To print a test page, click the "Print a test page" checkbox and select the machine.

Click [Finish] to exit the wizard.

#### 🚫 NOTE

When you have selected [**Device settings**] in Windows XP, the dialog box for device setting will appear after [**Finish**] is clicked. Configure the settings for options installed on the machine. Device settings can be configured after the installation is completed.

#### Printer Driver User Guide

If a system restart message appears, restart the computer by following the screen prompts. This completes the printer driver installation procedure.

If you are installing the TWAIN driver, continue by configuring the following:

Setting TWAIN Driver (page 2-47)

#### **Custom Install**

The following procedure is an example for installing the software in Windows 8.1 using [Custom Install].






#### NOTE

- Installation on Windows must be done by a user logged on with administrator privileges.
- If the "Welcome to the Found New Hardware Wizard" dialog box displays, select [Cancel].
- If the autorun screen is displayed, click [Run setup.exe].
- If the user account management window appears, click [Yes] ([Allow]).

#### **2** Display the screen.



- 1 Click [View License Agreement] and read the License Agreement.
- 2 Click [Accept].

#### **3** Select [Custom Install].

#### Install the software.

1 Select the device to be installed.

() 	 2
int.	1

#### **IMPORTANT**

If Wi-Fi or Wi-Fi Direct is enabled, be sure to specify the IP address for the port name. Installation may fail if the host name is specified.


#### ΝΟΤΕ

- The machine cannot be detected unless it is on. If the computer fails to detect the machine, verify that it is connected to the computer via a network or USB cable and that it is turned on and click C (Reload).
- If the desired device does not appear, select [Add custom device] to directly select the device.

**2** Select the driver to be installed.

A Constant	
ter In International Automatica Automatica	- 1
Martin Transferration	3
And Address of the Ad	Contraction of
1001	And Inte

**3** Click [**Utility**] tab and select the utility to be installed.



4 Click [Install].



#### NOTE

To install Status Monitor on Windows versions preceding Windows 8, it is necessary to install Microsoft .NET Framework 4.0 beforehand.



#### **5** Finish the installation.

4	and Party Street, 1	
Distant Construction and some		
<ul> <li>Control</li> <li>Control</li></ul>	Loral Telefol Contore Solare Contore Contore Solare	
1. 日本 - Haba pape 1. 日本 - Haba pape 1. 日本 - Anno - Haba - Haba 1. 日本 - Anno - Haba	l.	
		- Ren -

When "Your software is ready to use" appears, you can use the software. To print a test page, click the "Print a test page" checkbox and select the machine.

Click [Finish] to exit the wizard.

#### 🚫 NOTE

When you have selected [**Device settings**] in Windows XP, the dialog box for device setting will appear after [**Finish**] is clicked. Configure the settings for options installed on the machine. Device settings can be configured after the installation is completed.

#### Printer Driver User Guide

If a system restart message appears, restart the computer by following the screen prompts. This completes the printer driver installation procedure.

If you are installing the TWAIN driver, continue by configuring the following:

➡ Setting TWAIN Driver (page 2-47)

### **Uninstalling the Software**

Perform the following procedure to delete the Software from your computer.

#### 阈 ΝΟΤΕ

Uninstallation on Windows must be done by a user logged on with administrator privileges.

#### **1** Display the screen.

Click [**Search**] in charms, and enter "Uninstall Kyocera Product Library" in the search box. Select [**Uninstall Kyocera Product Library**] in the search list.

#### 💽 NOTE

In Windows 7, click [Start] button on the Windows and then select [All Programs], [Kyocera], and [Uninstall Kyocera Product Library] to display the Uninstall Wizard.

#### 2 Uninstall the software.

Place a check in the check box of the software to be deleted.

NACON Websites in the Self	anini Ramma P	Viene		
Provident discrimination of all the state balance				
C Secol		1		
		1'		
_			2	

#### **3** Finish uninstalling.

If a system restart message appears, restart the computer by following the screen prompts. This completes the software uninstallation procedure.

#### NOTE

- The software can also be uninstalled using the Product Library.
- In the Product Library screen, click [**Uninstall**], and follow the on-screen instructions to uninstall the software.

## **Installing Software in Mac Computer**

The machine's printer functionality can be used by a Mac computer.

#### NOTE

- Installation on Mac OS must be done by a user logged on with administrator privileges.
- When printing from a Macintosh computer, set the machine's emulation to [KPDL] or [KPDL(Auto)].
- Printer (page 8-24)
- If connecting by Bonjour, enable Bonjour in the machine's network settings.
- Bonjour (page 8-30)
- In the Authenticate screen, enter the name and password used to log in to the operating system.
- · When printing via AirPrint, you do not have to install the software.



Double-click the [Kyocera] icon.



#### **Display the screen.**

	C. B. M. AND ST.	A. 107 Jan 1411	(*)		The second	a ha shi a ha	
III dinti	M .	in the second se	1	ili and	2	and the second	

Double-click [Kyocera OS X x.x] depending on your Mac OS version.

#### **Install the Printer Driver.** 3

86.2 ·	The Designment of the local data and the local data
Remains "	na in an ann an Anna an Anna an Anna
I the factor of the	
4.62	The set of the definition of the set of the
0.24. Aut 10.000	
Contraction of the second	
1 Barrense	
SOUCHES.	
144400000	Contract Lange

Install the printer driver as directed by the instructions in the installation software.

This completes the printer driver installation.


If a USB connection is used, the machine is automatically recognized and connected. If an IP connection is used, the settings below are required.

#### **1** Configure the printer.

1 Open System Preferences and add the printer.

and the second s	Million and Annual A
	2
# # @ # # # # # <b>@</b> @	Construction of the local division of the lo

2 Select [**Default**] and click the item that appears in "Name" and then select the driver in "Use".



#### 

When using an IP connection, click the IP icon for an IP connection and then enter the host name or IP address. The number entered in "Address" will automatically appear in "Name". Change if needed.

**3** Select the options available for the machine.



4 The selected machine is added.



## **Setting TWAIN Driver**

Register this machine to the TWAIN Driver. Instructions are based on interface elements as they appear in Windows 8.1.

#### 1 Display the screen.

1 Click [Search] in charms, and enter "TWAIN Driver Setting" in the search box. Select [TWAIN Driver Setting] in the search list. TWAIN Driver screen appears.

#### NOTE

In Windows 7, select [Start] button on the Windows, [All Programs], [Kyocera] and then [TWAIN Driver Setting].

#### 2 Click [Add].




#### 2

#### Configure TWAIN Driver.

	(Network)
1- 2-	-4
3-	
5-	The constraints are a second and the second area and the second ar
	6 A

- 1 Enter the machine name.
- 2 Select this machine from the list.
- 3 Enter the machine's IP address or host name.
- 4 Set units of measurement.
- 5 When using SSL, select the checkbox beside SSL.
- 6 Click [OK].



- 1 Enter the machine name.
- 2 Select this machine from the list.
- 3 Set units of measurement.
- 4 Set the Compression Level.
- 5 Click [**OK**].

#### NOTE

When the machine's IP address or host name is unknown, contact Administrator.

### **3** Finish registering.

1 here	The .	101-006-0
1 carrier	ant in the figure	
		44.
		1000

### 

Click [Delete] to delete the added machine. Click [Edit] to change names.

### **Setting WIA Driver**

Register this machine to the WIA Driver. Instructions are based on interface elements as they appear in Windows 8.1.

#### **1** Display the screen.

1 Click [Search] in charms, and enter "View scanners and cameras" in the search box. Select [View scanners and cameras] in the search list then the Scanners and Cameras screen appears.

#### 💽 NOTE

In Windows 7, click [Start] button on the Windows and enter [Scanner] in [Program and File Search]. Click [View scanners and cameras] in the search list then the Scanners and Cameras screen appears.

2 Select the same name as this machine from WIA Drivers, and click [Properties].

t. Teal (			-
for a set	1 <b>5</b> .		
	J	2	
1.65	12-12-12	2	

#### **2** Configure WIA Driver.

(Network)

An Stress

- 1 Click the [Settings] tab.
- 2 Enter the machine IP addresses or host name.
- 3 When using SSL, select the checkbox beside SSL.
- 4 Set units of measurement.
- 5 Click [OK].




- 1 Click the [Settings] tab.
- 2 Set the Compression Level.
- 3 Set units of measurement.
- 4 Click [OK].

## **Checking the Counter**

Check the number of sheets printed and scanned.

#### **1** Display the screen.

[System Menu/Counter] key > [Counter]



## **Additional Preparations for the Administrator**

In addition to the information provided in this chapter, the administrator of this machine should check the following, and configure the settings as needed.

## Sending Documents to a PC

#### To Send to a Shared Folder (Send to Folder (SMB))

To send a document that has been loaded, you need to create a shared folder to receive the document on your computer.

Preparation for Sending a Document to a Shared Folder in a PC (page 3-10)

#### To E-mail Scanned Images (Send as E-mail)

You can send a scanned original image as an E-mail attachment.

E-mail Settings (page 2-58)

## **Strengthening the Security**

This machine is shipped with two default users registered one with Machine Administrator rights, and another with Administrator rights.Logging in as this user will allow you to configure all settings; therefore, please change the login user name and password.

In addition, this machine is equipped with user authentication function, which can be configured to limit the access to this machine to only those who have a registered login name and password.

User Authentication and Accounting (User Login, Job Accounting) (page 9-1)

I want to	Function	Reference page
Restrict the users of the machine.	User Login	page 9-2
	Auto Panel Reset	page 8-38
	ID Card Settings <sup>*1</sup>	page 9-25
Restrict the basic functions that can be used.	Group Authorization Set.	<u>page 9-15</u>
Prevent the data stored in the machine from being leaked.	PDF Encryption Functions	page 6-28
Protect the transmission from interception and wiretapping.	IPP over SSL	page 8-33
	HTTPS	page 8-32
	LDAP Security	Refer to the Command Center RX User Guide.
	SMTP Security	page 8-35
	POP3 Security	page 8-35
	FTP Encrypted TX	page 6-33
	Enhanced WSD over SSL	page 8-34
	IPSec	page 8-30
	SNMPv3	<u>page 8-32</u>

\*1 The optional Card Authentication Kit is required.

## **Command Center RX**

If the machine is connected to the network, you can configure various settings using Command Center RX.

This section explains how to access Command Center RX, and how to change security settings and the host name.

#### Command Center RX User Guide

#### 💽 NOTE

To fully access the features of the Command Center RX pages, enter the User Name and Password and click [Login]. Entering the predefined administrator password allows the user to access all pages, including Document Box, Address Book, and Settings on the navigation menu. The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)

Login User Name: Admin Login Password: Admin

Settings that the administrator and general users can configure in Command Center RX are as follows.

Setting	Description	Administ- rator	General User
Device Information	The machine's structure can be checked.	0	0
Job Status	Displays all device information, including print and scan jobs, storing jobs, scheduled jobs, and job log history.	0	0
Document Box <sup>*1</sup>	Configures settings related to the Job Box.	0	-
Address Book	Create, edit, or delete addresses and address groups.	0	⊖ <sup>*2</sup>
Device Settings	Configure the advanced settings of the machine.	0	-
Function Settings	Configure the advanced function settings.	0	-
Network Settings	Configure the network advanced settings.	0	-
Security Settings	Configure the security advanced settings.	0	-
Management Settings	Configure the advanced management settings.	0	-

\*1 Expansion memory or an SD/SDHC memory card is required.

\*2 The logged in user may not be able to configure some settings, depending on the permissions of the user.

#### NOTE

Here, information on the FAX settings has been omitted.

FAX Operation Guide

## **Accessing Command Center RX**

#### Display the screen.

- 1 Launch your Web browser.
- 2 In the address or location bar, enter the machine's IP address or the host name.

Click in the following order to check the machine's IP address and the host name.

[Device Information] in the home screen > [Identification/Wired Network]

Examples: https://192.168.48.21/ (for IP address) https://MFP001 (if the host name is "MFP001")

Com	mand Cent	er RXC	Modal : 1 is 3 More - Lateniko :	
1122	Fry de	v Transfer	A Listuphies Anstatopiese es	G
Userhave	Unite this	_		
Televerd	Testa Testa	2011.4 8	nah.	
	<b>B</b> 500 M		Seeds.	
directiones ()	12 -12		-0.0 h	
diese >	Stan Verage		Seed.	

The web page displays basic information about the machine and Command Center RX as well as their current status.

#### NOTE

If the screen "There is a problem with this website's security certificate." is displayed, configure the certificate.

#### Command Center RX User Guide

You can also continue the operation without configuring the certificate.

#### **2** Configure the function.

Select a category from the navigation bar on the left of the screen.

#### 🚫 NOTE

To fully access the features of the Command Center RX pages, enter the User Name and Password and click [Login]. Entering the predefined administrator password allows the user to access all pages, including Document Box, Address Book, and Settings on the navigation menu. The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)

Login User Name: Admin Login Password: Admin

## **Changing Security Settings**

**1** Display the screen.

- 1 Launch your Web browser.
- In the address or location bar, enter the machine's IP address or the host name.
   Click in the following order to check the machine's IP address and the host name.
   [Device Information] in the home screen > [Identification/Wired Network]
- 3 Log in with administrator privileges.



The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)

Login User Name: Admin Login Password: Admin

4 Click [Security Settings].

#### **2** Configure the Security Settings.

From the [Security Settings] menu, select the setting you want to configure.

Light	Research Streets Streets		_	
	International State			
The Passage	H <sup>ree</sup> cox	Solet M II - MA	Patricia	
-	1.50 Darka	() Olvek	@Uddets	_
Egiberariahanataa >	1.58(H-10 <sup>+</sup> )	Oracle	@ Cirera	
States 3	USD Glaike	Olive.	estates.	
Constant like (	Lass Cynodice Penal			
ALENSE DO.M. >	Chord and Health in	Usi pet		<b>X</b>
(Haraverhear )	Distor Country			
Antorio alingo	Display Jobs Distail Status	Show M		Set 1
Carbo Sebar >	(16004) 4005 (160°	Sine /4		v
Researchanter >	Disoley FAX Log	⊛ Qav Al	C (BrA	
Diseases -	Automatical ending endings			
United States	Una Acata Lata ( SA ata			
CARDING B	Loojand Folicji :	⇒ Qa	16 CB	
Henrik Satada Derikasia	Harden in Statings			
E- W	These of the Parison	110.04	12040	

#### **NOTE**

For details on settings related to certificates, refer to the following:

Command Center RX User Guide

## **Changing Device Information**

**1** Display the screen.

- 1 Launch your Web browser.
- In the address or location bar, enter the machine's IP address or the host name.
   Click in the following order to check the machine's IP address and the host name.
   [Device Information] in the home screen > [Identification/Wired Network]
- 3 Log in with administrator privileges.



The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)

Login User Name: Admin Login Password: Admin

4 From the [Device Settings] menu, click [System].

com	mand Center	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	dan : 4 Muniare Alfonti	
😤 Usano -	Contra Service - Ogerere	44	109.04.91 123.727 - 67 19 19	6
= +++ =	Coron Letter	_		-
	3 Cellos Information	Texaserite		
No: Proverlar	Asse Hunder			_
Olevice riceration 3	Lacator :	1		司
Jacona >	Colora:			
Byersawa 1	Larguege:	$[\exists \phi \in (lepson x)]$	2	Ê
- BADIOR BAD	www.comment.com	3907 M	10.00	
Normalian >	RAM Disk Sta	[0: VB (1-6	41	
	орасы такалар	Ficked		1
here the v	US2 Keyboeix Type	[J.S.Decisio	<u></u>	ŧ.
Partolicement	owende oan atar:	Corr	8.00	
Edonal Document becage Suscerifying	Hassannal		0.00	
DataTine	HINRY LINE	we separate a	89)	
20ku	Defail: So win 11	[] izine/		

#### 2

#### Specify the host name.

Enter the device information, and then click [Submit].

#### **IMPORTANT**

After changing the setting, restart the network or turn the machine OFF and then ON.

To restart the network, click [Reset] in the [Management Settings] menu, and then click [Restart Network] in "Restart".

## **E-mail Settings**

By configuring the SMTP settings, it is possible to send the images scanned by the machine as E-mail attachments and to send E-mail notices when jobs have been completed.

To use this function, this machine must be connected to a mail server using the SMTP protocol.

In addition, configure the following.

- SMTP settings Item: "SMTP Protocol" and "SMTP Server Name" in "SMTP"
- The sender address when the machine sends E-mails Item: "Sender Address" in "E-mail Send Settings"
- The setting to limit the size of E-mails Item: "E-mail Size Limit" in "E-mail Send Settings"

The procedure for specifying the SMTP settings is explained below.


#### Display the screen.

Display the SMTP Protocol screen.

- 1 Launch your Web browser.
- In the address or location bar, enter the machine's IP address or the host name.
   Click in the following order to check the machine's IP address and the host name.
   [Device Information] in the home screen > [Identification/Wired Network]
- **3** Log in with administrator privileges.

Admin Login	Beece S
🖉 Uwitani	Device
Acher	
Passoan	
- 2981	$\geq$

The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)



4 From the [Network Settings] menu, click [Protocol].

Laged	Phylopol Collings			
	Print Phylicial A			
	NADCUI.	(¥ 3)	001	
Part Tapatha	" "Value" in Holevan	IV March Hartwart March Hartwart March Detwart	2** H	
Lind Ostantino Anno 2	Weat a star	KV/Het forten	- 51	
Weterin >	Convert:		- 1	
- Price A	1 60	10.00	0.00	
Dire stand Des 🔹 👌	Assiliable Network:	i⊅ Wine Hetsak R washing	28 MH)	
Act was book 0	FTP Servic (Respire)	-96 (m)	$\odot 07$	
Same same >	Weaton Helesate.	[∠] When Hermonic [2] We B Datest	ઝલ્લના	
	1777 -	(8. Dr)		
1 Binnin Seiner 🤌	War old fair. He fee an	ig: Witco Hickson, ig: Wit∩ Direct;	$\overline{\mathbf{N}} \in \mathbf{U}$	11
Manage Standing -	The Chemistry	<u></u>		
· Taxati	17P com 30	18. M	0.07	
2		terraine The second section production of the second section	Card Training Contact Control	
Maan 15h	Astalia dia Nativopot	RZ voltas Heatstars RZ voltas Heatstars	जेलमः	
Securb Sulary )		Note writing the first second of the second	y said 199 see 221 see	
Contraction and	The Paralest	445 (* - 32/64)		
Baser >	170 we coll centure :	Device Certificate (		3.
(Pro-				

# **2** Configure the settings.

Set "SMTP (E-mail TX)" to [On] in the "Send Protocols".

s MER (El Hall Es)	60 Pm	D OL
	ener Person collination de la	an Beat Bell as
UK TE SECURE	- 4	~
	ter ter 16 die die de ter trager des	ne da <u>recentration</u>
FIF Charles (Lances and	66 <sup>2</sup> M	1.00 M
NIS HUITCH:	<b>un (</b> 1 - 605)	5
There is To	C) 7m	(0) OF
	Least The set there experted to a	ALTER SHOP IN THE
5 ML	$\pm va$	ंश्व
No. 1 March 19	na lla soa	ν.
NSE 8	1991 î. ma	**
	Horas Telesco filoso accertos de Linea	al. Audule ( deur la 246
5 GG	44 Fe	(1) <b>O</b> T
$W_{\rm e}$ is take for $\omega < L$	ion of the second se	Z1#H
5 60	40 fm	0.00

# **3** Display the screen.

Display the E-mail Settings screen.

From the [Function Settings] menu, click [E-mail].

1999	G-mail Sections		
	50° H		
Billion Properties	KNIN ANJON.	: F: 	
Burrennan >	SMPANAKA	strange of the Point of the Point of the	
Job Curas >		Francesche Die second die hier die Stellen die hier bei die 75 in die 1920 - 1920 -	
-	SMTP Not Norther a	<u> 25</u> ](1+65555)	
	SVIT? Setur 7 mesul	10 another	
Address Book >	Rathandication Fratecole	joe 🗸	
Divisio Saninas >	DUTP SHARE:	а <del>т</del> .	
		The second second second	
Ban basalay 🛛 🖉	Canal watch in real	and the second sec	
Composition Online	the new Application	or v	
Marci I		G.e. # 10.1	
Samefree	1073		

## 4

## Configure the settings.

Enter "SMTP" and "E-mail Send Settings" items.

	Setting	Description			
SMTP		Set to send e-mail from the machine.			
	SMTP Protocol	Displays the SMTP protocol settings. Check that "SMTP Protocol" is set to [ <b>On</b> ]. If [ <b>Off</b> ] is set, click [ <b>Protocol</b> ] and set the SMTP protocol to [ <b>On</b> ].			
	SMTP Server Name <sup>*1</sup>	Enter the host name or IP address of the SMTP server.			
	SMTP Port Number	Specify the port number to be used for SMTP. The default port number is 25.			
	SMTP Server Timeout	Set the amount of time to wait before time-out in seconds.			
	Authentication Protocol	To use SMTP authentication, enter the user information for authentication.			
	SMTP Security	Set SMTP security.			
		Turn on "SMTP Security" in "SMTP (E-mail TX)" on the [Protocol Settings] page.			
	Connection Test	Tests to confirm that the E-mail function is operating under the settings without sending a mail.			
	Domain Restriction	To restrict the domains, click the [ <b>Domain List</b> ] and enter the domain names of addresses to be allowed or rejected. Restriction can also be specified by e-mail address.			
POP3	POP3 Protocol	You don't need to set the following items when you only			
	Check Interval	<ul> <li>enable the function of sending e-mail from the machine. Set the following items if you want to enable the function of</li> </ul>			
	Run once now	receiving e-mail on the machine.			
	Domain Restriction	Command Center RX User Guide			
	POP3 User Settings				
E-mail Send Settings	E-mail Size Limit	Enter the maximum size of E-mail that can be sent in kilobytes. When E-mail size is greater than this value, an error message appears and E-mail sending is cancelled. Use this setting if you have set E-mail Size Limit for SMTP server. If not, enter a value of 0 (zero) to enable E-mail sending regardless of the size limit.			
	Sender Address <sup>*1</sup>	Specify the sender address for when the machine sends E-mails, such as the machine administrator, so that a reply or non-delivery report will go to a person rather than to the machine. The sender address must be entered correctly for SMTP authentication. The maximum length of the sender address is 128 characters.			
	Signature	Enter the signature. The signature is free form text that will appear at the end of the E-mail body. It is often used for further identification of the machine. The maximum length of the signature is 512 characters.			
	Function Defaults	Change the function default settings in [Common/Job Default Settings] page.			

\*1 Be sure to enter the items.

# 5 Click [Submit].

# **Registering Destinations**



- 1 Launch your Web browser.
- In the address or location bar, enter the machine's IP address or the host name.
   Click in the following order to check the machine's IP address and the host name.
   [Device Information] in the home screen > [Identification/Wired Network]
- **3** Log in with administrator privileges.



The factory default setting for the default user with administrator privileges is shown below. (Upper case and lower case letters are distinguished (case sensitive).)

Login User Name: Admin Login Password: Admin

4 From the [Address Book] menu, click [Machine Address Book].

Lagest	Oddardan .		_	_	
	Type: Al. S	Assault -	5716	Administ Name	- p
🔁 das Propolitos 🔁 dences reformation 👂	first terr				
State )	Salari Hina Typ	e Name	Dete		
🔁 damest (bar 🔅					
Restore Soci	1				
Nachas Address Bask	2				

5 Click [Add].

#### Populate the fields.

1 Enter the destination information.

Enter the information for the destination you want to register. The fields to populate are the same as when registering via operation panel.

- Registering Destinations in the Address Book (page 3-20)
- 2 Click [Submit].

# **Transferring Data from Our Other Products**

By using the machine's utility, you can smoothly migrate address books when the machine is to be replaced.

This section explains how to transfer data between our products.

# **Migrating the Address Book**

The Address Book registered on the machine can be backed up or migrated using the KYOCERA Net Viewer on the included DVD.

For details on operating the KYOCERA Net Viewer, refer to the following:

KYOCERA Net Viewer User Guide

#### Backing Up Address Book Data to PC

#### Launch the KYOCERA Net Viewer.

#### **2** Create a backup.


1 Right-click on the model name from which you want to back up the Address Book, and select [Advanced] - [Set multiple devices].

a second second	+ Paren	Heal event	
1	in contra In queres Refereix Derice some page		
	Notices and very Gold-Acone		
2 (	Nami tal no settogo Comercia tal no setto		Sea na ultima a cavita a
- U			Minarge replications


2 Select [Custom Mode] and click [Next].

	ALC: NO	
Math-Set Mode Sale: MathSet Role tool		
· Ladam mode		
		2
	1114	Net Stand


3 Select destination device group and click [Next].



4 Select [Device Address Book] and click [Next].



5 Select [Create from device] and remove the checkmark from [Overwrite settings on target device], and then click [Next].



6 Select the model you want to back up, and click [Next].

1 1				13
Bauron Deside Select asserts dansa				
Carles tons	a state	And a second second	and the second	_
(	ALC DESIGN A	met a fue for		
				- 1
			2	
		Chen.		(and it
		1.000.	Net	Garoof (1)

## **NOTE**

If the "Admin Login" screen appears, enter the "Admin Login" and "Login Password", and then click [**OK**]. The default settings are as follows (Upper case and lower case letters are distinguished (case sensitive)).

Login User Name:	Admin
Login Password:	Admin

7 Click on [Save to file].

and the second se	
Conferences One: and set revised disk from	
Construction and a second seco	
Carlors Address Roll	
Heliumi Fuur pircemi	
Source 1	
Committe part new on target devices for	
Schorten See hite Date Fach Seed	

8 Specify the location to save the file, enter the file name, and then click [Save].For "Save as type", make sure to select "XML File".

9 After saving the file, always click [Cancel] to close the screen.

and the second sec	E3
Confirmation Charl and survey and click from	
Ceremengenaa Derberge Dervers Antoneen Bank Redverd Paser site om Generaties set fans en fannet de voer Be	
Schwerber Bennete (2000) Profe Const	D

Please note that selecting [Finish] will write the data to the machine's Address Book.

#### Writing Address Book Data to the Machine



# Launch the KYOCERA Net Viewer.

#### Load the Address Book data. 2


1 Right-click on the model name to which you want to transfer the Address Book, and select [Advanced] - [Set multiple devices].

I have no home	a Patric	Heat country	
1	Proposition Proposition Reference Decrise normal page		
	Mittage Landvets Briefe Kester Cille	-	
20	North follow without Communication and Advanced		Searcy altrips carticar
- 0			Manage spiketises . Manage spiketises . Manage spiketises

2 Select [Custom Mode] and click [Next].

A REAL PROPERTY AND A REAL	
Matte Get Monte Select MattrSet Role tool	
( * Data mate) 1	
	2
	The Art


3 Select destination device group and click [Next].



4 Select [Device Address Book] and click [Next].


	The second se
Betangó Scient settings to caso	
<ul> <li>Jamos Syster Serves</li> <li>Jamos Setuel Serves</li> <li>Jamos Setuel Serves</li> <li>Jamos Setuel Setue</li> <li>Jamos Setue</li> </ul>	2

5 Select [Create from file] and remove the checkmark from [Overwrite settings on target device], and then click [Next].



Selecting the [**Overwrite settings on target device**] checkbox will overwrite the machine's Address Book from entry No.1.

6 Click [Browse] and select the backup Address Book file, and then click [Next].



7 Click [Finish].

Ball M	
Conferences Charl pair setting and did Trees	
Derson group Gerner group Course Addminist Basis Material Proof the Souther and they an target derive by	_
Schwertner Sam herte Voors Produ Vo	

The write process of the Address Book data starts.

8 Once the write process is complete, click [Close]

# **3 Preparation before Use**


This chapter explains the following operations.

Loading Paper	
Precaution for Loading Paper	
Selecting the Paper Feeder Units	
Loading in the Cassette 1	3-4
Loading in the Cassette 2	
Precautions for Outputting Paper	3-9
Paper Stopper	
Preparation for Sending a Document to a Shared Folder in a PC	
Making a note of the computer name and full computer name	
Making a note of the user name and domain name	
Creating a Shared Folder, Making a Note of a Shared Folder	3-12
Configuring Windows Firewall	
Registering Destinations in the Address Book	3-20
Adding a Destination (Address Book)	
Adding a Destination on One Touch Key (One Touch Key)	

# **Loading Paper**

# **Precaution for Loading Paper**

When you open a new package of paper, fan the sheets to separate them slightly prior to loading in the following steps.



Fan the paper, then tap it on a level surface.

In addition, note the following points.

- If the paper is curled or folded, straighten it before loading. Paper that is curled or folded may cause a jam.
- Avoid exposing opened paper to high humidity as dampness can be a cause of problems. Seal any remaining paper after loading in the multipurpose tray or cassettes back in the paper storage bag.
- If the machine will not be used for a prolonged period, protect all paper from humidity by removing it from the cassettes and sealing it in the paper storage bag.

#### **IMPORTANT**

If you copy onto used paper (paper already used for printing), do not use paper that is stapled or clipped together. This may damage the machine or cause poor image quality.


#### 阈 NOTE

If you use special paper such as letterhead, paper with holes or paper with pre-prints like logo or company name, refer to the following:

Paper (page 11-11)

# **Selecting the Paper Feeder Units**

Select the paper feeder units according to the size and type of paper.




No.	Name	Paper Size	Paper Type	Capacity	Page
1	Cassette 1	A4, B5, A5-R, A5, A6, B6, Legal, Oficio II, Letter, Executive, Statement-R,	Plain, Preprinted, Bond, Recycled, Rough, Letterhead, Color,	250 sheets (80 g/m <sup>2</sup> )	<u>page 3-4</u>
2	Cassette 2	Folio, 16K, 216mm×340mm, B5(ISO), Custom	Prepunched, Thick, High Quality, Custom 1 to 8	(60 g/m )	<u>page 3-7</u>

# ΝΟΤΕ


- The number of sheets that can be held varies depending on your environment and paper type.
- You should not use inkjet printer paper or any paper with a special surface coating. (Such paper may cause paper jams or other faults.)
- For higher quality color printing, use special color paper.



# **2** Adjust the paper length guide to the paper size required.





When using Folio, Oficio II or Legal



## ΝΟΤΕ


In some regions the cassette comes with a cover. If the cassette has a cover, open the cover to adjust the guide.






- Before loading the paper, be sure that it is not curled or folded. Paper that is curled or folded may cause paper jams.
- Ensure that the loaded paper does not exceed the level indicator (see illustration above).
- If paper is loaded without adjusting the paper length guide and paper width guide, the paper may skew or become jammed.

# **5** Gently push the Cassette 1 back in.



## 

When Folio, Oficio II, or Legal is used, the cassette will extend out from the machine.



# **6** Display the screen.

[System Menu/Counter] > [Cassette/MP Tray Settings]

# **7** Configure the function.


Select the paper size and paper type.

# **Loading in the Cassette 2**


Pull the Cassette 2 completely out of the machine.




**2** Adjust the paper length guide to the paper size required.



**3** Adjust the position of the paper width guides located on the left and right sides of the Cassette 2.





#### **IMPORTANT**

- Load the paper with the print side facing up.
- After removing new paper from its packaging, fan the paper before loading it in the multipurpose tray.
- Precaution for Loading Paper (page 3-2)
- Before loading the paper, be sure that it is not curled or folded. Paper that is curled or folded may cause paper jams.
- Ensure that the loaded paper does not exceed the level indicator (see illustration above).
- If paper is loaded without adjusting the paper length guide and paper width guide, the paper may skew or become jammed.

#### **5** Gently push the Cassette 2 back in.



#### **6** Display the screen.

[System Menu/Counter] > [Cassette/MP Tray Settings]

## 7 Configure the function.

Select the paper size and paper type

# **Precautions for Outputting Paper**

# **Paper Stopper**

When using paper B5/Letter or larger, open the paper stopper shown in the figure.



# Preparation for Sending a Document to a Shared Folder in a PC

Check the information that needs to be set on the machine and create a folder to receive the document on your computer. Screens of Windows 8.1 are used in the following explanation. The details of the screens will vary in other versions of Windows.

NOTE

Log on to Windows with administrator privileges.

# Making a note of the computer name and full computer name

Check the name of the computer name and full computer name.

#### 1 Display the screen.

In Windows 8.1, right-click **[PC]** in the Start screen and select **[Properties]**. Or, right-click the Window icon and select **[System]**.

In Windows 8, select the desktop in the Start screen, right-click [**Computer**] from [Libraries], and then select [**Properties**].

#### 💽 NOTE

In Windows XP, right-click [**My Computer**] and select [**Properties**]. The [**System Properties**] dialog box appears. Click the [**Computer Name**] tab in the window that appears.

In Windows 7, from [Start] button on the Windows, select [Computer] and then [System Properties].

In Windows 10, right-click [Start] button on the Windows and select [System].

#### Check the computer name.

Computernanc, domain, a	nd workgroup settings	
Computer name:	PDIN	😵 Change settings
Full computer name	PC001abednet.com	
Computer descriptions		

Check the computer name and full computer name.

Screen example: Computer name: PC001 Full computer name: PC001.abcdnet.com

#### Windows XP:

If the full computer name does not have a dot (.), the full computer name and the computer name are the same.

If the full computer name has a dot (.), the text string in front of the dot (.) in the full computer name is the computer name.

Example: PC001.abcdnet.com PC001 is the computer name PC001.abcdnet.com is the full computer name

After checking the computer name, click the **[Close]** button to close the **"System Properties**" screen.

In Windows XP, after checking the computer name, click the [Cancel] button to close the "System Properties" screen.

# Making a note of the user name and domain name

Check the domain name and user name for logging onto Windows.

#### Display the screen.

Click [Search] in charms, and enter "Command Prompt" in the search box. Select [Command Prompt] in the search list.

In Windows 7, from [Start] button on the Windows, select [All Programs] (or [Programs]), [Accessories] and then [Command Prompt].


In Windows 10, right-click [Start] button on the Windows and select [Command Prompt].

The Command Prompt window appears.

#### 2

#### Check the domain name and user name.

At the Command Prompt, enter "net config workstation" and then press [Enter].



Check the user name and domain name.

Screen example: User Name: james.smith Domain Name: ABCDNET

# **Creating a Shared Folder, Making a Note of a Shared Folder**

Create a shared folder to receive the document in the destination computer.

# NOTE

If there is a workgroup in System Properties, configure the settings below to limit folder access to a specific user or group.

1 Select [Settings] in charms on Desktop, and select [Control Panel], [Appearance and Personalization], and then [Folder Options].



In Windows XP, click [My Computer] and select [Folder Options] in [Tools].

In Windows 7, from [Start] button on the Windows, select [Control Panel], [Appearance and Personalization], and then [Folder Options].

In Windows 10, open up a window in File Explorer and select [View], [Options], and then [Folder Options].



Remove the checkmark from [Use Sharing Wizard (Recommended)] in "Advanced settings".

In Windows XP, click the [View] tab and remove the checkmark from [Use Simple File Sharing (Recommended)] in "Advanced settings".

#### Create a folder.

Create a folder on your computer.

For example, create a folder with the name "scannerdata" on the desktop.



#### **2** Configure permission settings.

1 Right-click the "scannerdata" folder, select [Property], and click [Sharing] and [Advanced Sharing].



In Windows XP, right-click the "scannerdata" folder and select [Sharing and Security] (or [Sharing]).

2 Select the [Share this folder] checkbox and click the [Permissions] button.


PHINTER 1
Ann an Chattan
2

In Windows XP, select [Share this folder] and click the [Permissions] button.

- 3 Make a note of the [Share name].
- 4 Click the [Add] button.

L Bernard B		
Contraction (CCC)		
The second se		
a a a a a a a a a a a a a a a a a a a		
l c		
	44.	Tere i a
n ing ang ang ang ang ang ang ang ang ang a		Bady'
1 x ya 100	÷.	-
	26.0	

**5** Specify the location.



1 If the computer name that you made a note of on page is the same as the domain name:

If the computer name is not shown in "From this location", click the [Locations] button, select the computer name, and click the [OK] button.

Example: PC001

If the computer name that you made a note of on page is not the same as the domain name:

If the text after the first dot (.) in the full computer name that you made a note of does not appear in "From this location", click the [Locations] button, select the text after the dot (.), and click the [OK] button.

Example: abcdnet.com

▶ Making a note of the user name and domain name (page 3-11)

2 Enter the user name that you made a note of on page in the text box, and click the [**OK**] button.

Also the user name can be made by clicking the [Advanced] button and selecting a user.

1 Select the user you entered.

3 Press [OK].

2 Select the [Allow] checkbox of the "Change" and "Read" permissions

5 Set the access permission for the user selected.

Protocial de la <b>1</b> Militaria I Patrila acadel	
For same 5 P222	()]]]())))]]]]) Ale: No.
Ano bo	2

In Windows XP, go to step 7.

#### ि NOTE

"Everyone" gives sharing permission to everyone on the network. To strengthen security, it is recommended that you select "Everyone" and remove the "Read" [Allow] checkmark.

6 Click the [OK] button in the "Advanced Sharing" screen to close the screen.

7 Check the details set in the [Security] tab.

No	Cardina Cardona		
Record to a la l	÷ 2		
Distantiant	n sera de con	349	_
ally make	n PCC71-ann h.	54) 	
V strange to me	essensis, tele	LE I	les.
graneses:	0.00	- 1995 (	(M. M. )
	SO 50		•
feed Langue	÷	- 52 -	3
The second se	encie de la companya	196	- 1
(th		-3-	
P, quality in	the state of the	less III	energia de la
Tellink Conserved.			and the second second

- 1 Select the [Security] tab.
- 2 Select the user you entered. If the user does not appear on "Group or user names", click [Edit] button to add user in a similar way of "configuration of permission settings".
- 3 Make sure that checkmarks appear on [Allow] checkbox for the "Modify" and "Read & execute" permissions.
- 4 Click the [Close] button.

In Windows XP, make sure that checkmarks appear on [Allow] checkbox for the "Modify" and "Read & execute" permissions, and click the [OK] button.

# **Configuring Windows Firewall**

Permit sharing of files and printers and set the port used for SMB transmission.

## NOTE

Log on to Windows with administrator privileges.

# **1** Check file and printer sharing.

1 In charms on Desktop, click [Settings], [Control Panel], [System and Security], and then [Windows Firewall].



# NOTE

If the User Account Control dialog box appears, click the [Continue] button.

2 Select the [File and Printer Sharing] checkbox.

+			
8215	$g_{i}^{\mu}$ ). There is the transition is the $\gamma$ -th interaction with a minor density	- Q Cover Central	-
	Allow append a communicate francasti windows Threwsi Traditions and a new direction of selection in 100 areas to see		
	<ul> <li>For the second se</li></ul>	S Department	
	- An event agent to Charles al.	515-12 (Sec. 20)	
	NEW DOOR ST.	2	
	14 Tangk 2+	H P	
	<ul> <li>Definition of the second secon</li></ul>		
	<ul> <li>Bellement Figure - α-based bits (b);</li> <li>Bellement Figure - α-based bits (b);</li> <li>Bellement - and a set (b);</li> </ul>	83	
	[5] etc., Concerning and Recapite 14 (days).		
	Diffect of a stranger Stories Article		
		Contract Contract	
		3	

## **2** Add a port.

1 In charms on Desktop, click [Settings], [Control Panel], [System and Security], and [Check firewall status].



2 Select [Advanced settings].



3 Select [Inbound Rules].




4 Select [New Rules].

÷	and the second se	CONTRACTOR OF STREET, ST.			20 A 1
Co. which Some Labor					
中市 北京 由田田					
🚰 Anders Inter I mår förans	stand fires			Selected	
Be Constants for a		<ul> <li>(p) - e e per calabra como estas Como estas terras de como formas</li> </ul>	34	<ul> <li>Bernen</li> <li>Bernen</li> <li>Bernen</li> <li>Bernen</li> <li>Bernen</li> <li>State</li> <li>State</li> <li>State</li> <li>State</li> </ul>	~

5 Select [Port].

ann Barg an carlige foreach Strand	
-1. reveal	
<ul> <li>Second concerns on the Anna Y and Mignet</li> <li>Problematic Concerns Second Secon</li></ul>	
22	
	Constraint Description (constraints) (condition States contraints) with constraints Of states

6 Select [**TCP**] as the port to apply the rule to. Then select [**Specific local ports**] and enter "445" then click [**Next**].



7 Select [Allow the connection] and click the [Next] button.



8 Make sure all checkboxes are selected and click the [Next] button.

2	and and a second se
Peorl In Scenit: The coldina is of	er har site a store
(Ann. 19 Fear	1 A Constant and set of A Constant of the constant of a special decrement of the constant of
	2
	la par 💶 🔤 👘 kase 👘

9 Enter "Scan to SMB" in "Name" and click [Finish].

÷	And a local data and a local data and a	
None: Vents for next address	ufen di Le ele	
Ven - Los	1 Ante Barris Silli Marris Carlos	
		2

#### In Windows 7

- 1 From [Start] button on the Windows, select [Control Panel], [System and Security], and [Allow a program through Windows Firewall]. If the User Account Control dialog box appears, click the [Continue] button.
- 2 Configure the settings.
  - Configuring Windows Firewall (page 3-15)

#### In Windows XP or Windows Vista

1 In Windows XP, from [Start] button on the Windows, select [Control Panel], and then [Windows Firewall].

In Windows Vista, from [Start] button on the Windows, select [Control Panel], [Security], and then [Turn Windows Firewall on or off].

If the User Account Control dialog box appears, click the [Continue] button.

- 2 Click the [Exceptions] tab and then the [Add port...] button.
- 3 Specify Add a Port settings. Enter any name in "Name" (example: Scan to SMB). This will be the name of the new port. Enter "445" in "Port Number". Select [TCP] for "Protocol".
- 4 Click [OK] button.

#### In Windows 10

1 Right-click [Start] button on the Windows and select [Control Panel], [System and Security], and then [Allow an app through Windows Firewall].

If the User Account Control dialog box appears, click the [Continue] button.

- **2** Configure the settings.
  - Configuring Windows Firewall (page 3-15)

# **Registering Destinations in the Address Book**

Save frequently used destinations to the Address Book or One Touch Keys. The saved destinations can be changed. The destinations are available for Send as E-mail, Send to Folder, and Fax Transmission.

## 💽 ΝΟΤΕ

Registering and editing of the Address Book can also be done in Command Center RX.

➡ Registering Destinations (page 2-62)

# **Adding a Destination (Address Book)**

Add a new destination to the Address Book. There are two registering methods, contacts and groups. When adding a group, enter the group name and select group members from the Address Book.

## NOTE

If user login administration is enabled, you can only edit destinations in the Address Book by logging in with administrator privileges.

#### **Registering a contact address**

A maximum of 100 contact addresses can be registered. Each address can include the information such as destination name, E-mail address, FTP server folder path, computer folder path, and FAX No.

#### Display the screen.

[System Menu/Counter] key > [Address Book/One Touch] > [Address Book] > [ ] > [Contact]

## **2** Add the name.

Enter the destination name to be displayed on the Address Book > [Next]

#### NOTE

Up to 32 characters can be entered. Refer to the following for details on entering characters.

Character Entry Method (page 11-8)

## 3 Add the address.

E-mail Address

[E-mail Address] > Enter the E-mail address > [OK]

#### 🚫 NOTE

Up to 128 characters can be entered. Refer to the following for details on entering characters.

Character Entry Method (page 11-8)

#### The Folder (SMB) Address

#### [SMB] > [Host Name], [Path], [Port], [Login User Name] and [Login Password] > [OK]

## 💽 ΝΟΤΕ

For the computer name, share name, domain name, and user name, enter the information that you noted when you created the shared folder. For details on creating shared folders, refer to the following:

Preparation for Sending a Document to a Shared Folder in a PC (page 3-10)

The table below explains the items to be entered.

ltem	Description	Max. No. of Characters
Host Name	Computer name	Up to 64 characters
Path	Share name For example: scannerdata If saving in a folder in the shared folder: share name\folder name in shared folder	Up to 128 characters
Port	Port number (Normally 445.)	1 - 65535
Login User Name	If the computer name and domain name are the same: User Name For example: james.smith If the computer name and domain name are different: Domain name\User name For example: abcdnet\james.smith	Up to 64 characters
Login Password	Windows logon password (Case sensitive.)	Up to 64 characters

To search for a folder on a PC on the network, select in the following order.

#### [Menu] > [Search Folder from Network] or [Search Folder by Host Name]

If you selected [**Search Folder from Network**], you can search all PCs on the network for a destination.

If you selected [**Search Folder by Host Name**], you can enter the "Domain/Workgroup Name", and "Host Name" to search PCs on the network for the destination.

Up to 500 addresses can be displayed. The login user name and login password entry screen appears.

Select the host name (PC name) that you want to specify in the screen that appears > [Next].

## ΝΟΤΕ

- Refer to the following for details on entering characters.
- Character Entry Method (page 11-8)
- Select [Menu] > [Connection Test] to check the connection to the server you chose. If the
  connection fails, check the entries you made.

#### The Folder (FTP) Address

[FTP] > [Host Name], [Path], [Port], [Login User Name] and [Login Password] > [OK] The table below explains the items to be entered.

ltem	Descriptions	Max. No. of Characters
Host Name	Host name or IP address of FTP server	Up to 64 characters
Path <sup>*1</sup>	Path for the file to be stored For example: User\ScanData If no path is entered, the file is stored in the home directory.	Up to 128 characters
Port	Port number (Normally 21.)	1 - 65535
Login User Name	FTP server login user name	Up to 64 characters
Login Password	FTP server login password	Up to 64 characters

\*1 When the FTP server is based on Linux/UNIX, the path including the sub-folder is combined by the slash "/" not using the back-slash.

#### **NOTE**

- Refer to the following for details on entering characters.
- Character Entry Method (page 11-8)
- Select [Menu] > [Connection Test] to check the connection to the FTP server you chose. If the connection fails, check the entries you made.
- When [SSL] is enabled in [Security Settings], you can select [Menu] > [Connection Test (Encrypted TX)] to check the FTP encrypted transmission connection. If the connection fails, check the entries you made.
- 1 To specify the Address Number, select [Address Number].
- 2 Use [+] / [-] or the numeric keys to enter an address number (001 to 120).

To have the number assigned automatically, enter "000".

#### NOTE

- Address Number is an ID for a destination. A free number can be selected.
- If you specify an address number that is already in use, an error message appears.
- 3 Select [OK].

#### Check if the destination entry is correct > [Save]

The destination is added to the Address Book.

#### **Registering a Group**

Compile two or more contacts into a group. Designations in the group can be added at the same time. When adding a group, a maximum of 20 groups can be added in the Address Book.

# 阈 ΝΟΤΕ

To add a group, you need individually added destinations. Register one or more individual destinations as needed before proceeding. Up to 100 individually registered destinations and a combined total of up to 5 SMB and FTP destination folders can be registered in a single group.

#### Display the screen.

[System Menu/Counter] key > [Address Book/One Touch] > [Address Book] > [ a a solution of the set o

## **2** Add the name.

Enter the group name to be displayed on the Address Book > [Next]

#### 💽 ΝΟΤΕ

Up to 32 characters can be entered. Refer to the following for details on entering characters.

Select the members (destinations).

Character Entry Method (page 11-8)

#### 3

- 1 Select [Member].
- 2 Select [-].
- 3 Select destinations (contacts) to add to the group. The selected destinations are indicated by a checkmark in the check box.

#### 💽 NOTE

Destinations can be sorted or searched by destination name or address number.

- Specifying Destination (page 5-33)
- 4 Select [OK].

If you have more destinations to add, repeat Steps 2 to 4.

- 5 Select [End].
- 6 To specify the Address Number, select [Address Number].
- 7 Use [+] / [-] or the numeric keys to enter an address number (001 to 120).

To have the number assigned automatically, enter "000".

#### 💽 NOTE

- Address Number is an ID for a destination. A free number can be selected.
- If you specify an address number that is already in use, an error message appears.
- 8 Select [OK].

#### Check if the selected destination was added to the group > [Save]

The group is added to the Address Book.

#### **Editing Address Book Entries**

Edit the destinations (contacts) you added to the Address Book.

#### **1** Display the screen.

[System Menu/Counter] key > [Address Book/One Touch] > [Address Book]

## 2 Edit the destination.

#### NOTE

Destinations can be sorted or searched by destination name or address number.

Choosing from the Address Book (page 5-34)

#### **Editing a Contact**

- 1 Select [\_\_\_] for the destination (contacts) to edit.
- Change "Name", "Address Number" and destination type and address.
   <u>Registering a contact address (page 3-20)</u>
- After you have completed the changes, [Save] > [Yes]
   Register the changed destination.

#### **Editing a Group**

- 1 Select [ \_\_\_\_] for the group to edit.
- 2 Change "Name" and "Address Number".
  - Registering a Group (page 3-23)
- 3 Select [Member].
- To delete any destination from the group, select the destination > [ 20 ] > [Yes]
   To add the destination, select [ 21 ].
- 5 After you have completed the changes, [Save] > [Yes] Register the changed group.

#### **Deleting Address Book Entries**

Delete the destinations (contacts) you added to the Address Book.

### **1** Display the screen.

- 1 [System Menu/Counter] key > [Address Book/One Touch] > [Address Book]
- 2 Select a destination or group to delete.

#### NOTE

Destinations can be sorted or searched by destination name or address number.

Choosing from the Address Book (page 5-34)



#### [@] > [Yes]

Delete the contact or group.

# Adding a Destination on One Touch Key (One Touch Key)

Assign a new destination (contact or group) to an one touch key. A maximum of 100 destinations can be registered.

# NOTE

- · Refer to the following for use of One Touch Key.
- Specifying Destination (page 5-33)
- You can add One Touch keys and change their settings on Command Center RX.
- Registering Destinations (page 2-62)


#### **1** Display the screen.

[System Menu/Counter] key > [Address Book/One Touch] > [One Touch Key]

## 2 Add One Touch Keys.

 Select a One Touch Key number (001 to 100) for the destination > [♣] Selecting the [Quick No. Search] key enables direct entry of a One Touch Key number.

Select a One Touch Key with no registered destination.



2 Select a destination (contact or group) to add to the One Touch Key number > [Next] Selecting [\_\_\_] shows the detailed information of the selected destination.

## 💽 ΝΟΤΕ

Destinations can be sorted or searched by destination name or address number.

- Choosing from the Address Book (page 5-34)
- 3 Enter the One Touch Key name displayed in the send base screen > [Next]

## 💽 ΝΟΤΕ

Up to 24 characters can be entered. Refer to the following for details on entering characters.

Character Entry Method (page 11-8)

4 Select [Save].

The destination will be added to the One Touch Key.

#### **Editing One Touch Key**

#### Display the screen.

- 1 [System Menu/Counter] key > [Address Book/One Touch] > [One Touch Key]
- 2 Select a One Touch Key number (001 to 100) to edit. Selecting the [Quick No. Search] key enables direct entry of a One Touch Key number.

The procedure differs depending on the details to be edited.

#### 2 Change the registered information.

#### 1 [Menu] > [Edit] > [Destination]

2 Select a new destination (contact or group). Selecting [\_\_\_] shows the detailed information of the selected destination.

Address Book (All)	A CL	10:10
001 ABCD	123456	
002 EFGH	efg@efg.com	= 1/2
003 📊 IJKL	12345.com	
	11111.com	<b>~</b>
Menu	Cancel	ОК +

#### NOTE

Destinations can be sorted or searched by destination name or address number.

- Specifying Destination (page 5-33)
- 3 [OK] > [Save] > [Yes]

Add the destination to the One Touch Key.

#### **Deleting One Touch Key**

#### Display the screen.

- 1 [System Menu/Counter] key > [Address Book/One Touch] > [One Touch Key]
- 2 Select a One Touch Key number (001 to 100) to edit. Selecting the [Quick No. Search] key enables direct entry of a One Touch Key number.

The procedure differs depending on the details to be edited.

#### **2** Delete the registered information.

Select [ ] > [Yes]

001 AAA	e Touch - One Touch	003 CCC	
	SOL BBB		1
<sup>004</sup> None	005 None	006 None	
<sup>007</sup> None	008 None	009 None	1/9
<sup>010</sup> None	011 None	<sup>012</sup> None	$\sim$

Deletion of the data registered in the One Touch Key.

# **4 Printing from PC**


#### This chapter explains the following topics:

Printer Driver Properties Screen	
Displaying the Printer Driver Help	
Changing the Default Printer Driver Settings (Windows 8.1)	
Printing from PC	
Printing on Standard Sized Paper	
Printing on Non-standard Sized Paper	
Canceling Printing from a Computer	
Printing from the Handheld Device	
Printing by AirPrint	
Printing by Google Cloud Print	
Printing by Mopria	
Printing with Wi-Fi Direct	
Printing Data Saved in the Printer	
Specifying the Job Box from a Computer and Storing the Job	
Printing Documents from Private Print Box	
Deleting the Documents Stored in the Private Print Box	
Printing Document from Stored Job Box	
Deleting the Documents Stored in the Stored Job Box	
Printing Document from Quick Copy Box	
Deleting the Documents Stored in the Quick Copy Box	
Printing Document from Proof and Hold Box	
Deleting the Documents Stored in the Proof and Hold Box	
Monitoring the Printer Status (Status Monitor)	
Accessing the Status Monitor	
Exiting the Status Monitor	
Quick View State	
Printing Progress Tab	4-17
Paper Tray Status Tab	
Toner Status Tab	4-17
Alert Tab	4-18
Status Monitor Context Menu	
Status Monitor Notification Settings	

## **Printer Driver Properties Screen**

The printer driver properties screen allows you to configure a variety of print-related settings.


#### Printer Driver User Guide



No.	Description
1	[Quick Print] tab
	Provides icons that can be used to easily configure frequently used functions. Each time you click an icon, it changes to an image resembling the print results and applies the settings.
	[Basic] tab
	This tab groups basic functions that are frequently used. You can use it to configure the paper size and duplex printing.
	[Layout] tab
	This tab lets you configure settings for printing various layouts, including booklet printing, combine mode, poster printing, and scaling.
	[Imaging] tab
	This tab lets you configure settings related to the quality of the print results.
	[Publishing] tab
	This tab lets you create covers and inserts for print jobs and put inserts between sheets of OHP film.
	[Job] tab
	This tab lets you configure settings for saving print data from the computer to the machine. Regularly used documents and other data can be saved to the machine for easy printing later. Since saved documents can be printed directly from the machine, this function is also convenient when you wish to print a document that you don't want others to see.
	[Advanced] tab
	This tab lets you configure settings for adding text pages or watermarks to print data.
2	[Profiles]
	Printer driver settings can be saved as a profile. Saved profiles can be recalled at any time, so it's a convenient practice to save frequently used settings.
3	[Reset]
	Click to revert settings to their initial values.

### **Displaying the Printer Driver Help**

The printer driver includes Help. To learn about print settings, open the printer driver print settings screen and display Help as explained below.



- 1 Click the [?] button in the upper right corner of the screen.
- 2 Click the item you want to know about.

#### 

The Help appears, even when you click the item you want to know about and press the [F1] key on your keyboard.

### **Changing the Default Printer Driver Settings** (Windows 8.1)

The default printer driver settings can be changed. By selecting frequently used settings, you can omit steps when printing. For the settings, refer to the following:

- Printer Driver User Guide
  - **1** In charms on Desktop, click [Settings], [Control Panel], and then [Devices and Printers].
  - **2** Right-click the printer driver icon of the machine, and click the [Printer properties] menu of the printer driver.
  - **3** Click the [Basic] button on the [General] tab.
  - **A** Select the default settings and click the [OK] button.

# **Printing from PC**

This section provides the printing method using the KX DRIVER.

#### 💽 NOTE

- To print the document from applications, install the printer driver on your computer from the supplied DVD (Product Library).
- In some environments, the current settings are displayed at the bottom of the printer driver.



- When printing the cardstock or envelopes, load the cardstock or envelopes in the multipurpose tray before performing the following procedure.
- Loading Paper in the Multipurpose Tray (page 5-5)

### **Printing on Standard Sized Paper**

If you loaded a paper size that is included in the print sizes of the machine, select the paper size in the [Basic] tab of the print settings screen of the printer driver.

#### Ó NOTE

Specify the paper size and media type to print from the operation panel.

Cassette/MP Tray Settings (page 8-8)



#### **Display the screen.**

Click [File] and select [Print] in the application.

#### **Configure the settings.** 2

1 Select the machine from the "Printer" menu and click the [Properties] button.



- 2 Select the [Basic] tab.
- 3 Click "Print size" menu and select the paper size to use for printing.

To load the paper of size that is not included in print sizes of the machine such as cardstock or envelopes, the paper size needs to be registered.

Printing on Non-standard Sized Paper (page 4-6)

To print on the special paper such as thick paper or transparency, click "Media type" menu and select the media type.

	the start sector of	
Grander ・ Day <u>王 era</u> 上 ara 二 王 ara 王 ara 王 ara	Harr Lizzia de constant Martin Lizzia de constant Martin Lizzia de constant Lizzia de con	
teanut Sij en daa kit		

4 Click [**OK**] button to return to the Print dialog box.

#### **3** Start printing.

Click the [OK] button.

### **Printing on Non-standard Sized Paper**

If you loaded a paper size that is not included in the print sizes of the machine, register the paper size in the [**Basic**] tab of the print settings screen of the printer driver.

The registered size can be selected from the "Print size" menu.

#### 

To execute printing at the machine, set the paper size and type in the following:

Paper Settings (page 8-13)

#### Display the screen.

1 In charms on Desktop, click [Settings], [Control Panel], and then [Devices and Printers].

#### NOTE

In Windows 7, click [Start] button on the Windows, and then click [Devices and Printers].

- 2 Right-click the printer driver icon of the machine, and click the [**Printer properties**] menu of the printer driver.
- **3** Click the [**Basic**] button on the [**General**] tab.

#### 2 Register the paper size.

1 Click the [Basic] tab.


ie const • tu E ensi E ensi		2	F#] [22]
E ens	Dec Di	4	
di maria	A Design of the local data and the		14.00
the second second	A res		1 Hours
1 ang	party and the	1.5	V 문 + + +
2.6	dente de la		
E General			Call Citation
	THE REAL PROPERTY AND		
	E		101 JUNE
	100		10 all and a
			1
			100
		111128	1.1
Rainel			

- 2 Click the [Page Size...] button.
- 3 Click the [New] button.

1		
A particular part 1 particular DV 2 million 1 particular 1 particula		
C	— 3 — 4	
T <u>≥n 3</u> ≈  1 ***	— 4 — 5	. 6
C	— 7	

- 4 Enter the paper size.
- 5 Enter the name of the paper.

- 6 Click the [Save] button.
- 7 Click the [OK] button.
- 8 Click the [OK] button.




#### 3

#### Display the print settings screen.

Click [File] and select [Print] in the application.

#### **4** Select the paper size and type of non-standard size paper.

**1** Select the machine from the "Printer" menu and click the [**Properties**] button.



2 Select the [**Basic**] tab.

3 Click "Print size" menu and select the paper size registered in step 2.

To print on the special paper such as thick paper or transparency, click "Media type" menu and select the media type.

		-	• · · · · · · · · · · · · · · · · · · ·
President of the second	Allen, at an		166
Lind Line E person ( <sup>2</sup> .d	national anglesis Sant Sant Sant Sant Sant Sant Sant Sant		1         1           Control         1           T         1           S         1           Points ST
Micro			ŢŢĘ.~.
aus.		- A Mary A	- New -
of the No			<u></u>

#### **NOTE**

If you loaded a postcard or envelope, select [Cardstock] or [Envelope] in the "Media type" menu.

- 4 Select the paper source in the "Source" menu.
- **5** Click **[OK]** button to return to the Print dialog box.

5

#### Start printing.

Click the [OK] button.

### **Canceling Printing from a Computer**

To cancel a print job executed using the printer driver before the printer begins printing, do the following:

#### NOTE

When canceling printing from this machine, refer to the following:

Canceling Jobs (page 5-16)

**1** Double-click the printer icon ( **m**) displayed on the taskbar at the bottom right of the Windows desktop to display a dialog box for the printer.



# **Printing from the Handheld Device**

This machine supports the AirPrint, Google Cloud Print, Mopria and Wi-Fi Direct.

According to the supported OS and application, you can print the job from any handheld device or computer without installing a printer driver.

### **Printing by AirPrint**

AirPrint is a printing function that is included standard in iOS 4.2 and later products, and Mac OS X 10.7 and later products.

To use the AirPrint, make sure that the AirPrint setting is enabled in the Command Center RX.

Command Center RX User Guide



### **Printing by Google Cloud Print**

Google Cloud Print is a printing service provided by Google. This service enables a user with a Google account to print from a machine connected to the Internet.

The machine can be configured in the Command Center RX.

Command Center RX User Guide

#### 💽 ΝΟΤΕ

A Google account is necessary to use Google Cloud Print. Obtain a Google account if you do not have one.

It is also necessary to register the machine with the Google Cloud Print service in advance. The machine can be registered from a PC connected to the same network.

### **Printing by Mopria**

Mopria is a standard on printing function included in Android 4.4 or later products. Mopria Print Service needs to be installed and enabled in advance.

For details on how to use, refer to a Web site of Mopria Alliance.

### **Printing with Wi-Fi Direct**

Wi-Fi Direct is a wireless LAN standard that Wi-Fi Alliance has been established. This is one of the functions of the wireless LAN, without a wireless LAN access point or wireless LAN router, between devices can communicate directly on a peer to peer basis.

The printing procedure by the Wi-Fi Direct is the same as that from the normal handheld devices.

When you use a printer name or Bonjour name on the port settings of the printer property, you can print the job by specifying the name at Wi-Fi Direct connection.

When you use an IP address for the port, specify the IP address of this machine.

## **Printing Data Saved in the Printer**

You can save the print job into the Job Box of this device and print it as necessary.

To use the Stored Job Box and the Quick Copy Box, an SD/SDHC memory card must be installed in the device.

To use the Private Print Box and the Proof and Hold Box, an expansion memory or SD/SDHC memory card must be installed in the device.

#### **IMPORTANT**

Unencrypted data is saved on the SD/SDHC memory card. Exercise caution when saving sensitive documents.

#### 阈 ΝΟΤΕ

- To use expansion memory, [RAM Disk Setting] must be [On].
- RAM Disk Setting (page 8-37)
- If you are using an SD/SDHC memory card to use a job box, set [RAM Disk Setting] to [Off].

If you configure settings in the [**Job**] tab of the printer driver and then print, the print job will be saved in the Job Box (memory) and printing can be executed at the machine.

Follow the work flow below when using Job Box.

Specifying the Job Box from a computer and sending the print job. (page 4-11)

Using the operation panel to specify a file within a Box and printing it.

You can print the documents from the following boxes.

- Printing Documents from Private Print Box (page 4-12)
- Printing Document from Stored Job Box (page 4-13)
- Printing Document from Quick Copy Box (page 4-14)
- Printing Document from Proof and Hold Box (page 4-15)

# Specifying the Job Box from a Computer and Storing the Job

#### **1** Click [File] and select [Print] in the application.

The Print dialog box displays.

**9** Select the machine from the "Name" menu.

#### **3** Click the [Properties] button.

The Properties dialog box displays.

# **4** Click the [Job] tab and select the [Job storage (e-MPS)] check box to set the function.

#### 🚫 NOTE

For information on how to use the printer driver software, refer to the following:

Printer Driver User Guide

### **Printing Documents from Private Print Box**

In Private Printing, you can specify that a job is not to be printed until you operate the machine. When sending the job from the application software, specify a 4-digit access code in the printer driver. The job is released for printing by entering the access code on the operation panel, ensuring confidentiality of the print job. The data will be deleted upon completion of the print job or after the power switch is turned off.

#### **1** Display the screen.

- 1 [Home] key > [Job Box]
- 2 Select [Private Print/Stored Job].
- **3** Select the creator of the document.

#### **2** Print the document.

- 1 Select the document to print > [Print]
- 2 Enter the access code.
- 3 Specify the number of copies to print as desired.
- 4 Select [OK].

```
Printing starts.
Upon completion of printing, the Private Print job is automatically deleted.
```

### **Deleting the Documents Stored in the Private Print Box**

#### **1** Display the screen.

- 1 [Home] key > [Job Box]
- 2 Select [Private Print/Stored Job].
- **3** Select the creator of the document.

#### **2** Delete the document.

Select the document to delete > [minimized] > Enter the access code

2014/10/10 10:10	
2014/10/10 11:11	
	1/1
	1

The document is deleted.

### **Printing Document from Stored Job Box**

In Stored Job, the print data sent from the application is saved to the machine. You can set up an access code as necessary. If you set up an access code, enter the access code when printing. Print data will be stored in the Stored Job Box after printing. This will allow printing of the same print data repeatedly.

#### **1** Display the screen.

- 1 [Home] key > [Job Box]
- 2 Select [Private Print/Stored Job].
- **3** Select the creator of the document.

#### **2** Print the document.

1 Select the document to print > [Print]

#### 💽 NOTE

If the document is protected by an access code, the password entry screen will be displayed. Enter the password using the numeric keys.

- 2 Specify the number of copies to print as desired.
- 3 Select [OK].

Printing starts.


### **Deleting the Documents Stored in the Stored Job Box**

#### Display the screen.

- 1 [Home] key > [Job Box]
- 2 Select [Private Print/Stored Job].
- **3** Select the creator of the document.

#### **2** Delete the document.

Select the document to delete > [m]



2 Select [Yes].

The document is deleted.

#### NOTE

If the document is protected by an access code, the password entry screen will be displayed. Enter the password using the numeric keys.

### **Printing Document from Quick Copy Box**

Quick Copy feature facilitates additional prints of a document already printed. Activating Quick Copy and printing a document using the printer driver allow the print data to be stored in the Quick Copy Job Box. When additional copies are required, you can reprint the required number of copies from the touch panel. By default, up to 32 documents can be stored. When power is turned off, all stored jobs will be deleted.

#### 

- When the number of jobs reaches the limit, the oldest job will be overwritten by the new one.
- To maintain free space on the box, you can set the maximum number of stored jobs.
- Quick Copy Job Retention (page 8-22)

#### 1 Display the screen.

- 1 [Home] key > [Job Box]
- 2 Select [Quick Copy/Proof and Hold].
- **3** Select the creator of the document.

#### **2** Print the document.

- 1 Select the document to print > [Print]
- 2 Specify the number of copies to print as desired.
- Select [OK].
   Printing starts.

### **Deleting the Documents Stored in the Quick Copy Box**

#### **1** Display the screen.

- 1 [Home] key > [Job Box]
- 2 Select [Quick Copy/Proof and Hold].
- **3** Select the creator of the document.

#### **2** Delete the document.

Select the document to delete > [ ]



2 Select [Yes].

The document is deleted.

### **Printing Document from Proof and Hold Box**

The Proof and Hold feature produces only a single proof print of multiple-print job and holds printing of the remaining copies. Printing a multiple-print job in Proof and Hold using the printer driver allows only a single copy to be printed while maintaining the document data in the Job Box. To continue to print the remaining copies, use the touch panel. You can change the number of copies to print.

#### Display the screen.

- 1 [Home] key > [Job Box]
- 2 Select [Quick Copy/Proof and Hold].
- **3** Select the creator of the document.

#### **2** Print the document.

- 1 Select the document to print > [Print]
- 2 Specify the number of copies to print as desired.
- 3 Select [OK].

Printing starts.

### Deleting the Documents Stored in the Proof and Hold Box

#### Display the screen.

- 1 [Home] key > [Job Box]
- 2 Select [Quick Copy/Proof and Hold].
- **3** Select the creator of the document.

#### **2** Delete the document.

Select the document to delete > [ 2018]



#### 2 Select [Yes].

The document is deleted.

# Monitoring the Printer Status (Status Monitor)

The Status Monitor monitors the machine status and provides an ongoing reporting function.

#### 

When you activate Status Monitor, check the status below.

- KX DRIVER is installed.
- Either [Enhanced WSD] or [Enhanced WSD over SSL] is enabled.
- Network (page 8-26)

### **Accessing the Status Monitor**

The Status Monitor also starts up when printing is started.


### **Exiting the Status Monitor**

Use either of the methods listed below to exit the Status Monitor.

- Exit manually: Click the settings icon and select Exit in the menu to exit the Status Monitor.
- Exit automatically: The Status Monitor automatically shuts down after 7 minutes if it is not being used.

### **Quick View State**

The status of the machine is displayed using icons. Detailed information is displayed when the Expand button is clicked.




- 1 Printing Progress Tab
- 2 Paper Tray Status Tab
- 3 Toner Status Tab
- 4 Alert Tab
- 5 Expand button
- 6 Settings icon

Detailed information is displayed by clicking on each icon tab.

### **Printing Progress Tab**

The status of the print jobs is displayed.



Select a job on the job list and it can be canceled using the menu displayed with a right-click.

### **Paper Tray Status Tab**

Information is displayed about the paper in the printer and about the amount of paper remaining.

			0
6. Permit 106 Cal-	Tran- Plate Hom	1eer 0%	
	w. <u>A</u>	nic AL Plate	ne AL Nov 6%


### **Toner Status Tab**

The amount of toner remaining is displayed.

and the second se	U U U 🖂		0
5.7 MA	ee wa wa		
	Sec.	fesel Classes	
	Disct	SHIS, THE SCHLIGS	
Contraction of the local distance of the loc	Qún	8cc 10.004003	
- CO	Magerite	902 00520095	
1	Vel sta	265 TIC \$24175	
1			
1000 C			


### **Alert Tab**

If an error occurs, a notice is displayed using a 3D image and a message.



### **Status Monitor Context Menu**

The following menu is displayed when the settings icon is clicked.



#### Command Center RX

If the printer is connected to a TCP/IP network and has its own IP address, use a web browser to access the Command Center RX to modify or confirm the network settings. This menu is not displayed when using USB connection.

#### Command Center RX User Guide

#### Notification...

This sets the display of the Status Monitor.

- Status Monitor Notification Settings (page 4-19)
- www.kyoceradocumentsolutions.com Open our website.
- Exit Exits the Status Monitor.

### **Status Monitor Notification Settings**

Click the setting icon to display valid events in the status monitor notification screen.

<u>a</u> urrera	cue:			_
4,000 cont				
1000	yand 6	o∱kosini p	0.00	
Serve meet	2200			
2000000				
- States				
Sing Get contra-				
See yes				
Set includes				
/ rendering	60			
Sec.				
		1.0	4	1 Same
			- C	

Select whether notification is performed when an error in the event list occurs.

#### 1

#### Select Enable event notification.

If this setting is set to Off, then the Status Monitor will not start up even when printing is executed.

# **2** Select an event to use with the text to speech function in Available events.

#### **3** Click Sound file / Text to Speech column.

Click the browse (...) button to notify the event by sound file.

	Care and the second second second	B
Zhitter	a mail sizes	
a provincia	read to first respect	_
See a	with the second s	
1000000		Ę

#### NOTE

The available file format is WAV.

When customizing the message texts to read on the screen aloud, enter the texts in the text box.

# **Operation on the Machine**

#### This chapter explains the following topics:

5

Loading Originals 5-2
Placing Originals on the Platen 5-2
Loading Originals in the Document
Processor 5-3
Loading Paper in the Multipurpose Tray 5-5
Favorites
Registering Favorite Using the Wizard
Mode 5-9
Registering Favorite Using the Program
Mode 5-10
Recalling Favorite using the Wizard
Mode
Recalling Favorite using the Program
Mode 5-12
Editing Favorite 5-12
Deleting Favorite 5-12
Registering Shortcuts 5-13
Adding Shortcuts 5-13
Editing Shortcuts 5-14
Deleting Shortcuts 5-14
Copying 5-15
Basic Operation 5-15
Canceling Jobs
Frequently-Used Sending Method 5-17
Sending Document via E-mail
Configuring Settings before Sending 5-18
Sending Scanned Document via
E-mail 5-18
Sending Document to Desired Shared Folder
on a Computer (Scan to PC)
Configuring Settings before Sending 5-20
Sending Document to Desired Shared Folder on a Computer 5-20
Sending Document to Folder on an FTP Server
(Scan to FTP) 5-23
Configuring Settings before Sending 5-23
Sending Document to Folder on an FTP
Server
Scanning using TWAIN or WIA
Configuring Settings before Sending 5-25
Scanning Document Using
Application
Useful Sending Method 5-26
WSD Scan
Installing Driver Software 5-27
WSD scan 5-28

Scanning with File Management Utility 5-29
Configuring Settings before Sending 5-29
Recalling a Favorite Configured in FMU 5-29
Sending to Different Types of Destinations (Multi Sending)
(
Configuring Settings before Sending 5-31
Sending a document to the mail address of the logged in user
55
5 5
Handling Destination
Specifying Destination
Choosing from the Address Book 5-34
Choosing from the External Address
Book
Choosing from the One Touch Key 5-37
Checking and Editing Destinations 5-37
Confirmation Screen of Destinations 5-38
Recall
How to use the FAX Function 5-39
Using Document Boxes 5-40
What is Job Box? 5-40
What is Removable Memory Box? 5-40
Sub Address Box/Polling Box 5-40
Operating using Removable USB Memory 5-41
Printing Documents Stored
in Removable USB Memory 5-41
Saving Documents to USB Memory
(Scan to USB) 5-43
Check the USB Memory Information 5-44
Removing USB Memory 5-44


# **Loading Originals**

Load the originals on the platen or document processor, depending on the original size, type, volume, and function.

- Platen: Place the sheet, book, postcards, and envelopes.
- Document Processor: Place the multiple originals. You can also place the two sided originals.

### **Placing Originals on the Platen**

You may place books or magazines on the platen in addition to ordinary sheet originals.




- 1 Put the scanning side facedown.
- 2 Align it flush against the original size indicator plates with the back left corner as the reference point.

#### 💽 ΝΟΤΕ

For details on Original Orientation, refer to the following:

Original Orientation (page 6-18)

#### When you place envelopes or cardstock on the platen



- 1 Put the scanning side facedown.
- 2 Align it flush against the original size indicator plates with the back left corner as the reference point.

#### 阈 ΝΟΤΕ

For the procedure for feeding envelopes or cardstock, refer to the following:

When you load envelopes or cardstock in the multipurpose tray (page 5-7)

# 

Do not leave the document processor open as there is a danger of personal injury.

#### **IMPORTANT**

- Do not push the document processor forcefully when you close it. Excessive pressure may crack the platen glass.
- When placing books or magazines on the machine, do so with the document processor in the open position.

### **Loading Originals in the Document Processor**

The document processor automatically scans each sheet of multiple originals. Both sides of two-sided originals are scanned.

The document processor supports the following types of originals.

Weight	50 to 160 g/m <sup>2</sup> (duplex: 50 to 160 g/m <sup>2</sup> )
Sizes	Maximum A4 (Legal) to Minimum A6 (Statement)
No. of sheets	Plain paper (80 g/m <sup>2</sup> ): 50 sheets or less (Mixed size originals: 30 sheets)


Do not use the document processor for the following types of originals. Otherwise, the originals may be jammed or the document processor may become dirty.

- Originals bound with clips or staples (Remove the clips or staples and straighten curls, wrinkles or creases before loading. Failure to do so may cause the originals to jam.)
- · Originals with adhesive tape or glue
- Originals with cut-out sections
- · Curled original
- Originals with folds (Straighten the folds before loading. Failure to do so may cause the originals to jam.)
- Carbon paper
- Crumpled paper

#### **IMPORTANT**

- Before loading originals, be sure that there are no originals left on the original eject table. Originals left on the original eject table may cause the new originals to jam.
- Do not make an impact on the document processor top cover, such as aligning the originals on the top cover. It may cause an error in the document processor.


# Open the original table and then adjust the original width guides.





#### Place the originals.

1 Put the side to be scanned (or the first side of two-sided originals) face-up. Slide the leading edge into the document processor as far as it will go.




#### NOTE

For details on Original Orientation, refer to the following:

Original Orientation (page 6-18)

#### **IMPORTANT**


Confirm that the original width guides exactly fit the originals. If there is a gap, readjust the original width guides. The gap may cause the originals to jam.



Ensure that loaded originals do not exceed the level indicator. Exceeding the maximum level may cause the originals to jam.

Originals with punched holes or perforated lines should be placed in such a way that the holes or perforations will be scanned last (not first).

2 Open the original stopper to fit the size of the original set (Original size: Legal).



# **Loading Paper in the Multipurpose Tray**

For details of the supported paper sizes, refer to the following:

<u>Choosing the Appropriate Paper (page 11-12)</u>

For the paper type setting, refer to the following:

Media Type Setting (page 8-15)

Be sure to use the multipurpose tray when you print on any special paper.

#### **IMPORTANT**

- If you are using a paper weight of 106 g/m<sup>2</sup> or more, set the media type to Thick and set the weight of the paper you are using.
- Remove each transparency from the inner tray as it is printed. Leaving transparencies in the inner tray may cause a paper jam.


The capacity of the multipurpose tray is as follows.

- Plain paper (80 g/m<sup>2</sup>) or recycled paper: 50 sheets
- Thick paper (209 g/m<sup>2</sup>): 15 sheets
- Thick paper (157 g/m<sup>2</sup>): 30 sheets
- Thick paper (104.7 g/m<sup>2</sup>): 50 sheets
- Hagaki (Cardstock): 15 sheets
- Envelope DL, Envelope C5, Envelope #10, Envelope #9, Envelope #6 3/4, Envelope Monarch, Youkei 4, Youkei 2: 5 sheets
- OHP film: 1 sheet
- Coated: 30 sheets

#### 🚫 NOTE

- When you load custom size paper, enter the paper size by referring to the following:
- Paper Settings (page 8-13)
- When you use special paper such as transparencies or thick paper, select the media type by referring to the following:
- Multipurpose Tray (page 8-9)


#### Open the multipurpose tray.




2

#### Adjust the multipurpose tray size.

Paper sizes are marked on the multipurpose tray.



#### **3** Load paper.



Insert the paper along the paper width guides into the tray until it stops.

After removing new paper from its packaging, fan the paper before loading it in the multipurpose tray.

Precaution for Loading Paper (page 3-2)

#### **IMPORTANT**

- When loading the paper, keep the print side facing up.
- Curled paper must be uncurled before use.
- When loading paper into the multipurpose tray, check that there is no paper left over in the tray from a previous job before loading the paper. If there is just a small amount of paper left over in the multipurpose tray and you want to add more, first remove the left-over paper from the tray and include it with the new paper before loading the paper back into the tray.
- If there is a gap between the paper and the paper width guides, readjust the guides to fit the paper in order to prevent skewed feeding and paper jams.
- Ensure that the loaded paper does not exceed the load limits.

# 4 Specify the type of paper loaded in the multipurpose tray using the operation panel.


Multipurpose Tray (page 8-9)

#### When you load envelopes or cardstock in the multipurpose tray

Load the paper with the print side facing up. For the procedure for printing, refer to the following:

Printer Driver User Guide

Example: When printing the address.



- 1 Oufuku hagaki (Return postcard)
- 2 Hagaki (Cardstocks)
- 3 Portrait form envelopes
- 4 Landscape form envelopes

#### **IMPORTANT**

- Use unfolded Oufuku hagaki (Return postcard).
- How to load envelopes (orientation and facing) will differ depending on the type of envelope. Be sure to load it in correctly, otherwise printing may be done in the wrong direction or on the wrong face.

#### NOTE

When you load envelopes in the multipurpose tray, select the envelope type by referring to the following:

Cassette/MP Tray Settings (page 8-8)

## **Favorites**

Frequently used functions can be registered as favorites so that they can be called up easily.

The following functions are pre-registered on this machine. You can delete these functions as well as register new functions.

Favorites Name	Description	Default Registration
ID Card Copy	Use this when you want to copy a driver's license or an insurance card. When you scan the front and back of the card, both sides will be combined and copied onto a single sheet.	<ul> <li>Copying Functions</li> <li>Program mode</li> <li>Combine: [2 in 1] Color Selection: [Black &amp; White] Continuous Scan: [On] Original Size: [A5/Statement] Paper Selection: Cassette 1 Zoom: [Auto Zoom]</li> </ul>
Paper Saving Copy	Use this when you want to reduce paper use. Page combining and two-sided copying can be set by following the screen.	<ul> <li>Copying Functions</li> <li>Wizard mode</li> <li>Combine: [2 in 1] 2-sided/Original: [1-sided] Duplex: [1-sided&gt;&gt;2-sided] Paper Selection: Cassette 1 Copies: 1</li> </ul>
Scan to PC (Address Entry)	Use this when you want to send the image to either a shared folder on a PC or an FTP server folder. The settings such as the destination and color selection can be set by following the screen.	<ul> <li>Sending Functions</li> <li>Wizard mode</li> <li>Destination: New PC Folder Color Selection: [Full Color] File Name Entry: Default File Format: [PDF] Continuous Scan: [Off] Scan Resolution: [300×300 dpi]</li> </ul>
Scan to PC (Address Book)	Use this when you want to send the image to either a shared folder on a PC registered in the Address Book or to an FTP server folder. The settings such as the destination and color selection can be set by following the screen.	<ul> <li>Sending Functions</li> <li>Wizard mode</li> <li>Destination: Address Book Color Selection: [Full Color] File Name Entry: Default File Format: [PDF] Continuous Scan: [Off] Scan Resolution: [300×300 dpi]</li> </ul>
Scan to E-mail (Address Entry)	Use this when you want to send the image to an E-mail address. The settings such as the destination and color selection can be set by following the screen.	<ul> <li>Sending Functions</li> <li>Wizard mode</li> <li>Destination: New E-mail Address Color Selection: [Full Color] File Name Entry: Default File Format: [PDF] Continuous Scan: [Off] Scan Resolution: [300×300 dpi] E-mail subject: Default E-mail body: Default</li> </ul>

Favorites Name	Description	Default Registration
Scan to E-mail (Address Book)	Use this when you want to send the image to an E-mail address registered in the Address Book. The settings such as the destination and color selection can be set by following the screen.	<ul> <li>Sending Functions</li> <li>Wizard mode</li> <li>Destination: Address Book Color Selection: [Full Color] File Name Entry: Default File Format: [PDF] Continuous Scan: [Off] Scan Resolution: [300×300 dpi] E-mail subject: Default E-mail body: Default</li> </ul>

#### 

Up to 20 settings can be registered as favorites.

When registering a favorite, you can choose from two methods for calling it up:

- Wizard mode: Registered settings are called up in order and configured as you check or change each one.
- Program mode: Settings are called up immediately when you select the key to which they are registered.

### **Registering Favorite Using the Wizard Mode**

#### Display the screen.

[Home] key > [Task Screen] > [Favorites]



- 1 [Menu] > [Add]
- 2 Select the job type.
- 3 Select [Wizard].
- 4 Select the recall function > [Next]

#### NOTE

When the job type is "Copy", the Destination Recall Method screen will not be displayed.

- 5 Enter the new favorite name > [Next]
  - Character Entry Method (page 11-8)

6 Check the settings and change or add information as needed.

Item	Description
Name	Enter the name displayed on the favorite screen (up to 32 characters).
Job Type	The type of the selected job is displayed.
Number <sup>*1</sup>	Enter the favorite number. If you enter 00, the smallest number available will be automatically assigned.
Destination <sup>*2</sup>	Selects the Destination Recall Method.
Functions	Selects the functions to be displayed in the wizard.
Function Type	Selects the method for recalling favorites.

\*1 If user login administration is enabled, you can only change the settings by logging in with administrator privileges.

- \*2 Displayed when the job type is [Send] or [FAX].
- 7 Select [Save].

The favorite is registered.

8 "Do you want to add a new function to the home screen?" screen appears. To display a registered favorite on the Home screen, select [Yes] and specify the position in which you want to display the icon of registered favorite, and select [Save].


### **Registering Favorite Using the Program Mode**

When registering favorites in program mode, configure the copy function, send function, fax function, destination, or other setting to register.

Sending is explained as an example below.

#### Display the screen.

- 1 [Home] key > [Send]
- 2 Select the sending functions and destinations that you want to register in the program.
- 3 Select [Favorites].



- 1 [Menu] > [Add]
- 2 Select the job type.
- 3 Select [Program].
- 4 Enter the new favorite name > [Next]
  - Character Entry Method (page 11-8)

**5** Check the settings and change or add information as needed.

Item	Description
Name	Enter the name displayed on the favorite screen (up to 32 characters).
Number <sup>*1</sup>	Enter the favorite number. If you enter 00, the smallest number available will be automatically assigned.
Job Type	The type of the selected job is displayed.
Function Type	Selects the method for recalling favorites.

- \*1 If user login administration is enabled, you can only change the settings by logging in with administrator privileges.
- 6 Select [Save].

The favorite is registered.

7 "Do you want to add a new function to the home screen?" screen appears. To display a registered favorite on the Home screen, select [Yes] and specify the position in which you want to display the icon of registered favorite, and select [Save].

### **Recalling Favorite using the Wizard Mode**

#### Display the screen.

Select [Favorites] registered in the home screen, or select the icon that appears in [Task Screen] > [Favorites].

#### **2** Execute the favorite.

The registered screens are displayed in order. Make the desired settings and select [Next].
 When all the settings are complete, the confirmation screen is displayed.

#### NOTE

To edit the settings, select [**<Back**] and make changes as desired.

2 Place the originals > [Start] key

### **Recalling Favorite using the Program Mode**



#### **Display the screen.**

Select [Favorites] registered in the home screen, or select the icon that appears in [Task Screen] > [Favorites].



#### **Execute the favorite.**

Place the originals > [Start] key

### **Editing Favorite**

You can change favorite number and favorite name.

1

#### **Display the screen.**

[Home] key > [Task Screen] > [Favorites]

#### Edit the favorite. 2

- 1 [Menu] > [Edit]
- 2 Select the favorite you wish to edit.
- 3 Change the favorite number and favorite name.
  - ➡ When registering a favorite, you can choose from two methods for calling it up: (page) 5-9)
- 4 [Save] > [Yes]

### **Deleting Favorite**



#### **Display the screen.**

[Home] key > [Task Screen] > [Favorites]

#### **Delete the favorite.** 2

- 1 [Menu] > [Delete]
- 2 Select the favorite you wish to delete.
- 3 Select [Yes].

## **Registering Shortcuts**

You can register shortcuts for easy access to the frequently used functions. The settings for the selected function can also be registered. A function name linked to a registered shortcut can be changed as necessary.

### **Adding Shortcuts**

Shortcut registration is performed in the "Functions" screen of each function.

#### Display the screen.

In the Copy, Send, Document Box, or FAX screen, select as follows.

[Functions] > [Add/Edit Shortcut]

#### NOTE

When user control is set to local authentication and the user logs in with user rights, [Add/ Edit Shortcut] does not appear.

#### 2 Register the shortcuts.

- 1 Select [Add].
- 2 Select the key to which you wish to register the shared shortcut.

#### 阈 NOTE

If you select a shortcut number already registered, the currently registered shortcut can be replaced with a new one.

- 3 Select the function screen to display with the shortcut.
- 4 Enter the shortcut name > [Next]

#### 

Up to 24 characters can be entered.

- <u>Character Entry Method (page 11-8)</u>
- 5 Select [Save].

The shortcut is registered.

### **Editing Shortcuts**

**1** In the "Functions" screen of each function, select [Add/Edit Shortcut] in the bottom of the screen.

#### **2** Edit the shortcut.

- 1 Select [Edit].
- 2 Select the shortcut type and number you wish to edit.
- 3 Select [Number] or [Name].
- 4 Change the settings > [OK]
- 5 [Save] > [Yes]

### **Deleting Shortcuts**

**1** In the "Functions" screen of each function, select [Add/Edit Shortcut] in the bottom of the screen.



#### Delete the shortcut.


- 1 Select [Delete].
- **2** Select the shortcut you wish to delete.
- 3 Select [Yes].


# Copying

The procedures here represent the basic copy operation and how to cancel the copy.

### **Basic Operation**

- [Home] key > [Copy]
- **2** Place the originals.





#### **3** Select the functions.

To configure the settings for functions, select the function key. By selecting [**Functions**], other selectable functions will be shown as a list.

✤ About Functions Available on the Machine (page 6-2)

#### **4** Use the numeric keys to enter the copy quantity.

Specify the desired number up to 999.

#### **5** Press the [Start] key.

Copying begins.

## **Canceling Jobs**

#### **1** Select the [Stop] key with the copy screen displayed.

#### **2** Cancel a job.

When there is a job is being scanned The copy job is canceled.

#### When there is a job printing or on standby

Canceling job screen appears. The current print job is temporarily interrupted. Select the job you wish to cancel > [**Delete**] > [**Yes**]


## **Frequently-Used Sending Method**

This machine can send a scanned image as an attachment of an E-mail message or to a PC linked to the network. In order to do this, it is necessary to register the sender and destination (recipient) address on the network.


A network environment which enables the machine to connect to a mail server is required in order to send E-mail. It is recommended that a Local Area Network (LAN) be used to assist with transmission speed and security issues.

Follow the steps below for basic sending. The following four options are available.

- Send as E-mail (E-mail Addr Entry): Sends a scanned original image as an E-mail attachment.
- Sending Document via E-mail (page 5-18)



- Send to Folder (SMB): Stores a scanned original image in a shared folder of any PC.
- ◆ Sending Document to Desired Shared Folder on a Computer (Scan to PC) (page 5-20)
- Send to Folder (FTP): Stores a scanned original image in a folder of an FTP server.
- Sending Document to Folder on an FTP Server (Scan to FTP) (page 5-23)



- Image Data Scanning with TWAIN / WIA: Scan the document using a TWAIN or WIA compatible application program.
- Scanning using TWAIN or WIA (page 5-25)

#### 💽 NOTE

- Different sending options can be specified in combination.
- Sending to Different Types of Destinations (Multi Sending) (page 5-30)
- The fax function can be used on products equipped with fax capability.
- ✤ FAX Operation Guide

## **Sending Document via E-mail**

When transmitting using wireless LAN, select the interface dedicated to the send function in advance.

Primary Network (Client) (page 8-36)

### **Configuring Settings before Sending**


Before sending an E-mail, configure the SMTP and E-mail settings using the Command Center RX.

E-mail Settings (page 2-58)

### **Sending Scanned Document via E-mail**

- [Home] key > [Send]
- **2** Place the originals.





Loading Originals (page 5-2)

#### **3** In the basic screen for sending, select [E-mail].



5

#### Enter destination E-mail address > [OK]

Up to 128 characters can be entered.

Character Entry Method (page 11-8)

To enter multiple destinations, select [**Next Destination**] and enter the next destination. Up to 100 E-mail addresses can be specified.

You can register the entered E-mail address in the Address Book by selecting [Menu] > [Add to Address Book]. You can also replace the information for a previously registered destination.

Destinations can be changed later.

Confirmation Screen of Destinations (page 5-38)

#### Select the color mode setting.

→ Color Selection (page 6-16)

#### 6

#### Select the functions.

Select [Functions] to display other functions.

Send (page 6-4)



#### Press the [Start] key.

Sending starts.

## Sending Document to Desired Shared Folder on a Computer (Scan to PC)

## **Configuring Settings before Sending**


Before sending an document, configure the following settings.


- Make a note of the computer name and full computer name
  - Making a note of the computer name and full computer name (page 3-10)
  - Make a note of the user name and domain name
    - Making a note of the user name and domain name (page 3-11)
- Create a shared folder and make a note of a shared folder
  - Creating a Shared Folder, Making a Note of a Shared Folder (page 3-12)
- Configure the Windows firewall
  - Configuring Windows Firewall (page 3-15)

# Sending Document to Desired Shared Folder on a Computer



**2** Place the originals.





✤ Loading Originals (page 5-2)

- In the basic screen for sending, select [Folder].
- Select [SMB] from the folder type.

#### **5** Select the folder specification method.

To search for a folder on a PC on the network, select [Search Folder from Network] or [Search Folder by Host Name].

If you selected [**Search Folder from Network**], you can search all PCs on the network for a destination.

If you selected [**Search Folder by Host Name**], you can enter the "Domain/Workgroup", and "Host Name" to search PCs on the network for the destination.

Up to 500 addresses can be displayed. Select the host name (PC name) that you want to specify in the screen that appears, and select [**Next**]. The login user name and login password entry screen appears.

After you enter the login user name and login password name of the destination PC, the shared folders appear. Select the folder that you want to specify and select [**Next**]. The address of the selected shared folder is set.

Select the folder from the Search Results list.

#### 6 Enter the destination information.

Enter the next information. Once you have entered one item, select [Next] to advance to the next item.

#### Character Entry Method (page 11-8)

The table below lists the items to be set.

Item	Detail	Max. characters
Host Name <sup>*1</sup>	Computer name	Up to 64 characters
Path	Share name For example: scannerdata If saving in a folder in the shared folder: share name\folder name in shared folder	Up to 128 characters
Login User Name	If the computer name and domain name are the same: User Name For example: james.smith If the computer name and domain name are different: Domain name\User name For example: abcdnet\james.smith	Up to 64 characters
Login Password	Windows logon password (Case sensitive.)	Up to 64 characters

\*1 You can also specify the port number. Enter the following format separated by a colon. "Host name: port number" or "IP address: port number"

To enter the IPv6 address, enclose the address in brackets [].

(Example: [2001:db8:a0b:12f0::10]:445)

If the port number is not specified, the default port number is 445.

#### **7** Check the status.

1 Check the information.

Change the delay as required.

2 Check the connection.

#### [Menu] > [Connection Test]

"Connected." appears when connection to the destination is correctly established. If "Cannot connect." appears, review the entry.

To enter multiple destinations, select [Next Destination] and enter the next destination.

You can register the entered information in the Address Book by selecting [Add to Address Book].

#### 8 Select [OK].

Destinations can be changed later.

Confirmation Screen of Destinations (page 5-38)

#### Select the functions.

Select [Functions] to display other functions.

Send (page 6-4)

### **10** Press the [Start] key.

Sending starts.

## Sending Document to Folder on an FTP Server (Scan to FTP)


## **Configuring Settings before Sending**


Before sending an document, configure the FTP Client (Transmission).

Protocol Settings (page 8-30)

## **Sending Document to Folder on an FTP Server**

- [Home] key > [Send]
- **?** Place the originals.





➡ Loading Originals (page 5-2)

- **3** In the basic screen for sending, select [Folder].
- **A** Select [FTP] from the folder type.

#### **5** I

#### Enter the destination information.

Enter the next information. Once you have entered one item, select [Next] to advance to the next item.

#### Character Entry Method (page 11-8)

The table below lists the items to be set.

Item	Data to be entered	Max. characters
Host Name <sup>*1</sup>	Host name or IP address of FTP server	Up to 64 characters
Path <sup>*2</sup>	Path to the receiving folder For example: User\ScanData Otherwise the data will be saved in the home directory.	Up to 128 characters
Login User Name	FTP server login user name	Up to 64 characters
Login Password	FTP server login password (Case sensitive.)	Up to 64 characters

\*1 You can also specify the port number. Enter the following format separated by a colon.
 "Host name: port number" or "IP address: port number"
 To enter the IPv6 address, enclose the address in brackets [].
 (Example: [2001:db8:a0b:12f0::10]:21)

If the port number is not specified in [Host Name], the default port number is 21.

\*2 When the FTP server is based on Linux/UNIX, the path including the sub-folder is combined by the slash "/" not using the back-slash.

#### **6** Check the status.

1 Check the information.

Change the delay as required.

- 2 Check the connection.
  - [Menu] > [Connection Test]

"Connected." appears when connection to the destination is correctly established. If "Cannot connect." appears, review the entry.

To enter multiple destinations, select [Next Destination] and enter the next destination.

You can register the entered information in the Address Book by selecting [Add to Address Book].

#### **7** Select [OK].

Destinations can be changed later.

Confirmation Screen of Destinations (page 5-38)

#### 8 Select the functions.

Select [Functions] to display other functions.

Send (page 6-4)

#### Press the [Start] key.

Sending starts.

q

## **Scanning using TWAIN or WIA**

## **Configuring Settings before Sending**

Before sending an document, confirm that TWAIN/WIA driver is installed on a computer and the settings are configured.

- Setting TWAIN Driver (page 2-47)
- Setting WIA Driver (page 2-49)

### **Scanning Document Using Application**

This subsection explains how to scan an original using TWAIN. The WIA driver is used in the same way.

#### Display the screen.

- 1 Activate the TWAIN compatible application software.
- 2 Select the machine using the application and display the dialog box.

#### 💽 NOTE

For selecting the machine, see the Operation Guide or Help for each application software.


#### 2 Configure the scan settings.


Select scanning settings in the dialog box that opens.

#### 💽 NOTE

For the settings, refer to Help in the dialog box.

#### **3** Place the originals.





#### **4** Scan the originals.

Click the [Scan] button. The document data is scanned.

## **Useful Sending Method**

You can specify the following useful scanning (sending) methods.

- WSD Scan: Saves images of originals scanned on this machine as files on a WSD-compatible computer.
- ► WSD Scan (page 5-27)
- Scanning with File Management Utility:Scans a document using the settings of File Management Utility and saves it to a specified network folder or PC.
- Scanning with File Management Utility (page 5-29)
- Sending to different types of destinations (Multi sending): Sends to different types of destination (E-mail addresses, folders, etc.) in a single operation.
- ✤ Sending to Different Types of Destinations (Multi Sending) (page 5-30)
- Send to Me (E-mail): Sends to the E-mail address of the logged in user when user login is enabled.
- Send to Me (E-mail) (page 5-31)

## **WSD Scan**

WSD Scan saves images of originals scanned on this machine as files on a WSD-compatible computer.

#### NOTE

- To use WSD Scan, confirm that the computer used for WSD scanning and the machine is network-connected, and "WSD Scan" is set to [**On**] in the network settings.
- ➡ WSD Scan (page 8-31)
- For information on operating the computer, refer to the computer's help or the operation guide of your software.

### **Installing Driver Software**

In Windows 8, Windows 8.1 and Microsoft Windows Server 2012

## **1** Click [Search] in charms, [Control Panel], and then [View devices and printers].

#### Install the driver.

Click [Add a device]. Select the machine's icon and then click [Next].

When the machine's icon is displayed in "**Printers**" on the [**Devices and Printers**] screen, the installation is completed.

#### In Windows 7

#### Display [Network] in the Start menu.

Click [Start] button on the Windows and then select [Network].

#### 💽 NOTE

When [Network] does not appear in the Start menu, perform the following procedure.

- 1 Right-click [Start] and click [Property] in the menu that appears.
- 2 Select the [[Start] menu] tab in the "Task bar and [Start] menu properties" screen, and click [Customize].
- 3 When the "Customize [Start] menu" screen appears, select the "Network" check box and click [OK].

#### **2** Install the driver.

Right-click the machine's icon and then click [Install].

#### 💽 NOTE

If the "User Account Control" window appears, click [Continue]. If the "Found New Hardware" window appears, click [Cancel].

During the installation, double-click the icon shown on the task bar to display the "Driver Software Installation" screen. When "Your devices are ready to use" is displayed on the [Driver Software Installation] screen, the installation is completed.

#### In Windows 10

## Right-click [Start] button on the Windows and select [Control Panel] and then [View devices and printer].

#### **2** Install the driver.


Click [Add a device]. Select the machine's icon and then click [Next].


When the machine's icon is displayed in "**Printers**" on the [**Devices and Printers**] screen, the installation is completed.

### **WSD** scan

[Home] key > [Send]







Loading Originals (page 5-2)

3 Display the screen.

Select [WSD Scan].

#### Scan the originals.

Procedure using this machine

- 1 Select [From Operation Panel].
- Select the destination computer > [OK]
   Select [Reload] to reload the computer list.
   You can view information on the selected computer by selecting [\_\_\_].
- 3 Press the [Start] key.

Sending begins and the software installed on the computer is activated.

#### **Procedure from Your Computer**

- 1 [From Computer] > [OK]
- **2** Use the software installed on the computer to send the images.

## **Scanning with File Management Utility**

File Management Utility is an application that sends a scanned document to a specified network folder or PC. You can create a work flow with FMU for processing of the scanned document, and register the workflow in the machine as a favorite.

## **Configuring Settings before Sending**

To use this function, you must install File Management Utility on your computer and configure settings for the multifunction machine to be used, scanning conditions, and the file save location. To install File Management Utility, refer to the following.

Installing Software (page 2-37)

#### 

For information on using File Management Utility, refer to the following:

➡ File Management Utility User Guide

## **Recalling a Favorite Configured in FMU**

- **1** Make sure that File Management Utility is running on the computer (or server) on which File Management Utility is installed.
- **?** Place the original.

#### **3** Recall a favorite.

Select [**Favorites**] registered in the home screen, or select the icon that appears in [**Task Screen**] > [**Favorites**].

- **4** Follow the on-screen instructions to enter the necessary information and select [Next].
- **5** When the scan settings screen appears, select each item and configure the necessary settings.


The features that can be set depend on File Management Utility.

6 Press the [Start] key.

Sending starts.

# Sending to Different Types of Destinations (Multi Sending)

You can specify destinations that combine E-mail addresses, folders (SMB or FTP) and fax numbers. This is referred to as Multi Sending. This is useful for sending to different types of destination (E-mail addresses, folders, etc.) in a single operation.



No. of broadcast items: Up to 100

However, number of items are restricted for the following sending options.

Folders (SMP, FTP): Total of 5 SMB and FTP

Procedures are the same as used in specifying the destinations of respective types. Continue to enter E-mail address or folder path so that they appear in the destination list. Press the [**Start**] key to start transmission to all destinations at one time.

#### 

If the destinations include a fax, the images sent to all destinations will be black and white.

## Send to Me (E-mail)

When user login is enabled, the document is sent to the E-mail address of the logged in user.

#### 

- To use this function, user control must be set to network authentication and the e-mail address of the user must be registered in the network authentication server.
- For the procedure for setting an e-mail address, check with the administrator for network authentication server users.

## **Configuring Settings before Sending**

- To use this function, the function icon must be displayed in the home screen.
- Editing the Home Screen (page 2-13)

# Sending a document to the mail address of the logged in user



Select [Send to Me (E-mail)] .

#### 

If the e-mail address is not registered in the network authentication server, e-mail cannot be sent.

## **Canceling Sending Jobs**

#### **1** Select the [Stop] key with the send screen displayed.

#### **2** Cancel a job.

#### When there is a job is being scanned

Job Cancel appears.

#### When there is a job sending or on standby

Canceling job screen appears. Select the job you wish to cancel > [**Delete**] > [**Yes**]

#### 💽 ΝΟΤΕ

Selecting the [Stop] key will not temporarily stop a job that you have already started sending.

## **Handling Destination**

This section explains how to select and confirm the destination.

## **Specifying Destination**

Select the destination using either of the following methods except entering address directly:

- Choosing from the Address Book
  - Choosing from the Address Book (page 5-34)
- Choosing from the External Address Book
   For details on the External Address Book, refer to the following:
  - Command Center RX User Guide
- Choosing from One Touch key.
  - Choosing from the One Touch Key (page 5-37)
- Choosing from the FAX
  - FAX Operation Guide

#### 

- You can set the machine up so that the address book screen appears when you select the [Send] key.
- ➡ Default Screen (page 8-21)
- You can specify the fax destination. Enter the other party number using the numeric keypad.

### **Choosing from the Address Book**

For more information about how to register destinations in the Address Book, refer to the following:

Registering Destinations in the Address Book (page 3-20)

#### In the basic screen for sending, select [Address Book].

#### 💽 NOTE

For details on the External Address Book, refer to the following:

Command Center RX User Guide

#### 2 Select the destinations.

Select the checkbox to select the desired destination from the list. The selected destinations are indicated by a checkmark in the check box.

You can also select [Menu] to perform a more detailed search.

#### 💽 NOTE

To deselect, select the checkbox again and remove the checkmark.

#### **Destination Search**

Destinations registered in the Address Book can be searched.

1 -	Address Book (All)	- v v : c.			10:10	- 3
•	001 ABCD	1234		0	~	Ŭ
	002 EFGH	efg@	)efg.com	-	1/2	
	003	1234	5.com	-	1/2	
	004 MNOP	111	1.com	-	$\sim$	
2 —	Menu	Cancel	< Back	OK		

	Keys used	Search type	Subjects searched
1		Advanced search by destination	Advanced search by type of registered destination (Email, Folder (SMB/FTP), FAX or Group).
2	Narrow Down	Advanced search by destination	Advanced search by type of registered destination (Email, Folder (SMB/FTP), FAX or Group).
	Search (Name)	Search by name	Search by registered name.
	Search (No.)	Search by number	Search by registered address number.
	Sort (Name)	Change of display order	Sorts the list by destination name.
	Sort (No.)	Ulder	Sorts the list by destination address number.
3		Search by name	Search by registered name.

#### 🔇 NOTE

You can specify a destination by address number by selecting the [Quick No. Search] key.

### **3** Accept the destination > [OK]

Destinations can be changed later.

Confirmation Screen of Destinations (page 5-38)

#### **NOTE**

You can set the default "Sort" settings.

✤ Sort (page 8-23)

## **Choosing from the External Address Book**

#### NOTE

For details on the External Address Book, refer to the following:

#### Command Center RX User Guide

## In the basic screen for sending, select [External Address Book].



#### Select the destinations.

Select the checkbox to select the desired destination from the list. The selected destinations are indicated by a checkmark in the check box.

You can also select [Menu] to perform a more detailed search.

💽 NOTE

To deselect, select the checkbox again and remove the checkmark.

#### 3 Accept the destination > [OK]

Destinations can be changed later.

Confirmation Screen of Destinations (page 5-38)



You can set the default "Sort" settings.

Sort (page 8-23)

2

### **Choosing from the One Touch Key**

#### 💽 ΝΟΤΕ

This procedure assumes that One Touch Keys have already been registered. For more information on adding One Touch keys, refer to the following:

➡ Adding a Destination on One Touch Key (One Touch Key) (page 3-26)

#### In the basic screen for sending, select [One Touch Key].

#### Select the One Touch Keys where the destination is registered.

If the One Touch Keys for the desired destination is hidden on the touch panel, select  $[\sim]$  or  $[\wedge]$  to scroll and view next or previous One Touch Keys.

#### 💽 NOTE

You can specify a One Touch Key by one touch number by selecting the [Quick No. Search] key.

#### **3** Select [OK].

Destinations can be changed later.

Confirmation Screen of Destinations (page 5-38)

### **Checking and Editing Destinations**

#### Display the screen.

- 1 Specify the destination.
  - Specifying Destination (page 5-33)
- 2 Select [Check].

#### **?** Check and edit the destination.

To add a new destination, select [

To display details for the destinations, select [ \_\_\_\_]. New E-mail addresses and PC folders can be edited if they have been specified.

To delete the selected destination, select [2023].

#### 🚫 NOTE

- When selecting [On] for Entry Check for New Destination, the confirmation screen appears. Enter the same host name and path again, and select [OK].
- Entry Check for New Dest. (page 8-21)
- When selecting [**On**] for Destination Check before Send, the confirmation screen appears after pressing the [**Start**] key.
- <u>Dest. Check before Send (page 8-21)</u>
   <u>Confirmation Screen of Destinations (page 5-38)</u>

### **Confirmation Screen of Destinations**

When selecting **[On]** for Destination Check before Send, the confirmation screen of destinations appears after pressing the **[Start]** key.

Dest. Check before Send (page 8-21)

1

Check the destinations Destinations Check	and press [Check].	8	10:10
A OFFICE	1234567890	0	20
B OFFICE	2345678901		1/2
C OFFICE	3456789012	-	1/2
D OFFICE	4567890123	-	$\sim$
Menu	Cancel	Che	eck

#### Select [ $\checkmark$ ] or [ $\land$ ] to confirm all destination.

Selecting [ \_\_\_] shows the detailed information of the selected destination. To delete the destination, select the destination you want to delete > [ 📷 ] > [Yes] To add the destination, select [**Cancel**] and then return to the destination screen.

#### 2 Select [Check].

#### 

Be sure to confirm all destination by displaying them on the touch panel. You cannot select [**Check**] unless you have confirmed all destination.

### Recall

Recall is a function allowing you to send the last entered destination once again. When you want to send the image to the same destination, select [**Recall**], and you can call the destination you sent on the destination list.

#### Select [Recall].

The destination you sent is displayed on the destination list.

#### 

When the last sending included FAX, folders and E-mail destinations, they are also displayed. If necessary, add or delete the destination.

#### 2 Press the [Start] key.

Sending starts.

#### NOTE

- When [On] is selected in "Dest. Check before Send", a destination confirmation screen is displayed when you press the [Start] key.
- Confirmation Screen of Destinations (page 5-38)
- · Recall information is canceled in the following conditions.
  - When you turn the power off
  - When you send a next image (new recall information is registered)
  - When you log out

## How to use the FAX Function

FAX function can be used with the machine.

FAX Operation Guide

## **Using Document Boxes**

The available Document Boxes are as follows: Job Box, Removable Memory Box, Sub address Box, and Polling Box.

### What is Job Box?

Job Box is a generic name for the "Private Print/Stored Job Box", "Quick Copy/Proof and Hold Box". These Job Boxes cannot be created or deleted by a user.

#### 💽 ΝΟΤΕ

- To use the Stored Job Box and the Quick Copy Box, an SD/SDHC memory card must be installed in the device.
- To use the Private Print Box and the Proof and Hold Box, an expansion memory or SD/SDHC memory card must be installed in the device.
- You can set up the machine so that temporary documents in job boxes are automatically deleted.
- Deletion of Job Retention (page 8-22)
- · For details on operating the Job Box, refer to the following:
- Printing Data Saved in the Printer (page 4-11)

#### **IMPORTANT**

Unencrypted data is saved on the SD/SDHC memory card. Exercise caution when saving sensitive documents.

## What is Removable Memory Box?

A USB memory stick can be connected to the USB memory slot on the machine to print a saved file. You can print data directly from the USB memory without a PC. Image files scanned using this machine can also be saved to USB memory in the PDF, TIFF, JPEG, XPS, OpenXPS or high compression PDF format (Scan to USB).

## **Sub Address Box/Polling Box**

Sub Address Box/Polling Box store the fax data.

FAX Operation Guide

## **Operating using Removable USB Memory**

Plugging USB memory directly into the machine enables you to quickly and easily print the files stored in the USB memory without having to use a computer.

The following file types can be printed:

- PDF file (Version 1.7 or older)
- TIFF file (TIFF V6/TTN2 format)
- JPEG file
- XPS file
- OpenXPS file
- Encrypted PDF file

In addition, you can store scanned image files in USB memory connected to the machine.

The following file types can be stored:

- PDF file format
- TIFF file format
- JPEG file format
- XPS file format
- OpenXPS file format
- · High-compression PDF file format


### **Printing Documents Stored in Removable USB** Memory

#### NOTE

- PDF files you wish to print should have an extension (.pdf).
- Files to be printed should be saved no further down than the top 3 folder levels, including the root folder.
- · Use USB memory properly formatted by this machine.
- · Plug the USB memory directly into the USB Memory Slot.

#### Plug the USB memory.

1 Plug the USB memory into the USB Memory Slot.



2 When the machine reads the USB memory, "Removable Memory is recognized. Displaying files. Are you sure?" may appear. Select [**Yes**].

Displays the removable memory screen.

#### NOTE

If the message does not appear, select [Removable Memory] on the Home screen.

#### **2** Print the document.

**1** Select the folder containing the file to be printed.

The machine will display documents in the top 3 folder levels, including the root folder.

#### NOTE

- 1,000 documents can be displayed.
- To return to a higher level folder, select [Back].
- 2 Select the file to be printed > [Print]
- 3 Change the number of copies, duplex printing, etc. as desired.

For the features that can be selected, refer to the following:

- Removable Memory (Store File, Printing Documents) (page 6-6)
- 4 Press the [Start] key.


Printing of the selected file begins.


## **Saving Documents to USB Memory (Scan to USB)**



The maximum number of the storable files is 1,000.








► Loading Originals (page 5-2)

#### **2** Plug the USB memory.

1 Plug the USB memory into the USB Memory Slot.



2 When the machine reads the USB memory, "Removable Memory is recognized. Displaying files. Are you sure?" may appear. Select [**Yes**] to display the removable memory screen.

#### NOTE

If the message does not appear, select [Removable Memory] on the Home screen.

#### **3** Store the document.

1 Select the folder where the file will be stored.

The machine will display the top 3 folder levels, including the root folder.

2 Select [ 👘 ].



**3** Set the color mode, type of original, file format, etc., as desired.

For the features that can be set, refer to the following:

- Removable Memory (Store File, Printing Documents) (page 6-6)
- 4 Press the [Start] key.

The original is scanned and the data is stored in the USB memory.

### **Check the USB Memory Information**

1 In the removable memory screen, select [Menu] > [Memory Information].

**9** Once you confirm the information, select [End].

### **Removing USB Memory**

#### **IMPORTANT**

Be sure to follow the proper procedure to avoid damaging the data or USB memory.



#### Display the screen.

Select [Removable Memory] on the Home screen.

2

#### [Menu] > [Remove Memory]

Select [**OK**], and remove the USB memory after "Removable Memory can be safely removed." is displayed.

#### 💽 ΝΟΤΕ

USB memory can also be removed after checking the status of the device.

Device/Communication (page 7-11)

# **6 Using Various Functions**

#### This chapter explains the following topics:

Functions Available on the Machine	6-2
About Functions Available on the Machine	
Сору	
Send	
Removable Memory (Store File, Printing Documents)	
Functions	
Paper Selection	
Zoom	6-10
Density	
Duplex	
Combine	
Color Selection	
Collate	6-16
Original Size	6-17
Original Orientation	6-18
Mixed Size Originals	
Original Image	
EcoPrint	
Hue Adjustment	
Color Balance	
Sharpness	
Contrast	6-22
Background Density Adj. (Background Density Adjustment)	
Skip Blank Page	
Saturation	
Continuous Scan	6-24
Job Finish Notice	6-25
File Name Entry	6-26
Priority Override	6-26
File Format	6-27
Duplex (2-sided Original)	6-30
Sending Size	6-31
File Separation	6-31
Scan Resolution	6-32
E-mail Subject/Body	6-32
FTP Encrypted TX	6-33
Storing Size	
Encrypted PDF Password	
JPEG/TIFF Print	
XPS Fit to Page	6-34


## **Functions Available on the Machine**

## **About Functions Available on the Machine**

This machine provides the various functions available.

## Сору

To configure the settings for functions, select the function key. By selecting [**Functions**], other selectable functions will be shown as a list.



Ready to copy. (Full Color)		10:10
Functions		1-11
Collate	On	1
Original Size	A4 📷	1/5
Original Orientation	Top Edge on Top	1/5
Mixed Size Originals	Off	14
Close	Add/Ed Shortc	
<b>↑</b>		

For details on each function, see the table below.

Function key	Description	Reference page
Paper Selection	Select the cassette or multipurpose tray that contains the required paper size.	<u>page 6-9</u>
Zoom	Adjust the zoom to reduce or enlarge the image.	page 6-10
Density	Adjust density.	page 6-11
Duplex	Produces two-sided prints. You can also create single-sided prints from two-sided originals.	<u>page 6-12</u>
Combine	Combines 2 or 4 original sheets into 1 printed page.	page 6-14
Color Selection	Select the color mode setting.	page 6-16

Functions	Description	Reference page
Collate	Offsets the output by page or set.	<u>page 6-16</u>
Original Size	Specify the original size to be scanned.	page 6-17
Original Orientation	Select the orientation of the original document top edge to scan correct direction.	<u>page 6-18</u>
Mixed Size Originals	Scan the documents of different sizes that are set in the document processor all at once.	<u>page 6-19</u>
Original Image	Select original image type for best results.	page 6-19
EcoPrint	EcoPrint saves toner when printing.	page 6-20
Hue Adjustment	Adjust the color (hue) of images.	page 6-20
Color Balance	Adjust the strength of cyan, magenta, yellow, and black.	page 6-21
Sharpness	Adjusts the sharpness of image outlines.	page 6-22
Contrast	You can adjust the contrast between light and dark areas of the image.	page 6-22

Functions	Description	Reference page
Background Density Adj.	Removes dark background from originals, such as newspapers.	<u>page 6-23</u>
Skip Blank Page	When there are blank pages in a scanned document, this function skips the blank pages and prints only pages that are not blank.	page 6-23
Saturation	Adjust the color saturation of the image.	page 6-24
Continuous Scan	Scans a large number of originals in separate batches and then produce as one job.	page 6-24
Job Finish Notice	Sends E-mail notice when a job is complete.	page 6-25
File Name Entry	Adds a file name.	page 6-26
Priority Override	Suspends the current job and gives a new job top priority.	page 6-26

## Send

To configure the settings for functions, select the function key. By selecting [**Functions**], other selectable functions will be shown as a list.



Ready to send. (FullColor)		10:10
Functions		-
Color Selection	Black & White	0
File Format	PDF	1/7
Original Size	A4 📭	1,,
Original Orientation	Top Edge on Top	Q.
Close	Add/E Shorto	
<b>↑</b>		


For details on each function, see the table below.

Functions	Description	Reference page
Color Selection	Select the color mode setting.	<u>page 6-16</u>
File Format	Specify the image file format. Image quality level can also be adjusted.	page 6-27
Original Size	Specify the original size to be scanned.	page 6-17
Original Orientation	Select the orientation of the original document top edge to scan correct direction.	page 6-18
Mixed Size Originals	Scan the documents of different sizes that are set in the document processor all at once.	<u>page 6-19</u>
Duplex	Select the type and orientation of the binding based on the original.	page 6-30
Sending Size	Select size of image to be sent.	page 6-31
File Separation	Creates several files by dividing scanned original data page by page, and sends the files.	<u>page 6-31</u>
Scan Resolution	Select fineness of scanning resolution.	page 6-32
Density	Adjust density.	page 6-11
Original Image	Select original image type for best results.	page 6-19
Sharpness	Adjusts the sharpness of image outlines.	page 6-22
Contrast	You can adjust the contrast between light and dark areas of the image.	page 6-22
Background Density Adj.	Removes dark background from originals, such as newspapers.	page 6-23
Skip Blank Page	When there are blank pages in a scanned document, this function skips the blank pages and prints only pages that are not blank.	page 6-23
FAX TX Resolution	Select fineness of images when sending FAX.	Refer to the FAX Operation Guide.
Zoom	Adjust the zoom to reduce or enlarge the image.	page 6-10
Continuous Scan	Scans a large number of originals in separate batches and then produce as one job.	page 6-24
File Name Entry	Adds a file name.	page 6-26
E-mail Subject/Body	Adds subject and body when sending a document.	page 6-32
Job Finish Notice	Sends E-mail notice when a job is complete.	page 6-25

Functions	Description	Reference page
FTP Encrypted TX	Encrypts images when sending via FTP.	page 6-33
FAX Delayed Transmission	Set a send time.	Refer to the FAX Operation Guide.
FAX Direct Transmission	Sends FAX directly without reading original data into memory.	Refer to the FAX Operation Guide.
FAX Polling RX	Dial the destination and receive documents for Polling Transmission stored in the polling box.	Refer to the FAX Operation Guide.
FAX TX Report	Print a report of FAX transmission results.	Refer to the FAX Operation Guide.

## **Removable Memory (Store File, Printing Documents)**

To configure the settings for functions, select the function key. By selecting [Functions], other selectable functions will be shown as a list.



For details on each function, see the table below.

#### **Store File**

Function key	Description	Reference page
File Format	Specify the image file format. Image quality level can also be adjusted.	page 6-27
Duplex	Select the type and orientation of the binding based on the original.	page 6-30
Scan Resolution	Select fineness of scanning resolution.	page 6-32
Density	Adjust density.	page 6-11
File Name Entry	Adds a file name.	page 6-26
Color Selection	Select the color mode setting.	page 6-16

Functions	Description	Reference page
Original Size	Specify the original size to be scanned.	page 6-17
Original Orientation	Select the orientation of the original document top edge to scan correct direction.	page 6-18
Mixed Size Originals	Scan the documents of different sizes that are set in the document processor all at once.	<u>page 6-19</u>
Storing Size	Select size of image to be stored.	page 6-33
Original Image	Select original image type for best results.	page 6-19
Sharpness	Adjusts the sharpness of image outlines.	page 6-22
Contrast	You can adjust the contrast between light and dark areas of the image.	page 6-22
Background Density Adj.	Removes dark background from originals, such as newspapers.	page 6-23
Skip Blank Page	When there are blank pages in a scanned document, this function skips the blank pages and prints only pages that are not blank.	page 6-23
Zoom	Adjust the zoom to reduce or enlarge the image.	page 6-10
Continuous Scan	Scans a large number of originals in separate batches and then produce as one job.	page 6-24
Job Finish Notice	Sends E-mail notice when a job is complete.	page 6-25
File Separation	Creates several files by dividing scanned original data page by page, and sends the files.	page 6-31

#### **Printing Documents**

Function key	Description	Reference page
Paper Selection	Select the cassette or multipurpose tray that contains the required paper size.	<u>page 6-9</u>
Collate	Offsets the output by page or set.	<u>page 6-16</u>
Duplex	Print a document on both sides of the paper.	page 6-13
Color Selection	Select the color mode setting.	page 6-16

Functions	Description	Reference page
EcoPrint	EcoPrint saves toner when printing.	<u>page 6-20</u>
Job Finish Notice	Sends E-mail notice when a job is complete.	page 6-25
Priority Override	Suspends the current job and gives a new job top priority.	page 6-26
Encrypted PDF Password	Enter the preassigned password to print the PDF data.	<u>page 6-34</u>
JPEG/TIFF Print	Select the image size when printing JPEG or TIFF files.	page 6-34
XPS Fit to Page	Reduces or enlarges the image size to fit to the selected paper size when printing XPS file.	<u>page 6-34</u>

# **Functions**

On pages that explain a convenient function, the modes in which that function can be used are indicated by icons.



# **Paper Selection**



Select the cassette or multipurpose tray that contains the required paper size.

If [Auto] is selected, the paper matching the size of the original is selected automatically.

#### NOTE

· Specify in advance the size and type of the paper loaded in the cassette.

- Cassette/MP Tray Settings (page 8-8)
- · Cassette 2 is displayed when the optional paper feeder is installed.

To select [**MP tray**], select [**Paper Size**] and [**Media Type**], and specify the paper size and the media type. The available paper sizes and media types are shown in the table below.

lte	em	Value	Description
Paper Size	Metric	A4, A5-R, A5, A6, B5, B6, Folio, 216 × 340 mm	Select from the Metric standard sizes.
	Inch	Letter, Legal, Statement-R, Statement, Executive, Oficio II	Select from the Inch series standard sizes.
	Others	16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2, Custom <sup>*1</sup>	Select from special standard sizes and custom sizes.
	Size Entry	Metric X: 70 to 216 mm (in 1 mm increments) Y: 148 to 356 mm (in 1 mm increments) Inch X: 2.76 to 8.50" (in 0.01" increments) Y: 5.83 to 14.02" (in 0.01" increments)	Enter the size not included in the standard size. <sup>*2</sup> When you have selected [ <b>Size Entry</b> ], use [+]/[-] or the numeric keys to set the sizes of "X" (horizontal) and "Y" (vertical).
Media type		Plain (60 to 105 g/m <sup>2</sup> ), Transparency, Rough, Vellum (60 to 220 g/m <sup>2</sup> ), Labels, Recycled, Preprinted Bond, Cardstock, Color, Prepunched <sup>*3</sup> , Letterhead <sup>*3</sup> , Envelope, Thick (106 to 220 g/m <sup>2</sup> ), Coated, High Quality, Custom 1 to 8 <sup>*3</sup>	

- \*1 For instructions on how to specify the custom paper size, refer to the following:
   <u>Custom Paper Size (page 8-13)</u>
- \*2 The input units can be changed in System Menu. For details, refer to the following: ▶ Measurement (page 8-18)
- \*3 For instructions on how to specify the custom paper types 1 to 8, refer to the following: → Media Type Setting (page 8-15)
  - To print on preprinted or prepunched paper or on letterhead, refer to the following:
  - Special Paper Action (page 8-14)

### 阈 ΝΟΤΕ

• You can conveniently select in advance the size and type of paper that will be used often and set them as default.

- Multipurpose Tray (page 8-9)
- If the specified size of paper is not loaded in the paper source cassette or multipurpose tray, a confirmation screen appears. Load the required paper in the multipurpose tray and select [Continue] to start copying.

# Zoom




Adjust the zoom to reduce or enlarge the image.

### Copying

The following zoom options are available.

#### Auto

Adjusts the image to match the paper size.



#### **Standard Zoom**

Reduces or enlarges at preset magnifications.

Model	Zoom Level (Original Copy)		Model	Zoom Level (0	Original Copy)
Metric Models	400% Max.	90% Folio>>A4	Inch Models	400% Max.	78% Legal>>Letter
	200%	70%		200%	64% Letter>>Statement
	141% A5 >> A4	50%		129% Statement>>Letter	50%
	100%	25% Min.		100%	25% Min.


#### Others

Reduces or enlarges at magnifications other than the Standard Zoom.

Model	Zoom Level (Original Copy)		Model	Zoom Leve	l (Original Copy)
Metric Models	115% B5 >> A4	78% Legal>>Letter	Inch Models	141% A5 >> A4	86% A4 >> B5
	86% A4 >> B5 129% Statement>>Letter	64% Letter>>Statement		115% B5 >> A4 90% Folio>>A4	70% A4 >> A5

#### **Zoom Entry**

Manually reduces or enlarges the original image in 1% increments between 25% and 400%. Use the numeric keys or select [+] or [-] to enter the any magnification.



### Sending/Storing

Item	Description
100%	Reproduces the original size.
Auto	Reduces or enlarges original to sending/storing size.

### 

To reduce or enlarge the image, select the paper size, sending size, or storing size.

 Paper Selection (page 6-9) Sending Size (page 6-31) Storing Size (page 6-33)

# Density



Adjust density.

(Value: [-4] to [+4] (Lighter to Darker))




# **Duplex**



Produces two-sided prints. You can also create single-sided prints from two-sided originals.

The following modes are available.

### One-sided to Two-sided



Produces two-sided copies from one-sided originals. In case of an odd number of originals, the back side of the last copy will be blank.

The following binding options are available.

- A Binding Left/Right: Images on the second sides are not rotated.
- B Binding Top: Images on the second sides are rotated 180 degrees. Copies can be bound on the top edge, facing the same orientation when turning the pages.


#### Two-sided to One-sided



Copies each side of a two-sided original onto two individual sheets. The following binding options are available.

- Binding Left/Right: Images on the second sides are not rotated.
- Binding Top: Images on the second sides are rotated 180 degrees.

### Two-sided to Two-sided



Produces two-sided copies from two-sided originals.

### 阈 ΝΟΤΕ

The paper sizes supported in Two-sided to Two-sided mode: A4, B5, A5-R, Folio, Legal, Letter, Statement, Oficio II, Executive, 216 × 340 mm, ISO B5, Envelope C5, 16K

### vo-sided to Olie-sided

### Copying

Prints 1-sided originals to 2-sided, or 2-sided originals to 1-sided. Select the binding orientation for original and finished documents.

Item 1-sided>>1-sided		Value	Description	
		—	Disables the function.	
1-sided>>2-sided		-	Copy the original with the default setting. For the default	
2-sided>>	1-sided	-	<ul> <li>settings, refer to the following:</li> <li>Function Defaults (page 8-16)</li> </ul>	
2-sided>>2-sided		-		
Others	Duplex	1-sided>>1-sided, 1-sided>>2-sided, 2-sided>>1-sided, 2-sided>>2-sided	Select the desired duplex option.	
	Binding in Original <sup>*1</sup>	Left/Right, Top	Select the binding orientation of originals.	
	Binding in Finishing <sup>*2</sup>	Left/Right, Top	Select the binding orientation of copies.	
	Original Orientation	Top Edge on Top, Top Edge on Left	Select the orientation of the original document top edge to scan correct direction.	

\*1 Displayed when [2-sided>>1-sided] or [2-sided>>2-sided] is selected for "Duplex".

\*2 Displayed when [1-sided>>2-sided] or [2-sided>>2-sided] is selected for "Duplex".

When placing the original on the platen, consecutively replace each original and press the [Start] key.

After scanning all originals, select [Finish Scan] to start copying.

#### Printing

Print a document on both sides of the paper.

Item	Description
1-sided	Disables the function.
2-sided	Prints a 2-sided document so that the sheets are aligned properly for binding on the left or right.
2-sided	Prints a 2-sided document so that the sheets are aligned properly for binding on the top.

# Combine



Combines 2 or 4 original sheets into 1 printed page.

You can select the page layout and the type of boundary lines around the pages.

The following types of the boundary lines are available.





2





Positioning Mark

	Item	Value	Description
Off		—	Disables the function.
2 in 1		_	Copy the original with the default setting. For the default settings,
4 in 1		-	<ul> <li>refer to the following:</li> <li>Function Defaults (page 8-16)</li> </ul>
Others	Combine	Off, 2 in 1 (L to R/T to B), 2 in 1 (R to L/B to T), 4 in 1 (Right then Down), 4 in 1 (Left then Down), 4 in 1 (Down then Right), 4 in 1 (Down then Left)	Select the page layout of scanned originals.
	Border Line <sup>*1</sup>	None, Solid Line, Dotted Line, Positioning Mark	Select the boundary line type.
	Original Orientation <sup>*1</sup>	Top Edge on Top, Top Edge on Left	Select the orientation of the original document top edge to scan correct direction.

\*1 Appears when [2 in 1] or [4 in 1] is selected in "Combine".

#### Layout image

	Item	Image
2 in 1	L to R/T to B	
	R to L/B to T	
4 in 1	Right then Down	
	Left then Down	
	Down then Right	
	Down then Left	

### 

- The paper sizes supported in Combine mode: A4, A5-R, B5, Folio, 216 × 340 mm, Letter, Legal, Statement, Oficio II, 16K
- When placing the original on the platen, be sure to copy the originals in page order.

# **Color Selection**



Select the color mode setting.

### **Copying/Printing**

Item	Description	
Full Color	Prints documents in full color.	
Black & White	Prints documents in black and white.	

### Sending/Storing

Item	Description	
Full Color	Scans the document in full color.	
Grayscale	Scans the document in grayscale. Produces a smooth, detailed image.	
Black & White	Scans the document in black and white.	

# Collate



Offsets the output by page or set.

(Value: [Off] / [On])



# **Original Size**



Specify the original size to be scanned.

Select [Auto (DP)], [Metric], [Inch], or [Others] to select the original size.

Item	Value	Description
Auto (DP)	_	Automatically detect the original size.
Metric	A4, A5, A6, B5, B6, Folio, 216 × 340 mm	Select from the Metric standard sizes.
Inch Letter, Legal, Statement, Executive, Oficio II		Select from the Inch series standard sizes.
Others	16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2, Custom <sup>*1</sup>	Select from special standard sizes and custom sizes.

\*1 For instructions on how to specify the custom original size, refer to the following:

 Custom Original Size (page 8-11)

### NOTE

Select whether to automatically detect originals of the document processor.

→ Auto Detect Original Size (DP) (page 8-11)

Be sure to always specify the original size when using custom size original.

# **Original Orientation**




Select the orientation of the original document top edge to scan correct direction.

To use any of the following functions, the document's original orientation must be set.

- Duplex
- Combine
- Duplex (2-sided Original)

Select original orientation from [Top Edge on Top] or [Top Edge on Left].



### NOTE

The default setting for Original Orientation can be changed.

➡ Original Orientation (page 8-16)

# **Mixed Size Originals**



Scan the documents of different sizes that are set in the document processor all at once.


This function cannot be used if platen is used.

(Value: [Off] / [On])

#### **Supported Combinations of Originals**

Folio and A4 (Legal and Letter)

Folio	A4
(Legal)	(Letter)



## **Original Image**



Select original image type for best results.

### **Copying/Printing**

Item	Description	
Text+Photo <sup>*1</sup>	Best for mixed text and photo documents.	
Photo	Best for photos taken with a camera.	
Text	Best for documents that are mostly text.	
Graphic/Map <sup>*2</sup>	Best for graphics and maps.	
Printer Output <sup>*2</sup>	Best for documents printed on this machine originally.	

\*1 If gray text is not printed completely using [**Text + Photo**], selecting [**Text**] may improve the result.

\*2 This function is displayed while copying.

### Sending/Storing

Item	Description		
Text+Photo	Best for mixed text and photo documents.		
Photo	Best for photos taken with a camera.		
Text	Best for documents that are mostly text.		
Light Text/Fine Line	Clearly reproduces faint characters written in pencil, etc., and thin lines on map originals or diagrams.		
Text (for OCR) <sup>*1</sup>	Scanning produces an image that is suitable for OCR.		

\*1 This function is only available when "Color Selection" is set to [Black & White]. For details, refer to the following:

Color Selection (page 6-16)


# **EcoPrint**



EcoPrint saves toner when printing.

Use this function for test prints or any other occasion when high quality print is not required.

(Value: [Off] / [On])



# **Hue Adjustment**



Adjust the color (hue) of images.

Make adjustments such as adjusting red to a strong yellow-red or yellow to a strong green-yellow to make more creative copies.



When adjusting yellow to more green, blue to more magenta (the v part)





When adjusting yellowish-red to more yellow, bluish-cyan to more blue (the ▼ part)

Item	Description	
Off		
All	Adjust hue for all colors. Select [<] or [>] to adjust the hue.	
Individual	Select individual colors to adjust the hue. Select [ <b>Red</b> ], [ <b>Yellow</b> ], [ <b>Green</b> ], [ <b>Cyan</b> ], [ <b>Blue</b> ] or [ <b>Magenta</b> ] and then select [<] or [>] to adjust the hue.	

### 

This feature is used with full color and auto color copying.

These adjustments are especially useful on rich color images.

# **Color Balance**



Adjust the strength of cyan, magenta, yellow, and black.

#### Example:



Item		Description			
Off	Off				
On	Cyan	Select [ $\langle$ ] or [ $\rangle$ ] on each side of the color (Cyan, Magenta, Yellow, Black) to adjust			
	Magenta	each color.			
	Yellow				
	Black				

### 

This feature is used with full color and auto color copying.

## **Sharpness**



Adjusts the sharpness of image outlines.

When copying penciled originals with rough or broken lines, clear copies can be taken by adjusting sharpness toward "Sharpen". When copying images made up of patterned dots such as magazine photos, in which moire<sup>\*1</sup> patterns appear, edge softening and weakening of the moire effect can be obtained by setting the sharpness toward "Blur".

#### Less Sharp

#### Original







More Sharp

Item	Description	
[+1] to [+3] (Sharpen)	Emphasizes the image outline.	
[-1] to [-3] (Blur)	Blurs the image outline. Can weaken a Moire <sup>*1</sup> effect.	

\*1 Patterns that are created by irregular distribution of halftone dots.

# Contrast

[-1] to [-4] (Lower)



You can adjust the contrast between light and dark areas of the image.

Creates smoother colors.

Original Higher		
Description		
Increases the sharpness of colors.		
	Bescription	

# **Background Density Adj. (Background Density Adjustment)**



Removes dark background from originals, such as newspapers.

This feature is used with full color.

Item	Description	
Off	Does not adjust the ground color.	
Manual	Select [1] to [5] (Lighter - Darker) to adjust the background density manually.	

# **Skip Blank Page**



When there are blank pages in a scanned document, this function skips the blank pages and prints only pages that are not blank.

When set to [High], the level at which blank paper is recognized is higher.

The machine detects blank pages, saving unnecessary printing without the need to check for blank pages in the document.

Select [Low], [Middle] or [High] in [On].


### 

The originals with punched holes or originals printed on a colored substrate may not be recognized as blank pages.

# **Saturation**



Adjust the color saturation of the image.



### ο ΝΟΤΕ

This feature is used with full color.

Item	Description	
[-1] to [-3] (Grayish)	Results in paler color.	
[+1] to [+3] (Vivid)	Results in more vivid color.	

## **Continuous Scan**



Scans a large number of originals in separate batches and then produce as one job.

Originals will be scanned continuously until you select [Finish Scan].

(Value: [Off] / [On])



# **Job Finish Notice**



Sends E-mail notice when a job is complete.

Users can be notified of the completion of a job while working at a remote desk, saving the time spent waiting beside the machine to finish.

#### **NOTE**

PC should be configured in advance so that E-mail can be used.

#### ✤ Command Center RX (page 2-52)

E-mail can be sent to a single destination.

ltem	Description	
Off	Disables the function.	
On	Displays the destination list.	
	<ul> <li>Add a Destination</li> <li>To add a new destination, select [Menu] &gt; [Add].</li> <li>Address Book: Select the notification destination from the address book and select [OK].</li> <li>Ext. Address Book<sup>*1</sup>: Select the notification destination from the external address book.</li> <li>Address Entry: Enter the e-mail address directly. Enter the address (up to 128 characters) and select [OK].</li> </ul>	
	My Address <sup>*2</sup> : Uses the e-mail address of the logged in user.      Check the Destination     To display details for the destinations, select [].      Delete the Destination     To delete the selected destination, select [ ].	

\*1 For details on the External Address Book, refer to the following:

Command Center RX User Guide

\*2 Displayed when user login administration is enabled.

# **File Name Entry**



Adds a file name.

Additional information such as job number and date and time can also be set. You can check a job history or job status using the file name, date and time, or job number specified here.

Enter the file name (up to 32 characters), and select [Next].

To add date and time, select [Date and Time]. To add job number, select [Job No.]. To add both, select [Job No. & Date and Time] or [Date and Time & Job No.].

# **Priority Override**



Suspends the current job and gives a new job top priority.

The suspended job resumes after the other job is finished.

(Value: [Off] / [On])

#### 💽 NOTE

- This function is not available if current job was an override.
- Priority override may not be available depending on the status of the current print job and memory usage.

# **File Format**




Specify the image file format. Image quality level can also be adjusted.

Select the file format from [PDF], [TIFF], [JPEG], [XPS], [OpenXPS], and [High Comp. PDF].

When the color mode in scanning has been selected for Grayscale or Full Color, set the image quality.

If you selected [PDF] or [High Comp. PDF], you can specify encryption or PDF/A settings.



	ltem	Value	Description
PDF		—	Set the file format selected.
High Comp	D. PDF	—	The image quality and PDF/A settings will be the default settings. For the default settings, refer to the following:
TIFF		_	Function Defaults (page 8-16)
JPEG		_	
XPS		_	
OpenXPS		_	
Others	File Format	PDF, High Comp. PDF, TIFF, JPEG, XPS, OpenXPS	Select the image file format.
	Image Quality <sup>*1</sup>	Compression Ratio Priority, Standard, Quality Priority	Set the quality level for High Compression PDF.
	Image Quality <sup>*2</sup>	1 Low (High Comp.) to 5 High (Low Comp.)	Set the image quality.
	PDF/A <sup>*3</sup>	Off, PDF/A-1a, PDF/A-1b	Set PDF/A-1 format type.
	Encryption <sup>*3</sup>	—	You can use PDF encryption functions.
			PDF Encryption Functions (page 6-28)

\*1 Displayed when [High Comp. PDF] is selected for "File Format".

\*2 Displayed when something other than [High Comp. PDF] is selected for "File Format".

\*3 Displayed when [PDF] or [High Comp. PDF] is selected for "File Format".

### ο ΝΟΤΕ

If encryption is enabled, PDF/A settings cannot be specified.

### **PDF Encryption Functions**

If you have selected PDF or High Comp. PDF for file format, you can restrict the access level for displaying, printing, and editing PDF's by assigning a secure password.

#### Select [Others], [PDF] or [High Comp. PDF] in [File Format], and select [Encryption].

Items that can be set vary depending on the setting selected in [Compatibility].

#### Acrobat 3.0 and later, Encryption Level: Middle(40-bit)

ltem	Value	Description
Password to Open Document	Off, On	Enter the password to open the PDF file. Select [ <b>On</b> ], enter a password (up to 256 characters) and then select [ <b>Next</b> ]. Enter the password again for confirmation, and select [ <b>OK</b> ].
Password to Edit/Print Document	Off, On	<ul> <li>Enter the password to edit the PDF file.</li> <li>Select [<b>On</b>], enter a password (up to 256 characters) and then select [<b>Next</b>].</li> <li>Enter the password again for confirmation, and select [<b>OK</b>].</li> <li>When you have entered the password to edit/print document, you can specifically limit the operation.</li> </ul>
Printing Allowed	Not Allowed, Allowed	Restricts printing of the PDF file.
Changes Allowed	Not Allowed	Disables the change to the PDF file.
	Commenting Page Layout except extracting Pages	Can only add commenting. Can change the page layout except extracting the pages of the PDF file.
	Any except extracting Pages	Can conduct all operations except extracting the pages of the PDF file.
Copying of Text/Images/Others	Disable, Enable	Restricts the copying of text and objects on the PDF file.

#### Acrobat 5.0 and later, Encryption Level: High(128-bit)

ltem		Value	Description
Password to Oper	n Document	Off, On	Enter the password to open the PDF file.
			Select [ <b>On</b> ], enter a password (up to 256 characters) and then select [ <b>Next</b> ].
			Enter the password again for confirmation, and select [OK].
Password to Edit/	Print	Off, On	Enter the password to edit the PDF file.
Document			Select [ <b>On</b> ], enter a password (up to 256 characters) and then select [ <b>Next</b> ].
			Enter the password again for confirmation, and select [OK].
			When you have entered the password to edit/print document, you can specifically limit the operation.
Printing All	owed	Not Allowed	Disables the printing of PDF file.
		Allowed (Low Resolution only)	Can print the PDF file only in low resolution.
		Allowed	Can print the PDF file in original resolution.
Changes Al	llowed	Not Allowed	Disables the change to the PDF file.
		Inserting/Deleting/Rotating Pages	Can only insert, delete, and rotate the pages of the PDF file.
		Commenting	Can only add commenting.
		Any except extracting Pages	Can conduct all operations except extracting the pages of the PDF file.
Copying of Text/Images		Disable, Enable	Restricts the copying of text and objects on the PDF file.

# **Duplex (2-sided Original)**



Select the type and orientation of the binding based on the original.

Item		Value	Description	
1-sided		—	Disables the function.	
2-sided		_	Set when using a 2-sided sheet original.	
Others	Duplex	1-sided, 2-sided (Binding Left/Right), 2-sided (Binding Top)	Select the binding orientation of originals.	
	Original Orientation <sup>*1</sup>	Top Edge on Top, Top Edge on Left	Select the orientation of the original document top edge to scan correct direction.	

\*1 Displayed when [2-sided (Binding Left/Right)] or [2-sided (Binding Top)] is selected in "Duplex".

### Sample image

	Value	Image
2-sided	Binding Left/Right	
	Binding Top	

# **Sending Size**



Select size of image to be sent.

Select [Same as Original Size], [Metric], [Inch], or [Others] to select the sending size.

Item	Value	Description
Same as Original Size	_	Automatically sends the same size as the original.
Metric	A4, A5, A6, B5, B6, Folio, 216 × 340 mm	Select from the Metric standard sizes.
Inch	Letter, Legal, Statement, Executive, Oficio II	Select from the Inch series standard sizes.
Others	16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufukuhagaki (Return postcard), Youkei 4, Youkei 2	Select from special standard sizes and custom sizes.

#### Relationship between Original Size, Sending Size, and Zoom

Original Size, Sending Size and Zoom are related to each other. For details, see the table below.

Original size and sending size are	the same	different
Original Size (page 6-17)	Specify as necessary.	Specify as necessary.
Sending Size	Select [Same as Original Size].	Select the desired size.
Zoom (page 6-10)	Select [100%] (or [Auto]).	Select [Auto].

### NOTE

When you specify the sending size that is different from the original size, and select the zoom of [100%], you can send the image as the actual size (No Zoom).

# **File Separation**



Creates several files by dividing scanned original data page by page, and sends the files.

(Value: [Off] / [Each Page])

Select [Each Page] to set File Separation.



### NOTE

A three-digit serial number such as "abc\_001.pdf, abc\_002.pdf..." is attached to the end of the file name.

# **Scan Resolution**



Select fineness of scanning resolution.

(Value: [600 × 600dpi] / [400 × 400dpi Ultra] / [300 × 300dpi] / [200 × 400dpi Super] / [200 × 200dpi Fine] / [200 × 100dpi Normal])



### NOTE

The larger the number, the better the image resolution. However, better resolution also means larger file sizes and longer send times.


When scanning a two-sided original in full color or grayscale, [600 × 600dpi], [400 × 400dpi Ultra], and [200 × 400dpi Super] cannot be selected.

# E-mail Subject/Body



Adds subject and body when sending a document.

Select [Subject] / [Body] to enter the E-mail subject/body.



### 阈 ΝΟΤΕ

The subject can include up to 60 characters, and the body can include up to 500 characters.

# **FTP Encrypted TX**



Encrypts images when sending via FTP.

Encryption secures the document transmission.

(Value: [Off] / [On])

#### 

Click [**Security Settings**], and then [**Network Security**] in the Command Center RX. Be sure that "SSL" of Secure Protocol Settings is "On" and one or more effective encryption are selected in Client side settings.

Command Center RX User Guide

## **Storing Size**



Select size of image to be stored.

Select [Same as Original Size], [Metric], [Inch], or [Others] to select the storing size.

Item	Value	Description
Same as Original Size —		Store an image the same size as the original.
Metric	A4, A5, A6, B5, B6, Folio, 216 × 340 mm	Select from the Metric standard sizes.
Inch	Letter, Legal, Statement, Executive, Oficio II	Select from the Inch series standard sizes.
Others	16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufukuhagaki (Return postcard), Youkei 4, Youkei 2	Select from special standard sizes and custom sizes.

#### Relationship between Original Size, Storing Size, and Zoom

Original Size, Storing Size and Zoom are related to each other. For details, see the table below.

Original Size and the size you wish to store as are	the same	different
Original Size (page 6-17)	Specify as necessary.	Specify as necessary.
Storing Size	Select [Same as Original Size].	Select the desired size.
Zoom (page 6-10)	Select [100%] (or [Auto]).	Select [Auto].

### 🚫 NOTE

When you select Storing Size that is different from Original Size, and select the Zoom [100%], you can store the image as the actual size (No Zoom).

# **Encrypted PDF Password**



Enter the preassigned password to print the PDF data.

Enter the Password, and select [OK].

### NOTE

For details on entering the password, refer to the following:

Character Entry Method (page 11-8)

# **JPEG/TIFF** Print



Select the image size when printing JPEG or TIFF files.

(Value: [Paper Size] / [Image Resolution] / [Print Resolution])




Item	Description
Paper Size	Fits the image size to the selected paper size.
Image Resolution	Prints at resolution of the actual image.
Print Resolution	Fits the image size to the print resolution.

# **XPS Fit to Page**



Reduces or enlarges the image size to fit to the selected paper size when printing XPS file.

(Value: [Off] / [On])



# 7 Status/Job Cancel

#### This chapter explains the following topics:

Checking Job Status	7-2
Details of the Status Screens	7-3
Checking Detailed Information of Jobs	7-7
Checking Job History	7-8
Checking the Detailed Information of Histories	7-9
Sending the Log History	7-9
Job Operation	7-10
Pause and Resumption of Jobs	7-10
Canceling of Jobs	7-10
Device/Communication	
Checking the Remaining Amount of Toner and Paper (Paper/Supplies)	7-13

# **Checking Job Status**

Check the status of jobs being processed or waiting to be printed.

#### **Available Status Screens**

The processing and waiting statuses of jobs are displayed as a list on the touch panel in four different screens - Printing Jobs, Sending Jobs, Storing Jobs, and Scheduled Jobs.

The following job statuses are available.

Status Display	Job status to be displayed
Print Job Status	<ul> <li>Copy</li> <li>Printer</li> <li>FAX reception</li> <li>E-mail reception</li> <li>Printing from Document Box</li> <li>Printing data from removable memory</li> <li>Application</li> <li>Job Report/List</li> </ul>
Send Job Status	<ul> <li>FAX transmission</li> <li>E-mail</li> <li>Folder transmission</li> <li>Application</li> <li>Multiple destination</li> </ul>
Store Job Status	<ul><li>Scan</li><li>FAX</li><li>Printer</li></ul>
Scheduled Job	Sending Job FAX using Delayed transmission

#### **Displaying Status Screens**

#### Display the screen.

Select the [Status/Job Cancel] key.

### 9 Select the job you want to check.

Select either of [**Print Job Status**], [**Send Job Status**], [**Store Job Status**] or [**Scheduled Job**] to check the status.

 Print Job Status Screen (page 7-3) Send Job Status Screen (page 7-4) Store Job Status Screen (page 7-5) Scheduled Job Status Screen (page 7-6)

# **Details of the Status Screens**

### NOTE


- You can show the job statuses of all users, or only the statuses of your own jobs.
- Display Status/Log (page 8-19)
- This setting can be changed from Command Center RX.
- Command Center RX User Guide

#### **Print Job Status Screen**




No.	ltem	Description	
1	Job No.	Acceptance No. of job	
2	Туре	Icons that indicate the job type	
		Сору јоб	
		Printer job	
		Job from Document Box	
		Job from Document Box         FAX reception         E-mail reception         Data from removable memory	
		E-mail reception	
		Data from removable memory	
		Application	
		Report/List	
3	Job Name	Job Name or file name	
4	[]	Select this key for the job for which you wish to display detailed information.	
		Checking Detailed Information of Jobs (page 7-7)	
5	Status	Status of job	
		(Number of copies printed)/(Total number of copies to be printed): Printing	
		Processing: The status before starting to print.	
		Waiting: Print Waiting	
		Pause: Pausing print job or error	
		Canceling: Canceling the job	
6	[Cancel]	Select the job you want to cancel from the list, and select this key.	
7	[Pause All Print Jobs]	Pauses all the printing jobs. By selecting this key again, the printing jobs will be resumed.	

### Send Job Status Screen



No.	Item	Description	
1	Job No.	Acceptance No. of job	
2	Туре	Icons that indicate the job type Sending Job FAX Sending Job E-mail Sending Job Folder (SMB/FTP) Sending Job Application Multi Sending	
3	Job Name	Job Name or file name	
4	[ _]	<ul> <li>Select this key for the job for which you wish to display detailed information.</li> <li><u>Checking Detailed Information of Jobs (page 7-7)</u></li> </ul>	
5	Status	Status of job         Processing: The status before starting sending such as during scanning originals         Sending: Sending         Waiting: Waiting Sending         Canceling: Canceling the job         Pause: Pausing the job	
6	[Cancel]	Select the job you want to cancel from the list, and select this key.	

### Store Job Status Screen



No.	Item	Description
1	Job No.	Acceptance No. of job
2	Туре	Icons that indicate the job type         Storing Job Scan         Storing Job Printer         E       Storing Job FAX
3	Job Name	Job name or file name is displayed.
4	[=]	Select this key for the job for which you wish to display detailed information.
5	Status	Status of job Processing: The status before starting to save such as during scanning originals Storing: Storing Data Canceling: Canceling the job Pause: Pausing the job
6	[Cancel]	Select the job you want to cancel from the list, and select this key.

### **Scheduled Job Status Screen**



No.	Item	Description
1	Job No.	Acceptance No. of job
2	Туре	Icons that indicate the job type Storing Job FAX
3	Destination	Destination (Either destination name, FAX number, or No. of broadcast items)
4	[]	<ul> <li>Select this key for the job for which you wish to display detailed information.</li> <li>Checking Detailed Information of Jobs (page 7-7)</li> </ul>
_		
5	Start Time	Time to start the scheduled job
6	[Menu]	Selecting this key displays [ <b>Start Now</b> ]. Select the job you wish to send immediately > [ <b>Menu</b> ] > [ <b>Start Now</b> ]
7	[Cancel]	Select the job you want to cancel from the list, and select this key.

# **Checking Detailed Information of Jobs**

### 

When you have logged in as a user, you can only check your own jobs. When you have logged in as administrator, you can check all jobs.

### Display the screen.

Details of the Status Screens (page 7-3)

### **2** Check the information.

1 Select [ \_\_\_\_] for the job for which you wish to display detailed information.

Send Job Status		-		
0005		rocess		
1				
	1	1/1		
1	12	$\sim$		
Menu	Cancel	Close		

Detailed information of the selected job is displayed.

Use  $[\checkmark]$  or  $[\land]$  to see the next or previous page of information. More detailed information can be checked if a white item is selected.

In Sending Jobs, you can check the destination by selecting [Status/Destination].

2 To exit from the detailed information, select [End].

# **Checking Job History**

### 

- · Job history is also available by Command Center RX or KYOCERA Net Viewer from the computer.
- Command Center RX User Guide
- KYOCERA Net Viewer User Guide
- You can show the job log of all users, or only your own job log.
- Display Status/Log (page 8-19)
- This setting can also be changed from Command Center RX.
- Command Center RX User Guide

#### **Available Job History Screens**

The job histories are displayed separately in four screens - Printing Jobs, Sending Jobs, Storing Jobs, and FAX Jobs. The following job histories are available.

Screen	Job histories to be displayed
Print Job Log	• Сору
	Printer
	FAX reception
	E-mail reception
	Printing from Document Box
	Job Report/List
	Printing data from removable memory
	Application
Send Job Log	• FAX
	• E-mail
	• Folder
	Application
	Multiple destination
Store Job Log	• Scan
	• FAX
	Printer
FAX Job Log	FAX Operation Guide

#### **Display Job History Screen**

Display the screen.

Select the [Status/Job Cancel] key.

#### **7** Select the job you want to check.

1

# **Checking the Detailed Information of Histories**

#### Display the screen.

Display Job History Screen (page 7-8)

### **2** Check the information.

1 Select [\_\_\_] for the job for which you wish to check details.

		10:10
	Completed	
-	Canceled	1/3
-	Completed	
-	Error	$\sim$
		Canceled Canceled Canceled

Detailed information of the selected job is displayed.

### 

To check the information of the next/previous page, select  $[\lor]$  or  $[\land]$ .

2 To exit from the detailed information, select [Close].

# **Sending the Log History**

You can send the log history by E-mail. You can either send it manually as needed or have it sent automatically whenever a set number of jobs is reached.

Sending Log History (page 8-7)

# **Job Operation**

# **Pause and Resumption of Jobs**

Pause/resume all printing jobs in printing/waiting.

**1** Display the screen.

Select the [Status/Job Cancel] key.

**2** Select [Pause All Print Jobs] on the printing jobs status screen.

Printing is paused.

When resuming the printing of jobs that have been paused, select [Resume All Print Jobs].

# **Canceling of Jobs**

A job in printing/waiting status can be canceled.

**1** Display the screen.

Select the [Status/Job Cancel] key.

**2** Select the job to be canceled from the list, and select [Cancel].

**3** Select [Yes] in the confirmation screen.

# **Device/Communication**

Configure the devices/lines installed or connected to this machine or check their status.

#### Display the screen.

- 1 Select the [Status/Job Cancel] key.
- 2 Select the device you wish to check.

The screen to check the status or configure the devices is displayed.

#### 2 Check the status.

The items you can check are described below.

#### "Scanner"

Statuses such as the original scanning status and standby are displayed.

#### "Printer"

Error information such as waiting or printing are displayed.

#### "FAX"

- The information such as sending/receiving and dialing is displayed.
- Select [Line Off] to cancel a fax in sending/receiving.
  - FAX Operation Guide

#### "Removable Memory (USB Memory)"

- The usage, capacity and free space of the external media connected to this machine are displayed.
- Select [Menu] > [Format] to format external media.

# IMPORTANTWhen [Format] is selected, all data in the external media is erased.

• Select [**Remove**] to safely remove the external media.

#### "USB Keyboard"

The status of the optional USB Keyboard is displayed.

#### "Network Connection Status"

The network connection status appears.

#### "Wi-Fi Direct"

- This function is displayed when the wireless network function is available on the machine.
- Information on the device that is connected by Wi-Fi Direct appears.
- Select [Connected Device List] to display the list of connected devices. To refresh the list, select [Reload] in the Connected Device List screen. To disconnect all devices, select [Disconnect All].
- Select [**Push Button Setup**] and execute the push button of the device you want to connect to start the connection to the machine.

#### "Wi-Fi"

- This function is displayed when the wireless network function is available on the machine.
- The Wi-Fi connection status and network name (SSID) of the machine appear.

# **Checking the Remaining Amount of Toner** and Paper (Paper/Supplies)

Check the remaining amount of toner, and paper on the touch panel.

#### **Display the screen.** 1

- 1 Select the [Status/Job Cancel] key.
- 2 Select the device you wish to check.

#### 2

#### Check the status.

The items you can check are described below.

#### "Toner Status"

The amount of toner remaining is shown in levels.

#### "Paper Status"

The amount of paper remaining is shown.

8

# Setup and Registration (System Menu)

This chapter explains the following topics:

System Menu	8-2
Operation Method	8-2
System Menu Settings	8-3
Language	8-5
Report	8-5
User Property	8-7
Cassette/MP Tray Settings	8-8
Common Settings	8-10
Home	8-19
Сору	8-20
Send	8-21
Document Box	8-22
FAX	8-22
Address Book/One Touch	8-22
User Login/Job Accounting	8-23
Printer	8-24
System/Network	8-26
Date/Timer/Energy Saver	8-38
Adjustment/Maintenance	8-41

# System Menu

Configure settings related to overall machine operation.

# **Operation Method**

#### 1

#### **Display the screen.**

Select the [System Menu/Counter] key.

### Select a function.

Date/Time

Date Format

Time Zone

Auto Panel Reset

System Menu/Counter. System Menu	10:10
Quick Setup Wizard	A
Language	
Report	• 1/5
Counter	$\sim$
	Close 2
System Menu/Counter.	10:10

	_		values of
	1/5		entirety
		3	Displays

- 1 Displays the System Menu items.
- 2 Scrolls up and down when the list of cannot be displayed in its on a single screen.
- s setting items. Select the key of a function to display the setting screen.
- 4 Returns to the previous screen.

Configure the settings.

10/10/2014 10:10

+09:00 Osaka, Sapporo, Tokvo

< Back

DD/MM/YYYY

On



- 1 Selecting a value it to be accepted.
- Returns to the original screen without 2 making any changes.
- 3 Accepts the settings and exits.

#### NOTE

In order to change settings that require administer privileges, you must log in with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600 Login Password: 2600

If function default settings have been changed, the [Reset] key can be selected in each function screen to immediately change the settings.

Refer to System Menu Settings on the following page and configure as needed.

# **System Menu Settings**

This section explains the functions that can be configured in System Menu. To configure the settings, select the item in System Menu and select the setting item. For details on each function, see the table below.

The Quick Setup Wizard configures Fax, Paper, Network and Energy Saver settings.		
anguage displayed on the touch panel.	page 8-5	
s to check the machine settings, status, and history. Settings	page 8-5	
or printing reports can also be configured.		
	page 8-6	
	page 8-7	
the number of pages printed or scanned.	page 2-50	
to view information about logged in users and edit some of tion.	<u>page 8-7</u>	
of paper in Cassette 1 (2).	page 8-8	
of paper in multipurpose tray.	page 8-9	
creen appearing right after start-up (default screen).	page 8-10	
for buzzer sound during the machine operations.	page 8-10	
settings for originals.	page 8-11	
settings for paper.	page 8-13	
the values automatically set after the warm-up is completed <b>at</b> ] key is selected. ults for available settings such as copying and sending. Setting	<u>page 8-16</u>	
ly-used values as defaults makes subsequent jobs easier.		
number of copies that can be made at one time.	page 8-17	
her to cancel or continue the job when error has occurred.	page 8-18	
her printing is prohibited or the Print in Black and White ed for printing once the color toner runs out.	<u>page 8-18</u>	
c or inch for the unit for paper dimensions.	page 8-18	
ount of remaining toner to notify the administrator when to er when the toner is running low.	page 8-18	
layout of the touch panel keyboard used to enter characters.	page 8-19	
ype of USB keyboard that you want to use.	page 8-19	
SD/SDHC memory card.	page 8-19	
lay method of the Status/Log.	page 8-19	
her the confirmation message is displayed, when Power essed.	page 8-19	
ettings for Home screen.	page 8-19	
settings for copying functions.	page 8-20	
sattings for sanding functions	page 8-21	
settings for sending functions.	page 8-22	
	settings for copying functions. settings for sending functions. settings related to the Job Box, Sub Address Box and Polling etails on Sub Address Box and Polling Box, refer to the following:	

Item	Description	Reference Page
FAX	<ul> <li>Configures settings for fax functions.</li> <li>FAX Operation Guide</li> </ul>	—
Address Book/One Touch	Configures Address Book and One Touch Key settings. Address Book: ▲ <u>Adding a Destination (Address Book) (page 3-20)</u> One Touch Key: ▲ <u>Adding a Destination on One Touch Key (One Touch Key) (page 3-26)</u>	page 8-22
User Login/Job Accounting	Configures settings related to machine management. User Login: <ul> <li><u>Overview of User Login Administration (page 9-2)</u></li> <li>Job Accounting:</li> <li><u>Overview of Job Accounting (page 9-28)</u></li> </ul>	_
Printer	Printing from computers, settings are generally made on the application software screen. However, the following settings are available for configuring the defaults to customize the machine.	page 8-24
Network	Configures network settings.	page 8-26
Primary Network (Client)	Specify the network to be used for the send function, the network authentication and connecting to external address book.	<u>page 8-36</u>
Interface Block Setting	This allows you to protect this machine by blocking the interface with external devices such as USB hosts.	<u>page 8-36</u>
Security Level	The Security Level setting is primarily a menu option used by service personnel for maintenance work. There is no need for customers to use this menu.	—
Restart	Restart the machine without turning the power switch off. Use this to deal with any unstable operation by the machine. (Same as the computer restart.)	<u>page 8-37</u>
RAM Disk Setting	A RAM disk can be created and its size can be set.	page 8-37
Optional Memory	When optional memory is installed, select the memory allocation scheme based on the application in which you are using the equipment.	page 8-37
Optional Function	You can use the optional applications installed on this machine.	page 8-37
Date/Timer/Energy Saver	Configures settings related to the date and time.	page 8-38
Adjustment/Maintenance	Adjust printing quality and conduct machine maintenance.	page 8-41

### Language

[System Menu/Counter] key > [Language]

Item Description	
Language	Select the language displayed on the touch panel.

### Report

Print reports to check the machine settings, status, and history. Settings for printing reports can also be configured.

### **Report Print**

#### [System Menu/Counter] key > [Report] > [Report Print]

Item	Description		
Status Page	Prints the status page, allowing you to check the information including current settings, memory capacity, and optional equipment installed.		
Font List	Prints the font list, allowing you to check the font samples installed in the machine.		
Network Status	Prints the network status, allowing you to check the information including network interface firmware version, network address and protocol.		
Service Status	Prints the service status. More detailed information is available than on the Status Page. Service personnel usually print the service status pages for maintenance purpose.		

ltem	Description
Accounting Report	Prints the accounting report, allowing you to check the accounts that have been registered on the machine.
Sub Address Box List	Prints the report on the FAX function.
FAX List (Index)	➡ FAX Operation Guide
FAX List (No.)	
Outgoing FAX Report	
Incoming FAX Report	

#### **Admin Report Settings**

#### [System Menu/Counter] key > [Report] > [Admin Report Settings]

Configure settings for Outgoing FAX report and Incoming FAX report.

✤ FAX Operation Guide

#### **Result Report Settings**

#### [System Menu/Counter] key > [Report] > [Result Report Settings]

	ltem	Description
Send Result Report		Automatically print a report of transmission result when a transmission is complete.
E-mail/Folder		Automatically print a report of transmission result when E-mail or SMB/FTP transmission is complete. Value: Off, On, Error Only
-	FAX	FAX Operation Guide
	Canceled before Sending <sup>*1</sup>	Print a send result report if the job is canceled before being sent. Value: Off, On
	Recipient Format <sup>*1</sup>	Select the Recipient Format for the send result report. Value: Name or Destination, Name and Destination
RX Result Report		FAX Operation Guide
Job Finish Notice Setting		Attaches sent images to job finish notices. Value: Do Not Attach Image, Attach Image

\*1 When "E-mail/Folder" and "FAX" are set to [Off], this function will not be displayed.

### Sending Log History

#### [System Menu/Counter] key > [Report] > [Sending Log History]

Item	Description	
Sending Log History	You can also send the log history to the specified destinations manually.	
Auto Sending	<ul> <li>This function automatically sends the log history to the specified destinations whenever a set number of jobs has been logged.</li> <li>Value: Off, On</li> <li>NOTE</li> <li>If [On] is selected, specify the number of job histories. The setting range is 1 to 16.</li> </ul>	
Destination	Set the destination to which log histories are sent. Only E-mail address can be set.	
Job Log Subject	Set the subject automatically entered when sending log histories by E-mail. Value: Up to 60 characters	
Personal Information	Select whether to include personal information in the job log. Value: Include, Exclude	

### **User Property**

#### [System Menu/Counter] key > [User Property]

Allows you to view information about logged in users and edit some of that information.

Enabling User Login Administration (page 9-3)

# **Cassette/MP Tray Settings**

Select paper size and media type for cassettes and multipurpose tray.

#### Cassette 1 (2)

#### [System Menu/Counter] key > [Cassette/MP Tray Settings] > [Cassette 1 (2)]

Select paper size and media type for Cassettes 1 and 2.

Selection Item		Selectable Size/Type
Paper Size	Metric	Select from the Metric standard sizes. Values: A4, A5-R, A5, A6, B5, B6, Folio, 216 × 340 mm
	Inch	Select from the Inch series standard sizes. Values: Letter, Legal, Statement-R, Executive, Oficio II
	Other	Select from special standard sizes and custom sizes. Values: 16K, ISO B5, Custom <sup>*1</sup>
Media type <sup>*2</sup>		Select the media type. Values: Plain (60 to 105 g/m <sup>2</sup> ), Rough, Vellum (60 to 163 g/m <sup>2</sup> ), Recycled, Preprinted <sup>*3</sup> , Bond, Color, Prepunched <sup>*3</sup> , Letterhead <sup>*3</sup> , Thick (106 to 163 g/m <sup>2</sup> ), High Quality, Custom 1 to 8

\*1 The custom paper sizes are set for each cassette. → <u>Custom Paper Size (page 8-13)</u>

When a paper weight that cannot be loaded in the cassette is set for a media type, that media type does not appear.

\*3 To print on preprinted or prepunched paper or on letterhead.

Special Paper Action (page 8-14)

#### **Multipurpose Tray**

#### [System Menu/Counter] key > [Cassette/MP Tray Settings] > [Multipurpose Tray]

Select paper size and media type for the multipurpose tray.

Item		Description
Paper Size	Metric	Select from the Metric standard sizes. Values: A4, A5-R, A5, A6, B5, B6, Folio, 216 × 340 mm
	Inch	Select from the Inch series standard sizes. Values: Letter, Legal, Statement-R, Statement, Executive, Oficio II
	Other	Select from special standard sizes and custom sizes. Values: 16K, ISO B5, Envelope #10, Envelope #9, Envelope #6, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku hagaki (Return postcard), Youkei 4, Youkei 2, Custom <sup>*1</sup>
Media Type <sup>*2</sup>		Select the media type. Values: Plain (60 to 105 g/m <sup>2</sup> ), Rough, Transparency, Vellum (60 to 220 g/m <sup>2</sup> ), Labels, Recycled, Preprinted <sup>*3</sup> , Bond, Cardstock, Color, Prepunched <sup>*3</sup> , Letterhead <sup>*3</sup> , Envelope, Thick (106 to 220 g/m <sup>2</sup> ), Coated, High Quality, Custom 1 to 8

\*1 For instructions on how to specify the custom paper size.

- Custom Paper Size (page 8-13)
- \*2 To change to a media type other than "Plain".

Media Type Setting (page 8-15)

- \*3 To print on preprinted or prepunched paper or on letterhead.
  - Special Paper Action (page 8-14)

### **Common Settings**

Configures overall machine operation.

#### **Default Screen**

[System Menu/Counter] key > [Common Settings] > [Default Screen]

Item	Description	
Default Screen	Select the screen appearing right after start-up (default screen).	
	Value: Home, Copy, Send, FAX, Job Box, Removable Memory, Sub Address Box, Polling Box, Favorites, Status	

#### Sound

#### [System Menu/Counter] key > [Common Settings] > [Sound]

Item	Description	
Buzzer	Set options for buzzer sound during the machine operations.	
Key Confirmation	Emit a sound when the operation panel and touch panel keys are selected. Value: Off, On	
Job Finish	Emit a sound when a print job is normally completed. Value: Off, On, FAX Reception Only	
Ready	Emit a sound when the warm-up is completed. Value: Off, On	
Warning	Emit a sound when errors occur. Value: Off, On	
USB Keyboard	Emit a sound to confirm keypresses with a sound. Value: Off, On	
FAX Speaker Volume	FAX Operation Guide	
FAX Monitor Volume	FAX Operation Guide	

### **Original Settings**

#### [System Menu/Counter] key > [Common Settings] > [Original Settings]

Configure settings for originals.

Item	Description		
Custom Original Size	Set up frequently-used custom original size.		
	The custom size option is displayed on the screen to select original size.		
	Value		
	Metric		
	X: 50 to 356 mm (in 1 mm increments) Y: 50 to 216 mm (in 1 mm increments)		
	Inch		
	X: 1.97 to 14.02" (in 0.01" increments) Y: 1.97 to 8.50" (in 0.01" increments)		
	X=Length, Y=Width		
	Horizontal		
Auto Detect Original Size (DP)	Select whether to automatically detect originals of the document processor.		
Auto Detect	Select whether to enable automatic detection of original size. Value: off, on		
System of Units	Select metric or inch for the unit of original size detection. Value: Metric, Inch		
Legal/Oficioll/ 216 x 340 mm	As Legal, OficioII and 216 x 340 mm are similar in size, select either one of them for automatic detection.		
	Value: Legal, Oficioll, 216 x 340 mm		
	NOTE		
	When [System of Units] is set to [Metric], this function will not be displayed.		

Item	Description
Default Original Size	Set the default original size.
	Value
	Metric: A4, A5, A6, B5, B6
	Inch: Letter, Statement, Executive
	Others: 16K
	ΝΟΤΕ
	When [Auto Detect] is set to [On], this function will not be displayed.
Default Original Size (Platen)	Select a default size for the originals placed on the platen.
	If [Off] is selected, a confirmation will be displayed before each job is processed.
	Value
	Off
	Metric: A4, A5, A6, B5, B6
	Inch: Letter, Statement, Executive
	Others: 16K
	NOTE
	When [Auto Detect] is set to [Off], this function will not be displayed.

### **Paper Settings**

### [System Menu/Counter] key > [Common Settings] > [Paper Settings]

Configure settings for paper.

Custom Paper Size	Description		
	Set up frequently-used custom paper size.		
	One custom paper size is set for each paper supply source. The custom size option is displayed on the screen to select paper size.		
Cassette 1 Size	Register the custom paper size to be used in Cassette 1.		
	Value		
	Metric		
	X: 105 to 216 mm (in 1 mm increments) Y: 148 to 356 mm (in 1 mm increments)		
	Inch		
	X: 4.13 to 8.50" (in 0.01" increments) Y: 5.83 to 14.02" (in 0.01" increments)		
	X=Length, Y=Width		
	Vertical		
	Y		
Cassette 2 Size	Register the custom paper size to be used in Cassette 2.		
	Value		
	Metric		
	X: 105 to 216 mm (in 1 mm increments) Y: 148 to 356 mm (in 1 mm increments)		
	Inch		
	X: 4.13 to 8.50" (in 0.01" increments) Y: 5.83 to 8.50" (in 0.01" increments)		
MP Tray Size	Register the custom paper size to be used in the multipurpose tray.		
	Value		
	Metric		
	X: 70 to 216 mm (in 1 mm increments) Y: 148 to 356 mm (in 1 mm increments)		
	Inch		
	X: 2.76 to 8.50" (in 0.01" increments) Y: 5.83 to 14.02" (in 0.01" increments)		
	X=Length, Y=Width		
	Vertical Horizontal		

ltem	Description		
Media Type Setting	<ul> <li>Select weight for each media type.</li> <li>For Custom 1 to 8, settings for duplex printing and media type name can be changed.</li> <li>Media Type Setting (page 8-15)</li> </ul>		
Default Paper Source	Select the default paper source. Value: Cassette 1 (2), Multipurpose Tray		
	<b>ICassette 2</b> ] is displayed when the optional paper feeder is installed.		
Paper Selection	Set the default paper selection. Value Auto: Automatically select the cassette containing paper in the same size as originals. Default Paper Source: Select paper source set by "Default Paper Source".		
Media for Auto (Color)	Select a default media type for auto paper selection when [Auto] is selected of Paper		
Media for Auto (B&W)	Selection. If [ <b>Plain</b> ] is selected, the paper source with plain paper loaded in the specific size is selected. Select [ <b>All Media Types</b> ] for the paper source with any kind of paper loaded in the specific size.		
	Value: All Media Types, Plain, Transparency, Rough, Vellum, Labels, Recycled, Preprinted, Bond, Cardstock, Color, Prepunched, Letterhead, Envelope, Thick, Coated, High Quality, Custom 1 to 8		
Special Paper Action	When printing on Prepunched, Preprint, and Letterhead, punch-holes might not be aligned or the print direction might be upside-down depending on how originals are set and the combination of copying functions. In such a case, select [Adjust Print Direction] to adjust the print direction. When paper orientation is not important, select [Speed Priority].		
	If [Adjust Print Direction] is selected, load paper according to the steps below. Example: copying on Letterhead		
	Example: copying on Letternead         Image: Copying on Letternead         <		
	Original Paper Finished Cassette Multipurpose Tray		
	Value: Adjust Print Direction, Speed Priority		
Show Paper Setup Message	Set whether to display the confirmation screen for the paper setting when a new paper is set for		
Cassette 1 (2)	each cassette. Value: Off, On		
Multipurpose Tray			
	[Cassette 2] is displayed when the optional paper feeder is installed.		

#### Media Type Setting

The following media type and paper weight combinations are available.

Paper Weight	Weight (g/m <sup>2</sup> )	Paper Weight	Weight (g/m <sup>2</sup> )
Light	52 g/m <sup>2</sup> to 59 g/m <sup>2</sup>	Heavy 1 <sup>*1</sup>	106 g/m <sup>2</sup> to 135 g/m <sup>2</sup>
Normal 1	60 g/m² to 74 g/m²	Heavy 2 <sup>*1</sup>	136 g/m <sup>2</sup> to 163 g/m <sup>2</sup>
Normal 2	75 g/m <sup>2</sup> to 90 g/m <sup>2</sup>	Heavy 3 <sup>*1</sup>	164 g/m <sup>2</sup> to 220 g/m <sup>2</sup>
Normal 3	91 g/m <sup>2</sup> to 105 g/m <sup>2</sup>	Extra Heavy <sup>*1</sup>	Transparencies

\*1 The processing speed will be slower than normal.

Each media type's default weight is indicated.

Media Type	Default	Media Type	Default
Plain	Normal 2	Color	Normal 2
Rough	Normal 3	Prepunched	Normal 2
Vellum	Heavy 1	Letterhead	Normal 2
Labels	Heavy 1	Envelope	Heavy 2
Recycled	Normal 2	Thick	Heavy 2
Preprinted	Normal 2	High Quality	Normal 2
Bond	Normal 3	Coated	Heavy 1
Cardstock	Heavy 3	Custom 1 to 8	Normal 2

For Custom 1 to 8, settings for duplex printing and media type name can be changed.

Item		Description
Duplex Print	Permit	Duplex printing allowed.
Prohibit         Duplex printing not allowed.		Duplex printing not allowed.
Name		Change names for Custom 1 to 8. Names should be not more than 16 characters. Selecting media type at multipurpose tray, the name after change will be displayed.
		<u>Character Entry Method (page 11-8)</u>

#### **Function Defaults**

#### [System Menu/Counter] key > [Common Settings] > [Function Defaults]

ltem	Description	
File Format	Select the default type of the files to be sent. Value: PDF, High Comp. PDF, TIFF, JPEG, XPS, OpenXPS	
Original Orientation	Set the original orientation defaults. Value: Top Edge on Top, Top Edge on Left	
Collate	Set the defaults for Collate. Value: Off, On	
File Separation	Select the default file separation setting. Value: Off, Each Page	
Scan Resolution	Select the default scanning resolution. Value: 600×600dpi, 400×400dpi Ultra Fine, 300×300dpi, 200×400dpi Super Fine, 200×200dpi Fine, 200×100dpi Normal	
Color Selection (Copy)	Set the default copying color mode setting. Value: Full Color, Black & White	
Color Select.(Send/Store)	Select the default color mode for scanning documents. Value: Full Color, Grayscale, Black & White	
Original Image (Copy)	Set the default original document type for copying. Value: Text+Photo, Photo, Text, Graphic/Map, Printer Output	
Original Image (Send/Store)	Set the default original document type for sending/storing. Value: Text+Photo, Photo, Text, Text (for OCR), Light Text/Line NOTE [Text (for OCR)] is only available when "Color Selection" is set to [Black & White].	
Background Density Adj. (Copy)	Set the default Background Density (Copy). Value: Off, Manual (Darker 5)	
Background Density Adj. (Send/Store)	Set the default Background Density (Send/Store). Value: Off, Manual (Darker 5)	
EcoPrint	Select the EcoPrint default. Value: Off, On	
Skip Blank Page (Copy)	Set the default Skip Blank Page (Copy) settings. Value: Off, On	
Skip Blank Page (Send/Store)	Set the default Skip Blank Page (Send/Store) settings. Value: Off, On	
FAX TX Resolution	FAX Operation Guide	
Zoom	Select the enlarged/reduced default when paper size/sending size changed after the originals set. Value: 100%, Auto	
Continuous Scan (Copy)	Set the continuous scan (Copy) defaults. Value: Off, On	
Continuous Scan (FAX)	→ FAX Operation Guide	
Continuous Scan (Send/Store)	Set the continuous scan (Send/Store) defaults. Value: Off, On	

Item Description	
File Name Entry	Set an automatically entered name (default) for jobs. Additional information such as Date and Time and Job No. can also be set.
	File Name: Up to 32 characters can be entered.
	Additional Info: None, Date and Time, Job No., Job No. & Date and Time, Date and Time & Job No.
E-mail Subject/Body	Set the subject and body automatically entered (default subject and body) when sending the scanned originals by E-mail.
	Value Subject: Up to 60 characters can be entered.
	Body: Up to 500 characters can be entered.
FTP Encrypted TX	Set the default value for document encryption during transmission. Value: Off, On
	This setting is displayed when the security settings "SSL" setting is [ <b>On</b> ].
JPEG/TIFF Print	Select the image size (resolution) when printing JPEG or TIFF file.
	Value: Paper Size, Image Resolution, Print Resolution
XPS Fit to Page	Set the default value for the XPS fit to page function.
	Value: Off, On
Detail Settings	—
Image Quality	Set the default value for the image quality adjustment range when selecting the file format with which to send and store images.
	Value: 1 Low (High Comp.), 2, 3, 4, 5 High (Low Comp.)
PDF/A	Set the default value for PDF/A when selecting the file format with which to send and store images.
	Value: Off, PDF/A-1a, PDF/A-1b
High Comp. PDF	Select the default quality setting for high compressed PDF files.
	Value: Compression Ratio Priority, Standard, Quality Priority
Blank Detection L	Select the default Blank Detection Level (Copy) settings.
(Сору)	Value: Low, Middle, High
Blank Detection L	
(Send/Store)	Value: Low, Middle, High

#### **Preset Limit**

[System Menu/Counter] key > [Common Settings] > [Preset Limit]

Item	Description
Preset Limit	Restrict the number of copies that can be made at one time. Value: 1 to 999 copies.

### **Error Handling**

#### [System Menu/Counter] key > [Common Settings] > [Error Handling]

Select whether to cancel or continue the job when error has occurred.

Item	Description
Duplexing Error	Set what to do when duplex printing is not possible for the selected paper sizes and media types.
	Value 1-sided: Printed in 1-sided
	Display Error: Message to cancel printing is displayed.
Paper Mismatch Error	Set what to do when the selected paper size or type does not match paper size or type loaded in the specified paper source while printing from the computer by specifying the cassette or multipurpose tray.
	Value
	Ignore: The setting is ignored and the job is printed.
	Display Error: Message to cancel printing is displayed.

#### **Color Toner Empty Action**

#### [System Menu/Counter] key > [Common Settings] > [Color Toner Empty Action]

Item	Description
Color Toner Empty Action	Select whether printing is prohibited or the Print in Black and White setting is used for printing once the color toner runs out.
	Value: Stop printing, Print in Black & White

#### Measurement

#### [System Menu/Counter] key > [Common Settings] > [Measurement]

Item	Description
Measurement	Select metric or inch for the unit for paper dimensions.
	Value: mm, inch

#### Low Toner Alert

#### [System Menu/Counter] key > [Common Settings] > [Low Toner Alert]

Item	Description
Low Toner Alert	Set the amount of remaining toner to notify the administrator when to order a toner when the toner is running low. This notification is used for event report, Status Monitor, SNMP Trap. Value: Off, On
	<b>NOTE</b> If [ <b>On</b> ] is selected, set the amount of remaining toner to alert. The setting range is 5 to 100% (in 1% increments).

#### **Keyboard Layout**

#### [System Menu/Counter] key > [Common Settings] > [Keyboard Layout]

Item	Description
Keyboard Layout	Change the layout of the touch panel keyboard used to enter characters. Value: QWERTY, QWERTZ, AZERTY

#### **USB Keyboard Type**

#### [System Menu/Counter] key > [Common Settings] > [USB Keyboard Type]

Item	Description
USB Keyboard Type	Select the type of USB keyboard that you want to use. Value: US-English, US-English with Euro, French, German

#### Format SD Card

[System Menu/Counter] key > [Common Settings] > [Format SD Card]

Format an SD/SDHC memory card.

A new SD card must be formatted before it can be used in the machine.

#### **IMPORTANT**

Formatting will destroy any existing data on a storage device including a used SD card.

#### **Display Status/Log**

[System Menu/Counter] key > [Common Settings] > [Display Status/Log]

	ltem	Description
Displ	ay Status/Log	Set the display method of the Status/Log.
	Display Jobs Detail Status	Value: Show All, My Jobs Only, Hide All
	Display Jobs Log	Value: Show All, My Jobs Only, Hide All
	Display FAX Log	Value: Show All, Hide All

#### Show Power Off Message

[System Menu/Counter] key > [Common Settings] > [Show Power Off Message]

Item	Description
Show Power Off Message	Set the mode whether display a confirmation message in power supply off.
	Value: Off, On

### Home

#### [System Menu/Counter] key > [Home]

Configure settings for Home screen.

Editing the Home Screen (page 2-13)

# Сору

### [System Menu/Counter] key > [Copy]

Configures settings for copying functions.

Item	Description
Auto Paper Selection	If [Auto] is selected for Paper Selection, set the paper size selection method when the zoom changes. Value
	Most Suitable Size: Select paper based on the current zoom and the size of the original.
	Same as Original Size: Select paper that matches the size of the original, regardless the zoom.
Auto % Priority	When a paper source of different size from the original is selected, select whether automatic zoom (reduce/zoom) is performed.
	Value: Off, On
DP Read Action	When the document processor is used, select the scanning operation for the document processor.
	Value
	Speed Priority: Gives priority to scanning speed.
	Quality Priority: Gives priority to image quality at a slightly slower scan speed.
Platen Scan Action	When the platen is used, select the scanning operation for the platen.
	Value
	Speed Priority: Gives priority to scanning speed.
	Quality Priority: Gives priority to image quality at a slightly slower scan speed.

### Send

#### [System Menu/Counter] key > [Send]

Configures settings for sending functions.

	ltem	Description
Dest. Check	k before Send	When performing sending jobs, display the confirmation screen of destinations after pressing the [ <b>Start</b> ] key. <sup>*1</sup> Value: Off, On
Entry Check for New Dest.		When adding new destination, display the entry check screen to check the entered destination. <sup>*1</sup> Value: Off, On
Send and F	orward	Set whether to send the original to another destination and store it when sending images.
Forw	vard	Set the rule to send the original. Value: Off, On NOTE When selecting [On], select rules to forward from [FAX], [E-mail], [Folder (SMB)] and [Folder (FTP)].
Dest	ination	<ul> <li>Set the destination to which the original is forwarded. One destination can be set. You can check and edit the set address.</li> <li>Follow the steps below to register the destination.</li> <li>Address Book</li> <li>Ext. Address Book</li> <li>Address Entry (E-mail)</li> <li>Address Entry (folder)</li> <li>Specifying Destination (page 5-33)</li> </ul>
Color TIFF	Compression	Select the compression method for TIFF images handled on this machine. Value: TIFF V6, TTN2
Default Screen		Use this procedure to set the default screen displayed when you select the [Send] key. Value: Destination, Address Book, Ext. Address Book, One Touch
New Destination Entry		Select whether to permit direct entry of destination. Value: Prohibit, Permit <sup>*1</sup>
Recall Destination		Select whether to permit usage of [ <b>Recall</b> ] on the Send screen. <sup>*1</sup> Value: Prohibit, Permit

\*1 Also applies when sending the fax.

### **Document Box**

#### [System Menu/Counter] key > [Document Box]

Configures settings related to the Job Box, Sub Address Box and Polling Box.

Item	Description
Sub Address Box	FAX Operation Guide
Job Box         Configure settings for Job Box.	
Quick Copy Job Retention	To maintain free space on the box, you can set the maximum number of stored jobs. Value: number between 0 and 300
	When 0 is set, Quick Copy cannot be used.
Deletion of Job Retention	This setting specifies that documents, such as Private Printing, Quick Copying, or Proof and Hold Printing, saved temporarily in the job box are automatically deleted after they have been saved for a set time. Value: Off, 1 hour, 4 hours, 1 day, 1 week
	ΝΟΤΕ
	This function is valid for documents saved after the function is set. Regardless of this function setting, temporary documents are deleted when the power switch is turned off.
Polling Box	FAX Operation Guide

# FAX

#### [System Menu/Counter] key > [FAX]

Configure settings for FAX.

FAX Operation Guide

# **Address Book/One Touch**

#### **Address Book**

#### [System Menu/Counter] key > [Address Book/One Touch] > [Address Book]

Configure settings for address book.

➡ Adding a Destination (Address Book) (page 3-20)

#### **One Touch Key**

#### [System Menu/Counter] key > [Address Book/One Touch] > [One Touch Key]

Configure settings for One Touch Key.

Adding a Destination on One Touch Key (One Touch Key) (page 3-26)

#### **Address Book Defaults**

#### [System Menu/Counter] key > [Address Book/One Touch] > [Address Book Defaults]

Item	Description
Sort	Select the default sort setting of the address for the address book. Value: No., Name
Address Book	Specify the default sort setting of the external address book.

#### **Print list**

[System Menu/Counter] key > [Address Book/One Touch] > [Print list]

FAX Operation Guide

### **User Login/Job Accounting**

[System Menu/Counter] key > [User Login/Job Accounting]

Configure settings related to machine management.

Overview of User Login Administration (page 9-2)
 Overview of Job Accounting (page 9-28)
 Unknown User Settings (page 9-42)

# **Printer**

#### [System Menu/Counter] key > [Printer]

Printing from computers, settings are generally made on the application software screen. However, the following settings are available for configuring the defaults to customize the machine.

ltem	Description	
Emulation	Select the emulation for operating this machine by commands oriented to other types of printers.         Value: PCL6, KPDL, KPDL (Auto)         Image: NOTE         When you have selected [KPDL (Auto)], set "Alt Emulation", too.         When you have selected [KPDL] or [KPDL (Auto)], set "KPDL Error Report", too.	
Alt Emulation	When you have selected [ <b>KPDL (Auto)</b> ] as emulation mode, you can switch between KPDL and another emulation mode (alternative emulation) automatically according to the data to print. Value: PCL6	
KPDL Error Report	When an error has occurred during printing in KPDL emulation mode, set whether or not the error report is output. Value: Off, On	
Color Setting	You can choose whether reports are printed in color or black and white. Value: Color, Black & White	
EcoPrint	EcoPrint conserves toner when printing. This is recommended for test copies where faded printing is not a problem. Value: Off, On	
Override A4/Letter	<ul> <li>Select whether to treat A4 size and Letter, which are similar in size, as the same size when printing.</li> <li>Value</li> <li>Off: A4 and Letter are not regarded as the same in size.</li> <li>On: A4 and Letter are regarded as the same in size. The machine will use whichever size is in the paper source.</li> </ul>	
Duplex	Select binding orientation for duplex mode. Value: 1-sided, 2-sided Bind LongEdge, 2-sided Bind ShortEdge	
Copies	Set the default number of copies, from 1 to 999. Value: 1 to 999 copies	
Orientation	Set the default orientation, [Portrait] or [Landscape]. Value: Portrait, Landscape	
Wide A4	Turn this to on to increase the maximum number of characters that can be printed in a line for an A4 page (78 characters at 10 pitch) and Letter size page (80 characters at 10 pitch). This setting is only effective in PCL6 emulation. Value: Off, On	
Form Feed TimeOut	<ul> <li>Receiving print data from the computer, the machine may sometimes wait if there is no information signaling that the last page does not have any more data to be printed. When the preset timeout passes, the machine automatically prints paper. The options are between 5 and 495 seconds.</li> <li>Value: 5 to 495 seconds (in 5 second increments)</li> </ul>	
LF Action	Set the line feed action when the machine receives the line feed code (character code 0AH). Value: LF Only, LF and CR, Ignore LF	

ltem	Description
CR Action	Set the character return action when the machine receives the character return code (character code 0DH). Value: CR Only, LF and CR, Ignore CR
Job Name	Set whether the job name set in the printer driver is displayed.
JOD Name	Value: Off, On
	When selecting [ <b>On</b> ], select the job name to be displayed from [ <b>Job Name</b> ], [ <b>Job No. &amp; Job Name</b> ], or [ <b>Job Name &amp; Job No.</b> ].
User Name	Set whether the user name set in the printer driver is displayed.
	Value: Off, On
MP Tray Priority	If paper is set in the multipurpose tray then it is possible for priority to be given to that multipurpose tray in the paper feed.
	Value
	Off: The printer driver settings are followed. Auto Feed: If Auto is selected in the printer driver and there is paper in the multipurpose
	tray then the paper feed will be from the multipurpose tray.
	Always: If there is paper in the multipurpose tray then the paper feed will be from the multipurpose tray regardless of what is set in the printer driver.
Paper Feed Mode	While printing from the computer, select how to feed paper when the paper source and type are specified.
	Value
	Auto: Search the paper source that matches the selected paper size and type. Fixed: Print on paper loaded in the specified paper source.
Auto cocotto Change	
Auto cassette Change	Select the following actions when the paper runs out in the paper source while printing. Value: Off, On
	NOTE
	When selecting [ <b>Off</b> ], the machine displays "Add the following paper in cassette #." (# is a cassette number) or "Add the following paper in the multipurpose tray.", and stops printing.
	Load the paper according to the paper source displayed to resume printing.
	To print from the other paper cassette, select [ <b>Paper Selection</b> ]. Select the desired paper source.
	When selecting [ <b>On</b> ], the machine continues printing automatically when the other cassette
	contains the same paper as the currently-used cassette.
Resolution	Set the resolution used for printing.         Value: 600 dpi, 1200 dpi
	ΝΟΤΕ
	Settings that are received from the printer driver have priority over the operation panel settings.
Gloss Mode	Gloss Mode increases the effect of glossiness in printing. However, printing takes longer time.
	Value: Off, On
	Gloss Mode is not available when [Labels] or [Transparency] is selected as the paper type setting.
	Cassette/MP Tray Settings (page 8-8)
	Depending on the paper used, printing in gloss mode may cause curl in paper. To reduce curl, try using thicker paper.

# System/Network

Configures machine system settings.

#### Network

#### [System Menu/Counter] key > [System/Network] > [Network]

Configures network settings.

#### Host Name

Item	Description
Host Name	Check the host name of the machine. Host name can be changed from Command Center RX.
	Changing Device Information (page 2-56)

#### **Wi-Fi Direct Settings**

Set Wi-Fi Direct.

### ο ΝΟΤΕ

This function is displayed when the wireless network function is available on the machine.

Item	Description
Wi-Fi Direct	Select whether to use Wi-Fi Direct.
	Value: Off, On
Device Name	Specify the device name.
	NOTE
	Up to 32 characters can be entered.
	This function is displayed when [Wi-Fi Direct] is set to [On].
IP Address	Check the IP address of the machine.
	► <u>TCP/IP Setting (page 8-28)</u>
	NOTE
	This function is displayed when [Wi-Fi Direct] is set to [On].
Auto Disconnect	Automatically disconnect devices connected through Wi-Fi Direct.
	Value: Off, On
	NOTE
	If you select [ <b>ON</b> ], set the waiting time for automatic disconnection.
	This function is displayed when [Wi-Fi Direct] is set to [On].

#### Wi-Fi Settings

Set Wi-Fi.

### 

This function is displayed when the wireless network function is available on the machine.

Item	Description	
Wi-Fi	Select whether to use Wi-Fi.	
	Value: Off, On	

Item		Description		
tup		-		
Connection Status		Check the wireless LAN status.		
Quic	k Setup Wizard	If the machine will connect to an access point that supports the automatic wireless network setup, connection settings can be configured by Quick Setup.		
		When [ <b>Reload</b> ] is selected, the list is reloaded.		
		If you are connecting to an access point that has WEP enabled, select [ <b>WEP Key Index</b> ] and select the WEP key index.		
Α	vailable Network	Displays access points to	o which the ma	achine can connect.
	WEP Key Index	Select the key index of the	he access poin	ıt.
		Value: 0 to 3		
Ρ	ush Button Method	If the access point supports the push button method, wireless settings can be configured usin the push button. This setting executes push button, and the connection is started by pressing the push button on the access point.		
		The push button method	I supports only	the WPS.
	IN Code Method Device)	Starts connection using the machine's PIN code. Enter the PIN code into the access point. The PIN code of the machine is automatically generated.         The detailed settings for wireless LAN can be changed.         Set the SSID (Service Set Identifier) of the wireless LAN to which the machine connects.		
Cust	com Setup			
Ν	letwork Name (SSID)			
		NOTE		
		Up to 32 characters can be entered.		
Ν	letwork Authentication	Select network authentication type.		
		Value: Open, WPA2/WPA-PSK, WPA2-PSK, WPA2/WPA-EAP, WPA2-EAP		
E	ncryption	Select encryption method. The setting values vary depending on the Network Authentication setting.		
		Network		Encryption
		Authentication		
		Open	Disable	—
			WEP	WEP Key: Up to 26 characters
				WEP Key Index: 0 to 3
		WPA2/WPA-PSK	Data Encry	ption: AES, Auto
			Preshared k	Key: Up to 64 characters
		WPA2-PSK		otion: AES , Auto Key: Up to 64 characters
				ation: AES Auto
		WPA2/WPA-EAP	Data Encryp	otion: AES, Auto

ltem	Description	
CP/IP Setting	-	
TCP/IP	Select whether to use TCP/IP Protocol. Value: Off, On	
IPv4	Set up TCP/IP (IPv4) to connect to the network. This setting is available when [ <b>TCP/IP</b> ] is set [ <b>On</b> ].	
DHCP	Select whether to use the DHCP (IPv4) server. Value: Off, On	
Auto-IP	Select whether to use Auto-IP. Value: Off, On	
IP Address	Set the IP address. Value: ###.###.### <b>NOTE</b>	
Subnet Mask	When DHCP is set to [ <b>On</b> ], this function will be grayed out and the value cannot be entered.         Set the IP subnet mask.         Value: ###.###.###         Image: The subnet mask is a set of the subnet mask.         Value: ###.###.###	
	When DHCP is set to [ <b>On</b> ], this function will be grayed out and the value cannot be entered.	
Default Gateway	Set the IP gateway address. Value: ###.###.###	
	<b>NOTE</b> When DHCP is set to [ <b>On</b> ], this function will be grayed out and the value cannot be entered.	

### 

• When setting the Auto-IP, enter "0.0.0.0" in [IP Address].

• After changing the setting, restart the network or turn the machine OFF and then ON.

ltem	Description           Set up TCP/IP (IPv6) to connect to the network. This setting is available when [TCP/IP] is [On].	
IPv6		
IPv6	Select whether to use IPv6.         Value: Off, On         Image: NOTE         Selecting [On] displays IP address in [IP Address (Link Local)] after restarting the network.	
Manual Setting	<ul> <li>Manually specify the IP address, prefix length, and gateway address of TCP/IP (IPv6).</li> <li>Value</li> <li>IP Address (Manual): 128-bits address is expressed in eight groups consisting of four-digit hexadecimal digits. The groups are separated by colon (:)</li> <li>Prefix Length: 0 to 128</li> <li>Default Gateway: 128-bits address is expressed in eight groups consisting of four-digit hexadecimal digits. The groups are separated by colon (:).</li> <li>NOTE</li> <li>This function is displayed when [IPv6] is set to [On].</li> <li>To enter "Default Gateway", set [RA (Stateless)] to [Off].</li> </ul>	
RA (Stateless)	Select whether to use RA (Stateless).         Value: Off, On         Image: NOTE         • This function is displayed when [IPv6] is set to [On].         • Selecting [On] displays IP address in [IP Address (Stateless)] after restarting the network	
DHCP	<ul> <li>Select whether to use the DHCP (IPv6) server.</li> <li>Value: Off, On</li> <li>NOTE</li> <li>This function is displayed when [IPv6] is set to [On].</li> <li>Selecting [On] displays IP address in [IP Address (Stateful)] after restarting the network.</li> </ul>	
start Network	Restarts the network.	

### **IMPORTANT**

After changing the setting, restart the network or turn the machine OFF and then ON.

#### Wired Network Settings

Configure wired network settings.

Item	Description	
TCP/IP Setting	For details on setting value.	
	★ <u>TCP/IP Setting (page 8-28)</u>	
LAN Interface	AN Interface Specify the settings for the LAN interface to be used. Value: Auto, 10BASE-Half, 10BASE-Full, 100BASE-Full, 100BASE-Full, 1000BASE-T	

### 

After changing the setting, restart the network or turn the machine OFF and then ON.

#### Bonjour

Item	Description	
Protocol Setting	Select whether to use Bonjour. Value: Off, On	
Available Network (Wi-Fi Direct) <sup>*1</sup>	Set whether to enable this function for each network. Value: Disable, Enable	
Available Network (Wi-Fi) <sup>*1</sup>		
Available Network (Wired Network)		

\*1 Displayed only when the wireless network function is available on the machine.

#### IPSec

Item	Description	
IPSec	Make this setting when you use IPSec. Value: Off, On	

#### **Protocol Settings**

Configure protocol settings.

ltem		Description	
N	etBEUI	-	
	Protocol Setting	Selects whether to receive documents using NetBEUI. <sup>*1</sup> Value: Off, On	
	Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable	
	Available Network (Wi-Fi) <sup>*2</sup>		
	Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].	
LF	PD	-	
	Protocol Setting	Selects whether to receive documents using LPD. <sup>*1</sup> Value: Off, On	
	Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable	
	Available Network (Wi-Fi) <sup>*2</sup>		
	Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].	
SI	MTP (E-mail TX)	Select whether to send E-mail using SMTP. Value: Off, On	
POP3 (E-mail RX)		Select whether to receive E-mail using POP3. Value: Off, On	
FTP Client (Transmission)		Select whether to send documents using FTP. When selecting [ <b>On</b> ], set the FTP Port Number. The default port number is 21. Value: Off, On (Port Number: 1-65535)	

Item	Description
FTP Server (Reception)	-
Protocol Setting	Select whether to receive documents using FTP. <sup>*1</sup> Value: Off, On
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
SMB Client (Transmission):	Select whether to send documents using SMB. When selecting [ <b>On</b> ], set the SMB default Port Number. The default port number is 445.
	Value: Off, On (Port Number: 1-65535)
WSD Scan	-
Protocol Setting	Select whether to use WSD Scan. <sup>*1</sup> Value: Off, On
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
WSD Print	-
Protocol Setting	Set whether to use our proprietary web services. WIA driver, TWAIN driver and Network FAX driver use this Enhanced WSD web service. <sup>*1</sup> Value: Off, On
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
DSM Scan	Select whether to use DSM scan. <sup>*1</sup> Value: Off, On
LDAP	Select whether to use LDAP. Value: Off, On
SNMP	-
Protocol Setting	Select whether to communicate using SNMP. <sup>*1</sup> Value: Off, On
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].

	Item	Description
SI	NMPv3	-
	Protocol Setting	Select whether to communicate using SNMPv3. <sup>*1</sup> Value: Off, On
	Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
	Available Network (Wi-Fi) <sup>*2</sup>	NOTE
	Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
H.	ГТР	-
	Protocol Setting	Select whether to communicate using HTTP. <sup>*1</sup> Value: Off, On
	Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
	Available Network (Wi-Fi) <sup>*2</sup>	
	Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
H.	TTPS	-
	Protocol Setting	Select whether to communicate using HTTPS. <sup>*1, *3</sup> Value: Off, On
	Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
	Available Network (Wi-Fi) <sup>*2</sup>	
	Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
IP	Ρ	-
	Protocol Setting	Selects whether to receive documents using IPP. To use the IPP protocol, select [ <b>Not Secure</b> ( <b>IPP&amp;IPPS</b> )] on IPP Security under Security Settings from the Command Center RX. <sup>*1</sup> Value: Off, On
	Port Number	Set the IPP default Port Number. The default port number is 631. Value: 1-32767
		NOTE
		This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
	Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
	Available Network (Wi-Fi) <sup>*2</sup>	
	Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].

Item	Description
IPP over SSL	-
Protocol Setting	Select whether or not to use IPP over SSL. <sup>*1, *3</sup> Value: Off, On
	<b>NOTE</b> When selecting <b>[On]</b> , it also requires a certificate for SSL. the default certificate is the self-certificate of the machine.
	Command Center RX User Guide
Port Number	Set the IPP over SSL default Port Number. The default port number is 443. <sup>*1</sup> Value: 1-32767
	NOTE
	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
Raw Port	-
Protocol Setting	Select whether to receive documents using Raw Port. <sup>*1</sup> Value: Off, On
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].

ltem	Description
ThinPrint	-
Protocol Setting	Select whether to use ThinPrint. <sup>*1, *3</sup> Value: Off, On
	<b>NOTE</b> This function is displayed only when the optional ThinPrint Option is activated.
Port Number	Set the ThinPrint default Port Number. The default port number is 4000. Value: 1-32767
	NOTE This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
Thin Print over SSL	To use the Thin Print over SSL protocol, set [Thin Print Over SSL] to [On]. <sup>*1, *3</sup> Value: Off, On
	NOTE
	<ul> <li>This function is displayed when [Protocol Setting] is set to [On].</li> <li>When selecting [On], it also requires a certificate for SSL. The default certificate is the self-certificate of the machine.</li> </ul>
	Command Center RX User Guide
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
Enhanced WSD	-
Protocol Setting	Set whether to use our proprietary web services. <sup>*1</sup> Value: Off, On
	NOTE
	Selecting [Off] will disable the functionality of WIA, TWAIN, and Network FAX driver.
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network.
Available Network (Wi-Fi) <sup>*2</sup>	Value: Disable, Enable
Available Network (Wired Network)	NOTE This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
Enhanced WSD over SSL	-
Protocol Setting	Set whether to use our proprietary web services over SSL.*1, *3 Value: Off, On
	<b>NOTE</b> Selecting [ <b>Off</b> ] will disable the functionality of WIA, TWAIN and Network FAX drivers.
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].

Item	Description
eSCL	-
Protocol Setting	Selects whether to receive scanned documents using eSCL. <sup>*1</sup> Value: Off, On
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	NOTE
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].
eSCL over SSL	-
Protocol Setting	Selects whether to receive scanned documents using eSCL over SSL.*1, *3 Value: Off, On
Available Network (Wi-Fi Direct) <sup>*2</sup>	Set whether to enable this function for each network. Value: Disable, Enable
Available Network (Wi-Fi) <sup>*2</sup>	
Available Network (Wired Network)	This function is displayed when [ <b>Protocol Setting</b> ] is set to [ <b>On</b> ].

\*1 The setting will be changed after restarting the device or network.

\*2 Displayed only when the wireless network function is available on the machine.

\*3 Set "SSL" to [On] in Security Settings.

Security Settings (page 8-35)

# **IMPORTANT**

After changing the setting, restart the network or turn the machine OFF and then ON.

#### **Security Settings**

Item	Description
SSL	Select whether or not to use SSL. Value: Off, On
IPP Security	Select the IPP security level. This setup is available when SSL is [ <b>On</b> ]. Value: IPP/IPP over SSL, IPPoverSSL only
HTTP Security	Select the HTTP security level. This setup is available when SSL is [ <b>On</b> ]. Value: HTTP/HTTPS, HTTPS Only
SMTP Security	Select the communication protocol according to the type of security employed by the SMTP server. This setup is available when SSL is [ <b>On</b> ]. <b>Value: Off, SSL/TLS, STARTTLS</b>
POP3 Security (User 1)	Select the communication protocol according to the type of security employed by the POP3
POP3 Security (User 2)	server. This setup is available when POP3 is [ <b>On</b> ]. Value: Off, SSL/TLS, STARTTLS
POP3 Security (User 3)	

#### Ping

Item	Description
Ping	Checks if communication with the destination by entering the host name or IP address of the destination is possible.

#### **Restart Network**

Item	Description
Restart Network	Restarts the network.

# Primary Network (Client)

#### [System Menu/Counter] key > [System/Network] > [Primary Network (Client)]

# NOTE

This function is displayed when the wireless network function is available on the machine.

Item	Description
Primary Network (Client)	Specify the network to be used for the send function, the network authentication and connecting to external address book. Value: Wi-Fi, Wired Network

# Interface Block Setting

#### [System Menu/Counter] key > [System/Network] > [Interface Block Setting]

This allows you to protect this machine by blocking the interface with external devices such as USB hosts.

Item	Description
USB Host	This locks and protects the USB port (USB host). Value: Unblock, Block
USB Device	This locks and protects the USB interface connector (USB Device). Value: Unblock, Block
USB Storage	This locks and protects the USB memory slot.         Value: Unblock, Block         Image: Optimized in the state of t

# **IMPORTANT**

After changing the setting, restart the network or turn the machine OFF and then ON.

# Security Level

[System Menu/Counter] key > [System/Network] > [Security Level]

Item	Description
Security Level	Specify the security level.
	<ul> <li>Low: This mode is used during maintenance. Do not use normally.</li> <li>High: This is the security setting we recommend. Use this setting normally.</li> <li>Very High: In addition to [High] setting, this setting disables the machine settings to be changed from external command.</li> </ul>

# Restart

#### [System Menu/Counter] key > [System/Network] > [Restart]

Item	Description
Restart	Restart the machine without turning the power switch off. Use this to deal with any unstable operation by the machine. (Same as the computer restart.)

# **RAM Disk Setting**

#### [System Menu/Counter] key > [System/Network] > [RAM Disk Setting]

Item	Description
RAM Disk Setting	A RAM disk can be created and its size can be set.
	Creating a RAM disk makes it possible to print from a Job Box.
	Value
	RAM Disk Setting: Off, On
	RAM Disk Size: The setting range varies depending on the amount of memory installed and the option memory usage setting.
	NOTE
	This function is displayed when optional memory is installed.

#### **IMPORTANT**

After changing the setting, restart the network or turn the machine OFF and then ON.

# **Optional Memory**

#### [System Menu/Counter] key > [System/Network] > [Optional Memory]

Item	Description
Optional Memory	When optional memory is installed, select the memory allocation scheme based on the application in which you are using the equipment. Value: Printer Priority, Normal, Copy Priority

### **IMPORTANT**

After changing the setting, restart the network or turn the machine OFF and then ON.

### **Optional Function**

[System Menu/Counter] key > [System/Network] > [Optional Function]

Item	Description
Optional Function	You can use the optional applications installed on this machine.
	Optional Applications (page 11-6)

# **Date/Timer/Energy Saver**

# [System Menu/Counter] key > [Date/Timer/Energy Saver]

Configures settings related to the date and time.

ltem	Description
Date/Time	Set the date and time for the location where you use the machine. If you perform Send as E-mail, the date and time set here will be displayed on the header.
	Value: Year (2000 to 2037), Month (1 to 12), Day (1 to 31), Hour (00 to 23), Minute (00 to 59), Second (00 to 59)
	➡ Setting Date and Time (page 2-23)
	ΝΟΤΕ
	If you change the date/time while using the trial version of an optional application, you will no longer be able to use the optional application.
Date Format	Select the display format of year, month, and date. The year is displayed in Western notation.
	Value: Month/Day/Year, Day/Month/Year, Year/Month/Day
Time Zone	Set the time difference from GMT. Choose the nearest listed location from the list. If you select a region that utilizes summer time, configure settings for summer time.
Auto Panel Reset	If no jobs are run for a certain period of time, automatically reset settings and return to the default setting. Select to use Auto Panel Reset or not.
	Value: Off, On
	The time allowed to elapse before the panel is reset is set with the following:
	▶ Panel Reset Timer (page 8-38)
Panel Reset Timer	If you select [ <b>On</b> ] for Auto Panel Reset, set the amount of time to wait before Auto Panel Reset.
	Value: 5 to 495 seconds (in 5 second increments)
	ΝΟΤΕ
	This function is displayed when [Auto Panel Reset] is set to [On].

Item	Description
Sleep Rules (models for Europe)	<ul> <li>Select whether to use the Sleep mode for the following functions individually:</li> <li>Network</li> <li>Card Reader<sup>*1</sup></li> <li>FAX</li> <li>Value: Off, On</li> <li>NOTE</li> <li>When the machine has entered sleep mode with Energy Saver setting, the ID card cannot be recognized.</li> </ul>
Sleep Level (models except for Europe)	Select the sleep level. Set the Energy Saver mode to reduce power consumption even more than Quick Recovery mode. Value: Quick Recovery, Energy Saver
Sleep Rules	<ul> <li>Select whether to use the Energy Saver mode for the following functions individually:</li> <li>Network</li> <li>Card Reader<sup>*1</sup></li> <li>FAX</li> <li>Value: Off, On</li> <li>NOTE</li> <li>When the machine has entered sleep mode with Energy Saver setting, the ID card cannot be recognized.</li> </ul>
Sleep Timer	Set amount of time before entering Sleep. Value For Europe: 1 to 60 minutes (1 minute increments) Except for Europe: 1 to 240 minutes (1 minute increments)
EnergySaver RecoveryLevel	Select the method of recovery from energy saver.         Value:         Full Recovery:       This mode enables the use of all functions immediately. However, this mode saves less energy.         Normal Recovery:       In this mode, you can select the method from the following: enabling the use of all functions immediately or enabling the use of desired functions only. If you want to use all functions immediately, select the [Energy Saver] key.         Power Saving Recovery:       This mode enables the use of desired functions only. This mode saves energy most effectively.

Item	Description
Power Off Rule (models for Europe)	Select whether or not the machine enters Power Off mode for the following function. Select <b>[On]</b> to set the Power Off mode.
	Network
	• FAX
	USB Cable
	USB Host
	RAM Disk
	Remote Diagnostics
	Value: Off, On
	NOTE
	Even when any of the functions is set to [ <b>On</b> ], if [ <b>FAX</b> ] is set to [ <b>Off</b> ], the machine does not enter Power Off Mode.
	Even when [ <b>Network</b> ] or [ <b>USB Cable</b> ] is set to [ <b>Off</b> ], if the machine does not communicate with the other devices, the machine will enter Power Off Mode.
Power Off Timer (models for	Select whether to turn off the power automatically after a period of inactivity.
Europe)	Value: 1 hour, 2 hours, 3 hours, 4 hours, 5 hours, 6 hours, 9 hours, 12 hours, 1 day, 2 days, 3 days, 4 days, 5 days, 6 days, 1 week
Auto Error Clear	If an error occurs during processing, processing stops to wait for the next step to be taken by the user. In the Auto Error Clear mode, automatically clear the error after a set amount of time elapses. Value: Off, On
Error Clear Timer	If you select [ <b>On</b> ] for Auto Error Clear, set the amount of time to wait before automatically clearing errors.
	Value: 5 to 495 seconds (in 5 second increments)
	NOTE NOTE
	This function is displayed when [Auto Error Clear] is set to [On].
Unusable Time	Set a time period during which the machine will not print received faxes.
	FAX Operation Guide.
Ping Timeout	Set the time until timeout occurs when [Ping] is executed in "System/Network".
	Value: 1 to 30 seconds (in 1 second increments)

\*1 Displayed when the optional Card Authentication Kit is activated.

# **Adjustment/Maintenance**

### [System Menu/Counter] key > [Adjustment/Maintenance]

Adjust printing quality and conduct machine maintenance.

ltem	Description
Density Adjustment	Adjust density.
Сору	Adjust copy density. Value: -3 (Lighter), -2, -1, 0 (Normal), +1, +2, +3 (Darker)
Send/Box	Adjust scan density when sending or storing the data in Document Box. Value: -3 (Lighter), -2, -1, 0 (Normal), +1, +2, +3 (Darker)
Contrast	You can increase or decrease the overall contrast.
Сору	Increases or decreases the overall contrast of copies. Value: -3 (Lower), -2, -1, 0 (Normal), +1, +2, +3 (Higher)
Send/Box	Increases or decreases the overall contrast when documents are sent or saved in a document box. Value: -3 (Lower), -2, -1, 0 (Normal), +1, +2, +3 (Higher)
Correcting Black Line	Correct fine lines (streaks caused by contamination), which may appear on the image, when the document processor is used. Value: Off, On
Display Brightness	Set the brightness of the touch panel. Value: 1 (Darker), 2, 3, 4, 5 (Lighter)
Color Registration	<ul> <li>When first installing the machine or moving it to a new location, color drift during printing may occur. Use this function to correct the color position of each of cyan, magenta and yellow to resolve color drift.</li> <li>Color Registration Procedure (page 10-29)</li> </ul>
Drum Refresh	<ul> <li>Remove image blur and white dots from the printout. It takes about 2 minutes. The time required may vary depending on the operating environment and this process may take time.</li> <li>Drum Refresh (page 10-34)</li> <li>NOTE</li> <li>Drum Refresh cannot be performed while printing. Execute Drum Refresh after the printing is done.</li> </ul>
Calibration	Adjust color drift or hue of printed image in the most appropriate color.
Laser Scanner Cleaning	<ul> <li>Remove vertical white lines from the printout.</li> <li>▶ Laser Scanner Cleaning (page 10-34)</li> </ul>
Service Setting	Settings for machine maintenance and inspection. This menu is primarily used by service technicians to perform maintenance.

9

# User Authentication and Accounting (User Login, Job Accounting)

This chapter explains the following topics:

Overview of User Login Administration	
Managing the Job Account from PC	9-2
Enabling User Login Administration	9-3
Setting User Login Administration	9-4
Authentication Security	
Adding a User (Local User List)	9-5
Changing User Properties	
User Login Administration for Printing	
Managing the Users to Scan Using TWAIN	
Managing the Users to Scan Using WIA	
Managing the Users that Send Faxes from a PC	
Group Authorization Settings	
Guest Authorization Set.	
Obtain NW User Property	
Simple Login Settings	
ID Card Settings	
PIN Login Settings	
Using User Login Administration	
Login/Logout	
Overview of Job Accounting	
To Manage the Number of Sheets Used on Jobs Printed from a PC	
Enabling Job Accounting	
Job Accounting Access	
Setting an Account	
Adding an Account	
Restricting the Use of the Machine	
Editing an Account	
Deleting an Account	
Job Accounting for Printing	
Job Accounting for Scan Using TWAIN	
Job Accounting for Scan Using WIA	. 9-36
Job Accounting for the FAX Transmitted from a Computer	
Configuring Job Accounting	
Default Setting	
Counting the Number of Pages Printed	
Print Accounting Report	
Using Job Accounting	
Login/Logout	
Unknown User Settings	
Unknown ID Job	
Registering Information for a User whose ID is Unknown	. 9-43

# **Overview of User Login Administration**

User login administration specifies how the user access is administered on this machine. Enter a correct login user name and password for user authentication to login.

Set the user

(page 9-5)

1 Enable User Login Administration



- 3 Enter the login user name and password and execute the job (page 9-27)



Access are in three levels - "User", "Administrator", and "Machine Administrator". The security levels can be modified only by the "Machine Administrator".


# **Managing the Job Account from PC**

In addition to the above settings, the following are necessary to manage the job account from PC.

#### To Manage the Users to Print from PCs

Printer driver settings are necessary to manage the users that print on the machine from PCs.

1Set the User Login Administration<br/>on the printer driver (page 9-11)2Print



### Managing the Users to Use TWAIN for Scanning

TWAIN driver settings on the PC are necessary to manage the users that use TWAIN for scanning.

Managing the Users to Scan Using TWAIN (page 9-12)

### Managing the Users to Use WIA for Scanning

WIA driver settings on the PC are necessary to manage the users that use WIA for scanning.

Managing the Users to Scan Using WIA (page 9-13)

### Managing the Users to Send Faxes from a PC

FAX driver settings on the PC are necessary to manage the users that send faxes from a PC.

Managing the Users that Send Faxes from a PC (page 9-14)

# **Enabling User Login Administration**

This enables user login administration. Select one of the following authentication methods:

Item	Descriptions
Local Authentication	User authentication based on user properties on the local user list stored in the machine.
Network Authentication	User authentication based on Authentication Server. Use a user property stored in Authentication Server to access the network authentication login page.

# 1 Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

### 💽 NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [User Login Setting] > [User Login]

# **2** Configure the settings.

1 Select [Local Authentication] or [Network Authentication].

Select [Off] to disable user login administration.

If you select [Network Authentication], enter the host name (64 characters or less) and domain name (256 characters or less) for the Authentication Server. Select [NTLM], [Kerberos] or [Ext.] as the server type.

When selecting [Ext.] as the server type, enter the port number.

#### NOTE

- Selecting [Domain] displays the domain registration list.
- Enter the domain name. Up to 10 domain names can be registered.
- 2 "Do you want to add a new function to the home screen?" screen appears. To display a new function on the Home screen, select [Yes] and specify the position in which you want to display the icon of registered function.
  - Available Functions to Display on Desktop (page 2-14)

#### 💽 NOTE

If the login user name and password are rejected, check the following settings.

- · Network Authentication setting of the machine
- · User property of the Authentication Server
- · Date and time setting of the machine and the Authentication Server

If you cannot login because of the setting of the machine, login with any administrator registered in the local user list and correct the settings.

# **Setting User Login Administration**

This registers, alters and deletes users and configures the settings for User Login Administration.

# **Authentication Security**

If user authentication is enabled, configure the user authentication settings.

### **User Account Lockout Setting**

You can prohibit the use of a user account if an incorrect password is entered repeatedly to login with that account.

# **1** Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [User Login Setting] > [User Account Lockout Settings]

# **2** Configure the settings.

The following settings can be selected.

Item		Descriptions
Lockout	Select whether or no Value: Off, On	ot account lockout policy is enabled.
Lockout Policy	Specify the condition applied.	ns and the extent to which the account lockout is
	Number of Retries	until Locked: Specify how many login retries are allowed until the account is locked out. (1 to 10 times)
	Lockout Duration:	Specify how long the account is to be locked out until it is unlocked. (1 to 60 minutes)
	Lockout Target	Specify the extent to which the account lockout is applied. You can select from [All] or [Remote Login Only]. Remote Login Only locks out all operations from outside the operation panel.
Locked out Users List	Displays a list of loc user in the list, and	ked out users. You can unlock a user by selecting the selecting [ <b>Unlock</b> ].
	<b>NOTE</b> This function is disp	layed when account lockout policy is enabled.

User Authentication and Accounting (User Login, Job Accounting) > Setting User Login Administration

# **Adding a User (Local User List)**

You can add up to 20 users (including the default login user name).

# NOTE

By default, one of each default user with machine administrator rights and administrator privileges is already stored. Each user's properties are:

Machine Administrator
User Name: DeviceAdmin
Login User Name: 2600
Login Password: 2600
Access Level: Machine Administrator
Administrator
User Name: Admin
Login User Name: Admin
Login Password: Admin
Access Level: Administrator
* Upper case and lower case letters are distinguished (case sensitive).
It is recommended to periodically change the user name, login user nar

It is recommended to periodically change the user name, login user name and login password regularly for your security.

# **1** Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

# NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

2 [User Login Setting] > [Local User List] > [\*]

# **2** Enter the user information.

#### Select [Next].

The table below explains the user information to be registered.

Item	Descriptions
User Name	Enter the name displayed on the user list (up to 32 characters).
Login User Name	Enter the login user name to login (up to 64 characters). The same login user name cannot be registered.
Access Level	Select "Administrator" or "User" for user access privileges.

### NOTE

For details on entering characters, refer to the following:

Character Entry Method (page 11-8)

# **3** Check the user information.

Change or add information as needed.

Item	Descriptions
User Name <sup>*1</sup>	Enter the name displayed on the user list (up to 32 characters).
Login User Name <sup>*1</sup>	Enter the login user name to login (up to 64 characters). The same login user name cannot be registered.
Login Password	Enter the password to login (up to 64 characters). Reenter the same password for confirmation and select the [ <b>OK</b> ] key.
Account Name	Add an account where the user belongs. The user, who registered his/her account name, can login without entering the account ID.
	<ul> <li>Overview of Job Accounting (page 9-28)</li> </ul>
	Select [Menu] > [Search (Name)] or [Search (ID)] to search by account name or account ID.
	Select [Menu] > [Sort (Name)] or [Sort (ID)] to sort the account list.
Access Level <sup>*1</sup>	Select "Administrator" or "User" for user access privileges.
ID Card	Register ID card information.
Information	Place the ID card on the ID card reader, and select [Read].
	This function is displayed when the optional Card Authentication Kit is activated.
	Optional Applications (page 11-6)

\*1 Mandatory at user registration.

# NOTE

For details on entering characters, refer to the following:

<u>Character Entry Method (page 11-8)</u>

# **4** Select [Save].

A new user is added on the local user list.

# ΝΟΤΕ

If simple login is enabled, a confirmation screen appears when new registration is finished asking if you will configure simple login settings. To configure simple login settings, select **[Yes]**. If you select **[No]**, you will return to the user list screen.

For the procedure for configuring simple login settings, refer to the following:

Simple Login Settings (page 9-23)

User Authentication and Accounting (User Login, Job Accounting) > Setting User Login Administration

# **Changing User Properties**

Types of user properties that could be changed may be different depending on user access privilege.

# NOTE

To change the user information of the machine administrator, you must log in with machine administrator authority. You can only view user information if you log in as a regular user.

The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

#### For a user with administrator rights who logs in

User properties can be changed and users can be deleted. The items, which can be added, are all able to be changed.

### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

2 [User Login Setting] > [Local User List]

#### **2** Change the user properties.

Changing user properties

Select [ ] for the user to edit.

Admin	Admin	
DeviceAdmin	5000	1/1
User A	User A	

### NOTE

- To sort the user list, select [Menu] > [Sort (User Name)] and [Sort (Login User Name)].
- To search by name or login user name, select [Menu] > [Search (User Name)] or [Search (Login User Name)].
- 2 Refer to step 3 of "Adding a User (Local User List)" to change a user property.
  - Adding a User (Local User List) (page 9-5)
- 3 [Save] > [Yes]

The user information is changed.

#### **Deleting a user**

- 1 Select the user to delete.
- 2 [@] > [Yes]

The selected user will be deleted.

### **NOTE**

The default user with machine administrator rights cannot be deleted.

### To change the user information of logged in user (User Property)

These users can partially change their own user properties including user name, login password, and Simple Login.

Although "Login User Name", "Access Level", or "Account Name" cannot be changed, the users can check the present status.

### 1 Display the screen.

[System Menu/Counter] key > [User Property]

# **2** Change the user properties.

- 1 Refer to step 3 of "Adding a User (Local User List)" to change a user property.
  - Adding a User (Local User List) (page 9-5)

Item	Description
User Name	Changes the name shown on the user list. Up to 32 characters can be entered.
Login User Name	Displays the login user name that is entered at login.
Login Password	Changes the password that is entered at login. Up to 64 characters can be entered.
Access Level	Displays the user's access level.
Account Name	Displays the account where the user belongs.
Job Accounting	Displays the usage restriction that is set for the logged in user.
	NOTE
	[ <b>Job Accounting</b> ] shows the account name set for the logged in user and the usage restrictions that are set for that account.
	This function appears when job accounting is set to [ <b>On</b> ]. For information on job accounting, refer to the following:
	Enabling Job Accounting (page 9-29)
ID Card Information	Displays the ID card information of the logged in user.
	This function is displayed when the optional Card Authentication Kit is activated.
	<ul> <li>Optional Applications (page 11-6)</li> </ul>
	This function does not appear when the server type is set to [ <b>Ext.</b> ] in Network Authentication, and logged in with the user account certificated in the server specified as the [ <b>Ext.</b> ] server type.
Simple Login	When simple login is enabled, changes associated settings.
	NOTE
	This function does not appear when Simple Login is set to [ <b>Off</b> ] or the user is not registered in Simple Login.

2 Select [Save].

The user information is changed.

# **User Login Administration for Printing**

It is possible to manage the users that print on this machine from a PC.

#### **Setting Printer Driver**

To manage the users that print on this machine from a PC, the following settings are necessary in the printer driver. Instructions are based on interface elements as they appear in Windows 8.1.

#### Display the screen.

 Select [Settings] in charms on Desktop, and select [Control Panel], and then [Devices and Printers].

#### **NOTE**

In Windows 7, click [Start] button on the Windows, and then click [Devices and Printers].

- 2 Right-click the printer driver icon of the machine, and click the [Printer properties] menu of the printer driver.
- 3 Click [Administrator] on the [Device Settings] tab.

### Configure the settings.

1 Select [User Login] on the [User Login] tab.

and ashindle a construct a close des	
20000	
Concernation and an and a second s	
Di Di	
Shall in	
<ul> <li>All the second se</li></ul>	475
with the property in the second	1122310
	ALC: NOT
	and the second sec
	1 Acres

Set the User Login Administration.

[Use specific name]: This option can be used to specify a user name and password to use the same User login for every print job. If this option is selected, the user does not have to type the name and password for each print job.

[**Prompt for name**]: A screen for entering the user name and password will be displayed when attempting a printing. The user name and password must be entered each time a printing is attempted.

[**Prompt for name and validate**]: A screen for entering the user name and password will be displayed when attempting a printing. The user name and password stored in the Login user name list needs to be entered. The user name and password must be entered each time a printing is attempted.

[Validate user name (computer) or prompt for login user name]: When printing, the Windows user name is searched in the "Login user names" and printing is possible if the name is registered. If the name is not registered, the printing will be canceled for users with only user authority. If the user has administrator privileges, the screen to enter the user name and password will appear.

3 Click [OK].

#### 

For other settings of job accounting, refer to the following:

Printer Driver User Guide

# **Managing the Users to Scan Using TWAIN**

It is possible to manage the users that scan using TWAIN.

#### Setting TWAIN Driver

To manage the users that scan using TWAIN, the following settings are necessary in the TWAIN driver. Instructions are based on interface elements as they appear in Windows 8.1.

# Display the screen.

1 Select [Search] in charms, and enter "TWAIN Driver Setting" in the search box. Click [TWAIN Driver Setting] in the search list then the TWAIN Driver Setting screen appears.

#### NOTE

In Windows 7, select [Start] button on the Windows, [All Programs], [Kyocera] and then [TWAIN Driver Setting].

2 Select the machine, and click [Edit].





#### Configure the settings.

- 1 Click [User Authentication Settings].
- 2 Select the checkbox beside [Authentication], and enter Login User Name and Password.

Cite Second	
Laborate .	
and the second s	
E	
Course a	
Company Land	
Contraction of the second	2

3 Click [OK].

# **Managing the Users to Scan Using WIA**

It is possible to manage the users that scan using WIA.

#### Setting WIA Driver

To manage the users that scan using WIA, the following settings are necessary in the WIA driver. Instructions are based on interface elements as they appear in Windows 8.1.


### 1 Display the screen.

1 Click [Search] in charms, and enter "Scanner" in the search box. Click [View scanners and cameras] in the search list then the Scanners and Cameras screen appears.

#### **NOTE**

In Windows 7, click [Start] button on the Windows and enter [Scanner] in [Program and File Search]. Click [View scanners and cameras] in the search list then the Scanners and Cameras screen appears.

2 Select the same name as this machine from WIA Drivers, and press [Properties].



# 2 Configure the settings.

1 Select the checkbox beside [Authentication] on the [Settings] tab, and enter Login User Name and Password.

ter Dear	tone and the second sec	Elemento France
		Denning

2 Click [OK].

# Managing the Users that Send Faxes from a PC

It is possible to manage the users that send faxes from a PC.

#### Setting FAX Driver

To manage the users that send faxes from a PC, the following settings are necessary in the FAX driver. Instructions are based on interface elements as they appear in Windows 8.1.

#### Display the screen.

 Select [Settings] in charms on Desktop, and select [Control Panel], and then [Devices and Printers].


#### NOTE

In Windows 7, click [Start] button on the Windows, and then click [Devices and Printers].

- 2 Right-click the printer driver icon of the machine, and click the [Printer properties] menu of the printer driver.
- 3 Click [FAX TX Setting] on the [Printing Preferences] window.

### **2** Configure the settings.

1 Select [User Login] on the [Authentication] tab.



Set the User Login Administration.

[Use Specific Login User Name]: This option can be used to specify a user name and password to use the same User login for every FAX job. If this option is selected, the user does not have to type the name and password for each FAX job.

[**Prompt for Login User Name**]: A screen for entering the user name and password will be displayed when attempting a transmission. The user name and password must be entered each time a transmission is attempted.

**3** Click [**OK**].

# **Group Authorization Settings**

Set restrictions of the machine usage by each individual group registered in the authentication server.

# NOTE

To use the group authorization settings, [**Network Authentication**] must be selected for the authentication method in "Enabling User Login Administration". Select "On" for "LDAP" in "Protocol Settings".

 Enabling User Login Administration (page 9-3) Protocol Settings (page 8-30)

#### **Group Authorization**



#### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [User Login Setting] > [Group Authorization Set.] > [Group Authorization]



# Group List (Up to 20)

Register the groups that are restricted the machine usage. Other users and groups belong to "Others". The table below explains the group information to be registered.

Item	Descriptions	
Group ID <sup>*1</sup>	Enter the ID displayed on the group list (between 1 and 4294967295).	
Group Name	Enter the name displayed on the group list (up to 32 characters).	
Access Level	Select [Administrator] or [User] for group access privileges.	
Printer	Select whether or not to reject usage of print functions for the printer.	
Printer (Full Color)	Select whether or not to reject usage of color print functions for the printer.	
Сору	Select whether or not to reject usage of copy functions.	
Copy (Full Color)	Select whether or not to reject usage of only full-color print functions for copies.	
Duplex Restriction	Select whether only duplex printing is allowed.	
Combine Restrict.	Specify whether only Combine is allowed.	
EcoPrint Restriction	Specify whether only EcoPrint is allowed.	
Send	Select whether or not to reject usage of the send functions.	
FAX Transmission	Select whether or not to reject usage of the FAX transmissions.	
Storing in Box	Select whether or not to reject usage of storing in the document boxes.	
Storing in Memory	Select whether or not to reject usage of storing in the removable memory.	

\*1 For "Group ID", set the PrimaryGroupID shown in the user attributes that are displayed using ADSIEdit of Windows Server. In Windows Server 2003, ADSIEdit is a support tool that is included on the installation DVD of the Windows Server OS (in the \SUPPORT\TOOLS folder). In Windows Server 2008 and later, ADSIEdit is provided as a standard function.

# Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

### 💽 NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

2 [User Login Setting] > [Group Authorization] > [Group List] > [

roup Authorization			+
Others	L.	0	
	1		1/1
	10		1

# **2** Configure the settings.

- 1 Enter the group ID > [Next]
- 2 Enter the group name > [Next]

#### 

For details on entering characters, refer to the following:

- Character Entry Method (page 11-8)
- 3 Select the group access privileges > [Next]
- **4** Check the settings and change or add information as needed.

### **3** Register the group.

#### Select [Save].

A new group is added on the group list.

# **Guest Authorization Set.**

When User Login Administration is enabled, set the functions that guest users who cannot log in to the machine are allowed to use.

#### 💽 NOTE

To use Guest Authorization Set., User Login Administration must be enabled in "Enabling User Login Administration".

Enabling User Login Administration (page 9-3)

#### **Enabling Guest Authorization**

#### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### 💽 NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [User Login Setting] > [Guest Authorization Set.] > [Guest Authorization]

# 2 Select [On].

#### 💽 ΝΟΤΕ

If the guest authorization setting is enabled, the [Authentication/Logout] key must be selected when logging in.

In the guest user default settings, only monochrome copying can be used. If you wish to use a different function, log in as a user who can use that function, or change the settings in the guest properties.

### **Configuring Guest Property**

Register guest user information and functions that are restricted.

The table below explains the user information to be registered.

ltem	Descriptions	
User Name	Enter the name displayed on the user list (up to 32 characters).	
	The default setting is "Guest User".	
Access Level	The authority of the user appears. This cannot be changed.	
Account Name	Add an account where the user belongs.	
	If the user does not belong to any account, select [Other].	
Authorization Rules	Set usage authority for each user.	
	The items you can restrict the access level with are as follows.	
	Printer:	
	Select whether or not use of the print function of the printer is prohibited.	
	Printer (Full Color):	
	Select whether or not use of the print function (color) of the printer is prohibited.	
	Сору:	
	Select whether or not use of the copy print function is prohibited.	
	Copy (Full Color):	
	Select whether or not use of the copy print function (full color) is prohibited.	
	Duplex Restriction:	
	Select whether only duplex printing is allowed.	
	Combine Restrict.:	
	Specify whether only Combine is allowed.	
	EcoPrint Restriction:	
	Specify whether only EcoPrint is allowed.	
	Send:	
	Select whether or not use of the send function is prohibited.	
	FAX TX Restriction:	
	Select whether or not use of the fax send function is prohibited.	
	Storing in Box:	
	Select whether or not use of the box store function is prohibited.	
	Storing in Memory:	
	Select whether or not use of the removable memory store function is prohibited.	

#### **1** Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

# NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

2 [User Login Setting] > [Guest Authorization Set.] > [Guest Property]

# **2** Configure the settings.

Check the settings and change or add information as needed.

# **3** Register the group.

Select [Save].

# **Obtain NW User Property**

Set the required information to obtain the network user property from the LDAP server. The user name obtained with this setting is shown in the user information, the status confirmation screen, and the header of E-mail.

# 🚫 NOTE

To obtain the network user property from the LDAP server, [**Network Authentication**] must be selected for the authentication method in "Enabling User Login Administration". Select "On" for "LDAP" in "Protocol Settings".

 Enabling User Login Administration (page 9-3) <u>Protocol Settings (page 8-30)</u>

The table below explains the required information to be registered.

Item	Descriptions
Server Name <sup>*1</sup>	Enter the LDAP server name or the IP address (up to 64 characters). If a server name is not entered, user information will be acquired from the server set for Network Authentication.
Port	Port number for LDAP server. The default port number is 389.
Name 1 <sup>*2</sup>	Enter the LDAP Attribute to obtain the user name to be displayed from the LDAP server (up to 32 characters).
Name 2 <sup>*3</sup>	Enter the LDAP Attribute to obtain the user name to be displayed from the LDAP server (up to 32 characters).
Authentic at Type <sup>*4</sup>	Set the authentication method. Select [Simple] or [SASL]. After changing the setting, restart the system or turn the power off and then on.
Search Timeout	Set the amount of time to wait before time-out in seconds (from 5 to 255 seconds).

\*1 If using Active Directory of Windows, the server name may be the same as the server name entered in the network authentication.

\*2 If using Active Directory of Windows, displayName of Attribute may be used as "Name 1".

- \*3 "Name 2" can be left out. When you assign displayName in "Name 1" and department in "Name 2", and if the value of displayName is "Mike Smith" and the value of department is "Sales" in Active Directory of Windows, the user name appears as "Mike Smith Sales".
- \*4 Appears when the server type is set to "Kerberos" in "Network Authentication".

# **1** Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

# 🚫 NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

2 [User Login Setting] > [Obtain NW User Property] > [On]

# **2** Configure the settings.

- 1 [Server Name] > Enter the LDAP server name or the IP address > [OK]
- 2 [Port] > Enter the LDAP port number > [OK]
- 3 [Name 1] > Enter the LDAP Attribute to obtain the user name to be displayed > [OK]
- 4 Similar to steps 3, set [Name 2].
- 5 If you set the server type to "Kerberos", select [**Authentication Type**] and set the authentication method.
- 6 Select [Search Timeout] to set the amount of time to wait before time-out.
- 7 Select [+], [-] or the numeric keys to enter the time > [OK] > [OK]

# **Simple Login Settings**

The simple login function allows users to log in simply by selecting a user name. Users must be registered in advance to use this functionality.

#### 💽 NOTE

- · For user registration, refer to the following:
- Adding a User (Local User List) (page 9-5)
- To use Simple Login, User Login Administration must be enabled in "Enabling User Login Administration".
- Enabling User Login Administration (page 9-3)
- When the guest authorization setting is enabled, the Simple Login screen is not displayed.

#### **Enabling Simple Login**

#### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [User Login Setting] > [Simple Login Settings] > [Simple Login]

# 2 Select [On] or [Off].

#### Simple Login Setup

You can add up to 20 users.



#### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### 🔇 NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [User Login Setting] > [Simple Login Settings] > [Simple Login Setup]

### 2 Enter the user information.

1 Select the key to which you want to register a user.

2 Select [ 👘 ].

Simple login se		tup	+
01 None	02 None	03 None	
04 None	05 None	06 None	1/3
07 None	08 None	09 None	

3 To specify the user from local users, select [Local User]. To specify from network users, select [Network User].

The procedure differs depending on the transmission method selected.

#### Specifying the user from local users

Select the user to be set for simple login.

#### NOTE

- To search by name or login user name, select [Menu] > [Search (Name)] or [Search (Login User Name)].
- To sort the user list, select [Menu] > [Sort (Name)] and [Sort (Login User Name)].

#### Specifying the user from network users

System Menu/Counter. Add - Network User			10:10
Login User Name			
			Keyboard
Login Password			
			Keyboard
	Cancel	< Back	Next >

Select [**Keyboard**] for "Login User Name" and "Login Password", enter the information of the user to be registered, and select [**OK**].

If you are specifying a user for whom a domain is set in network authentication, select the "Domain" and select the domain where the user is registered.

Select [Next].

#### NOTE

For details on entering characters, refer to the following:

- Character Entry Method (page 11-8)
- 4 Enter the user name to be displayed, and select [OK].

#### 

For details on entering characters, refer to the following:

<u>Character Entry Method (page 11-8)</u>

- 5 [Password Login] > [On] or [Off] > [Icon]
- 6 Select the user icon to be displayed and select [OK].

#### 3 Register the user.

Select [Save].

User Authentication and Accounting (User Login, Job Accounting) > Setting User Login Administration

# **ID Card Settings**

If ID card authentication is enabled, select the authentication type.

### 🔘 ΝΟΤΕ

This functions appears when the Card Authentication Kit is activated.

Optional Applications (page 11-6)

#### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

2 [User Login Setting] > [ID Card Settings]

# **2** Configure the settings.

The following settings can be selected.

Item	Descriptions
Keyboard Login	When ID card authentication is enabled, select whether or not login by keyboard is allowed. Value: Permit, Prohibit
Additional Authentication <sup>*1</sup>	Select whether or not to require password entry after authenticating by ID card. Value: Off, Use Password, Use PIN <sup>*2</sup>

\*1 This function does not appear when the server type is set to [NTLM] or [Kerberos] in "Network Authentication".

\*2 This function appears when the server type is set to [Ext.] in Network Authentication.

# **PIN Login Settings**

# ΝΟΤΕ

This setting is only displayed when [**Network Authentication**] must be selected for the authentication method and the server type is set to [**Ext.**] in "Network Authentication".

Optional Applications (page 11-6)

### **1** D

# Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

# 

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

2 Select [PIN Login].

# **2** Configure the settings

- 1 Select [Off] or [On].
- 2 Select [OK].

User Authentication and Accounting (User Login, Job Accounting) > Using User Login Administration

# **Using User Login Administration**

This section explains procedures while setting job accounting.

# Login/Logout

If user login administration is enabled, the login user name and login password entry screen appears each time you use this machine.

### Login

If the login user name entry screen appears during operations, log in by referring to the following:


✤ Login (page 2-21)

# Logout

When the operations are complete, select the [Authentication/Logout] key to return to the login user name and login password entry screen.

## **Overview of Job Accounting**

Job accounting manages the copy/print/scan/FAX count accumulated by individual accounts by assigning an ID to each account.




## To Manage the Number of Sheets Used on Jobs Printed from a PC

To manage the number of jobs to be printed from the PC on the network, you need to configure settings by using the printer driver on the PC.

- Set Job Accounting for the PC on the network by using the printer driver. (page 9-34)
- 2 Execute printing.

3 Count the number of pages printed.



#### Managing the Scan Job Account by Using TWAIN

To manage the scan job account by using TWAIN, you need to configure the TWAIN driver settings on the computer connected to the machine.

Job Accounting for Scan Using TWAIN (page 9-35)

#### Managing the Scan Job Account by Using WIA

To manage the scan job account by using WIA, you need to configure the WIA driver settings on the computer connected to the machine.

Job Accounting for Scan Using WIA (page 9-36)

#### Managing the FAX Job Transmitted from a PC

To manage the number of FAX jobs transmitted from the PC, you need to configure the settings by using the FAX Driver on the PC.

Job Accounting for the FAX Transmitted from a Computer (page 9-37)

# **Enabling Job Accounting**

#### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [Job Accounting Settings] > [Job Accounting]

#### **2** Select [On].

#### 💽 NOTE

- · To disable job accounting, select [Off].
- When the display returns to System Menu default screen, logout is automatically executed and the screen to enter the Account ID appears. To continue the operation, enter the Account ID.

### **Job Accounting Access**

#### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [Job Accounting Settings] > [Job Accounting Access]

#### **2** Configure the settings.

Select [Local] or [Network].

# **Setting an Account**

You can add, change and delete an account and set the restriction for each account.

## **Adding an Account**

Up to 20 individual accounts can be added. The following entries are required.

Item	Descriptions
Account Name	Enter the account name (up to 32 characters).
Account ID	Enter the account ID as many as eight digits (between 0 and 99999999).
Restriction	This prohibits printing/scanning or restricts the number of sheets to load.
	<ul> <li><u>Restricting the Use of the Machine (page 9-31)</u></li> </ul>

#### **1** Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [Job Accounting Settings] > [Accounting List] > [ ]

#### 2

#### Enter the account information.

1 Enter the account name > [Next]

#### 🚫 NOTE

For details on entering characters, refer to the following:

- Character Entry Method (page 11-8)
- 2 Enter the account ID > [Next]

#### NOTE

Any "Account ID" that has already registered cannot be used. Enter any other account ID.

- 3 Activate or deactivate restriction.
  - Restricting the Use of the Machine (page 9-31)
- 4 Select [Save].

A new account is added on the Account List.

## **Restricting the Use of the Machine**

This section explains how to restrict the use of the machine by account or the number of sheets available.

The items that can be restricted differ depending on whether "Individual" or "Total" is selected for "Copy/Print Count".

Copy/Print Count (page 9-38)

#### **Restriction Items**

"Individual" selected for Copy/Printer Count"Split" selected for Copy/Printer Count

Item	Descriptions
Copy (Total)	Limits the number of sheets used for copying.
Copy (Full Color)	Limits the number of pages used for full-color copying.
Printer (Total)	Limits the number of sheets used for printing.
Printer (Full Color)	Limits the number of pages used for color printing.
Scan (Others)	Limits the number of sheets scanned (excludes copying).
FAX Transmission	Limits the number of sheets sent by fax.

#### "Total" selected for Copy/Printer Count

Item	Descriptions
Print (Total)	Limits the total number of sheets used for copying and printing.
Print (Full Color)	Limits the number of pages used for full-color printing.
Scan (Others)	Limits the number of sheets scanned (excludes copying).
FAX Transmission	Limits the number of sheets sent by fax.

#### **Applying Restriction**

Restriction can be applied in the following modes:

Item	Descriptions
Off	No restriction is applied.
Counter Limit	Restricts the print counter in one-page increments up to 9,999,999 copies.
Reject Usage	Restriction is applied.

## **Editing an Account**

#### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

2 [Job Accounting Settings] > [Accounting List]

#### **2** Edit an account.

1 Select [\_\_\_] for the account name you wish to edit.



#### NOTE

- To search by name or login user name, select [Menu] > [Search (Name)] or [Search (ID)].
- To sort the user list, select [Menu] > [Sort (Name)] and [Sort (ID)].
- **2** Select the account information to be changed and change the account information.
- 3 [Save] > [Yes]

The account information is changed.

## **Deleting an Account**

#### **1** Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [Job Accounting Settings] > [Accounting List]

#### **2** Delete an account.

- 1 Select the account name you wish to delete.
- 2 [@]>[Yes]

The account is deleted.

## **Job Accounting for Printing**

The number of jobs to be printed from the computer can be managed by Job Accounting.

#### **Setting Printer Driver**

To manage the number of jobs to be printed from the PC on the network, you need configure the following settings by using the printer driver on the PC. Instructions are based on interface elements as they appear in Windows 8.1.

#### Display the screen.

1 Select [Settings] in charms on Desktop, and select [Control Panel], and then [Devices and Printers].

#### 💽 NOTE

In Windows 7, click [**Start**] button on the Windows, and then click [**Devices and Printers**].

- 2 Right-click the printer driver icon of the machine, and click the [Printer properties] menu of the printer driver.
- 3 Click [Administrator] on the [Device Settings] tab.

#### **2** Configure the settings.

1 Select [Job accounting] on the [Job Accounting] tab.

Taxtoond.s		
- Million in role i scotti Br		
() familie average (		
And the second se		
A second of the second second program.	144	
	Seria -	
	200	
	a chail	
	1000	
Different to access a distance of a particular to the second seco		

Set the Account ID.

[Use specific account ID]: Enter the Account ID. Printing will be performed using the entered Account ID. If this option is selected, the user does not have to enter the Account ID for each print job.

[**Prompt for account ID**]: A screen for entering the Account ID will be displayed when attempting a printing. The Account ID must be entered each time a printing is attempted.

[**Prompt for account ID and validate**]: A screen for entering the Account ID will be displayed when attempting a printing. The Account ID stored in the Account ID list needs to be entered. The Account ID must be entered each time a printing is attempted.

[**Display account ID list**]: The Account ID list is displayed when printing. The Account ID to be used needs to be selected from the list.

[Validate user name (computer) or prompt for account ID]: When printing, the Windows user name is searched in the "Login user names" and printing is possible if the name is registered. If the name is not registered, the printing will be canceled for users with only user authority. If the user has administrator privileges, the screen to enter the user name and password will appear.

3 Click [OK].

#### 

For other settings of job accounting, refer to the following:

Printer Driver User Guide

## **Job Accounting for Scan Using TWAIN**

The number of jobs scanned by using TWAIN can be managed by Job Accounting.

#### **Setting TWAIN Driver**

To manage the number of jobs scanned by using TWAIN, you need to configure the following settings by using the TWAIN Driver on the computer. Instructions are based on interface elements as they appear in Windows 8.1.

#### 1 Display the screen.

1 Select [Search] in charms, and enter "TWAIN Driver Setting" in the search box. Click [TWAIN Driver Setting] in the search list then the TWAIN Driver Setting screen appears.

#### NOTE

In Windows 7, select [Start] button on the Windows, [All Programs], [Kyocera] and then [TWAIN Driver Setting].

2 Select the machine, click [Edit].





#### Configure the settings.

- 1 Click [User Authentication Settings].
- 2 Select the checkbox beside [Account], and enter the account ID.

1¢	
E	
F	

3 Click [OK].

## **Job Accounting for Scan Using WIA**

The number of jobs scanned by using WIA can be managed by Job Accounting.

#### **Setting WIA Driver**

To manage the number of jobs scanned by using WIA, you need to configure the following settings by using the WIA Driver on the computer. Instructions are based on interface elements as they appear in Windows 8.1.


#### **1** Display the screen.

1 Click [Search] in charms, and enter "Scanner" in the search box. Click [View scanners and cameras] in the search list then the Scanners and Cameras screen appears.

#### **NOTE**


In Windows 7, click [Start] button on the Windows and enter [Scanner] in [Program and File Search]. Click [View scanners and cameras] in the search list then the Scanners and Cameras screen appears.

2 Select the same name as this machine from WIA Drivers, and press [Properties].



#### **2** Configure WIA Driver.

**1** Select the checkbox beside [**Account ID**] on the [**Settings**] tab, and enter the Account ID.



2 Click [**OK**].

# Job Accounting for the FAX Transmitted from a Computer

The number of FAX jobs transmitted from the computer can be managed by Job Accounting.

#### Setting FAX Driver

To manage the number of FAX jobs transmitted from the computer, you need to configure the following settings by using the FAX Driver on the computer. Instructions are based on interface elements as they appear in Windows 8.1.

#### Display the screen.

1 Select [Settings] in charms on Desktop, and select [Control Panel], and then [Devices and Printers].

#### 底 NOTE

In Windows 8, click [**Start**] button on the Windows, and then click [**Devices and Printers**].

- 2 Right click the name of the machine to be used as the FAX Driver and select [**Printing preferences**] from the resulting pull-down menu.
- 3 Click [FAX TX Setting] in the [Printing Preferences] window.

#### **2** Configure the settings.

1 Select [Job Accounting] on the [Authentication] tab.

Probac .	
er personale ogé die konse.	
Inst. See Server	
(second ) Second second	
des Constantes	
A to form the set in	
Proprieto de la B	

2 Set the Job Accounting.

[Use Specific Account ID]: This option can be used to specify an account ID to use the same Account ID for every FAX job. If this option is selected, the user does not have to enter the Account ID for each FAX job.

[**Prompt for Account ID**]: A screen for entering the Account ID will be displayed when attempting a transmission. The Account ID must be entered each time a transmission is attempted.

3 Click [OK].

# **Configuring Job Accounting**

## **Default Setting**

Set the defaults for job accounting. To configure the settings, select the item in Default Setting and select the setting item.

[System Menu/Counter] key > [User Login/Job Accounting] > [Job Accounting Settings] > [Default Setting]

For details on each function, see the table below.

Item	Description
Apply Limit	This specifies how the machine behaves when the counter has reached the limit of restriction. The table below describes the action taken.
	Value Immediately: Job stops when the counter reaches its limit. The next job will be prohibited in sending or in storing in the box.
	Subsequently: Printing/scanning of the job continues but the subsequent job will be rejected.
	Alert Only: Job continues while displaying an alert message.
Copy/Print Count	You can select how the copying and printing page counts are shown - either the total of both or each of copying and printing individually (Split). The selection may influence restriction on the count and count method.
	Value: Total, Individual
	<ul> <li><u>Restricting the Use of the Machine (page 9-31)</u></li> <li><u>Print Accounting Report (page 9-40)</u></li> </ul>
Default Counter Limit	When you add a new account, you can change the default restrictions on the number of sheets used. You can set any number from 1 to 9,999,999.
	The items that can be set differ depending on whether [Individual] or [Total] is selected for [Copy/Print Count].
	Copy/Print Count (page 9-38)
[Individual] selected for C	copy/Printer Count
Copy (Total)	Sets the default restriction on the number of sheets used for copying.
Copy (Full Color)	Sets the default restriction on the number of sheets used for full-color copying.
Printer (Total)	Sets the default restriction on the number of sheets used for printing.
Printer (Full Color)	Sets the default restriction on the number of sheets used for color printing.
Scan (Others)	Sets the default restriction on the number of sheets used for scanning (excludes copying).
FAX Transmission	Sets the default restriction on the number of sheets used for sending faxes.
[Total] selected for Copy/	Printer Count
Print (Total)	Sets the default restriction on the total number of sheets used for copying and printing.
Print (Full Color)	Sets the default restriction on the number of sheets used for full-color printing.
Scan (Others)	Sets the default restriction on the number of sheets used for scanning (excludes copying).
FAX Transmission	Sets the default restriction on the number of sheets used for sending faxes.

## **Counting the Number of Pages Printed**

This counts the number of pages printed. Counts are classified into Total Job Accounting and Each Job Accounting. A new count can also be started after resetting the count data which was stored for a certain period of time.

[System Menu/Counter] key > [User Login/Job Accounting] > [Job Accounting Settings] > [Total Accounting] or [Each Job Account]

#### **Total Accounting**

This counts the number of pages for all accounts and resets the counts for those accounts together at the same time.

#### Each Job Account

This counts the number of pages for each account and resets the counts by account. When checking Each Job Accounting, select the account for which you want to check the count.

Types of the counts are as follows.

	Item	Descriptions
Print	ed Pages	Displays the number of pages copied and printed, and the total number of pages used. You can also use [FAX], [by Duplex] and [by Combine] to check the number of pages used.
	Copy (B & W)	Displays the number of pages used for black and white copying.
	Copy (Full Color)	Displays the number of pages used for full-color copying.
	Copy (Total)	Displays the number of pages copied.
	Printer (B & W)	Displays the number of pages used for black and white printing.
	Printer (Full Color)	Displays the number of pages used for color printing.
	Printer (Total)	Displays the number of pages printed.
	Copy/Printer (B/W)	Displays the total number of pages used for black-and-white copying and printing.
	Copy/Print. (Color)	Displays the total number of pages used for full-color copying and printing.
	Copy/Print. (Total)	Displays the total number of pages used for copying and printing.
	FAX	Displays the number of pages received.
	Total	Displays the total number of pages used.
	by Duplex	Displays the number of pages printed in [1-sided] mode, [2-sided] mode, and the total pages in both modes.
	by Combine	Displays the number of pages printed in [None] (no Combine) mode, [2 in 1] mode, [4 in 1] mode, and the total pages in both modes.
Scan	ned Pages	Displays the number of pages scanned for copying, faxing and other functions, as well as the total number of pages scanned.
FAX	TX Pages	Displays the number of pages faxed.
FAX	TX Time	Displays the total duration of FAX transmissions.
Counter Reset		Resets the counter. Select [ <b>Yes</b> ] in the confirmation screen.

## **Print Accounting Report**

The total pages counted of all relevant accounts can be printed as an accounting report.

Reports have different formats depending on how the count of copiers and printers is administered.

#### When "Individual" is selected for Managing the Copy/Printer Count.

ACCOUNT. REPORT	<b>K</b> KYOCERa
Firmware Version	

#### Prepare paper.

Check that A4 or Letter paper is loaded in the cassette.

#### **2** Display the screen.

[System Menu/Counter] key > [User Login/Job Accounting] > [Job Accounting Settings]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name:2600Login Password:2600

#### **3** Print the report.

[**Print Accounting Report**] > [**Yes**] Accounting report is printed.

# **Using Job Accounting**

This section explains procedures while setting job accounting.

## Login/Logout

If job accounting is enabled, an account ID entry screen appears each time you use this machine.

#### Login

When the screen for entry of account codes on the machine appears, perform the following.

1

#### Enter the account ID using the numeric keys > [Login]

#### NOTE

- If you entered a wrong character, select the [Clear] key and enter the account ID again.
- If the entered account ID does not match the registered ID, a warning beep will sound and login will fail. Enter the correct account ID.
- By selecting [Check Counter], you can refer to the number of pages printed and the number of pages scanned.

#### When the screen to enter the login user name and password appears

If user login administration is enabled, the screen to enter the login user name and password appears. Enter a login user name and password to login. If the user has already registered the account information, the account ID entry would be skipped.

Adding a User (Local User List) (page 9-5)

#### Proceed to complete the rest of the steps.

#### Logout

When the operations are complete, select the [Authentication/Logout] key to return to the account ID entry screen.

# **Unknown User Settings**

## **Unknown ID Job**

This specifies the behavior for handling the jobs sent with unknown or unsent login user names or User ID. If the User Login is set to invalid and Job Accounting is set to valid, follow the procedure when the Account ID is unknown.

The setting items are as follows.

Item	Descriptions
Permit	The job is permitted to be printed.
Reject	The job is rejected (not printed).

#### **1** Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [Unknown User Settings] > [Unknown ID Job]

#### **2** Configure the settings.

Select [Permit] or [Reject].

## **Registering Information for a User whose ID is Unknown**

If you register user information for a user whose ID is unknown, you can check information on the Job Status or Job History screens. In addition, you can restrict available functions.

#### 

This functions appears when [Unknown ID Job] is set to [Permit].

Unknown ID Job (page 9-42)

1

#### Display the screen.

1 [System Menu/Counter] key > [User Login/Job Accounting]

#### NOTE

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

2 [Unknown User Settings] > [User Property]

### **2** Enter the user information.

The table below explains the user information to be registered.

Item	Descriptions
User Name	Enter the name displayed on the user list (up to 32 characters).
	This is displayed when user login administration is enabled.
Account Name	Add an account where the user belongs. The user, who registered his/her account name, can login without entering the account ID.
	Overview of Job Accounting (page 9-28)
	<ul> <li>Select [Menu] &gt; [Search (Name)] or [Search (ID)] to search by account name or account ID.</li> </ul>
	<ul> <li>Select [Menu] &gt; [Sort (Name)] or [Sort (ID)] to sort the account list.</li> </ul>
	This is displayed when job accounting is enabled.
Authorization Rules	Set usage authority for each user. The items you can restrict the access level with are as follows.
	Printer:
	Select whether or not use of the print function of the printer is prohibited.
	Printer (Full Color):
	Select whether or not use of the print function (color) of the printer is prohibited.

# **10 Troubleshooting**

#### This chapter explains the following topics:

Regular Maintenance	10-2
Cleaning	10-2
Cleaning Glass Platen	10-2
Cleaning Slit Grass	10-3
Cleaning Paper Transfer Unit	10-4
Toner Container Replacement	10-5
Loading Paper	10-8
Troubleshooting	10-9
Solving Malfunctions	10-9
Machine Operation Trouble	10-9
Printed Image Trouble	10-12
Color printing trouble	10-15
Responding to Messages	10-16
Adjustment/Maintenance	10-29
Overview of Adjustment/Maintenance	10-29
Color Registration Procedure	10-29
Drum Refresh	10-34
Calibration	10-34
Laser Scanner Cleaning	10-34
Clearing Paper Jams	10-35
Jam Location Indicators	10-35
Remove any jammed paper in Cassette 1	10-36
Remove any jammed paper in Cassette 2	10-37
Remove any jammed paper in the Multipurpose Tray	10-39
Remove any jammed paper in Rear Cover 1	10-42
Remove any jammed paper in the Document Processor	10-45

# **Regular Maintenance**

## Cleaning

Clean the machine regularly to ensure optimum printing quality.


**CAUTION** For safety, always unplug the power cord before cleaning the machine.


## **Cleaning Glass Platen**

Wipe the inside of the document processor and the glass platen with a soft cloth dampened with alcohol or mild detergent.

**IMPORTANT** 

Do not use thinner or other organic solvents.





## **Cleaning Slit Grass**


When using the document processor, clean the slit glass surface and the reading guide with the dry cloth.


#### **IMPORTANT**


Do not use water, soap or solvents for cleaning.

#### NOTE

Dirt on the slit glass or the reading guide may cause black streaks to appear in the output.








## **Cleaning Paper Transfer Unit**

The paper transfer unit should be cleaned each time the toner container is replaced. To maintain optimum print quality, it is also recommended that the inside of the machine be cleaned once a month as well as when the toner container is replaced.

Print problems such as soiling of the reverse side of printed pages may occur if the paper transfer unit becomes dirty.

# 

Some parts are very hot inside the machine. Exercise caution as there is a risk of burn injury.



Wipe away the paper dust on the registration roller and the paper ramp using the cloth.

#### **IMPORTANT**

Be careful not to touch the transfer roller and transfer belt during cleaning as this may adversely affect print quality.

## **Toner Container Replacement**

When toner is empty, the following message will be displayed, replace the toner.

"Toner [C][M][Y][K] are empty."

When toner runs low, the following message will be displayed. Make sure you have a new toner container available for replacement.

"Toner is low. [C][M][Y][K] (Replace when empty.)"

#### **Frequency of Toner Container Replacement**

The life of the toner containers depends on the amount of toner required to accomplish your printing jobs. According to ISO/IEC 19798 and EcoPrint switched off the toner container can print as follows (A4/Letter paper is assumed):

Toner Color	Life of the Toner Container (Printable pages)
Black	4,000 images
Cyan	3,000 images
Magenta	3,000 images
Yellow	3,000 images

#### 💽 NOTE

- The average number of images that can be printed with each of the toner containers provided with the machine is 1,200 images.
- To maintain quality, we recommend using genuine Kyocera toner containers, which must pass numerous quality inspections.


## 

Do not attempt to incinerate parts which contain toner. Dangerous sparks may cause burns.


#### **Replacing the Toner Container**

Installation procedures of the toner container is same for every color. Here, we'll explain the yellow toner container, as an example.






Unlock the toner container. 2




3

Remove the toner container.



Put used toner containers into the plastic waste bag. 4






**6** Shake the toner container.



#### **7** Install the toner container.



#### 8 Close the right cover.



#### 

- If the right cover does not close, check that the new toner container is installed correctly.
- Return the exhausted toner container to your dealer or service representative. The collected toner container will be recycled or disposed in accordance with the relevant regulations.

## **Loading Paper**

When Cassette # runs out of paper, the following messages will be displayed.

"Add the following paper in cassette #." (# is a cassette number)

"Add the following paper in the multipurpose tray."

Loading Paper (page 3-2)

Loading Paper in the Multipurpose Tray (page 5-5)

#### 

If [Show Paper Setup Message] is set to [On], the confirmation screen for the paper setting will be displayed when a new paper is set. If a paper is changed, select [Change] and then change the settings of the paper.

<u>Cassette 1 (2) (page 8-14)</u>
 <u>Multipurpose Tray (page 8-14)</u>

# Troubleshooting

## **Solving Malfunctions**

The table below provides general guidelines for problem solving.

If a problem occurs with your machine, look into the checkpoints and perform procedures indicated on the following pages. If the problem persists, contact your Service Representative.

#### NOTE

When contacting us, the serial number will be necessary. To check the serial number, refer to the following:

 Display for Device Information (page 2-16) Machine Operation Trouble (page 10-9)

## **Machine Operation Trouble**

When the following machine operation troubles occur, implement appropriate procedures.

Symptom	Checkpoints	Corrective Actions	Reference Page
The screen does not respond when the power switch is turned on.	Check the power cord.	Connect both ends of the power cord securely.	page 2-9
Pressing the [ <b>Start</b> ] key does not produce copies.	Is there a message on the screen?	Determine the appropriate response to the message and respond accordingly.	page 10-16
	Is the machine in Sleep mode?	Select the [Energy Saver] key.	page 2-32
Blank sheets are ejected.	Are the originals loaded correctly?	When placing originals on the platen, place them face-down and align them with the original size indicator plates.	page 5-2
		When placing originals in the document processor, place them face-up.	<u>page 5-3</u>
	_	Check that the settings of the application software.	—
Paper often jams.	Is the paper loaded correctly?	Load the paper correctly.	page 3-4
	_	Turn the orientation 180 degrees around in which the paper is positioned.	page 3-4
	Is the paper of the supported type? Is it in good condition?	Remove the paper, turn it over, and reload it.	page 3-4
	Is the paper curled, folded or wrinkled?	Replace the paper with new paper.	page 3-4
	Are there any loose scraps or jammed paper in the machine?	Remove any jammed paper.	page 10-35
2 or more sheets are overlaps when ejected. (multi feed) ABC 123		Load the paper correctly.	<u>page 3-2</u>

Symptom	Checkpoints	Corrective Actions	Reference Page
Printouts are wrinkled.	Is the paper loaded correctly?	Load the paper correctly.	page 3-4
ABC 123	-	Turn the orientation 180 degrees around in which the paper is positioned.	page 3-2
	Is the paper damp?	Replace the paper with new paper.	page 3-4
Printouts are curled.	-	Turn the paper over in the cassette, or turn the orientation 180 degrees around in which the paper is positioned.	page 3-2
123	Is the paper damp?	Replace the paper with new paper.	<u>page 3-4</u>
Cannot print.	Is the machine plugged in?	Plug the power cord into an AC outlet.	—
	Is the machine powered on?	Turn on the power switch.	page 2-10
	Are the USB cable and network cable connected?	Connect the correct USB cable and network cable securely.	page 2-8
	Is the print job paused?	Resume printing.	page 7-10
Cannot print with USB memory.	Is the USB host blocked?	Select [ <b>Unblock</b> ] in the USB host settings.	page 8-36
USB memory not recognized.	-	Check that the USB memory is securely plugged into the machine.	_
While "Auto-IP" is set to [ <b>On</b> ], the IP address is not assigned automatically.	Is a value other than "0.0.0.0" entered for the IP address of TCP/IP(v4)?	Enter "0.0.0.0" for the IP address of TCP/IP(v4).	page 2-24

Symptom	Checkpoints	Corrective Actions	Reference Page
Cannot send via SMB.	Is the network cable connected?	Connect the correct network cable securely.	<u>page 2-8</u>
	Have the network settings for the equipment been configured properly?	Configure the TCP/IP settings properly.	page 8-29
	Have the folder sharing settings been configured properly?	Check sharing settings and access privileges under the folder properties.	page 3-12
	Has the SMB protocol been set to [On]?	Set the SMB protocol setting to [On].	page 8-30
	Has [ <b>Host Name</b> ] been entered properly? *1	Check the name of the computer to which data is being sent.	page 5-20
	Has [Path] been entered properly?	Check the share name for the shared folder.	page 5-20
	Has [ <b>Login User Name</b> ] been entered properly? *1 *2	Check the domain name and login user name.	page 5-20
	Has the same domain name been used for [Host Name] and [Login User Name]?	Delete the domain name and backslash ("/") from [Login User Name].	page 5-20
	Has [Login Password] been entered properly?	Check the login password.	page 5-20
	Have exceptions for Windows Firewall been configured properly?	Configure exceptions for Windows Firewall properly.	page 3-15
	Do the time settings for the equipment, domain server, and data destination computer differ?	Set the equipment, domain server, and data destination computer to the same time.	_
	Is the screen displaying Send error?	Refer to Responding to Send Error.	page 10-26
Cannot send via the e-mail.	Is the E-mail send size limit set in the SMTP server registered on the machine?	Check the limit value is entered to "E-mail Size Limit" of [ <b>E-mail</b> ] setting in Command Center RX and change the value as necessary.	<u>page 2-58</u>
The machine is emitting steam in the area around the paper ejection slot.	Check the room temperature to see if it is low, or if damp paper was used.	Depending on the printing environment and the paper's condition, the heat generated during printing will cause the moisture in the paper to evaporate, and the steam emitted may look like smoke. This is not a problem, and you can continue printing. If the steam concerns you, raise the room temperature, or replace the paper with a newer, dryer paper.	-

\*1 You can also enter a full computer name as the host name (for example, pc001.abcdnet.com).

\*2 You can also enter login user names in the following formats: Domain\_name/user\_name (for example, abcdnet/james.smith) User\_name@domain\_name (for example, james.smith@abcdnet)

## **Printed Image Trouble**

When the following printed image trouble occurs, implement appropriate procedures.

Symptom	Checkpoints	Corrective Actions	Reference Page
Printed images are totally	Is the paper damp?	Replace the paper with new paper.	page 3-2
too light.	Have you changed the density?	Select appropriate density level.	page 6-11
ABC ABC			page 8-41
123 123	Is the toner distributed evenly within the toner container?	Shake the toner container from side to side several times.	<u>page 10-5</u>
	Is EcoPrint mode enabled?	Disable [ <b>EcoPrint</b> ] mode.	page 8-16
	_	Run [Calibration].	page 10-34
	-	Run [ <b>Drum Refresh</b> ].	page 10-34
	_	Run [Laser Scanner Cleaning].	page 10-34
	_	Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [DEV-CLN], and then select [OK].	_
White background parts of	Have you changed the density?	Select appropriate density level.	page 6-11
the image appear to have a slight overall coloration.			page 8-41
ABC	_	Run [Calibration].	page 10-34
123	—	Run [ <b>Drum Refresh</b> ]	page 10-34
		Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [MC] and increase the adjustment value. Increase the adjustment value 1 level at a time from the current value. If there is no improvement after the value is increased by 1 level, increase by 1 level again. If there is still no improvement, return the setting to the original value.	
Copies have a moire pattern	Is the original a printed photograph?	Set the original image to [ <b>Photo</b> ].	<u>page 6-19</u>
(dots grouped together in patterns and not aligned uniformly).	-	When making copies Set [Sharpness] to a value from [-1] to [-3].	page 6-22
	_	When making copies Select the [System Menu/Counter] key > [Copy] > [DP Read Action] or [Platen Scan Act.], and set to [Quality Priority].	page 8-20 page 8-20
Texts are not clearly printed.	Did you choose appropriate image quality for the original?	Select appropriate image quality.	page 6-19
ABC	—	When making copies	page 6-22
123		Set [Sharpness] to a value from [+1] to [+3].	

Symptom	Checkpoints	Corrective Actions	Reference Page
Black or colored points appear in white background parts of the image.	Is the original holder or the glass platen dirty?	Clean the original holder or the glass platen.	<u>page 10-2</u>
		Run [Drum Refresh]	page 10-34
ABC 123	_	Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [MC] and increase the adjustment value. Increase the adjustment value 1 level at a time from the current value. If there is no improvement after the value is increased by 1 level, increase by 1 level again. If there is still no improvement, return the setting to the original value.	_
White or color dots appear on the printed images. ABC 123		Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [MC] and decrease the adjustment value. Decrease the adjustment value 1 level at a time from the current value. If there is no improvement after the value is decreased by 1 level, decrease by 1 level again. If there is still no improvement, return the setting to the original value.	
	_	Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [DEV-CLN], and then select [OK].	_
Printed images are fuzzy.	Is the machine being used in conditions of very humid, or humidity or temperature rapidly changes?	Use in an environment that has suitable humidity.	—
123		Run [ <b>Drum Refresh</b> ]	page 10-34
Printed images are skewed.	Are the originals placed correctly?	When placing originals on the platen, align them with the original size indicator plates.	page 5-2
ABC		When placing originals in the document processor, align the original width guides securely before placing the originals.	page 5-3
102	Is the paper loaded correctly?	Check the position of the paper width guides.	page 3-4
Irregular horizontal lines appear in the image.		Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [MC] and increase the adjustment value. Increase the adjustment value 1 level at a time from the current value. If there is no improvement after the value is increased by 1 level, increase by 1 level again. If there is still no improvement, return the setting to the original value.	_

Symptom	Checkpoints	Corrective Actions	Reference Page
The altitude is 1000 m or higher and irregular horizontal white lines appear in the image.	_	Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [Altitude Adjustment], and set to an elevation one level higher than the current setting.	_
The altitude is 1000 m or higher and dots appear in the image. $\dot{ABC}_{123}$		Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [Altitude Adjustment], and set to an elevation one level higher than the current setting.	_
Printouts have vertical lines.	Is the slit glass dirty?	Clean the slit glass.	page 10-3
ABC 123	_	Run [Laser Scanner Cleaning].	<u>page 10-34</u>
Dirt on the top edge or back of the paper. ABC 123	Is the interior of the machine dirty?	Clean the interior of the machine.	<u>page 10-4</u>
Part of the image is	—	Open and then close the rear cover.	
periodically faint or shows white lines.	<u> </u>	Run [Drum Refresh].	page 10-34
	_	Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [MC] and decrease the adjustment value. Decrease the adjustment value 1 level at a time from the current value. If there is no improvement after the value is decreased by 1 level, decrease by 1 level again. If there is still no improvement, return the setting to the original value.	_

Symptom	Checkpoints	Corrective Actions	Reference Page
The previous image remains and lightly printed.	-	Make sure the paper type setting is correct for the paper being used.	<u>page 8-15</u>
AB AB	_	Select the [System Menu/Counter] key > [Adjustment/Maintenance] > [Service Setting] > [MC] and increase the adjustment value. Increase the adjustment value 1 level at a time from the current value. If there is no improvement after the value is increased by 1 level, increase by 1 level again. If there is still no improvement, return the setting to the original value.	_

## **Color printing trouble**

When the following color printing trouble occurs, implement appropriate procedures.

Symptom	Checkpoints	Corrective Actions	Reference Page
Skewed-color printout.	_	Run [Calibration].	page 10-34
ABC	_	Run [Color Registration].	page 10-29
Colors appear different than you anticipated.	Did you choose appropriate image quality for the original?	Select appropriate image quality.	<u>page 6-19</u>
	Have you loaded color copy paper into the paper tray?	Load color copy paper into the paper tray.	_
	_	Run [Calibration].	page 10-34
	_	When making copies Adjust the color balance.	<u>page 6-21</u>
	_	When printing from a computer Adjust the color using the printer driver.	_
The color toner is empty.	Do you want to continue printing in black and white?	If the black toner is remained, the machine continues printing in black and white by selecting [ <b>Print in Black and White</b> ] of [ <b>Color Toner Empty Action</b> ].	<u>page 8-18</u>

## **Responding to Messages**

If the touch panel or the computer displays any of these messages, follow the corresponding procedure.

#### NOTE

When contacting us, the serial number will be necessary.

To check the serial number, refer to the following:

Checking the Equipment's Serial Number (page i)

#### Α

Message	Checkpoints	Corrective Actions	Reference Page
Access point was not detected.	_	Check if the access point has been set correctly.	—
Activation error.	_	Turn the power switch off and on. If the error exists, contact administrator.	<u>page 2-10</u>
Add the following paper in cassette #.	Is the indicated cassette out of paper?	Load paper. Select [ <b>Paper Selection</b> ] to select the other paper source. Select [ <b>Continue</b> ] to print on the paper in the currently selected paper source.	page 3-2
Add the following paper in the multipurpose tray.	Does the selected paper size matches the paper size loaded in the specified paper source?	Select [ <b>Continue</b> ] to continue printing. Select [ <b>Cancel</b> ] to cancel the job.	_
	Is the indicated cassette out of paper?	Load paper. Select [ <b>Paper Selection</b> ] to select the other paper source. Select [ <b>Continue</b> ] to print on the paper in the currently selected paper source.	page 3-2
Adjusting	_	The machine is under the adjustment to maintain its quality. Please wait.	_

Message	Checkpoints	Corrective Actions	Reference Page
Box is not found.	_	The specified box cannot be found. Job is canceled. Select [ <b>End</b> ].	_
Box limit exceeded. <sup>*1</sup>	Is [End] displayed on the screen?	The specified box is full, and no further storage is available; Job is canceled. Select [ <b>End</b> ]. Try to perform the job again after printing or deleting data from the box.	

\*1 When Auto Error Clear is set to [**On**], processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➡ Auto Error Clear (page 8-40)

	•	
C	÷	

Message	Checkpoints	Corrective Actions	Reference Page
Calibrating	_	The machine is under the adjustment to maintain its quality. Please wait.	page 10-34
Cannot connect to Authentication Server. <sup>*1</sup>	-	Set machine time to match the server's time.	page 2-23
	_	Check the domain name.	page 9-2
	—	Check the host name.	page 9-2
	_	Check the connection status with the server.	—
Cannot connect to Server.	_	Check the connection status with the server.	—
Cannot connect.	_	This appears when the Wi-Fi or Wi-Fi Direct connection did not complete. Check the settings, and check the signal conditions.	-
Cannot duplex print on the following paper. <sup>*1</sup>	Did you select a paper size/type that cannot be duplex printed?	Select [ <b>Paper Selection</b> ] to select the available paper. Select [ <b>Continue</b> ] to print without using Duplex function.	page 6-12

Message	Checkpoints	Corrective Actions	Reference Page
Cannot print the specified number of copies.*1   Copies.*1   Do you want to print the on in the USB memory?		<ul> <li>Only one copy is available. Select [Continue] to continue printing. Select [Cancel] to cancel the job.</li> <li>The machine may reproduce the same originals by arranging the following settings:</li> <li>Uncheck [RAM Disk] in the [Device Settings] tab of the printer's properties.</li> <li>NOTE</li> <li>If you unchecked the [RAM Disk],</li> </ul>	
		check the [ <b>RAM Disk</b> ] again after the printing is completed. If not, print speed may be reduced.	
	Do you want to print the data stored in the USB memory?	Only one copy is available. Select [ <b>Continue</b> ] to continue printing. Select [ <b>Cancel</b> ] to cancel the job.	
		The machine may reproduce the same originals by arranging the following settings:	
		Reduce the number of copies to be printed at once.	
		Furthermore, the machine may reproduce the same originals by arranging the following settings:	
		<ul> <li>Select [Copy Priority] of Optional Memory in System Menu.</li> </ul>	
		Before changing the Optional Memory setting, contact your administrator.	
Cannot process this job. <sup>*1</sup>	-	This job is canceled because it is restricted by User Authorization or Job Accounting. Select [ <b>End</b> ].	-
Cannot recognize.	_	Make sure your ID card has been registered.	Card Authentication Kit(B) Operation Guide
Cleaning the laser scanner	-	The machine is under the adjustment to maintain its quality. Please wait.	_

\*1 When Auto Error Clear is set to [**On**], processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➡ Auto Error Clear (page 8-40)

Message	Checkpoints	Corrective Actions	Reference Page
Failed to specify Job Accounting. <sup>*1</sup>	_	Failed to specify Job Accounting when processing the job externally. The job is canceled. Select [ <b>End</b> ].	_
Failed to store job retention data.		The job is canceled. Select [ <b>End</b> ]. Insufficient free space in the Job Box. Try to perform the job again after printing or deleting data from the Job Box.	_

\*1 When Auto Error Clear is set to [**On**], processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➡ Auto Error Clear (page 8-40)

#### Η

Message	Checkpoints	Corrective Actions	Reference Page
High temperature. Adjust room temp.	_	Adjust the temperature and the humidity of your room.	—

I

Message	Checkpoints	Corrective Actions	Reference Page
Incorrect account ID.*1	—	The account ID was incorrect when processing the job externally. The job is canceled. Select [ <b>End</b> ].	—
Incorrect box password.	_	The box password was incorrect when processing the job externally. The job is canceled. Select [ <b>End</b> ].	_
Incorrect Login User Name or Password. <sup>*1</sup>	_	The login user name or password was incorrect when processing the job externally. The job is canceled. Select [ <b>End</b> ].	_
Inner tray is full of paper.	_	Remove paper from the inner tray. Select [ <b>Continue</b> ] to resume printing. Select [ <b>Cancel</b> ] to cancel the job.	_

\*1 When Auto Error Clear is set to [**On**], processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➡ Auto Error Clear (page 8-40)

Message	Checkpoints	Corrective Actions	Reference Page
Job Accounting restriction exceeded.	Is the acceptable printing count restricted by Job Accounting exceeded?	The printing count exceeded the acceptable count restricted by Job Accounting. Cannot print any more. This job is canceled. Select [ <b>End</b> ].	_

Κ

Message	Checkpoints	Corrective Actions	Reference Page
KPDL error. <sup>*1</sup>	_	PostScript error has occurred. The job is canceled. Select [End].	

\*1 When Auto Error Clear is set to **[On]**, processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➡ Auto Error Clear (page 8-40)

L

Message	Checkpoints	Corrective Actions	Reference Page
Low temperature. Adjust room temp.	_	Adjust the temperature and the humidity of your room.	—

Μ

Message	Checkpoints	Corrective Actions	Reference Page
Machine failure.	_	Internal error has occurred. Make a note of the error code displayed on the screen, and contact your Service Representative.	_
Maximum number of scanned pages.	Is the acceptable scanning count exceeded?	Only one copy of the scanned pages is available. Select [ <b>Continue</b> ] to print, send or store the scanned pages. Select [ <b>Cancel</b> ] to cancel printing, sending or storing.	_
Memory card error.	—	An error has occurred on the memory card. Job is canceled. Select [ <b>End</b> ].	_
		The error cord is as follows. 04: Insufficient space on the memory card to complete this operation. Move data or delete unneeded data.	

Message	Checkpoints	Corrective Actions	Reference Page
Memory is full. <sup>*1</sup>	Do you want to send the scanned image to the PC, or store the image in the machine?	The process cannot be performed due to insufficient memory. If only [ <b>End</b> ] is available, select [ <b>End</b> ]. The job will be canceled.	<u>page 6-27</u>
		The machine may reproduce the same originals by arranging the following settings:	
		<ul> <li>Decrease [Image Quality] of [File Format].</li> </ul>	
		Furthermore, the machine may reproduce the same originals by arranging the following settings:	
		<ul> <li>Select [Normal] of Optional Memory in System Menu.</li> </ul>	
		Before changing the Optional Memory setting, contact your administrator.	
	Do you want to print data from the PC?	Unable to continue the job as the memory is used up. Select [ <b>Continue</b> ] to print the scanned pages. The print job cannot be processed completely. Select [ <b>Cancel</b> ] to cancel the job.	
		The machine may reproduce the same originals by arranging the following settings:	
		<ul> <li>Select [On] of RAM Disk Setting in System Menu, and then decrease the RAM disk size.</li> </ul>	
		Select [ <b>Printer Priority</b> ] of Optional Memory in System Menu.	
		Before changing the RAM Disk Setting or Optional Memory setting, contact your administrator.	

\*1 When Auto Error Clear is set to [**On**], processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

➡ Auto Error Clear (page 8-40)

Message	Checkpoints	Corrective Actions	Reference Page
Paper jam.	_	If a paper jam occurs, the machine will stop and the location of the jam will be indicated on the screen. Leave the machine on and follow the instruction to remove the jammed paper.	<u>page 10-35</u>
Preparing	_	The machine is under the adjustment to maintain its quality. Please wait.	—

Message	Checkpoints	Corrective Actions	Reference Page
RAM disk error.		An error has occurred on the RAM disk. Job is canceled. Select [ <b>End</b> ]. The error cord is as follows. 04: Insufficient space on the RAM disk. If the optional RAM disk is installed, increase the RAM disk size by changing RAM Disk Setting in System Menu. <b>NOTE</b> The range of RAM disk size can be increased by selecting [ <b>Printer</b> <b>Priority</b> ] in Optional Memory.	<u>page 8-37</u>
Removable memory error.	Is writing to a removable memory prohibited?	An error occurred in the removable memory. The job stopped. Select [End]. The error cord is as follows. 01: Connect a removable memory that can be written to.	_
		An error occurred in the removable memory. The job stopped. Select [End]. The error cord is as follows. 01: The amount of data that can be saved at once has been exceeded. Restart the system or turn the power OFF/ON. If the error still occurs, the removable memory is not compatible with the machine. Use the removable memory formatted by this machine. If the removable memory cannot be formatted, it is damaged. Connect a compatible removable memory.	

Message	Checkpoints	Corrective Actions	Reference Page
Removable Memory is full. <sup>*1</sup>	_	Job is canceled. Select [ <b>End</b> ]. Insufficient free space in the removable memory. Delete unnecessary files.	
Remove originals in the document processor.	Are there any originals left in the document processor?	Remove originals from the document processor.	_
Replace all originals and press [Continue].	_	Remove originals from the document processor, put them back in their original order, and place them again. Select [ <b>Continue</b> ] to resume printing. Select [ <b>Cancel</b> ] to cancel the job.	_
Running security function	_	Running security function. Please wait.	_

\*1 When Auto Error Clear is set to [**On**], processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

Auto Error Clear (page 8-40)
 Auto Error Clear (page 8

Message	Checkpoints	Corrective Actions	Reference Page
Scanner memory is full. <sup>*1</sup>		<ul> <li>Scanning cannot be performed due to insufficient memory of scanner. Only one copy of the scanned pages is available. Select</li> <li>[Continue] to print, send or store the scanned pages. Select [Cancel] to cancel the printing job.</li> <li>The machine may reproduce the same originals by arranging the following settings:</li> <li>Reduce the number of originals to be scanned at once. Furthermore, the machine may reproduce the same originals by arranging the following settings:</li> <li>Select [Copy Priority] of Optional Memory in System Menu.</li> <li>NOTE</li> <li>Before changing the Optional Memory setting, contact your administrator.</li> </ul>	
Scheduled sending jobs exceeded.		The number of jobs has exceeded the limit set for delayed transmission. Select [ <b>End</b> ]. The job is canceled. Wait until the delayed transmission is executed, or cancel the delayed transmission and then perform the job again.	

Message	Checkpoints	Corrective Actions	Reference Page
Send Error. <sup>*1</sup>	—	An error has occurred during transmission. The job is canceled. Select [ <b>End</b> ].	<u>page 10-26</u>
		Refer to Responding to Send Error for the error code and corrective actions.	
System error.	-	System error has occurred. Follow the instructions on the screen.	—

\*1 When Auto Error Clear is set to [**On**], processing resumes automatically after a set amount of time elapses. For details on Auto Error Clear, refer to the following:

Auto Error Clear (page 8-40)
 Auto Error Clear (page 8

Т

Message	Checkpoints	Corrective Actions	Reference Page
The cover is open.	Is there any cover which is open?	Close the cover indicated on the screen.	—
	Are the toner containers installed correctly? Is a toner container out of place?	Make sure all four colors of toner containers are installed correctly, and close the right cover.	page 10-5
The device cannot be connected because allowed connections would be exceeded.	_	Cancel a connection to a portable device that is not being used, or set the machine's auto disconnect time to break portable device connections.	_
The manufacturer assumes no responsibility for damage caused by a non-genuine toner.	Is the installed toner container our own brand?	We will not be liable for any damage caused by the use of third party supplies in this machine. If you want to continue, select [ <b>Next</b> ].	_
The phone receiver is off the hook.	_	Put down the receiver.	—
The slit glass requires cleaning.	_	Clean the slit glass.	page 10-3
This memory is not formatted. This will be formatted.	Is the removable memory formatted by this machine?	Perform [Format] on this machine.	_
Are you sure?			
This user account is locked out.	-	Contact administrator. Job is canceled. Select [ <b>End</b> ].	_

Message	Checkpoints	Corrective Actions	Reference Page
Toner [C][M][Y][K] are empty.		Replace the toner container to our specified toner container. Replace the toner container.           NOTE           If the color toner is empty but the black toner is remained, the machine continues printing in black and white by selecting [Print in Black and White] of Color Toner Empty Action.	<u>page 10-5</u>
Toner is low. [C][M][Y][K] (Replace when empty.)	_	It is almost time to replace the toner container. Obtain a new toner container.	_

### U

Message	Checkpoints	Corrective Actions	Reference Page
Unknown toner installed.	Is the installed toner container our own brand?	We will not be liable for any damage caused by the use of third party supplies in this machine.	_
Unknown Toner Installed. PC [C][M][Y][K]	Does the installed toner container's regional specification match the machine's?	Install the specified container.	—

Message	Checkpoints	Corrective Actions	Reference Page
Warning low memory.	_	Cannot start the job. Try again later.	—

Υ

Message	Checkpoints	Corrective Actions	Reference Page
You cannot use this box.	_	You cannot use the specified box. Job is canceled. Select [End].	_

## **Responding to Send Error**

Error Code	Message	Corrective Actions	Reference Page
1101	Failed to send the e-mail.	Check the host name of the SMTP server on the Command Center RX.	page 2-58
	Failed to send via FTP.	Check the host name of FTP.	page 5-23
	Failed to send via SMB.	Check the host name of SMB.	page 5-20
1102	Failed to send via SMB.	<ul><li>Check the SMB settings.</li><li>Login user name and login password</li></ul>	page 5-20
		<ul> <li>NOTE</li> <li>If the sender is a domain user, specify the domain name.</li> <li>Host name</li> <li>Path</li> </ul>	
	Failed to send the e-mail.	<ul> <li>Check the following on the Command Center RX.</li> <li>SMTP login user name and login password</li> <li>POP3 login user name and login password</li> <li>E-mail size limit</li> </ul>	page 2-58
	Failed to send via FTP.	<ul> <li>Check the FTP settings.</li> <li>Login user name and login password</li> <li>NOTE</li> <li>If the sender is a domain user, specify the domain name.</li> <li>Path</li> </ul>	page 5-23
		Folder share permissions of the recipient	
1103	Failed to send via SMB.	Check the SMB settings. <ul> <li>Login user name and login password</li> </ul>	page 5-20
		<b>NOTE</b> If the sender is a domain user, specify the domain name.	
		<ul><li>Path</li><li>Folder share permissions of the recipient</li></ul>	
	Failed to send via FTP.	<ul><li>Check the FTP settings.</li><li>Path</li><li>Folder share permissions of the recipient</li></ul>	page 5-23
1104	Failed to send the e-mail.	Check the e-mail address.	page 5-18
		<b>NOTE</b> If the address is rejected by the domain, you cannot send the email.	

Error Code	Message	Corrective Actions	Reference Page
1105	Failed to send via SMB.	Select [ <b>On</b> ] of the SMB settings on the Command Center RX.	page 2-52
	Failed to send the e-mail.	Select [ <b>On</b> ] of the SMTP settings on the Command Center RX.	page 2-58
	Failed to send via FTP.	Select [ <b>On</b> ] of the FTP settings on the Command Center RX.	page 2-52
1106	Failed to send the e-mail.	Check the sender address of SMTP on the Command Center RX.	page 2-58
1131	Failed to send via FTP.	Select [ <b>On</b> ] of the secure protocol settings on the Command Center RX.	page 8-35
1132	Failed to send the e-mail.	<ul><li>Check the following of the SMTP server.</li><li>Is SMTP over SSL available?</li><li>Is the encryption available?</li></ul>	Refer to the Command Center RX User Guide.
	Failed to send via FTP.	<ul><li>Check the following of the FTP server.</li><li>Is FTPS available?</li><li>Is the encryption available?</li></ul>	_
2101	Failed to send via SMB.	<ul> <li>Check the network and SMB settings.</li> <li>The network cable is connected.</li> <li>The hub is not operating properly.</li> <li>The server is not operating properly.</li> <li>Host name and IP address</li> <li>Port number</li> </ul>	_
	Failed to send via FTP.	<ul> <li>Check the network and FTP settings.</li> <li>The network cable is connected.</li> <li>The hub is not operating properly.</li> <li>The server is not operating properly.</li> <li>Host name and IP address</li> <li>Port number</li> </ul>	
	Failed to send the e-mail.	<ul> <li>Check the network and Command Center RX.</li> <li>The network cable is connected.</li> <li>The hub is not operating properly.</li> <li>The server is not operating properly.</li> <li>POP3 server name of the POP3 user</li> <li>SMTP server name</li> </ul>	<u>page 2-58</u>

Error Code	Message	Corrective Actions	Reference Page
2102 2103	Failed to send via FTP.	<ul><li>Check the network.</li><li>The network cable is connected.</li><li>The hub is not operating properly.</li><li>The server is not operating properly.</li></ul>	_
		<ul><li>Check the following of the FTP server.</li><li>Is FTP available?</li><li>The server is not operating properly.</li></ul>	_
	Failed to send the e-mail.	<ul><li>Check the network.</li><li>The network cable is connected.</li><li>The hub is not operating properly.</li><li>The server is not operating properly.</li></ul>	_
2201 2202 2203 2231	Failed to send the e-mail. Failed to send via FTP. Failed to send via SMB.	<ul><li>Check the network.</li><li>The network cable is connected.</li><li>The hub is not operating properly.</li><li>The server is not operating properly.</li></ul>	_
2204	Failed to send the e-mail.	Check the e-mail size limit of the SMTP settings on the Command Center RX.	page 2-58
3101	Failed to send the e-mail.	Check the authentication methods of both the sender and the recipient.	_
	Failed to send via FTP.	<ul><li>Check the network.</li><li>The network cable is connected.</li><li>The hub is not operating properly.</li><li>The server is not operating properly.</li></ul>	_
3201	Failed to send the e-mail.	Check the SMTP user authentication method of the recipient.	_
0007 4201 4701 5101 5102 5103 5104 7101 7102 7103		Turn the power switch off and back on. If this error occurs several times, make a note of the displayed error code and contact your service representative.	page 2-10
720f 9181	_	The scanned original exceeds the acceptable number of pages of 999. Send the excess pages separately.	

# **Adjustment/Maintenance**

# **Overview of Adjustment/Maintenance**

If there is an image problem and the message to run adjustment or maintenance menu appears, run Adjustment/Maintenance in the system menu.


The table below lists the item you can Procedure.

Item	Description	Reference Page
Color Registration Procedure	Correct the color position to resolve color drift.	<u>page 10-29</u>
Drum Refresh	Remove image blur and white dots from the printout.	page 10-34
Calibration	Adjust color drift or hue of printed image in the most appropriate color.	page 10-34
Laser Scanner Cleaning	Remove vertical white lines from the printout.	page 10-34

# **Color Registration Procedure**

When first installing the machine or moving it to a new location, color drift during printing may occur. Use this function to correct the color position of each of cyan, magenta and yellow to resolve color drift.


Auto registration and manual registration are available for Color Registration. Color drift can be largely corrected through auto registration. However, if it is not resolved or to perform more detailed settings, use the manual registration.



Before performing color registration, be sure to perform Calibration. If color drift remains, perform color registration. By performing color registration without performing Calibration, the color drift will be resolved once, however, it may cause the serious color drift later.

→ <u>Calibration (page 10-34)</u>

### **Auto Correction**



#### **IMPORTANT**


- Load the paper with the print side facing up.
- After removing new paper from its packaging, fan the paper before loading it in the multipurpose tray.
- Precaution for Loading Paper (page 3-2)
- Before loading the paper, be sure that it is not curled or folded. Paper that is curled or folded may cause paper jams.
- Ensure that the loaded paper does not exceed the level indicator (see illustration above).
- If paper is loaded without adjusting the paper length guide and paper width guide, the paper may skew or become jammed.

### **2** Display the screen.

[System Menu/Counter] key > [Adjustment/Maintenance] > [Color Registration] > [Auto]

#### **?** Print the chart.

Select [**Start**]. A chart is printed.




#### **Chart Example**

# 4


### Perform the color registration.

1 As shown in the illustration, place the printed side down on the platen with the edge with the arrows toward the back.



- 2 Select [Start] to scan the chart.When scanning is finished, color printing position correction starts.
- 3 When color printing position correction ends, Select [OK].

### Manual Correction



#### **IMPORTANT**

- Load the paper with the print side facing up.
- After removing new paper from its packaging, fan the paper before loading it in the multipurpose tray.
- Precaution for Loading Paper (page 3-2)
- Before loading the paper, be sure that it is not curled or folded. Paper that is curled or folded may cause paper jams.
- Ensure that the loaded paper does not exceed the level indicator (see illustration above).
- If paper is loaded without adjusting the paper length guide and paper width guide, the paper may skew or become jammed.

### **2** Display the screen.


[System Menu/Counter] key > [Adjustment/Maintenance] > [Color Registration] > [Manual]

### **3** Print the chart.

Select [Print Chart].


A chart is printed. On the chart, for each of M (magenta), C (cyan) and Y (yellow), charts for H-1 to 5 and V-1 to 5 are printed.

#### **Chart Example**



### **<u>1</u>** Enter the appropriate value.

1 Find the location on each chart where 2 lines most closely match. If this is the 0 position, registration for that color is not required. For the illustration, B is the appropriate value.



From charts H-1 to H-5, read the values from H-1 to H-5.

From charts V-1 to V-5, read only the values from V-3 (center).

#### 2 [Detail] > [Registration]

- 3 Select the chart to be corrected.
- **4** Select [+] or [-] to enter the values read from the chart.

Select [+] to increase the value from 0 to 9. To decrease, select [-].

By selecting [-], the value changes from 0 to alphabetic letters, going from A to I. To move in the reverse direction, select [+].

You cannot use the numeric keys to enter these values.

- **5** Repeat steps 3 and 4 to enter the registration values for each chart.
- 6 Select [Start] after all values have been entered. Color registration begins.
- 7 Select [OK] after color registration is complete.

# **Drum Refresh**

Remove image blur and white dots from the printout.

### ΝΟΤΕ

Drum Refresh cannot be performed while printing. Execute Drum Refresh after the printing is done.

### **1** Display the screen.

[System Menu/Counter] key > [Adjustment/Maintenance] > [Drum Refresh]



#### Perform the drum refresh.

Select [Start]. "Drum Refresh" begins.

# **Calibration**

Using this function enables printing in the most appropriate color by adjusting hue and color drift in detail.

### 1 Display the screen.

[System Menu/Counter] key > [Adjustment/Maintenance] > [Calibration]



### Perform the calibration.

Select [Start]. "Calibration" begins.

#### 💽 NOTE

When the hue and color drift are not enhanced even after performing calibration, refer to the following:

Color Registration Procedure (page 10-29)

# **Laser Scanner Cleaning**

Remove vertical white lines from the printout.

#### 1 Display the screen.

[System Menu/Counter] key > [Adjustment/Maintenance] > [Laser Scanner Cleaning]



#### Perform the laser scanner cleaning.

Select [Start]. "Laser Scanner Cleaning" begins.

# **Clearing Paper Jams**

If a paper jam occurs, the touch panel will display "Paper Jam." and the machine will stop. Refer to these procedures to remove the jammed paper.

# **Jam Location Indicators**


Next >] to follow ructions.	1/3 <b>3</b> Next >
	10:10
	1/5

- 1 Shows the location of a paper jam.
- 2 Shows the previous step.
- 3 Shows the next step.
- 4 Shows the removal procedure.
- 5 Selecting [Status/Job Cancel] key displays [Hold]. Selecting [Hold] displays status screen, and the status of jobs can be checked.
- 6 Select [**Display Error**] to return to the paper jam guidance.

0

0

If a paper jam occurs, the location of the jam will be displayed on the touch panel as well as the clearing instructions.



Paper Jam Location Indicator	Paper Jam Location	Reference Page
А	Cassette 1	page 10-36
В	Cassette 2	page 10-36
C	Multipurpose Tray	page 10-39
D	Document Processor	page 10-45
E	Duplex Unit	page 10-42
F	Rear Cover 1	page 10-42

After you remove the jam, the machine will warm up again and the error message will be cleared. The machine resumes with the page that was printing when the jam occurred.

# **Remove any jammed paper in Cassette 1**




• Do not reuse jammed papers.


1

• If the paper tears during removal, be sure to remove any loose scraps of paper from inside the machine. Scraps of paper left in the machine could cause subsequent jamming.


Pull Cassette 1 out toward you until it stops.







**3** Push Cassette 1 back in.




# **Remove any jammed paper in Cassette 2**




- Do not reuse jammed papers.
- If the paper tears during removal, be sure to remove any loose scraps of paper from inside the machine. Scraps of paper left in the machine could cause subsequent jamming.


**1** Open Rear Cover 2.




**2** Remove any jammed paper.



**3** Push Rear Cover 2.





0


0

# **Remove any jammed paper in the Multipurpose Tray**




- Do not reuse jammed papers.
- If the paper tears during removal, be sure to remove any loose scraps of paper from inside the machine. Scraps of paper left in the machine could cause subsequent jamming.


**1** Remove any jammed paper.



**2** Remove all the paper.




- 3
- Push the multipurpose tray.







Pull Cassette 1 out toward you until it stops.




### **5** Open Feed Cover.






**6** Remove any jammed paper.



**7** Push Feed Cover back in.











**9** Open the multipurpose tray.




# **10** Reload the paper.



# **Remove any jammed paper in Rear Cover 1**




The fixing unit is extremely hot. Take sufficient care when working in this area, as there is a danger of getting burned.







2













Remove any jammed paper.








# **Remove any jammed paper in the Document Processor**

# 


- Do not reuse jammed papers.
- If the paper tears during removal, be sure to remove any loose scraps of paper from inside the machine. Scraps of paper left in the machine could cause subsequent jamming.









Open the front cover and remove any jammed paper.



**3** Remove originals inside the document processor.





# **11** Appendix


#### This chapter explains the following topics:

Overview of Optional Equipment11-2Optional Applications11-2Starting Application Use11-2Checking Details of Application11-2Character Entry Method11-2Entry Screens11-1Entering Characters11-1Paper11-1Basic Paper Specifications11-1Choosing the Appropriate Paper11-1Special Paper11-1Specifications11-1Copy Functions11-2Printer Functions11-2Scanner Functions11-2Scanner Functions11-2Glossary11-2	Optional Equipment	
Optional Applications11-6Starting Application Use11-6Checking Details of Application11-7Character Entry Method11-8Entry Screens11-16Entering Characters11-17Paper11-17Basic Paper Specifications11-17Choosing the Appropriate Paper11-11Special Paper11-11Specifications11-12Machine11-12Printer Functions11-22Printer Functions11-22Document Processor11-22Paper Feeder11-22Paper Feeder11-22	Overview of Optional Equipment	
Checking Details of Application       11-1         Character Entry Method       11-4         Entry Screens       11-1         Entering Characters       11-10         Paper       11-11         Basic Paper Specifications       11-11         Choosing the Appropriate Paper       11-11         Special Paper       11-12         Specifications       11-12         Machine       11-12         Printer Functions       11-22         Printer Functions       11-22         Document Processor       11-22         Paper Feeder       11-22		
Character Entry Method       11-4         Entry Screens       11-1         Entering Characters       11-10         Paper       11-11         Basic Paper Specifications       11-11         Choosing the Appropriate Paper       11-12         Special Paper       11-12         Specifications       11-12         Machine       11-12         Copy Functions       11-22         Printer Functions       11-22         Scanner Functions       11-22         Document Processor       11-22         Paper Feeder       11-22	Starting Application Use	
Character Entry Method       11-4         Entry Screens       11-4         Entering Characters       11-10         Paper       11-11         Basic Paper Specifications       11-11         Choosing the Appropriate Paper       11-12         Special Paper       11-12         Specifications       11-12         Machine       11-12         Copy Functions       11-22         Printer Functions       11-22         Scanner Functions       11-22         Document Processor       11-22         Paper Feeder       11-22	Checking Details of Application	
Entry Screens11-4Entering Characters11-10Paper11-11Basic Paper Specifications11-11Choosing the Appropriate Paper11-12Special Paper11-14Specifications11-15Machine11-16Copy Functions11-12Printer Functions11-22Scanner Functions11-22Document Processor11-22Paper Feeder11-22Paper Feeder11-22	- · · ·	
Entering Characters11-10Paper11-11Basic Paper Specifications11-12Choosing the Appropriate Paper11-12Special Paper11-12Specifications11-12Machine11-12Copy Functions11-22Printer Functions11-22Scanner Functions11-22Document Processor11-22Paper Feeder11-22		
Basic Paper Specifications       11-11         Choosing the Appropriate Paper       11-12         Special Paper       11-12         Specifications       11-12         Machine       11-12         Copy Functions       11-22         Printer Functions       11-22         Scanner Functions       11-22         Document Processor       11-22         Paper Feeder       11-22	-	
Basic Paper Specifications       11-11         Choosing the Appropriate Paper       11-12         Special Paper       11-12         Specifications       11-12         Machine       11-12         Copy Functions       11-22         Printer Functions       11-22         Scanner Functions       11-22         Document Processor       11-22         Paper Feeder       11-22	Paper	11-11
Choosing the Appropriate Paper11-12Special Paper11-12Specifications11-19Machine11-19Copy Functions11-20Printer Functions11-22Scanner Functions11-22Document Processor11-22Paper Feeder11-22	•	
Special Paper       11-19         Specifications       11-19         Machine       11-19         Copy Functions       11-20         Printer Functions       11-21         Scanner Functions       11-22         Document Processor       11-22         Paper Feeder       11-22		
Specifications       11-19         Machine       11-19         Copy Functions       11-27         Printer Functions       11-27         Scanner Functions       11-27         Document Processor       11-27         Paper Feeder       11-27		
Copy Functions11-2Printer Functions11-2Scanner Functions11-2Document Processor11-2Paper Feeder11-2		
Copy Functions11-2Printer Functions11-2Scanner Functions11-2Document Processor11-2Paper Feeder11-2	Machine	
Printer Functions       11-2         Scanner Functions       11-2         Document Processor       11-2         Paper Feeder       11-2		
Document Processor		
Paper Feeder	Scanner Functions	
	Document Processor	
	Paper Feeder	
••••••		

# **Optional Equipment**

# **Overview of Optional Equipment**


The following optional equipment is available for the machine.



### (1) "Expansion Memory"

The machine can perform the more multiple jobs simultaneously by adding more memories. You can increase the machine's memory up to 1,536 MB by plugging in the optional memory modules.


#### **Precautions for Handling the Memory Modules**




To protect electronic parts, discharge static electricity from your body by wearing an antistatic wrist strap, if possible, when you install the memory modules. If you do not have a wristband, touch a metal object to discharge static electricity before inserting the memory.

#### Installing the Memory Modules

- 1 Turn off the machine and disconnect the power cord and interface cable.
- 2 Remove the covers.



- 3 Remove the memory module from its package.
- 4 With the memory connection terminal pointing toward the socket, align the cut-out part with the socket terminal and insert directly in at an angle.



- **5** Carefully press the inserted memory down and into the machine.
- 6 Reinstall the covers.

### (2) PF-5110 "Paper Feeder"

The paper feeder can be installed in the printer.

#### Loading in the Cassette 2 (page 3-7)

#### (3) Card Authentication Kit(B) "Card Authentication Kit"

User login administration can be performed using ID cards. To do so, it is necessary to register ID card information on the previously registered local user list. For more information about how to register this information, refer to the following:

#### Card Authentication Kit(B) Operation Guide

#### (4) UG-33 "ThinPrint Option"

This application allows print data to be printed directly without a print driver.

#### (5) "SD/SDHC Memory Card"

An SD/SDHC memory card is useful for storing fonts, macros, and overlays. The machine is equipped with a slot for an SDHC memory card with a maximum size of 32 GB, and an SD memory card with a maximum size of 2 GB.

#### **IMPORTANT**

Unencrypted data is saved on the SD/SDHC memory card. Exercise caution when saving sensitive documents.


#### Reading the SD/SDHC Memory Card

Once inserted in the machine's slot, the contents of the SD/SDHC memory card can be read from the operation panel or automatically when you power on or reset the machine.


#### Installing and Formatting the SD/SDHC Memory Card

To use an unused SD/SDHC memory card, you must first use the machine to format the SD/SDHC memory card.


- 1 Power off the machine and unplug the power cord.
- 2 Remove the cover.



3 Insert the SD/SDHC memory card into the SD/SDHC memory card slot.



4 Replace the covers.



### (6) USB Keyboard "USB Keyboard"

A USB keyboard can be used to enter information into the text fields on the operation panel. A special mount is also available to install the keyboard on the machine. Please contact your dealer or service representative for information on keyboards that are compatible with your machine before you purchase one.

# **Optional Applications**

The applications listed below are installed on this machine.

	Application
Card Authentication Kit	
ThinPrint Option <sup>*1</sup>	

#### \*1 This can be used on a trial basis for a limited time.

### 💽 ΝΟΤΕ

- Restrictions such as the number of times the application can be used during the trial period differ depending on the application.
- If you change the date/time while using the trial version of an application, you will no longer be able to use the application.

# **Starting Application Use**

# 1

# [System Menu/Counter] key > [System/Network] > [Optional Function]

#### 💽 ΝΟΤΕ

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

### **2** S

### Select the desired application and select [Activate].

You can view detailed information on the selected application by selecting [ \_\_\_].

### **3** Select [Official] and enter a license key.

Some applications do not require you to enter a license key. If the license key entry screen does not appear, go to Step 4.

To use the application as a trial, select [Trial] without entering the license key.

### **Select [Yes] in the confirmation screen.**

### 💽 ΝΟΤΕ

• If you started the Thin Print option and entered the license key, turn the power OFF/ON.

· Icons of activated application are displayed in the Home screen.

# **Checking Details of Application**

1

# [System Menu/Counter] key > [System/Network] > [Optional Function]

#### 

If the user authentication screen appears, enter your login user name and login password and select [**Login**]. For this, you need to login with administrator privileges. The factory default login user name and login password are set as shown below.

Login User Name: 2600

Login Password: 2600

### 2

### Select the desired application and select [\_\_].

You can view detailed information on the selected application.

The table below lists the item you can view.

Item
Function Name
License
Remaining Counts
Expiration Date
Status

#### Extend the trial period.

[Extend] > [Yes]

The trial period is extended.

# **Character Entry Method**

To enter characters for a name, use the on-display keyboard in the touch panel following the steps as explained below.

### 

#### **Keyboard Layout**

"QWERTY", "QWERTZ" and "AZERTY" are available as keyboard layouts the same as a PC keyboard. Select the [System Menu/Counter] key, [Common Settings] and then [Keyboard Layout] to choose the desired layout. "QWERTY" layout is used here as an example. You may use another layout following the same steps.

# **Entry Screens**

#### Lower-case Letter Entry Screen



No.	Display/Key	Description
1	Display	Displays entered characters.
2	Keyboard	Select the character to enter.
3	[Cancel]	Select to cancel entered characters and return to the screen before the entry was made.
4	[< Back]	Select to return to the previous screen.
5	[OK] / [Next >]	Select to save the entered characters and move to the next screen.
6	Enter Key	Select to enter a line break.
7	Space Key	Select to insert a space.
8	Delete Key	Select to delete a character to the left of the cursor.
9	[ <b>Input</b> ] / [ <b>Limit</b> ] Display	Displays maximum number of characters and the number of characters entered.
10	Cursor Key	Select to move the cursor on the display.
11	[ <b>A</b> /a] / [A/a]	Select to switch between upper case and lower case.
12	[ABC] / [Symbol]	Select the characters that are entered. To enter symbols or numbers, select [ <b>Symbol</b> ].

### Upper-case Letter Entry Screen

В							Input: 2 Limit: 3		10
		A	BC	A/a	100				Del.
Q	w	Е	R	Т	Y	U	I	0	Ρ
Α	S	D	F	G	H.	J	к	L	1
- 1	Z	Х	С	٧	В	N	М	~	1.84
-	Z	Х	-	V	-	N < Back	м	~ Next	

# Number/Symbol Entry Screen

3							Input: Limit:	3 32	12	
		Sy	mbol	17.1	1000		10.00		Del.	
1	2	3	4	5	6	7	8	9	0	
ſ	•	#	\$	%	&	$\left[ \cdot \right]$	ĨF	)	*	- 1
+	,	-		1	-	1	X			
			(	Cancel	1	< Back		Next >	-	


No.	Display/Key	Description
13	[^]/[\/]	To enter a number or symbol not shown in the keyboard, select the cursor key and scroll the screen to view other numbers or symbols to enter.

### **Entering Characters**

1

Follow the steps below to enter 'List A-1' for an example.

#### Enter 'List', (space).



To shift from lower case to upper case letters, select [A/a]. To shift from upper case to lower case letters, select [A/a].

#### **2** Enter 'A-1'.

Add - M	lame								-	Add -									
List A							Input: Limit: 3		-	List A	·1						Input: Limit:	8 32	10
		A	BC	A/a	126.00	1.1			Del.		<b>,</b> )	Sy	mbol	101			10.0		
1	w	Е	R	Т	Υ	U	I	0	Р	1	2	3	4	5	6	7	8	9	0
A	s	D	F	G	H	J	к	L.	-	10	-	#	\$	%	&	1	(	)	*
-	Z	X	С	V	В	N	м	~	er.	+	3	-		1	a sector	i tek	~		1
			(	Cancel	T	< Back	T	Next >	44	1000	d d	21	(	Cancel	T	< Back	T	Next >	

To enter numbers or symbols, select [ABC] to display [Symbol].

#### **3** Register the characters you entered.

_ist A-	1	Sy	mbol	i.			Input: Limit:	8 32		
1	2	3	4	5	6	7	8	9	0	
1		#	\$	%	&		(	)	*	
+	,	-		1		+1	$\sim$		$\sim$	
10114	8 3	1	(	Cancel	T	< Back	Γ	Next >	4	

Select [Next>]. The entered characters are registered.

# Paper

This section explains the paper sizes and types that can be used in the paper source.

For details on the sizes, types, and number of sheets of paper that can be loaded in each paper tray, refer to the following:

➡ Specifications (page 11-19)

### **Basic Paper Specifications**

This machine is designed to print on standard copy paper as used in regular ('dry') copiers and page printers such as laser printers. It also supports a variety of other types of paper that conform to the specifications given in this appendix.

Be careful when choosing paper. Paper unsuitable for the machine may cause jams or may be wrinkled.

#### **Supported Paper**

Use standard copy paper for regular copiers or laser printers. The printing quality will be affected by the quality of paper. Poor quality paper may result in unsatisfactory output.

#### Basic Paper Specifications that can be Used with This Machine

The following table lists the specifications of paper that is supported with this machine. Refer to the subsequent sections for further details.

Criteria	Specifications
Weight	Cassettes: 60 to 163 g/m <sup>2</sup>
	Multi purpose tray: 60 to 220 g/m <sup>2</sup> , 230 g/m <sup>2</sup> (Cardstock)
Dimensional accuracy	±0.7 mm
Squareness of corners	90° ±0.2°
Moisture content	4 to 6%
Pulp content	80% or more

#### 阈 ΝΟΤΕ

Some recycled paper does not meet requirements for use with this machine as listed in the Basic Paper Specifications shown below, such as moisture or pulp content. For this reason, we recommend purchasing a small amount of recycled paper as a sample for testing prior to use. Choose recycled paper that gives the best printing results and contains low levels of paper dust.

We are not responsible for the problems occurred from the use of paper that does not conform to our specifications.

### **Choosing the Appropriate Paper**

This section describes guidelines for choosing paper.

#### Condition

Avoid using paper with bent corners or that is curled, dirty, or torn. Do not use paper that has a rough surface or paper fiber lint, or that is especially delicate. Use of paper in any of these conditions will not only deliver poor copies but may also cause jams and shorten the useful life of the machine. Choose paper with a smooth and even surface; however, avoid coated paper or paper with a treated surface as it may damage the drum or fusing unit.

#### Ingredients

Do not use paper such as paper that has been coated or surface-treated or paper that contains plastic or carbon. Those types of paper may produce harmful fumes from the heat of printing and may damage the drum.

Be sure to use the standard paper that contains at least 80% pulp, i.e., not more than 20% of the total paper content consists of cotton or other fibers.

#### **Smoothness**

The paper surface should be smooth, but it must be uncoated. With paper that is too smooth and slippery, several sheets may accidentally be supplied at once, causing jams.

#### **Basis Weight**

In countries that use the metric system, basis weight is the weight in grams of one sheet of paper one square meter in area. In the United States, basis weight is the weight in pounds of one ream (500 sheets) of paper cut to the standard size (or trade size) for a specific grade of paper. Paper that is too heavy or too light may be supplied incorrectly or cause paper jams, which may cause excessive wear of the machine. Mixed paper weight (i.e., thickness) may cause several sheets to be supplied at once accidentally and may also cause blurring or other printing problems if the toner fails to adhere correctly.

#### **Moisture Content**

Paper moisture content is the ratio of moisture to dryness expressed as a percentage. Moisture affects how the paper is supplied, the electrostatic chargeability of the paper, and how the toner adheres.

Paper moisture content varies depending on the relative humidity in the room. High relative humidity causes paper to become damp, making the edges expand so it appears wavy. Low relative humidity causes paper to lose moisture, making the edges tighten and weakening print contrast.

Wavy or tight edges may cause the paper to slip when it is supplied. Try to keep the moisture content between 4 to 6%.

To maintain the right level of moisture content, bear in mind the following considerations.

- Store paper in a cool, well-ventilated place.
- Store paper flat and unopened in the package. Once the package is opened, reseal it if the paper is not to be used for a while.
- Store paper sealed in the original package and box. Put a pallet under the carton to keep it raised above the floor. Especially during rainy seasons keep the paper a sufficient distance away from wooden or concrete floors.
- Before using paper that has been stored, keep it at the proper moisture level for at least 48 hours.
- Do not store paper where it is exposed to heat, sunlight, or dampness.

#### Other Paper Specifications

Porosity: The density of the paper fibers.

Stiffness: Paper must be stiff enough or it may buckle in the machine, causing jams.

**Curl**: Most paper naturally tends to curl after the package is opened. When paper passes through the fixing unit, it curls upward slightly. To deliver flat printouts, load the paper so that the curl faces towards the bottom of the paper tray.

**Static electricity**: During printing, paper is electrostatically charged so that the toner adheres. Choose paper that can be discharged quickly so that copies do not cling together.

Whiteness: Paper whiteness affects print contrast. Use whiter paper for sharper, brighter copies.

**Quality**: Machine problems may occur if sheet sizes are not uniform or if corners are not square, edges are rough, sheets are uncut, or edges or corners are crushed. In order to prevent these problems, be especially careful when you cut the paper yourself.

**Packaging**: Choose paper that is properly packaged and stacked in boxes. Ideally, the packaging itself should have been treated with a coating to inhibit moisture.

**Specially treated paper**: We do not recommend printing onto the following types of paper, even if it conforms to the basic specifications. When you use these kinds of paper, purchase a small amount first as a sample to test.

- · Glossy paper
- · Watermarked paper
- Paper with an uneven surface
- · Perforated paper

#### Paper Sizes that can be Used with This Machine

Paper of the following sizes is supported by the machine.

Measurements in the table take into account a  $\pm 0.7$  mm dimensional accuracy for length and width. Corner angles must be 90°  $\pm$  0.2°.

#### Multipurpose Tray

- Hagaki (Cardstock) (100 × 148 mm)
- Oufuku hagaki (Return postcard) (148 × 200 mm)
- Envelope Monarch (3-7/8 × 7-1/2")
- Envelope #10 (4-1/8 × 9-1/2")
- Envelope DL (110 × 220 mm)
- Envelope C5 (162 × 229 mm)
- Envelope #9 (3-7/8 × 8-7/8")
- Envelope #6 3/4 (3-5/8 × 6-1/2")
- Statement
- Youkei 4 (105 × 235 mm)
- Youkei 2 (114 × 162 mm)
- Custom (70 × 148 to 216 × 356 mm)

#### **Cassettes or Multipurpose Tray**

- Executive (7-1/4 × 10-1/2")
- Letter
- Legal
- A4 (297 × 210 mm)
- B5 (257 × 182 mm)
- A5-R (148 × 210 mm)
- A5 (210 × 148 mm)
- A6 (148 × 105 mm)
- B6 (182 × 128 mm)
- B5(ISO) (176 × 250 mm)
- Oficio II
- 216 × 340 mm
- 16K (273 × 197 mm)
- Statement-R
- Folio (210 × 330 mm)
- Custom (Cassette: 105 × 148 to 216 × 356 mm, Multipurpose Tray: 70 × 148 to 216 × 356 mm)

### **Special Paper**

This section describes printing onto special paper and print media.

#### Special Paper that can be Used with This Machine

- Transparencies
- Preprinted paper
- Bond paper
- Recycled paper
- Thin paper
- Letterhead
- Colored paper
- Prepunched paper
- Envelopes
- Hagaki (Cardstock)
- Thick paper
- Labels
- Coated
- High-quality paper

When using these paper and media, choose those that are designed specifically for copiers or page printers (such as laser printers). Use the multipurpose tray for transparencies, thin paper, envelopes, cardstocks, label paper and coated.

#### **Choosing Special Paper**

Although special paper that meets the following requirements can be used with the machine, print quality will vary considerably due to differences in the construction and quality of special paper. Thus, special paper is more likely than regular paper to cause printing problems. Before purchasing special paper in volume, try testing a sample to ensure the print quality is satisfactory. General precautions when printing onto special paper are given below. Note that we are not responsible for any harm to the user or damage to the machine caused by moisture or specifications of special paper.

Select a cassette or multipurpose tray for special paper.

#### Transparencies

Transparencies must be able to withstand the heat of printing. Transparencies must meet the following conditions.

Heat resistance         Must withstand at least 190°C	
Thickness         0.100 to 0.110 mm	
Material	Polyester
Dimensional accuracy	±0.7 mm
Squareness of corners	90° ±0.2°

To avoid problems, use the multipurpose tray for transparencies and load transparencies with the long side facing the machine.


If transparencies jam frequently at output, try pulling the leading edge of sheets gently as they are ejected.

#### Label

Be sure to feed labels from the multipurpose tray.

For selecting labels, use extreme care so that the adhesive may not come in direct contact with any part of the machine and that the labels are not easily peeled from the carrier sheet. Adhesives that stick to the drum or rollers and peeled labels remaining in the machine may cause a failure.


When printing onto labels, you must be liable for the print quality and possible trouble.



Labels consist of three layers as shown in the illustration. The adhesive layer contains materials that are easily affected by the force applied in the machine. The carrier sheet bears the top sheet until the label is used. This composition of labels may cause more problems.

The label surface must be covered completely with the top sheet. Gaps between labels may cause peeling of labels, resulting in a serious failure.


Some label paper has large margins on the top sheet. When using such paper, do not peel these margins from the carrier sheet before completing output.



Use label paper that conforms to the following specifications.

Top sheet weight	44 to 74 g/m <sup>2</sup>
Basis weight (overall paper weight)	104 to 151 g/m <sup>2</sup>
Top sheet thickness	0.086 to 0.107 mm
Overall paper thickness	0.115 to 0.145 mm
Moisture content	4 to 6 % (composite)

#### Hagaki (Cardstock)



Before loading Hagaki (Cardstock) into the multipurpose tray, fan them and align the edges. If the Hagaki (Cardstock) paper is curled, straighten it before loading. Printing onto curled Hagaki (Cardstock) may cause jams.

Use unfolded Oufuku hagaki (Return postcard) (available at post offices). Some Hagaki (Cardstock) may still have rough edges developed by a paper cutter on the back side. Remove any such rough edges by placing the Hagaki (Cardstock) on a flat surface and rubbing the edges gently a few times with a ruler.

#### Envelopes

Use the multipurpose tray for envelopes.

Due to the structure of envelopes, printing evenly over the entire surface may not be possible in some cases. Thin envelopes in particular may be wrinkled by the machine in some cases as they pass through. Before purchasing envelopes in volume, try testing a sample to ensure the print quality.

Storing envelopes for a long period may cause them to become wrinkled. Thus, keep the package sealed until you are ready to use them.

Keep the following points in mind.

- Do not use envelopes with exposed adhesive. In addition, do not use the type of envelope in which the adhesive is exposed after the top layer is peeled off. Serious damage may be caused if the paper covering the adhesive comes off in the machine.
- Do not use envelopes with certain special features. For example, do not use envelopes with a grommet for winding a string to close the flap or envelopes with an open or film-covered window.
- · If paper jams occur, load fewer envelopes at once.

#### **Thick Paper**

Before loading thick paper, fan it and align the edges. Some thick paper may still have rough edges developed by a paper cutter on the back side. Remove any such rough edges just as with Hagaki (Cardstock) by placing the paper on a flat surface and rubbing the edges gently a few times with a ruler. Printing onto paper with rough edges may cause jams.

#### NOTE

If the paper is not supplied correctly even after it is smoothed, load the paper with the leading edge raised a few millimeters.

#### **Colored Paper**

Colored paper must conform to the specifications.

Basic Paper Specifications (page 11-11)

In addition, the pigments in the paper must be able to withstand the heat of printing (up to 200°C or 392°F).

#### **Preprinted Paper**

Preprinted paper must conform to the specifications.

Basic Paper Specifications (page 11-11)

The colored ink must be able to withstand the heat of printing. It must be resistant to silicone oil as well. Do not use paper with a treated surface such as glossy paper used for calendars.

#### **Recycled Paper**

Recycled paper must conform to the specifications; however, its whiteness may be considered separately.

Basic Paper Specifications (page 11-11)

#### NOTE

Before purchasing recycled paper in volume, try testing a sample to ensure satisfactory print quality.

#### **Coated Paper**

Coated paper is created by treating the surface of the base paper with a coating that provides higher printing quality than plain paper. Coated paper is used for particularly high quality printing.

The surface of high-quality or medium-quality paper is coated with special agents that improve ink adhesion by making the paper surface smoother. These agents are used either to coat both sides of the paper or just one side. The coated side appears slightly glossy.



When printing on coated paper in very humid environments, ensure that the paper is kept dry as moisture may cause sheets to stick together when they are fed into the machine. If printing in very humid environments, set coated paper for one sheet each.

# **Specifications**

#### **IMPORTANT**

Specifications are subject to change without notice.

#### NOTE

For more information on using the FAX, refer to the following:

FAX Operation Guide

### Machine

lte	m	Description				
Туре		Desktop				
Printing Method		Electrophotography by semiconductor laser				
Paper Weight	Cassette	60 to 163 g/m <sup>2</sup>				
	Multipurpose Tray	60 to 220 g/m <sup>2</sup> , 230 g/m <sup>2</sup> (Cardstock)				
Paper Type	Cassette	Plain, Rough, Recycled, Preprinted, Bond, Color, Prepunched, Letterhead, Thick, High Quality, Custom 1 to 8 (Duplex: Same as Simplex)				
	Multipurpose Tray	Plain, Transparency (OHP film), Rough, Vellum, Labels, Recycled, Preprinted, Bond, Cardstock, Coated, Color, Prepunched, Letterhead, Envelope, Thick, High Quality, Custom 1 to 8				
Paper Size	Cassette	A4, A5-R, A5, A6, B5, B6, Letter, Legal, Statement-R, Executive,Oficio II, Folio, 216 × 340 mm, 16K, B5(ISO), Custom (105 × 148 mm to 216 × 356 mm)				
	Multipurpose Tray	A4, A5-R, A5, A6, B5, B6, Folio, 216 × 340 mm, Letter, Legal, Statement-R, Statement, Executive, Oficio II, 16K, B5(ISO), Envelope #10, Envelope #9, Envelope #6 3/4, Envelope Monarch, Envelope DL, Envelope C5, Hagaki (Cardstock), Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2, Custom (70 × 148 mm to 216 × 356 mm)				
Printable area		Print margin for top, bottom and both sides is 4.2 mm.				
Warm-up Time	Power on	29 seconds or less				
23°C/73.4°F, 60 %	Sleep	13 seconds or less				
Paper Capacity	Cassette	250 sheets (80 g/m <sup>2</sup> ) <sup>*1</sup>				
	Multipurpose Tray	50 sheets (A4/Letter or smaller) (80 g/m <sup>2</sup> )				
Output Tray Capacity	Inner tray	150 sheets (80 g/m <sup>2</sup> )				
Image Write Syste	em	Semiconductor laser and electrophotography				
Memory		512 MB				
Warm-up Time 23°C/73.4°F, 60 % Paper Capacity Output Tray Capacity Image Write Syste	Sleep Cassette Multipurpose Tray Inner tray	Oufuku Hagaki (Return postcard), Youkei 4, Youkei 2, Custom (70 × 148 mm to 216 × 356 mm)         Print margin for top, bottom and both sides is 4.2 mm.         29 seconds or less         13 seconds or less         250 sheets (80 g/m <sup>2</sup> )*1         50 sheets (A4/Letter or smaller) (80 g/m <sup>2</sup> )         150 sheets (80 g/m <sup>2</sup> )         Semiconductor laser and electrophotography				

\*1 Up to upper limit height line in the cassette.

lte	m	Description		
Interface		USB Interface Connector: 1 (Hi-Speed USB) Network interface: 1 (10 BASE-T/100 BASE-TX/1000 BASE-T) USB Port: 1 (Hi-Speed USB) Wireless LAN support <sup>*1</sup> Fax: 1		
Operating	Temperature	10 to 32.5°C/50 to 90.5°F		
Environment	Humidity	10 to 80 %		
	Altitude	3,500 m/11,482 ft maximum		
	Brightness	1,500 lux maximum		
Dimension (W × D (Including the Do Processor)	-	16.42" × 16.89" × 19.49" 417 × 429 × 495 mm		
Weight (without toner co	ntainer)	Approx. 57.33 lb/Approx. 26 kg		
Space Required ( (Using multipurpo	•	16.42" × 24.14" 417 × 613 mm		
Power Source		120 V Specification Model: 120 V $\sim$ 60 Hz 8.6 A 230 V Specification Model: 220 to 240 V $\sim$ 50 Hz 4.5 A		
The power consu product in networ all network ports	rked standby (If	2.2W		
Options		Optional Equipment (page 11-2)		

\*1 Only ECOSYS M5526cdw

# **Copy Functions**

Ite	m		Description			
Copy Speed			Black and White Copying	Full Color Copying		
		A4/A5	26 sheets/min	26 sheets/min		
		Letter	27 sheets/min	27 sheets/min		
		Legal	22 sheets/min	22 sheets/min		
		B5	27 sheets/min	27 sheets/min		
		A5-R	27 sheets/min	27 sheets/min		
		A6	27 sheets/min	27 sheets/min		
			27 sheets/min	27 sheets/min		
First Copy Time (A4, place on	Black and White	8 seconds or le	SS			
the platen, feed from Cassette)	Color	10 seconds or less				
Zoom Level		Manual mode: 25 to 400%, 1% increments Auto mode: Preset Zoom				
Continuous Copy	ving	1 to 999 sheets				
Resolution		600 × 600 dpi, 9600 dpi equivalent × 600 dpi				
Supported Origin	al Types	Sheet, Book, 3-dimensional objects (maximum original size: Legal/ Folio)				
Original Feed Sys	stem	Fixed				

### **Printer Functions**

Ite	m	Description
Printing Speed		Same as Copying Speed.
First Print Time (A4, feed from	Black and White	9.5 seconds or less
Cassette)	Color	10.5 seconds or less
Resolution		9600 dpi equivalent × 600 dpi, 1200 dpi × 1200 dpi (Data resolution is 600 dpi.) <sup>*1</sup>
Operating System		Windows XP, Windows Server 2003, Windows Vista, Windows 7, Windows 8, Windows 8.1, Windows 10, Windows Server 2008/R2, Windows Server 2012/R2, Mac OS 10.5 or later
Interface		USB Interface Connector: 1 (Hi-Speed USB) Network interface: 1 (10 BASE-T/100 BASE-TX/1000 BASE-T) Wireless LAN support <sup>*2</sup>
Page Description Language		PRESCRIBE
Emulations		PCL6 (PCL-XL, PCL5c), KPDL3 (PostScript3 compatible), PDF, XPS, OpenXPS

\*1 The processing speed will be slower than normal.\*2 Only ECOSYS M5526cdw

## **Scanner Functions**

Item	Description
Resolution	300 × 300 dpi, 200 × 200 dpi, 200 × 100 dpi, 600 × 600 dpi <sup>*1</sup> , 400 × 400 dpi <sup>*1</sup> , 200 × 400 dpi <sup>*1</sup>
File Format	TIFF (MMR/JPEG compression), JPEG, PDF (MMR/JPEG compression), XPS, High compressive PDF, Encrypted PDF, OPEN XPS, PDF/A-1
Scanning Speed <sup>*2</sup>	1-sidedB/W 30 Images/min Color 12 Images/min2-sidedB/W 24 Images/min Color 8 Images/min(A4 landscape, 300 dpi × 600 dpi, Image quality: Text/Photo original)
Interface	Ethernet (10 BASE-T/100 BASE-TX/1000 BASE-T), USB, Wireless LAN support <sup>*3</sup>
Transmission System	SMBv3, SMTP, FTP, FTP over SSL, USB, TWAIN <sup>*4</sup> , WIA <sup>*5</sup> , WSD

\*1 One-sided scanning

\*2 When using the document processor (except TWAIN and WIA scanning)

\*3 Only ECOSYS M5526cdw

\*4 Available Operating System: Windows XP/Windows Vista/Windows Server 2003/Windows Server 2008/ Windows Server 2008 R2/Windows 7/Windows 8/Windows 8.1/Windows 10/Windows Server 2012/ Windows Server 2012 R2

\*5 Available Operating System: Windows Vista/Windows Server 2008/Windows Server 2008 R2/Windows 7/ Windows 8/Windows 8.1/Windows Server 2012/Windows Server 2012 R2/Windows 10

### **Document Processor**

Item	Description
Supported Original Types	Sheet originals
Paper Size	Maximum: Legal/A4 Minimum: Statement/A6
Paper Weight	50 to 160 g/m <sup>2</sup>
Loading Capacity	50 sheets (50 to 80 g/m <sup>2</sup> ) maximum <sup>*1</sup>

\*1 Up to upper limit height line in the document processor

# **Paper Feeder**

Item	Description
Paper Supply Method	Friction retard feeder (No. Sheets: 250, 80 g/m <sup>2</sup> , 1 cassette)
Paper Size	A4, A5-R, A5, B5, A6, B6, Letter, Legal, Folio, 216 × 340 mm, Statement-R, Executive, Oficio II, 16K, B5(ISO), Custom (105 × 148 to 216 × 356 mm)
Supported Paper	Paper weight: 60 to 163 g/m <sup>2</sup>
	Media types: Plain, Recycled, Special Paper
Dimensions	16.15" × 17.62" × 5.79"
(W) × (D) × (H)	410 × 447.5 × 147 mm
Weight	Approx. 8.16 lb/Approx. 3.6 kg

### ο ΝΟΤΕ

Consult your dealer or service representative for recommended paper types.



#### Accessibility

The machine is designed featuring good accessibility even for the elderly and those who are physically challenged or visually impaired.

#### Apple Talk

AppleTalk offers file sharing and printer sharing and it also enables you to utilize application software that is on another computer on the same AppleTalk network.

#### Auto Form Feed Timeout

During data transmission, the machine may sometimes have to wait until receiving the next data. This is the auto form feed timeout. When the preset timeout passes, the machine automatically prints output. However, no output is performed if the last page has no data to be printed.

#### Auto-IP

Auto-IP is a module that enables dynamic IPv4 addresses to be assigned to a device on startup. However, DHCP requires a DHCP server. Auto-IP is a server-less method of choosing an IP address. IP addresses between 169.254.0.0 to 169.254.255.255 are reserved for Auto-IP and assigned automatically.

#### Auto Paper Selection

A function to automatically select paper in the same size as originals when printing.

#### **Auto Sleep**

A mode designed for electrical power saving, activated when the machine is left unused or there is no data transfer for a specific period. In Sleep mode, power consumption is kept to a minimum.

#### Bonjour

Bonjour, also known as zero-configuration networking, is a service that automatically detects computers, devices and services on an IP network. Bonjour, because an industry-standard IP protocol is used, allows devices to automatically recognize each other without an IP address being specified or DNS server being set. Bonjour also sends and receives network packets by UDP port 5353. If a firewall is enabled, the user must check that UDP port 5353 is left open so that Bonjour will run correctly. Some firewalls are set up so as to reject only certain Bonjour packets. If Bonjour does not run stably, check the firewall settings and ensure that Bonjour is registered on the exceptions list and that Bonjour packets are accepted. If you install Bonjour on Windows XP Service Pack 2 or later, the Windows firewall will be set up correctly for Bonjour.

#### **Default Gateway**

This indicates the device, such as a computer or router, that serves as the entrance/exit (gateway) for accessing computers outside the network that you are on. When no specific gateway is designated for a destination IP address, data is sent to the host designated as the Default Gateway.

#### **DHCP (Dynamic Host Configuration Protocol)**

Dynamic Host Configuration Protocol (DHCP) that automatically resolves IP addresses, subnet masks, and gateway addresses on a TCP/IP network. DHCP minimizes the load of network management employing a large number of client computers because it relieves individual clients including printers from the IP address being assigned.

#### DHCP (IPv6)

DHCP (IPv6) is the next-generation of the Internet's Dynamic Host Configuration Protocol and supports IPv6. It extends the BOOTP startup protocol that defines the protocols used for transferring configuration information to hosts on the network. DHCP (IPv6) permits the DHCP server to use its expanded functionality to send configuration parameters to an IPv6 node. Because the network addresses that can be used are allocated automatically, the IPv6 node management workload is reduced in systems where the administrator has to exercise close control over IP address allocation.

#### dpi (dots per inch)

A unit for resolution, representing the number of dots printed per inch (25.4 mm).

#### EcoPrint Mode

A printing mode that helps save toner. Copies made in this mode are thus lighter than normal.

#### Emulation

The function to interpret and execute other printers' page description languages. The machine emulates operation of PCL6, KPDL3 (PostScript 3 compatible).

#### Enhanced WSD

Proprietary web services.

#### FTP (File Transfer Protocol)

A protocol to transfer files on the TCP/IP network, whether the Internet or an intranet. Along with HTTP and SMTP/POP, FTP is now frequently used on the Internet.

#### Grayscale

A computer color expression. Displayed images of this sort are typically composed of shades of gray, varying from black at the weakest intensity to white at the strongest, without any other colors. Gray levels are displayed in numerical levels: that is, white and black only for 1 bit; 256 gray levels (including white and black) for 8 bits; and 65,536 gray levels for 16 bits.

#### Help

A ? (Help) key is provided on this machine's operation panel. If you are unsure of how to operate the machine, would like more information on its functions or are having problems getting the machine to work properly, press the ? (Help) key to view a detailed explanation on the touch panel.

#### IP Address

An Internet protocol address is a unique number that represents a specific computer or related device on the network. The format of an IP address is four sets of numbers separated by dots, e.g. 192.168.110.171. Each number should be between 0 and 255.

#### IPP

IPP (Internet Printing Protocol) is a standard that uses TCP/IP networks such as the Internet to enable print jobs to be sent between remote computers and printers. IPP is an extension of the HTTP protocol used to view websites and enables printing to be carried out via routers on printers in remote locations. It also supports the HTTP authentication mechanisms along with SSL server and client authentication as well as encryption.

#### Job Box

The Job Box function stores print data on the printer and allows users to print single or multiple copies of the stored data later using the printer's operation panel.

#### **KPDL (Kyocera Page Description Language)**

Kyocera's PostScript page description language compatible with Adobe PostScript Level 3.

#### Multipurpose (MP) Tray

The paper supply tray on the front side of the machine. Use this tray instead of the cassettes when printing onto envelopes, Hagaki (Cardstock), transparencies, or labels.

#### NetBEUI (NetBIOS Extended User Interface)

An interface, developed by IBM in 1985, as an update from NetBIOS. It enables more advanced functions on smaller networks than other protocols such as TCP/IP, etc. It is not suitable for larger networks due to lack of routing capabilities to choose the most appropriate routes. NetBEUI has been adopted by IBM for its OS/2 and Microsoft for its Windows as a standard protocol for file sharing and printing services.

#### **Outline font**

With outline fonts, character outlines are represented with numerical expressions and fonts can be enlarged or reduced in different ways by changing the numeric values of those expressions. Printing remains clear even if you enlarge fonts, since the characters are defined with outlines represented with numerical expressions. You can specify the font size in steps of 0.25 points up to 999.75 points.

#### PDF/A

This is "ISO 19005-1. Document management - Electronic document file format for long-term preservation - Part 1: Use of PDF (PDF/A)", and is a file format based on PDF 1.4. It has been standardized as ISO 19005-1, and is a specialization of PDF, which has been mainly used for printing, for long-term storage. A new part, ISO 19005-2 (PDF/A-2), is currently being prepared.

#### POP3 (Post Office Protocol 3)

A standard protocol to receive E-mail from the server in which the mail is stored on the Internet or an intranet.

#### PostScript

A page description language developed by Adobe Systems. It enables flexible font functions and highly-functional graphics, allowing higher quality printing. The first version called Level 1 was launched in 1985, followed by Level 2 that enabled color printing and two-byte languages (e.g. Japanese) in 1990. In 1996, Level 3 was released as an update for the Internet access and PDF format as well as gradual improvements in implementation technologies.

#### **PPM** (prints per minute)

This indicates the number of A4 size printouts made in one minute.

#### **Printer Driver**

The software to enable you to print data created on any application software. The printer driver for the machine is contained in the DVD enclosed in the package. Install the printer driver on the computer connected to the machine.

#### **RA(Stateless)**

The IPv6 router communicates (transmits) information such as the global address prefix using ICMPv6. This information is the Router Advertisement (RA).

ICMPv6 stands for Internet Control Message Protocol, and is a IPv6 standard defined in the RFC 2463 "Internet Control Message Protocol (ICMPv6) for the Internet Protocol Version 6 (IPv6) Specification".

#### **RAM Disk**

Using part of the printer's memory as a virtual disk, you can set any amount of memory from overall printer memory as a RAM disk in order to use features such as electronic sorting (shortening print time).

#### Send as E-mail

A function to send the image data stored in the machine as an E-mail attachment. E-mail addresses can be selected from the list or entered at each time.

#### SMTP (Simple Mail Transfer Protocol)

A protocol for E-mail transmission over the Internet or an intranet. It is used for transferring mail between mail servers as well as for sending mail from clients to their servers.

#### Status Page

The page lists machine conditions, such as the memory capacity, total number of prints and scans, and paper source settings.

#### Subnet Mask

The subnet mask is a way of augmenting the network address section of an IP address.

A subnet mask represents all network address sections as 1 and all host address sections as 0. The number of bits in the prefix indicates the length of the network address. The term "prefix" refers to something added to the beginning and, in this context, indicates the first section of the IP address. When an IP address is written, the length of the network address is indicated by the prefix length after a forward slash (/). For example, "24" in the address "133.210.2.0/24". In this way, "133.210.2.0/24" denotes the IP address "133.210.2.0" with a 24-bit prefix (network section). This new network address section (originally part of the host address) made possible by the subnet mask is referred to as the subnet address. When you enter the subnet mask, be sure to set the "DHCP" setting to "Off".

#### TCP/IP (Transmission Control Protocol/Internet Protocol)

TCP/IP is a suite of protocols designed to define the way computers and other devices communicate with each other over a network.

#### TCP/IP (IPv6)

TCP/IP (IPv6) is based on the current Internet protocol, TCP/IP (IPv4). IPv6 is the next-generation Internet protocol and expands the available address space, which resolves the problem of the lack of addresses under IPv4, while also introducing other improvements such as additional security functionality and the capacity to prioritize data transmission.

#### **TWAIN (Technology Without An Interesting Name)**

A technical specification for connecting scanners, digital cameras, and other image equipment to computers. The TWAIN compatible devices enable you to process image data on any relevant application software. TWAIN is adopted on a large amount of graphic software (e.g. Adobe Photoshop) and OCR software.

#### USB (Universal Serial Bus) 2.0

A USB interface standard for Hi-Speed USB 2.0. The maximum transfer rate is 480 Mbps. This machine is equipped with USB 2.0 for high-speed data transfer.

#### WIA (Windows Imaging Acquisition)

A function to import images supported after Windows Me/XP from digital cameras and other peripheral devices. This function replaces what TWAIN used to do. The feature is provided as a part of Windows functions and improves ease of operation, so that you import images directly to My Computer without using any application.

#### WPS (Wi-Fi Protected Setup)

WPS is a network security standard created by Wi-Fi Alliance, to make it easy to connect with the wireless devices and set up the Wi-Fi Protected Access. The WPS-supported services can connect to the wireless access points by pushing a button or entering passphrases.

# Index

#### A

Accessibility 11-24 Address Book 3-20 Adding 3-20 Contact 3-20 Deleting 3-25 Editing 3-24 Group 3-23 Address Book/One Touch 8-22 Adjustment/Maintenance 8-41 AirPrint 4-10 Anti-theft Lock Slot 2-3 Apache License (Version 2.0) 1-14 Apple Talk 11-24 Auto Error Clear 8-40 Auto Form Feed Timeout 11-24 Auto Panel Reset 8-38 Auto Paper Selection 11-24 Auto Sleep 2-32, 11-24 Auto-IP 11-24 Settings 8-28 Automatic 2-Sided Print Function 1-17

#### B

Background Density Adjustment 6-23 Default 8-16 Bonjour 11-24 Settings 8-30 Button (Right Cover Open) 2-2

#### С

Cables 2-7 Calibration 8-41, 10-34 Card Authentication Kit 11-4 Cassette Loading Paper 3-4, 3-7 Cassette 1 2-2 Cassette 2 2-6 Cassette/MP Tray Settings 8-8 Character Entry Method 11-8 Checking the Counter 2-50 Checking the Remaining Amount of Toner 7-13 Cleaning 10-2 Glass Platen 10-2 Paper Transfer Unit 10-4 Slit Glass 10-3 Coated Paper 11-18 Collate 6-16 Default 8-16 Color Calibration 10-34 Color Balance 6-21 Saturation 6-24 Color Balance 6-21 Color Registration 8-41

Color Selection 6-16 Default 8-16 Combine 6-14 Command Center RX 2-52 Common Settings 8-10 Color Toner Empty Action 8-18 Default Screen 8-10 Display Status/Log 8-19 Error Handling 8-18 Format SD Card 8-19 Function Defaults 8-16 Keyboard Layout 8-19 Low Toner Alert 8-18 Measurement 8-18 Original Settings 8-11 Paper Settings 8-13 Preset Limit 8-17 Sound 8-10 USB Keyboard Type 8-19 Connecting LAN Cable 2-8 Power Cable 2-9 USB cable 2-9 Connection Method 2-7 Continuous Scan 6-24 Default 8-16 Contrast 6-22, 8-41 Conventions Used in This Guide xix Copy 5-15 Copy Settings 8-20 Auto % Priority 8-20 Auto Paper Selection 8-20 DP Read Action 8-20 Copy Speed 11-21 Correcting Black Line 8-41 Counting the Number of Pages Printed Counter 2-50 Each Job Account 9-39 Print Accounting Report 9-40 Total Accounting 9-39 Unknown ID Job 9-42

#### D

Date Format 8-38 Date/Time 8-38 Date/Timer/Energy Saver 8-38 Auto Error Clear 8-40 Auto Panel Reset 8-38 Date Format 8-38 Date/Time 8-38 EnergySaver RecoveryLevel 8-39 Error Clear Timer 8-40 Panel Reset Timer 8-38 Ping Timeout 8-40 Sleep Level 8-39 Sleep Rules 8-39, 8-40 Sleep Timer 8-39, 8-40 Time Zone 8-38 Unusable Time 8-40

Default Gateway 11-24 Settings 8-28 Default Screen 8-10 Density 6-11 Density Adjustment 8-41 Destination Adding a Destination 3-20 Address Book 5-34 Checking and Editing 5-38 Confirmation Screen of Destinations 5-38 Dest. Check before Send 8-21 Entry Check for New Dest. 8-21 Multi Sending 5-30 One Touch Key 3-26 Search 5-34 Sort 8-23 Device 7-11 DHCP 11-24 Settings 8-28 DHCP (IPv6) 11-25 Settings 8-29 Display Brightness 8-41 Display Status/Log 8-19 Document Box Job Box 4-11, 5-40 Removable Memory Box 5-40 Document Box Settings 8-22 Job Box 8-22 Polling Box 8-22 Sub Address Box 8-22 Document Processor 2-2 Loading Originals 5-3 **Originals Not Supported** by the Document Processor 5-3 **Originals Supported** by the Document Processor 5-3 Part Names 2-2 dpi 11-25 Drum Refresh 8-41 DSM Scan Protocol Settings 8-31 Duplex 6-12 Duplex (2-sided Original) 6-30

#### Е

EcoPrint 6-20, 11-25 Default 8-16 Printer 8-24 Edit Destination Address Book 3-20 Address Book Defaults 8-23 Contact 3-20 Group 3-23 One Touch Key 3-26 E-mail Settings 2-58 E-mail Subject/Body 6-32 Default 8-17 Emulation 11-25 Selection 8-24 Encrypted PDF Password 6-34 Energy Saver Recovery Level 8-39 Energy Saving Control Function 1-17 Energy Star (ENERGY STAR®) Program 1-17 Enhanced WSD 11-25 Protocol Settings 8-34 Enhanced WSD over SSL Protocol Settings 8-34 Enter key 2-19 Entry File Name 6-26 Subject 6-32 Environment 1-3 Error Clear Timer 8-40 Error Handling 8-18 eSCL Protocol Settings 8-35 eSCL over SSL Protocol Settings 8-35 Expansion Memory 11-3

#### F

Favorites 5-8 Editing and Deleting 5-12 Recalling 5-11 Registering 5-9 FAX 8-22 Feed Cover 2-4 File Format 6-27 PDF 6-28 Separation 6-31 File Format 6-27 Default 8-16 File Management Utility Connection 5-29 File Name Entry 6-26 Default 8-17 File Separation 6-31 Default 8-16 First Copy Time 11-21 First Print Time 11-21 FTP 11-25 FTP Client (Transmission) Protocol Settings 8-30 FTP Encrypted TX 6-33 Default 8-17 FTP Server (Reception) Protocol Settings 8-31 Function Defaults 8-16 Fuser Cover 2-4

#### G

Glossary 11-24 Google Cloud Print 4-10 GPL/LGPL 1-12 Grayscale 11-25 Group Authorization Set. 9-15 Group Authorization 9-15 Group List 9-16 Group Authorization Settings 9-15 Guest Authorization Set. 9-18 Guest Authorization 9-18 Guest Property 9-19 Guides Provided with the Machine XVI

#### Н

Handle 2-2, 2-3 Help 11-25 Help Screen 2-20 High Compression PDF 6-27 Default 8-17 Home 8-19 Customize Desktop 2-13 Customize Task Screen 2-13 Wallpaper 2-13 Home Screen 2-12 Host Name 8-26 HTTP Protocol Settings 8-32 HTTPS Protocol Settings 8-32 Hue Adjustment 6-20

#### I

Image Quality 6-27 Default 8-17 Inner Tray 2-2 Install Macintosh 2-45 Software 2-37 Windows 2-38 Interface Block Setting 8-36 IP Address 11-25 Settings 8-28 IPP 11-25 Protocol Settings 8-32 IPP over SSL Protocol Settings 8-33 **IPSec** Settings 8-30

#### J

Job Available Status 7-2 Canceling 7-10 Checking History 7-8 Checking Status 7-2 Detailed Information 7-7 Detailed Information of Histories 7-9 Details of the Status Screens 7-3 Displaying Status Screens 7-2 Pause and Resumption 7-10 Sending the Log History 7-9 Job Accounting 9-28 Adding an Account 9-30 Counting the Number of Pages Printed 9-39 Default Setting 9-38 Deleting an Account 9-33 Editing an Account 9-32 Enabling Job Accounting 9-29 FAX Driver 9-37 Job Accounting Access 9-29 Login 9-41 Logout 9-41 Overview of Job Accounting 9-28 Print Accounting Report 9-40 Printing 9-34 Restricting the Use of the Machine 9-31 **TWAIN 9-35** WIA 9-36 Job Box 11-26 Deletion of Job Retention 8-22 Private Print Box 4-12 Proof and Hold Box 4-15 Quick Copy Box 4-14 Quick Copy Job Retention 8-22 Specifying the Job Box from a Computer and Storing the Job 4-11 Stored Job Box 4-13 Job Finish Notice 6-25 JPEG/TIFF Print 6-34 Default 8-17

#### Κ

Keyboard Layout 8-19 Knopflerfish License 1-14 KPDL 11-26

#### L

Label 11-16 LAN Cable 2-7 Connecting 2-8 Language 8-5 Laser Scanner Cleaning 8-41, 10-34 LDAP Protocol Settings 8-31 Legal Information 1-11 Legal Restriction on Copying 1-9 Legal Restriction on Scanning 1-9 Limited Use of This Product 1-10 LINE Connector 2-4 Loading Originals 5-2 Loading Originals in the Document Processor 5-3 Placing Originals on the Platen 5-2 Login 2-21 Logout 2-22 Low Toner Alert 8-18 LPD Protocol Settings 8-30

#### Μ

Management 9-1

Manual Setting (IPv6) 8-29 Measurement 8-18 Media Type Setting 8-15 Mixed Size Originals 6-19 Monotype Imaging License Agreement 1-13 Mopria 4-10 Multi Sending 5-30 Multipurpose Tray 2-4, 11-26 Paper Size and Media Type 8-9

#### Ν

NetBEUI 11-26 Protocol Settings 8-30 Network Preparation 2-24 Settings 8-26 Network Interface 2-7 Network Interface Connector 2-4 Notice 1-2

#### 0

One Touch Key Adding 3-26 Deleting 3-28 Editing 3-27 OpenSSL License 1-12 Operation Panel 2-2 Option Card Authentication Kit 11-4 Expansion Memory 11-3 Overview 11-2 Paper Feeder (500-sheet) 11-4 SD/SDHC Memory Card 11-4 ThinPrint Option 11-4 USB Keyboard 11-5 Optional Applications 11-6 Optional Function 8-37 Optional Memory 8-37 Original Auto Detect Original Size (DP) 8-11 Custom Original Size 8-11 Default Original Size 8-12 Settings 8-11 Size XX Original eject table 2-2 Original Image 6-19 Default 8-16 Original Orientation 6-18 Default 8-16 Original Settings 8-11 Original Size 6-17 Original Size Indicator Plates 2-2 Original SSLeay License 1-12 Original Stopper 2-2 Original Table 2-2 Original Width Guides 2-2 Outline font 11-26

#### Ρ

Panel Reset Timer 8-38 Paper Checking the Remaining Amount of Paper 7-13 Appropriate Paper 11-12 Custom Paper Size 8-13 Default Paper Source 8-14 Loading Cardstock 5-7 Loading Envelopes 5-7 Loading Paper 3-2 Loading Paper in the Cassettes 3-4, 3-7 Media for Auto 8-14 Media Type Setting 8-14 Multipurpose Tray 8-9 Paper Settings 8-13 Size and Media Type 8-8, 11-11 Special Paper 11-15 Special Paper Action 8-14 Specifications 11-11 Weight 8-15 Paper Feed Mode 8-25 Paper Feeder (500-sheet) 11-4 Paper Jams 10-35 Cassette 1 10-36 Cassette 2 10-36 Cassette 3 (500-sheet x 2) 10-37 Document Processor 10-45 Jam Location Indicators 10-35 Multipurpose Tray 10-39 Rear Cover 1 10-42 Paper Length Guide 2-4, 3-4, 3-7 Paper Selection 6-9 Paper Settings 8-13 Paper Stopper 2-2, 3-9 Paper Width Guides 2-4, 3-4, 3-7 Part Names 2-2 PDF/A 6-27, 11-26 Default 8-17 Ping 8-35 Platen 2-2 POP3 11-26 POP3 (E-mail RX) Protocol Settings 8-30 PostScript 11-26 Power Cable Connecting 2-9 Power Management 1-17 Power Off 2-10 Power On 2-10 Power Switch 2-2 PPM 11-26 Precaution for Loading Paper 3-4, 3-7 Precautions for Use 1-4 Preset Limit 8-17 Primary Network (Client) 8-36 Print Settings 4-2, 4-9

Printer 8-24 Auto Cassette Change 8-25 Color Setting 8-24 Copies 8-24 CR Action 8-25 Duplex 8-24 EcoPrint 8-24 Emulation 8-24 Form Feed TimeOut 8-24 Gloss Mode 8-25 Job Name 8-25 LF Action 8-24 MP Tray Priority 8-25 Orientation 8-24 Override A4/Letter 8-24 Paper Feed Mode 8-25 Print setting 4-2 User Name 8-25 Wide A4 8-24 Printer Driver 11-26 Help 4-3 Printing Documents Stored in Removable USB Memory 5-41 Printing from PC 4-4 Printing Speed 11-21 Priority Override 6-26 Product Library XVII

#### Q

Quick No. Search key 2-19 Quick Setup Wizard 2-35 Quiet Mode 2-34

#### R

RA (Stateless) 11-27 Settings 8-29 RAM Disk 11-27 RAM Disk Setting 8-37 Raw Protocol Settings 8-33 Rear Cover 1 2-3 Rear Cover 2 2-6 Recycled Paper 11-18 Regarding Trade Names 1-11 Regular Maintenance 10-2 Toner Container Replacement 10-5 Report 8-5 Admin Report Settings 8-6 Report Print 8-5 Result Report Settings 8-6 Sending Log History 8-7 Report Print Accounting Report 8-6 Font List 8-5 Network Status 8-5 Service Status 8-5 Status Page 8-5 Resolution 6-32, 11-21 Resource Saving - Paper 1-17 Responding to Messages 10-16

Restart 8-37 Restart Network 8-36 Right Cover 2-2

#### S

Safety Conventions in This Guide 1-2 Saturation 6-24 Saving Documents to USB Memory 5-43 Scan Resolution 6-32 Default 8-16 SD Card Format 8-19 SD/SDHC Memory Card 11-4 Secure Protocol 8-35 Security Level 8-36 Security Precautions when Using Wireless LAN 1-9 Send and Forward 8-21 Send as E-mail 5-17 Send Result Report 8-6 Send Settings 8-21 Color TIFF Compression 8-21 Default Screen 8-21 Dest. Check before Send 8-21 Entry Check for New Dest. 8-21 New Destination Entry 8-21 Recall Destination 8-21 Send and Forward 8-21 Send to Folder (FTP) 5-17 Send to Folder (SMB) 5-17 Sending 5-17 Preparation for Sending a Document to a PC 3-10 Sending Size 6-31 Service Setting 8-41 Setting Date and Time 2-23 Sharpness 6-22 Shortcuts 5-13 Adding 5-13 Editing and Deleting Shortcuts 5-14 Simple Login 2-22 Simple Login Settings Simple Login 9-23 Simple Login Setup 9-23 Skip Blank Page 6-23 Sleep 2-32 Sleep Level 2-33, 8-39 Sleep Rules 2-33, 8-39, 8-40 Sleep Timer 8-39, 8-40 Slit Glass 2-2 SMB Client (Transmission) Protocol Settings 8-31 SMTP 11-27 SMTP (E-mail TX) Protocol Settings 8-30 SNMPv1/v2c Protocol Settings 8-31 SNMPv3 Protocol Settings 8-32 Solving Malfunctions 10-9 Sound 8-10

Specifications 11-19 Copy Functions 11-21 Document Processor 11-22 Machine 11-19 Paper Feeder (500-sheet) 11-23 Printer Functions 11-21 Scanner Functions 11-22 SSL 8-35 Status Page 11-27 Status/Job Cancel 7-1 Storing Size 6-33 Subnet Mask 11-27 Settings 8-28 Supplies Checking the Remaining Amount 7-13 Symbols 1-2 System Menu 8-2 Address Book/One Touch 8-22 Adjustment/Maintenance 8-41 Cassette/MP Tray Settings 8-8 Common Settings 8-10 Copy 8-20 Date/Timer/Energy Saver 8-38 Document Box 8-22 FAX 8-22 Home 2-12 Language 8-5 Operation Method 8-2 Printer 8-24 Quick Setup Wizard 2-35 Report 8-5 Send 8-21 System/Network 8-26 User Login/Job Accounting 8-23 User Property 8-7, 9-10 System/Network 8-26 Interface Block Setting 8-36 Network 8-26 Optional Function 8-37 Optional Memory 8-37 Primary Network (Client) 8-36 RAM Disk Setting 8-37 Restart 8-37 Security Level 8-36

#### Т

TCP/IP 11-27 Settings 8-28, 8-29 TCP/IP (IPv4) Settings 2-24, 8-28 TCP/IP (IPv6) 11-25 Settings 8-29 TEL Connector 2-4 Thin Print over SSL Protocol Settings 8-34 ThinPrint Protocol Settings 8-34 ThinPrint Option 11-4 Time Zone 8-38 Toner Container (Black) 2-5 Toner Container (Cyan) 2-5 Toner Container (Magenta) 2-5 Toner Container (Yellow) 2-5 Toner Container Lock Lever 2-5 Toner Container Replacement 10-5 Touch Panel 2-12 Tray Extension 2-4 Troubleshooting 10-9 TWAIN 11-27 Setting TWAIN Driver 2-47

#### U

USB 11-28 **USB** Cable Connecting 2-9 USB Interface 2-7 USB Interface Connector 2-4 USB Keyboard 11-5 USB Keyboard Type 8-19 **USB** Memorv Printing 5-41 Remove 5-44 Save 5-43 USB Memory Slot 2-2 User Login Administration 9-2 Adding a User 9-5 Changing User Properties 9-8 Enabling User Login Administration 9-3 FAX Driver 9-14 Group Authorization Settings 9-15 Guest Authorization Set. 9-18 ID Card Settings 9-25 Login 2-21 Logout 2-22 Obtain NW User Property 9-21 Overview of User Login Administration 9-2 Printing 9-11 Simple Login Settings 9-23 **TWAIN 9-12** User Account Lockout Setting 9-4 WIA 9-13 User Login/Job Accounting 8-23 Job Accounting 9-28 Unknown ID Job 9-42 User Login 9-2 User Property 8-7

#### W

WIA 11-28 Setting WIA Driver 2-49 Wi-Fi Settings 2-26, 8-26 Wi-Fi Direct Settings 2-30, 8-26 Wireless Connection 1-9 Wireless Network Settings 2-26 WPS 11-28 WSD Print Protocol Settings 8-31 WSD Scan 5-27 Protocol Settings 8-31

#### Χ

XPS Fit to Page 6-34 Default 8-17

**Z** Zoom 6-10 Default 8-16



#### **KYOCERA** Document Solutions America, Inc.

#### Headquarters

225 Sand Road, Fairfield, New Jersey 07004-0008, USA Phone: +1-973-808-8444 Fax: +1-973-882-6000

#### Latin America

8240 NW 52nd Terrace Dawson Building, Suite 100 Miami, Florida 33166, USA Phone: +1-305-421-6640 Fax: +1-305-421-6666

#### KYOCERA Document Solutions Canada, Ltd.

6120 Kestrel Rd., Mississauga, ON L5T 1S8, Canada Phone: +1-905-670-4425 Fax: +1-905-670-8116

#### **KYOCERA** Document Solutions

#### Mexico, S.A. de C.V.

Calle Arquimedes No. 130, 4 Piso, Colonia Polanco Chapultepec, Delegacion Miguel Hidalgo, Distrito Federal, C.P. 11560, México Phone: +52-555-383-2741 Fax: +52-555-383-7804

#### KYOCERA Document Solutions Brazil, Ltda.

Alameda África, 545, Pólo Empresarial Consbrás, Tamboré, Santana de Parnaíba, State of São Paulo, CEP 06543-306, Brazil Phone: +55-11-2424-5353 Fax: +55-11-2424-5304

#### **KYOCERA** Document Solutions Chile SpA

Jose Ananias 505, Macul. Santiago, Chile Phone: +562-2350-7000 Fax: +562-2350-7150

#### KYOCERA Document Solutions Australia Pty. Ltd.

Level 3, 6-10 Talavera Road North Ryde N.S.W, 2113, Australia Phone: +61-2-9888-9999 Fax: +61-2-9888-9588

#### **KYOCERA Document Solutions**

Fax: +64-9-415-4597

**New Zealand Ltd.** Ground Floor, 19 Byron Avenue, Takapuna, Auckland, New Zealand Phone: +64-9-415-4517

#### **KYOCERA Document Solutions Asia Limited**

Unit 3 & 5, 16/F.,Mita Centre, 552-566, Castle Peak Road Ts*u*en Wan, New Territories, Hong Kong Phone: +852-2496-5678 Fax: +852-2610-2063

#### **KYOCERA** Document Solutions

#### (China) Corporation

8F, No. 288 Nanjing Road West, Huangpu District, Shanghai,200003, China Phone: +86-21-5301-1777 Fax: +86-21-5302-8300

#### **KYOCERA** Document Solutions

#### (Thailand) Corp., Ltd.

335 Ratchadapisek Road, Wongsawang, Bangsue, Bangkok 10800, Thailand Phone: +66-2-586-0333 Fax: +66-2-586-0278

#### KYOCERA Document Solutions Singapore Pte. Ltd.

12 Tai Seng Street #04-01A, Luxasia Building, Singapore 534118 Phone: +65-6741-8733 Fax: +65-6748-3788

#### KYOCERA Document Solutions Hong Kong Limited

Unit 1,2,4,6,8 & 10, 16/F.,Mita Centre, 552-566, Castle Peak Road Tsuen Wan, New Territories, Hong Kong Phone: +852-3582-4000 Fax: +852-3185-1399

#### KYOCERA Document Solutions Taiwan Corporation

6F., No.37, Sec. 3, Minquan E. Rd., Zhongshan Dist., Taipei 104, Taiwan R.O.C. Phone: +886-2-2507-6709 Fax: +886-2-2507-8432

#### KYOCERA Document Solutions Korea Co., Ltd.

#3F Daewoo Foundation Bldg 18, Toegye-ro, Jung-gu, Seoul, Korea Phone: +822-6933-4050 Fax: +822-747-0084

#### **KYOCERA** Document Solutions

#### India Private Limited

Second Floor, Centrum Plaza, Golf Course Road, Sector-53, Gurgaon, Haryana 122002, India Phone: +91-0124-4671000 Fax: +91-0124-4671001

#### **KYOCERA** Document Solutions Europe B.V.

Bloemlaan 4, 2132 NP Hoofddorp, The Netherlands Phone: +31-20-654-0000 Fax: +31-20-653-1256

#### **KYOCERA** Document Solutions Nederland B.V.

Beechavenue 25, 1119 RA Schiphol-Rijk, The Netherlands Phone: +31-20-5877200 Fax: +31-20-5877260

#### **KYOCERA** Document Solutions (U.K.) Limited

Eldon Court, 75-77 London Road, Reading, Berkshire RG1 5BS, United Kingdom Phone: +44-118-931-1500 Fax: +44-118-931-1108

#### **KYOCERA** Document Solutions Italia S.p.A.

Via Monfalcone 15, 20132, Milano, Italy, Phone: +39-02-921791 Fax: +39-02-92179-600

#### **KYOCERA** Document Solutions Belgium N.V.

Sint-Martinusweg 199-201 1930 Zaventem, Belgium Phone: +32-2-7209270 Fax: +32-2-7208748

#### **KYOCERA** Document Solutions France S.A.S.

Espace Technologique de St Aubin Route de l'Orme 91195 Gif-sur-Yvette CEDEX, France Phone: +33-1-69852600 Fax: +33-1-69853409

#### **KYOCERA** Document Solutions Espana, S.A.

Edificio Kyocera, Avda. de Manacor No.2, 28290 Las Matas (Madrid), Spain Phone: +34-91-6318392 Fax: +34-91-6318219

#### **KYOCERA** Document Solutions Finland Oy

Atomitie 5C, 00370 Helsinki, Finland Phone: +358-9-47805200 Fax: +358-9-47805390

#### KYOCERA Document Solutions

#### Europe B.V., Amsterdam (NL) Zürich Branch

Hohlstrasse 614, 8048 Zürich, Switzerland Phone: +41-44-9084949 Fax: +41-44-9084950

# KYOCERA Bilgitas Document Solutions Turkey A.S.

Gülbahar Mahallesi Otello Kamil Sk. No:6 Mecidiyeköy 34394 Şişli İstanbul, Turkey Phone: +90-212-356-7000 Fax: +90-212-356-6725

#### KYOCERA Document Solutions Deutschland GmbH

Otto-Hahn-Strasse 12, 40670 Meerbusch, Germany Phone: +49-2159-9180 Fax: +49-2159-918100

#### KYOCERA Document Solutions Austria GmbH

Altmannsdorferstraße 91, Stiege 1, 2. OG, Top 1, 1120, Wien, Austria Phone: +43-1-863380 Fax: +43-1-86338-400

#### **KYOCERA Document Solutions Nordic AB**

Esbogatan 16B 164 75 Kista, Sweden Phone: +46-8-546-550-00 Fax: +46-8-546-550-10

#### **KYOCERA Document Solutions Norge Nuf**

Olaf Helsetsv. 6, 0619 Oslo, Norway Phone: +47-22-62-73-00 Fax: +47-22-62-72-00

#### **KYOCERA** Document Solutions Danmark A/S

Ejby Industrivej 60, DK-2600 Glostrup, Denmark Phone: +45-70223880 Fax: +45-45765850

#### **KYOCERA** Document Solutions Portugal Lda.

Rua do Centro Cultural, 41 (Alvalade) 1700-106 Lisboa, Portugal Phone: +351-21-843-6780 Fax: +351-21-849-3312

#### **KYOCERA** Document Solutions

#### South Africa (Pty) Ltd.

KYOCERA House, Hertford Office Park, 90 Bekker Road (Cnr. Allandale), Midrand, South Africa Phone: +27-11-540-2600 Fax: +27-11-466-3050

#### **KYOCERA** Document Solutions Russia LLC.

Building 2, 51/4, Schepkina St., 129110, Moscow, Russia Phone: +7(495)741-0004 Fax: +7(495)741-0018

#### **KYOCERA** Document Solutions Middle East

Dubai Internet City, Bldg. 17, Office 157 P.O. Box 500817, Dubai, United Arab Emirates Phone: +971-04-433-0412

#### **KYOCERA** Document Solutions Inc.

2-28, 1-chome, Tamatsukuri, Chuo-ku Osaka 540-8585, Japan Phone: +81-6-6764-3555 http://www.kyoceradocumentsolutions.com

© 2016 KYOCERA Document Solutions Inc.

KYOCERA Corporation



Rev.2 2016.9 2R7KDEN002