

DIGITUS 8K HDMI switch, 4x1

DS-55335

EAN 4016032495567



4x1 HDMI Switch, 8K/60Hz (4:4:4), Toslink, Stereo, EDID Control

The DIGITUS® 8K HDMI Switch, 4x1 offers additional HDMI connections for your output display - 4 signal sources can be connected to the screen via just 1 HDMI connection. Audio signals can also be decoupled via Toslink or 3.5 mm stereo connection and played back separately. Conveniently switch between signal sources via remote control, on the device itself or via automatic detection.

Expand your TV/monitor with additional HDMI connections - Convenient switching between signal sources without having to reconnect & additional audio extractor: Toslink / stereo (3.5 mm) for separate playback of the audio signal

- Convenient switching between 4 signal sources via remote control, on the device itself or via automatic detection
- Audio extractor: Toslink / Stereo (3.5 mm)
- EDID switch / management
- Max. Resolution: 8K/60Hz (4:4:4)
- Video bandwidth: 48 Gbps
- Supports High Dynamic Range (HDR)
- Supports HDCP 2.3
- Supports CEC (Consumer Electronics Control)
- Supports Deep Color (36 bit)
- HDMI 2.1
- Connections:
- 4x HDMI input (8K/60Hz)
- 1x HDMI output (8K/60Hz)
- 1x Toslink

- 1x 3.5 mm audio
- 1x Micro USB input - Service
- 1x DC socket (power supply) - power supply connection
- 8x status LEDs
- 1x changeover switch
- 1x IR receiver
- 1x EDID switch
- Operating temperature: 0-70°
- Power consumption: approx. 5W
- Housing: Metal
- Dimensions (housing): L 18.8 x W 7.1 x H 1.8 cm
- Weight: 287 g
- Color: black
- HDTV Resolution max.: 7680 × 4320 Pixel, 60Hz
- HDTV Standard: Ultra HD 8K
- Number of input ports: 4
- Number of output ports: 1
- Signal input: HDMI
- Signal output: HDMI
- Video connection ports: HDMI

Package contents

- 1x HDMI switch
- 1x remote control (2x AAA batteries, not included)
- 1x power supply unit (5V/1A, 1.2 m) with screw connector
- 1x QIG

Logistics						
	Number (pcs)	Weight (kg)	Depth (cm)	Width (cm)	Height (cm)	cm³
Packaging Unit Carton	1	0.00	0.00	0.00	0.00	0.00
Packaging Unit Inside	1	0.00	0.00	0.00	0.00	0.00
Packaging Unit Single	1	0.00	0.00	0.00	0.00	0.00
Net single without Packaging	1	0.29	18.80	7.10	1.80	0.00

More images:



Safety notes

- If the device is powered by a plug-in power supply, ensure that the power adapter is connected correctly and meets the specified requirements (e.g. voltage and current).
- Only use certified CAT5e or CAT6 cables to ensure stable signal transmission.
- For particularly long cable runs or in environments prone to interference, it is recommended to use shielded network cables.
- Make sure that all connections are tight and secure to avoid loose contacts that could affect the signal quality. Make sure that the HDMI and Ethernet connections are connected correctly.
- Make sure that the CAT cable is not laid near high-voltage power lines or other strong sources of electromagnetic interference to avoid signal interference.
- Only operate the device within the specified temperature range.
- Do not use the device outdoors or in damp or wet environments
- Check all connections and cables regularly for wear or damage. Cables and connections can wear out, especially with frequent use or long installations, which can lead to poor signal quality or system failure.

EU responsible person

EU based economic operator ensuring the product complies with the required regulations.

ASSMANN Electronic GmbH
Auf dem Schüffel 3
Lüdenscheid, Germany
<https://www.assmann.com>
info@assmann.com